


# ETHERNET CHIP SET IS HERE.



Now there's a VLSI Ethernet chip set you can take on the open road.

# The Am7990 LANCE and Am7992A SIA are ready to roll.

Fasten your seat belts.

Thanks to IMOX,<sup>™</sup> the Am7992A Serial Interface Adapter has the blinding speed it needs to meet demanding Ethernet specs.

And the Am7990 is just as hot. Jointly developed with DEC, this 10MHz LANCE is made to work with

every leading CPU.

Together, the Am7992A and Am7990 form the first perfectly matched Ethernet chip set to hit the streets for under \$100 a node. And, they're already second-sourced.

# You're all alone at the checkered flag.

The Am7990 family can put you as far ahead of the competition as we are. And it's just one of our VLSI families.

There are controllers, bipolar and MOS microprocessors, communication circuits,

The International Standard of Quality guarantees a 0.1% AQL on all electrical parameters, AC and DC, over the entire operating range.

TNT-STD-1000

signal processors and more.

And every part in every family meets or exceeds

the International Standard of Quality.


So grab a phone, ask us for our Ethernet booklet, and put on your driving gloves.

You're about to blow the doors off your competition.

# Advanced Micro Devices 27

901 Thompson Place, P.O. Box 3453, Sunnyvale, CA 94088 For direct factory response, call (408) 749-5000, outside California, call toll free (800) 538-8450, ext. 5000.

# THE WORLD'S FIRST





HIT THE OPEN ROAD.

# SURPRISE!

# Now a second source is your first choice for smart alphanumeric displays.

If you've been buying smart alphanumeric displays from Litronix, then here's great news. Now you can get a smart display from a second source—Hewlett-Packard. And your first HP display is free just for sending us your old Litronix part.

But a free display is only part of the story—HP's alphanumerics are a better buy. First, our displays have several product advantages; and second, they're backed by our world-wide sales force and complete technical support.

# Ours are compatible with theirs—and better.

HP's new fourcharacter HPDL-2416 Alphanumeric Displays are pin-for-pin compatible with the other guy's. So you don't have to redesign anything. But there are some notable differences that we know you'll like. For example, HP offers:

 A faster IC access time making it directly compatible with your microprocessor.

 Better ESD protection, featuring larger buffer diodes for better protection.



For pricing and delivery, contact your local Hewlett-Packard authorized components distributor. In the U.S., call Hall-Mark, Hamilton/Avnet, or Schweber. In Canada, call Hamilton/Avnet or Zentronics, Ltd. For more information, call your local HP sales office listed in the telephone directory white pages and ask for the Components Department.



 Wave solderability for faster and lower cost assembly.

• Industry standard TTL compatibility of 2.0 volts.

A wider operating temperature range,
20C degrees to
+70C degrees.

Let us prove our claims by

making HP your first choice for smart alphanumeric displays. So trade in and trade up. Send us one of your old Litronix displays and we'll send you one of ours.

### Yes! I want to trade in and trade up.

Yes, please send me a free HPDL-2416 smart alphanumeric display. Enclosed is my old Litronix part.

In the U.S. mail coupon to: Hewlett-Packard Company, 1820 Embarcadero Rd., Palo Alto, CA 94303. In Europe: Hewlett-Packard, Nederland BV, Central Mailing Department, P.O. Box 529, 1180 AM Amstelveen, The Netherlands.

. Encrosed is my	ora Entronax part.
Name	
Company	
Address	
City	State
Zip	Phone
My application is	s
ED	12/13/84

HP: The right choices for smart alphanumeric displays.



# ncredible 1 watt 0.7 to 4.2 GHz amplifiers...only \$895

Now is the time to rethink your design decisions if you require up to 1 watt output for low-distortion intermodulation testing...broadband isolation...flat gain over wide bandwidth—or if you need much higher output level from your signal/sweep generator or frequency synthesizer — you can now specify Mini-Circuits' new ZHL-42 power amplifier . . . for only \$895.

Using ultra-linear Class A design, this state-of-the-art four-stage amplifier provides 30dB gain, flat ( $\pm$ 1.0dB) over the 700 to 4200 MHz range, is unconditionally stable, includes overvoltage protection, and can be connected to any load impedance without amplifier damage or oscillation.

One week delivery ... and, of course, one-year guarantee.

finding new ways. setting higher standards

### lini-Circuits

A Division of Scientific Components Corporation
World's largest manufacturer of Double Balanced Mixers
P.O. Box 166, Brooklyn, New York 11235 (718) 934-4500 Domestic and International Telex 125460 International Telex 620156

# now available!

**ZHL-42 SPECIFICATIONS** 

Gain..... 30dB Min.

Gain Flatness. . . . . . . . . . . . . . . . . ±1.0dB

Power Out @ 1dB CP. . . . . . + 29dBm Min. 

Supply . . . . . . . . . . . . . . . . +15V @ 690mA

Third Order Intercept. . . . . . . . . . 38 dBm Min. Second Order Intercept...... 48 dBm Min.

..... 7" × 3½" × 2½"h

computer-automated performance data

CIRCLE 3

# **Electronic Design**

Editor-in-Chief: Lucinda Mattera Executive Editor: Stanley Runyon

Managing Editors:

Michael Riezenman, Technology Report Margaret Eastman, Design Entries Warren Andrews, Technology News Michael Robinson, New Products

Editor-at-large: Martin Gold **Associate Managing Editors:** David Bursky, West Coast Roger Allan, Special Features

**Executive Art Director:** Thomas Phon

Senior Editor: Max Schindler

**Technology Editors:** 

Analog & Power: Frank Goodenough Communications & Industrial: Roger Allan Computer Peripherals: Stephan Ohr (Sunnyvale) Instruments: Robert Milne

Semiconductors: David Bursky (Sunnyvale)

Software: Max Schindler

Field Editors:

East Coast: Carole Patton (Hasbrouck Heights);

Gary Elinoff (Boston)

West Coast: Curtis Panasuk (Sunnyvale); Ray Weiss (Los Angeles) Midwest: Terry Costlow (Chicago) South: Heather Bryce (Dallas) Europe: Mitch Beedie (England)

Associate Editor: Gil Bassak

Design Solutions Editor: Harold Winard New Products Editor: Susan Nordyk Chief Copy Editor: Diane Tunick-Smith

Copy Editors: Aaron Fischer, Ellen Muraskin, Teresa Meola

Editorial Production Manager: Anne Gilio Turtoro Assistants: Donna A. Carullo, Catherine Wolf

Assistant Art Director: Joanne M. Goodfellow Graphic Designers: Nancy J. Hajeski, Mary Van Bodegon

Illustrator: Alice Topf-Cirica

Editorial Secretaries: Mary James. Ruth Ottenheimer, Audrey Naumburg Editorial Administrator: Camille Metzler

**Editorial Offices:** 

Headquarters: 10 Mulholland Dr., Hasbrouck Heights, N.J. 07604 (201) 393-6000, TWX—710-990-5071 (HAYDENPUB HBHT), Cable Haydenpubs. Boston: 260 Bear Hill Rd., Suite 100, Waltham, Mass. 02154, (617) 890-8050. Sunnyvale: 1307 South Mary Ave., Suite 212, Sunnyvale, Calif. 94087, (408) 736-6667. Los Angeles: 8939 South Sepulveda Bivd., Suite 260, Los Angeles, Calif. 90045, (213) 641-6544. Chicago: 200 East Ontario, Chicago, Ill. 60611, (312) 337-0588. Dallas: 046518. Exceptive, Sittle 230. Delles Town, 75614, 414, 344, Bellas: 9451 LBJ Freeway, Suite 220, Dallas, Texas 75243, (214) 234-0508. England: Avalon House, Cranston Road, East Grinstead, West Sussex RH19 3HG, 0342-314111.

National Sales Manager: Paul C. Mazzacano Director of Marketing: Stephen E. Scrupski

Assistant: Betsy Tapp

Business Manager: Thomas E. Vachon Promotion Manager: Jay McSherry

Assistant: Evelyn Schmidt Copy Writer: James Keane

Research Manager: Kenneth J. Turtoro

Advertising Production Manager: Marjorie Duffy Assistants: Roseanne Erickson, Evelyn Porta Circulation Director: Barbara Freundlich Fulfillment Manager: Lori Shulman

Reprints: Jim Dysert

Vice President and Publisher:

Reader Service: Paula Greenleaf

Laurence Altman

## **BEHIND THE COVER**

n an industry dominated by the notion that faster is better, Robert Galin talks proudly about a slower local-area network controller. "This is one case when the reverse is true," he says, "since lower speed means lower cost." Galin, who works in strategic planning at Intel, is not making an empty assertion: He helped devise the specifications for the 82588 LAN controller featured in our cover story (p. 141).

The idea behind the chip was born in 1981, out of the conviction that the telecommunications world would need more economical networks than Ethernet. Back then, Galin felt that Ethernet's CSMA/CD would be vital to such systems, but at more modest bit rates. He also predicted that both baseband and broadband transmissions would be successful.

Out of these beliefs, Galin helped design a highly versatile, low-cost single-chip controller—one that could be tailored to the networks he envisioned. The 1- and 2-Mbit/s 82588 does follow in the footsteps of an earlier Ethernet coprocessor, but its lower bit rate allows Manchester encoding to be done on chip. It also makes for an economical logic-based method for detecting collisions on the network, rather than the more costly analog-based scheme used in Ethernet.

Despite these differences, it proved possible to lift about 60% of the 82588 out of the coprocessor. Specifically, both chips' serial sections (which include parallel-to-serial conversion, framing, error checking, and the CSMA/CD mechanism) use identical masks. Modular design, Galin emphasizes, cut development time by at least a year.

Galin is rightfully proud of his role in helping his predictions come true. Two new systems-IBM's 2-Mbit/s broadband PC Network and AT&T's 1-Mbit/s baseband Starlan—aim squarely at low-cost personal computers. The 82588 suits both to a T.

# ectronicDesign

### **DEPARTMENTS**

- 3 Behind the Cover
- 6 Contents Spotlight
- 11 On Reflection
- 15 Reader Feedback
- 27 U.S. Meetings
- 31 Personally Speaking
- 101 International Meetings
- 369 Index of Advertisers
- 370 Reader Service Card

### TECHNOLOGY REPORT


### 118 Transforming a simulated IC into silicon demands tools that unravel design decisions

Once an IC passes simulation, software helps choose the optimum silicon layout for gate arrays, standard cells, or custom chips.

### DESIGN ENTRIES

### 141 Cover: Monolithic controller builds PC network without toil or trouble

A controller chip puts CSMA/CD within the reach of personal computer networks, keeping a lid on parts count and simplifying software development.



### 157 Controller chips pair up in S interface for ISDN

Two CMOS LSI chips, the chief building blocks of a system terminal and a PBX line card, streamline implementation of the S interface for ISDN systems.

### 175 Built-in Basic interpreter turns controller chip into versatile system core

An extended set of Basic statements and operators transforms a chip into the foundation of embedded real-time systems.

### **TECHNOLOGY NEWS**

### 35 Newspulse Newsfront

- 47 Oxide isolation process builds RAM controller chip that needs no wait states
- 48 Two-processor board brings flexibility to voice applications
- 52 Pipelined structure ups tape controller's transfer rate by 30%

### **Conference Preview**

61 Application-specific ICs top the charts at February's ISSCC

### **News Analysis**

73 Making logic programs execute in parallel is today's Al challenge

### Viewpoint

- 85 The guest for a standard 1/2-in. tape cartridge may well be unnecessary
- 86 Thin-film LCD technology could be the key to largearea flat panels
- 99 International Newsfront

### 187 Chip duo allows transfer of controller electronics to smallest disk drives

With the disk drive electronics now housed in tiny packages, placing controller boards in the host computer is a has-been approach.

### 201 On-chip EEPROM holds changing register data for 8-bit microcomputer

With a 32-byte EEPROM built into its main registers, a computer chip lowers the risk of losing essential data, whether in multiprocessor or stand-alone setups.

### 217 Associative memory calls on the talents of systolic array chip

A monolithic systolic array puts its on-chip memory to good use, first searching out the desired information and then processing it.

### 233 Design Solutions:

Add-on circuit monitors trickle-charging system. Gate and instruction place interrupt under software control. Routines extend 8051 math to negative numbers.

### PRODUCT REPORT

### 251 Focus on board-level modems

Pushed on by the influx of small computers, modem makers are successfully shrinking their boards, adding new features, and pressing the upper speed limits.

#### IN THE NEXT ISSUE

Designer's Reference: Software standards for networks, operating systems, and CAE... Personal Computer Series: Part 2 of a reader survey... A high-speed, high-resolution workstation tackles 3D graphics.

Cover illustration by Maura C. Flynn 144,364 copies of this issue printed

ELECTRONIC DESIGN (USPS 172-080; ISSN 0013-4872) is published biweekly with one additional issue in February, May, October and December and two additional issues in August by Hayden Publishing Company, Inc., 10 Mulholland Dr., Hasbrouck Heights, N.J. 07604. Subscription rates are \$45 per year U.S. (foreign rates available upon request). James S. Mulholland Jr., President. Printed at Brown Printing Co., Waseca, Minn., Somerset Publishing Co., Somerset, N.J., and Wisconsin Cuneo Press, Milwakee, Wis. Second-class postage paid at Hackensack, N.J. 07602 and at additional mailing offices. Copyright © 1984, Hayden Publishing Company, Inc. All rights reserved. POSTMASTER: Please send change of address to ELECTRONIC DESIGN, PO BOX 1418, Riverton, N.J. 08077.

### **NEW PRODUCTS**

### Analog

- 269 CMOS comparator chip multiplexes 4 inputs under digital control
- 270 Analog array groups devices in like blocks for faster turnaround
- 273 574 a-d converter slips sample-and-hold chip into its 28-pin package
- 274 Resolver-to-digital converters deliver accurate velocity and data

#### **Digital ICs**

- 284 DMA controller chip addresses 4 Gbytes, works with 68000 family
- 285 Floppy-disk controller chip has everything but buffers
- 286 SAR chip consumes 10% to 1% the power

#### Instruments

294 Computer system automatically burns in and tests on-board PROMs

#### **Power**


331 Trio of power MOSFETs has lowest on-resistance for 50- and 60-V devices

#### **Computer Boards**

- 336 Slave processor puts distributed processing on the STD bus at low cost
- 339 Computer Systems
- 311 Software 346 Product News
- 314 Factory Automation 348 Application Notes
- 341 Packaging & Materials 350 New Literature
- 344 Components

# **frequency doublers**

+1 to +15 dBm input



1 to 1000 MHz only \$21<sup>95</sup> (5-24)

AVAILABLE IN STOCK FOR IMMEDIATE DELIVERY

- micro-miniature, 0.5 x 0.23 in. pc board area
- flat pack or plug-in mounting
- high rejection of odd order harmonics, 40 dB
- low conversion loss, 13 dB
- · hermetically sealed
- ruggedly constructed MIL-M-28837 performance\*

\*Units are not QPL listed

#### SK-2 SPECIFICATIONS

FREQUENCY RANGE, (MHz) INPUT 1-500 OUTPUT 2-1000 CONVERSION LOSS, dB 1-100 MHZ 100-300 MHz 300-500 MHz Spurious Harmonic Output, dB 2-200 MHz F1 F3 200-600 MHz F1 F3	TYP. 13 13.5 14.0 TYP. -40 -50 -25 -40	MAX. 15 15.5 16.5 MIN. -30 -40 -20
600-1000 MHz F1 F3	-40 -20 -30	-30 -15 -25

For complete specifications and performance curves refer to the 1980-1981 Microwaves Product Data Directory, the Goldbook or EEM.

finding new ways...
setting higher standards

### Mini-Circuits

A Division of Scientific Components Corporation World's largest manufacturer of Double Balanced Mixers 2625 E. 14th St. B'klyn, N.Y. 11235 (718) 769-0200 C78-3 REV. A

CIRCLE 4

## **C**ONTENTS SPOTLIGHT

### **Technology Report: CAE tools 118**

before and during IC simulation, but they rarely spend the same time on the steps that follow simulation. In fact, the decisions of how to translate the simulated circuit into silicon are perhaps the most critical, since they must balance cost, silicon use, and turnaround. As part two of our Technology Report details, a wealth of CAE software tools is emerging—many integrated into workstations—to steer designers to the optimum methods for layout and routing, verification, and circuit extraction.

### Cover: PC network controller 141


hough system designers frequently tie personal computers into local networks, the systems themselves are usually geared more for minicomputers than for micros. Now a controller solves that problem in one chip: Designed specifically for personal computer-based networks, it slashes board count, board space, and development time. Moreover, its transfer rate—1 or 2 Mbits/s—is well suited to inexpensive twisted-pair cable.

### Focus on board-level modems 251

ix small computers with the ubiquitous phone lines, and the need for trimmer yet more powerful modem boards becomes inevitable. While shrinking the board circuitry, manufacturers are raising the transmission rate to a new high of 14.4 kbits/s and packing more features into their cards.

### Conference Preview: ISSCC 61

oday's interest in application-specific ICs will be reflected when the International Solid-State Circuits Conference opens its doors next February. Naturally, memories and processors will grab the most attention, but traditional chips and analog circuits—including a 500-MHz digital-to-analog converter—will hold a place as well.



Need a stroke of an inch-and-a-half... or just one thirty-secondth? Need pull of 50 pounds...or just a fraction of an ounce? AC or DC? Intermittent or continuous duty? Pull or push? Box-frame, U-frame, laminated or tubular? Recognition under the component program of Underwriters' Laboratories, Inc.?

**Guardian's got 'em all.** And each features meticulous craftsmanship . . . true engineering genius. (Inspired, of course, by your very own Guardian Angel.)



SEND FOR CATALOG.

BOX-FRAME SOLENOIDS with Uni-Guard®
Il molded bobbin and coil covers...mechanical life measured in millions of cycles.

**U-FRAME SOLENOIDS** for minimum cost with high reliability...most with Uni-Guard\* II molded bobbin and coil covers.

LAMINATED SOLENOIDS in AC only for more pull over a longer stroke than DC solenoids of the same size...many with Uni-Guard® molded polyester coil covers.

TUBULAR SOLENOIDS in your choice of premium quality long life of up to 100 million operations or more...or traditional tubulars with an expected life of a million operations plus.


**GUARDIAN** 

SOLENOIDS IN MORE TYPES...WITH MORE INSPIRED DESIGN...THAN ANYONE ELSE IN THE WORLD.

GUARDIAN ELECTRIC MANUFACTURING COMPANY • 1550 West Carroll Ave., Chicago, Illinois 60607 • 312/243-1100

CIRCLE 5

"We couldn't have done a full chip simulation without the LE. We reduced chip costs by a factor of ten with a design that was 100% perfect in first silicon. It was absolutely phenomenal!"



®Mitel - Registered Trademark of Mitel Corporation. ™SX-2000 - Trademark of Mitel Corporation. HOW THE ZYCAD LOGIC EVALUATOR® HELPED MITEL® DESIGN ENGINEERS REDUCE THE MANUFACTURING COSTS OF A COMPLEX CMOS DIGITAL SWITCH.

Mitel Corporation of Kanata, Ontario, is one of the world's leading suppliers of sophisticated communications systems. They manufacture the SX-2000™ Integrated Communications System, a large PABX unit that is capable of handling from 150 to more than 10,000 phone lines.

### REDUCED COSTS THROUGH DESIGN ENGINEERING.

An SX-2000 unit may contain up to 400 dynamic digital crosspoint switches (DDX's) — complex chips that can switch up to 256 lines each.

Mitel's IC design group was assigned the task of integrating new technology into the manufacture of the DDX chips. Objective: maintain quality and function while making significant cost reductions.

# "COMPLEXITY CREATES THE NEED FOR INCREASED CAPACITY."

-Duncan Klett, Manager, Work Stations & CAE

"We wanted to integrate dynamic RAM and the new silicon technology into the DDX design," said Duncan Klett. "The problem was the complexity of the circuit design. As you get more complex, your simulation needs increase geometrically. Our existing capabilities let us test pages and blocks of the design, but we couldn't simulate the chip as a whole. We tried to verify the total design using software simulation. After 30 CPU hours there were still no results, and we couldn't justify tying up the computer any longer.'

### THE ZYCAD LOGIC EVALUATOR.

Mitel's Logic Evaluator (Model LE 1001) has a capacity of 50,000 gates and a speed of 500,000 events per second. It is a dedicated hardware processor designed for complex logic simulation.

### "THE LE GAVE US SIMULATION RESULTS WE COULDN'T GET ANY OTHER WAY."

Duncan Klett: "The Logic Evaluator was the perfect tool for this project. We found we could simulate the whole design quickly. As a matter of fact, we ran the DDX simulation over 100 times in a four month period and identified problems relating to interfaces and timing that wouldn't have shown up with partial simulation.'

### FIRST SILICON— RIGHT THE FIRST TIME.

In a project this complex, it is usual to go to a silicon prototype two, three or even more times. If the circuit design can be simulated and debugged perfectly before the first prototype, there are considerable savings in cost and the time it takes to get a new design to production.

Mike Dohler: "We found we could run a simulation of the complete DDX design in one hour and seventeen minutes on the LE. With that kind of capability, you can get all the information you need as fast as you can use it. That's a revolutionary shift for electronics designers."

### THE BEST TOOLS AVAILABLE FOR SOLVING CRITICAL DESIGN PROBLEMS.


The Zycad Logic Evaluator works for Mitel. The Logic Evaluator can also be used for fault simulation and development of diagnostic and system software.

For more information, call us or write:
Zycad Corporation
1315 Red Fox Road
St. Paul, MN 55112
(612) 631-3175





# The New 172 Relay We put Centigrid in civvies to save you money



Now you can have your cake and eat it too! The quality and performance—in fact, the same mechanism as a military TO-5/ Centigrid relay at prices you can afford for your commercial designs.

The secret is automation. It permits us to cut costs without cheapening the design. We've designed and built our unique equipment which not only speeds production, but insures quality. For example, our microprocessor-controlled header assembly system automatically tests the

subassemblies while they are being produced, cutting down on human error and insuring built-in reliability.

The 172 gives you all the popular Centigrid physical advantages: the rugged uniframe construction; the miniscule .14 sq. in. footprint; the .100 grid lead spacing for direct pc board plug-in without spreader pad, which retains the low .375 in. total profile.

But perhaps even more important, you get all the technical

advantages of twenty years of TO-5 leadership: a dependable, low power DPDT relay that has excellent RF characteristics up through UHF, and the proven performance and reliability of TO-5 technology.

If you'd like to know more about how to get military type performance without paying for the uniform, call or write today.


### TELEDYNE RELAYS

Innovations In Switching Technology

12525 Daphne Ave., Hawthorne, California 90250 • (213) 777-0077 U.K. Sales Office: Heathrow House, Bath Rd., Cranford, Hounslow, Middlesex, England TW5 9QQ • 01-897-2501 European Hqtrs.: Abraham Lincoln Strasse, 38-42 • 6200 Wiesbaden, W. Germany 06121-7680 Japan Sales Office: Nihon, Seimei Akasaka Building • 8-1-19 Akasaka, Minato-Ku, Tokyo, 107 Japan (03) 403-8140 France Sales Office: 85-87 Rue Anatole-France • 92300 Levallois-Perret, France • 758-71-60

# **ON REFLECTION**

# Be it design or test, cooperation is everyone's business



erhaps the biggest obstacle standing in the way of higher productivity and shorter turnaround is the traditional separation between design and test engineers. As a former board test engineer, I have experienced the frustration of having boards handed to me, fait accompli, with no thought of their testability or ease of manufacture. Unfortunately, the design engineer is rarely graded on his performance in those two areas. For that reason, he generally hands the test enginer a prototype board (replete with many jumpers) and a schematic that may or may not be current and simply says, "Here."

My former colleagues in chip testing encounter similar situations. Here too, design and testing are separate and often hostile groups. In most cases, the test engineer has no input into the early stages of the design process. If he did, his trained eye would no doubt detect problems in testability. Minor changes made at that point could save millions of dollars during test generation and manufacture.

Make no mistake about the amount of money—not to mention time—involved here. High-level engineering talent may spend several man-years generating test programs for modern VLSI chips. Worse still, chips designed with little thought of testability demand test programs of inordinate complexity. Extremely costly to produce, those chips may also cause more than their share of difficulties on the manufacturing floor.


Spurred on by designers' need to verify performance before making the costly commitment to silicon, the industry is beginning to right its wasteful ways. With the help of the ATE segment, design and testing are undergoing substantial changes. For instance, a new generation of powerful digital simulators is proving a boon not only to designers but also to test engineers, who apply them to test program generation.

As worthwhile as such tools may be, in the end communication is even more valuable. With today's local networks, there is no reason why critical information culled during the design stage and stored in a data base cannot be accessed by test engineers. Adding the appropriate security measures ensures that the design stands no danger of unauthorized access or modification.

Just think of the ramifications: Instead of discovering problems literally after "the die has been cast," test engineers can diagnose troublespots early, while they can still be easily—and inexpensively—rectified. With the test engineer involved in the design stages, the test program can be debugged and prepared months before it is now. That shorter turnaround time is something that everyone agrees with—designer, test engineer, and manager.


Gary Elinoff

\*\*ATE is important to us.
The company behind ATE is more important.
That's why we chose Teradyne. \*\* Bob Dances Xerox Corporation



"With the costs involved in getting new products to market today, we couldn't afford to buy ATE the way we used to.

"We couldn't just settle for a good piece of test gear. We had to find an ATE company that would work with us, partner to partner, to solve our toughest testing problems.



"A company like Teradyne." Bob Dances of Xerox under-

stands that vendor-customer relationships are important in ATE. So do we. That's why we created our Test Assistance Group (TAG), a worldwide organization with a single charter: helping customers realize the full potential of their Teradyne systems.

TAG engineers will work with you to get your systems up and running fast. And when you hit the rough spots, they'll be there to help you through them.

They can also deliver special hardware and software for specific applications, including turnkey packages.

In the age of VLSI, testing is often a do-or-die proposition, with the success of a product line or even a company hanging in the balance. We can respond to this challenge because we've made production-line testing our business for almost a quarter century.

Whatever it takes to keep your test systems running productively, we're ready to deliver, through a team of dedicated professionals only a phone call away.

When Xerox says ATE partnerships are important, it's a thought worth copying.



We measure quality.

In your system or on the bench...

# the latest HP counter delivers all the right numbers. At the right price.

### A new standard for your system.

The HP 5334A is quickly becoming the new system standard. And for good reason: Full HP-IB programmability is included in our low price of \$2,800\*. That means it's a natural for fully automatic systems. Add to that automatic peak amplitude measurements and our exclusive auto attenuation for a real counter breakthrough in this price range. Plus easy interfacing to computers, such as the HP Series 200. And the HP 5334A can even help boost your overall system performance. That's because its internal processor performs math functions and automatic measurements, which lower your system overhead.

### Fast and easy measurements on your bench.

Bench users will like the way this counter speeds manual measurements.

At the push of a button, you'll make waveform measurements such as peak, pulse width, rise and fall...automatically and fast. And its ability to store up to ten front-panel setups in its non-volatile memory will save you setup time and trouble.

### Measure for measure, you get more for less.

You get a lot of performance in this counter bargain. Single-shot resolution of 2 ns, 100 MHz frequency operaation is standard or 1.3 GHz C-channel optional. Fast, unformatted throughput of 150 measurements/second. There's even an optional 4-digit, autoranging, auto-polarity DVM. And naturally, it's fully compatible with the IEEE Recommended Practice for Code and Format Conventions of IEEE-728.

Whether you need precise measurements of oscillators, generators, transmitters, system clocks or other

frequency or time-related applications, the HP 5334A comes up with the right numbers.

### The quickest way to get our number.

For more information on the HP 5334A Universal Counter or the full range of solutions to your time interval or frequency measurement problems, request our data sheet and our complete counter brochure. Call your local HP sales office listed in the telephone directory white pages. Ask for the electronic instruments department.

\*U.S.A. list price only.



CIRCLE 9





020

# **R**EADER FEEDBACK

### Corrections

An extra zero in our Oct. 31 New Product story on Verbex's Series 4000 speech recognizer (p. 447) raised the price of the development software an order of magnitude. The correct price is \$500.

The Nov. 15 NewsPulse item on the C-1 supercomputer (p. 37) omitted the name of the manufacturer: Convex Computer Corp. (Richardson, Texas).

### Filling in a major omission

Your Product Report, "Focus on Monolithic Precision Op Amps," in the Oct. 31 issue [p. 337] is interesting but somewhat incomplete and not quite up to date: It overlooks the best monolithic FET operational amplifier on the market, Burr-Brown's model OPA111, which was featured as the cover article of your Feb. 9, 1984, issue [p. 97].

The OPA111, a DIFET (dielectrically isolated FET) amplifier, achieves an offset voltage of ±250 μV maximum, drift of  $\pm 1 \mu V$  maximum, an open-loop gain of 120 dB minimum, and common-mode and power supply rejection ratios of 100 dB minimum. What's more, noise is 100% tested and guaranteed (not just sample-tested) to be  $8 \, \text{nV} / \sqrt{\text{Hz}} \, \text{maximum} \, \text{at} \, 10$ kHz, and the bias current is only  $\pm 1$  pA maximum. In addition, a low-cost version, the OPA121KP, is now available


in an eight-pin plastic package.

Also, we thank the author for mentioning our new, enhanced version of the OPA27, but there are a few points that should be explained. Since we use the industry-standard grades in our OPA27 and OPA37, the minimum and maximum specifications remain unchanged, but performance has been improved in many areas. We now guarantee noise on the A and E grades by 100% testing. Furthermore, Burr-Brown is unique in providing 100% popcorn-noise screening on all OPA27 and OPA37 grades.

To avoid confusion when describing parameters on new products, I suggest you feature only minimum and maximum specifications. These guaranteed specs are what engineers must use for design—"typical" specs are provided only as a guide to help understand how a device performs.

Reputable manufacturers generate "typical" data from the mean performance of a large number of devices from many production lots, but there is always some unit-to-unit variation, and some manufacturers don't generate "typical" specs in this manner. It would therefore seem that the best standards for comparison would be the guaranteed minimums and maximum.

Neil P. Albaugh Electronics Engineer Burr-Brown Corp. Tucson, Ariz.



# Sprague-Goodman. Nobody Offers a Broader Selection of Trimmer Capacitors.

When it comes to high-quality trimmer capacitors, nobody comes close to Sprague-

We have the world's largest selection of models, styles and dielectrics: sub-miniature glass, quartz and sapphire Pistoncaps® plastic Filmtrims® or Ceramic single turn, Mica compression, Airtrim® air dielectric, multi-turn plastic and miniature LC tuners and Stab-L® metalized in-

ductors.

need standard or custom products, you can count on Sprague-Goodman. The first and last name in trimmer capacitors.

Sprague-Goodman SPRAGUE Electronics, Inc. GOODMAN


(An affiliate of the Sprague Electric Company) 134 Fulton Avenue Garden City Park, NY 11040 516-746-1385 TLX: 14-4533



CIRCLE 11

# easo

to call Zendex 2nd



### **ZX-186/30 CPU Board**

An 80186-based CPU board that is an ideal replacement for the iSBC-86/30 or iSBC/ 86/12A. It is fully software compatible with the ZX-86 and the entire iSBC-86 family.

Advanced features: 256KB zerowait-state on-board RAM (expandable to 1MB) two DMA channels, Dual multi-protocol USART, up to 128KB PROM and two iSBX connectors.

The other giant in the Multibus Market."

6700 Sierra Lane, Dublin, CA 94568, Phone: (415) 828-3000 TWX: 910 389 4009. Zendex products are available worldwide. Intel, iSBC and iSBX are trademarks of Intel Corp

### READER FEEDBACK

### **Engineers:** Keep it clean

R eading Heather Bryce's recent On Reflection [Oct.4, p. 11] brings another issue to mind. Cleaning up a desk or a workstation is the first step in "cleaning up" our business and technical minds. I consider it amazing how few (even brilliant) people recognize that personal "housekeeping" is mandatory, as is an orderly file system. But remember, out of sight, out of mind-always keep clear "flags" before your face.

Errol A. Campanella Component Engineer Los Angeles Components Alhambra, Calif.

Electronic Design welcomes the opinions of its readers on the issues raised in the magazine's editorial columns. Address letters to Editor-in-Chief, Electronic Design, 10 Mulholland Drive, Hasbrouck Heights, N.J. 07604. Try to keep letters under 200 words. Letters must be signed. Names will be withheld upon

### **ELECTRONIC DESIGN** is growing.

If you'd like to grow with us, you may be interested in one of the editorial opportunities we have in our New York area home office or in our Boston and Southern California field of-

We are interested in people with experience in all aspects of electronics, especially the explosive area of computer technology. To explore your potential in the exciting world of engineering journalism, send your reśumé to Lucinda Mattera, Editorin-Chief, ELECTRONIC DESIGN, 10 Mulholland Drive, Hasbrouck Heights, N.J. 07604.

# Motorola Reports DECEMBER ISSUE 1984

256K DRAMs make speed/density waves

- ☐ Ultrafasts oust tradition
- ☐ Stepper drive simplifies
- ☐ MC68020 development support



MOTOROLA



### Put four times the DRAM in the same slot...and still run faster.



Motorola's 256K MCM6257 dynamic RAM runs faster than the fastest 64Ks, and puts four times the memory in the same package.

It's a good thing. Demand for highspeed RAM is climbing astronomically, and forecasts project an industry shortfall of 256Ks despite the apparent number of suppliers. The world's systems crave more and more RAM, and the more they use the more they seem to need.

Motorola addresses these requirements with 256K dynamic RAMs that provide both flexibility and design freedom. All control and refresh lines are the same as with our 64Ks, and our 256Ks are also pin compatible with the 64Ks.

You get familiar architecture, technology and packaging, so ease of use is assured. The similarity stops there.

When we say the MCM6257 is fast, we're referring to the 100 ns maximum access time. Slightly slower versions

are also available, at 120 ns and 150 ns. Even with 100 ns speed, power dissipation is very low. Supply Current is only 4.5 mA standby, and 70 mA active. Operation is from a single +5 V supply.

High-performance triple-poly silicon-gate technology permits fabrication of denser, faster memory...the secret to packing so much performance on one small chip. Laser fuse-redundancy and direct step-on-wafer manufacturing ensure maximum yields. A row and column address input multiplexing scheme holds address lines down to nine, so the standard 300 mil wide 16-pin package handles the 256K with ease. For surface-mount applications, however, alternative 18-pin JEDEC-standard plastic J-leaded chip carriers will be available, too.

In addition to RAS-Only and CAS before RAS automatic refresh modes, the MCM6257 offers Nibble mode,

which allows serial access of up to four bits of data at very high rates... 20 ns access and 50 ns cycle times. Refresh is 256 cycle, 4 ms.

All MCM6257 inputs and outputs are TTL compatible, including clocks. Complete address decoding is performed on the chip with address latches incorporated. Data out is controlled by CAS, enhancing system flexibility.

The MCM6257 is just the beginning. We also have a variety of 256K DRAMs in the works with different speeds and, of course, CMOS.

So as the need grows for greater density and higher performance in a cost-contained environment for any conceivable application, look for Motorola. We're there.

Check □ A for information.



One way or the other, dual optointerrupters eliminate mechanicals.

The perfect interface between bidirectional movement and MPU — and one that completely eliminates failure-prone mechanical switches — can be yours with Motorola's new dual optointerrupters.

DARLINGTON OUTPUT
TRANSISTOR OUTPUT
SCHMITT TRIGGER OUTPUT

The MOC70W1-75W1 family provides a variety of functions, too: LED-to-transistor, LED-to-Darlington and LED-to-Schmitt trigger.

Actually two sets of opto couplers in one, these non-contacting, standard

packaged switching devices save space, time and costs in designing direction, motion and position sensing into a variety of

equipment
applications
from
computer track
balls to copying
machines. Plus,
they offer
complete
electrical isolation
of control circuitry
from load.

The emitter-detector slot is 0.125" wide, big enough to easily accommodate a wide variety of tripping mechanisms.


The high gain Darlingtons optimize applications calling for low-drive-current or larger output signal devices. The Schmitt trigger provides the fastest, cleanest signal sensing of all.

Narrow apperatures in front of each phototransistor allow strong signal transfer and shield the device from ambient light and crosstalk from the other LED and provide dirt and dust protection.

The standard dual optointerrupter package is designated by the "W" in the part number. Prices range from \$2.55 to \$3.55, 1K-up.

Check □ B for information.

### Benchmark 20: First to evaluate. First to market.



System integrators thinking about using the new 32-bit MC68020 MPU now have an excellent testbed for system evaluation: Benchmark 20.

This MC68020-based system package provides a variety of hardware and software tools to allow streamlined 32-bit benchmarking, code development and debugging. Packing a lot of power into a small space, the Benchmark 20 system contains a single-board microcomputer with the MC68020 MPU, plus an auxiliary

1 Megabyte RAM module, all configured with powerful debug/monitor firmware in a 4-slot chassis.

The result? You reduce time-to-market for your new 32-bit system product. Benchmark 20 is configured and ready to use alongside an appropriate software development host to trim your schedule for MC68020 benchmarking and code debugging.

The VM04 VERSAmodule CPU board utilizes the capacity of this new 32-bit performance standard to

achieve speeds in the 2-3 million instructions per second (MIPS) category. 4K long words of on-board instruction/data cache reduces off board memory accesses to insure top performance.

The companion dynamic RAM VM13 module provides 1Mbyte of random access memory dual ported with both RAMbus and VERSAbus. A perfect system mate for the VM04 32-bit monoboard, the VM13 RAM board has error detection and diagnostic capability.

To help you quickly evaluate the MC68020 and the VM04, the Benchmark 20™ system package incorporates the 020bug™ Debug/Monitor firmware package to allow you to de benchmarking and to debug code. The 020bug resident package allows full speed execution of system and user developed programs operating out of the Benchmark 20 system package. A powerful software and system debug command set allows access to all VM04 I/O, control, and memory facilities plus the full 4 gigabyte direct address range of the VERSAbus system bus.

Benchmark 20, 020bug, VERSAbus and RAMbus are trademarks of Motorola.

Check □ C for information.



### Get rid of the bits and pieces with all-in-one stepper drive.

It's linear, it's low-cost and it's uniquely capable of handling all the functions to directly drive sustained stepper motor currents up to 1/4 amp per phase without any extra power drivers.

It's the MC3479P and you can hang your entire disc drive, or similar steppermotor-drive application right on it to cut costs, time and space.


Optimized specifically for 2-phase (bipolar mode) steppers used in volume applications, the MC3479P package is a high (150°C junction) thermal dissipation version of the industry-standard 16-Pin DIP, chosen for ease of auto-insertion. Flexible operation controls include full/half step, CW/CCW and a high-impedance braking mode for high-speed microstepping.

All T<sup>2</sup>L-compatible, logic control inputs are provided with 400 mV hysterisis for improved noise immunity. Control logic can be initiated to phase A and a phase A output status indication is provided for track zero indication or other similar applications.

own transient suppression. Built-in diodes in series clamp motor-back EMF for trouble-free performance. It operates from single, +7.2 to +16.5 V and is priced at only \$3.10, 100-999. Step up to low-cost state-of-the-linear art from

The MC3479P carries its

Check □ D for information.



MC680 Target your systems with HDS-200

The HDS-200 microcomputer hardware development station, used in conjunction with the VME/10™, EXORset®, EXORmacs® or EXORciser® software development system, or a personal computer, provides a complete hardware/software development system for the Motorola MC6804, MC68HC04, MC6805, MC68HC05, and MC146805 families of microprocessors.

The HDS-200 is a fully functional substitute for the selected MCU in the target system. By plugging the HDS-200 into the socket of the prototype

hardware, it allows efficient testing of hardware as well as software debugging. It also supplies a powerful list of debugging commands. The easyto-use, plain language commands enable the user to rapidly debug and integrate the target system and produce prototype systems.

WC146805

By bringing the complicated hardware and software development processes together, it becomes economically feasible to test alternate design approaches in order to determine the best solution.

The HDS-200 has been designed to solve the problem of finding precise ROM patterns needed for optimum system performance by emulating the target MCU until its configuration has been fully proven. Changes and tests of the target configuration can be made quickly and easily.

The emulator can be applied and software run prior to availability of hardware. This allows an early start on the debugging process. As hardware changes occur, software updating and debugging is readily accomplished.

In providing systems integration and development, the HDS-200 provides real-time emulation of user code, sixteen prioritized breakpoints, a twolevel help command and user-defined macro commands for quick execution.

The HDS-200 is compatible with the Motorola VME/10 host system and the EXORmacs, EXORciser and **EXORset software development** stations.

EXORmacs, EXORciser and EXORset are registered trademarks of Motorola, VME/10 and HDS-200 are trademarks of Motorola.

Check ☐ E for information.



Convention says bipolar power transistors can't switch above collector-emitter breakdown and last much longer than a microsecond or two.

Ultrafast rectifiers are sweeping that idea away, fast.

By using Ultrafasts as high-speed clamp diodes with sub-nanosecond recovery times, third-generation bipolars are switching rated currents from bus voltages up to bulk breakdown under test conditions. Safely.

A bipolar's sustaining voltage becomes of academic interest if transition turn-on occurs rapidly enough. And it does with Ultrafast rectifiers. Once turned-on, the ability of the transistor to sustain voltage above B<sub>VCEO(sus)</sub> is of little importance, since the objective is to reduce collector voltage as rapidly as possible. The only real concern is safe area. Nanosecond transitions avoid hotspotting phenomena because they just don't

have time to develop. And without damaging hotspotting, bipolars can have considerably more capability than generally perceived. In fact, turn-on SOA up to collector-base breakdown, B<sub>VCEO</sub>, is possible, and designable.

This can have a profound effect on conversion efficiency, cost and the relative merits of bipolars vs. other types of power semiconductors.

Not to mention improvement over "the old way" by a factor of 2, and perhaps more, in amount of power controlled, required base drive and switching speed.

And Motorola Ultrafasts have the specs to do it. The new 4 A, MUR870/880/890/8100 series of 700 to 1,000 V devices in economical, TO-220 packaging is ideal for today's big-power jobs in high-line switching power supplies, inverters, PWM motor controls, solenoid and hammer devices.

They're also available in 1 A, axiallead plastic.

Less than 75 ns recovery times characterize the MUR130/140/150/160 family of 1 A units. Providing 300 to 600 V specs, they complement the MUR430/440/450/460, 4 A types, also in axial-lead.

And, the broadest lineup of its kind now extends to 200 A in the MUR20005CT/20010CT/20015CT PowerTap™ units. The sure-footed, labor-saving package design does away with variables in heatsinking, operates to 175°C and is easier, quicker and more convenient to install than equivalent DO-5s. Cooler, too.

We'll send you data sheets plus an eye-opening article reprint on what we found out about extending bipolar SOA with Ultrafasts.

Check ☐ F for information.


Low power is the difference in these CMOS Quad Line Drivers for telecomm applications.

Two new Motorola CMOS quad line drivers are electrically similar to the popular LM324 and MC3403, but there's a big difference between those standard operational amplifier types and our new MC143403/04.

Typically, the MC143403 draws a tiny  $400\,\mu$  A, and the MC143404 consumes a mere 1.5 mA.

Their characteristics make the MC143403 and 04 appropriate for a broad spectrum of industrial, consumer and instrumentation systems, but of all possibilities there is no question that they are ideal for lowand micro-power telecommunications systems....battery- or phone-line powered.

Both of these CMOS quad line drivers operate over a 4.75 to 12.6 V



range, from either single or split supplies, and provide an 800 kHz typical small signal bandwidth. Four differential input op amps apiece give these devices true differential input stages.

Input impedance is a high 12 megaohms. Maximum input bias is 10

nA. Input offset voltage is 10 mV, typ, and 30 mV, max.

Whether you want samples or production quantities, you order, we deliver. Both devices are the same price of \$1.47, plastic, and \$1.64, ceramic. Check  $\square$  G for information.



# MOD-line fiber optics. Moderate price for moderate performance over moderate distance.



Moderation in all things — and therefore a wise choice for a large middle-ground of applications — characterizes these new fiber optics components.

The emitter/detector pair opens the door to typical 90 MHz performance at low prices for working distances up to 1/2 km, ideal for video transmission, digital computer peripheral interconnects, LAN and industrial controls.

Like standard TO-52 packaging, the small, rugged, plastic units fit into standard AMP, Amphenol, Deutsch, Radiall and similar connectors. Internal lensing enables efficient coupling to 100 micron or larger cable. The

inexpensive cap has high transmission efficiency to IR and low to visible light; and the whole assembly costs less than half that of comparable, metal-and-glass, TO-52 setups.

The MFOE3200 850 nm LED has a 250 micron spot and launches up to  $40 \,\mu\text{W}$  into 100/140 fiber at an If of 50 mA. Distances up to 1,500 feet are easily obtained with 200 micron, NA = .4 cable.

The MFOD3100 PIN detector loafs along with a 200 MHz analog bandwidth. It's compatible with all IREDs including the MFOE3100 in the same efficient plastic package.

# re prices with low-cost, TO-220 zeners. Throttle those surges, spikes and

Check ☐ H for information.

1K up.

Throttle those surges, spikes and high-dollar demands of expensive DO-4s with what Motorola's become famous for — zener diodes and TO-220 packaging.

Moderate prices brighten the eye:

Just \$4.58 for the MFOE3200 LED, and \$4.58 for the MFOD3100 detector,

Suppress transients and

Our family of 10W and 50W MZTseries zener diodes give you everything an equivalent stud package does, except the high price.

All you have to do is think of the \$5-\$7 1N- number in stud packaging, translate to an MZT- prefix for these new TO-220s, and you've got 600 to 1,500W of peak power protection for sensitive communications systems, numerical and process controls, medical equipment, business machines, power supplies and anywhere else for as little as 75¢.

All the rest stays the same: 3.9 V to 200 V ranges, silicon oxide passivated junctions, low zener impedance, fast response, high heat dissipation and the knowledge you're receiving the highest quality and lowest cost in zener diodes. From Motorola, of course. Check 

K for information.

# Volume-production levels of fast 16K SRAM cranked to new highs.

The 2016H is the fastest 2K x 8 SRAM available, but has not always been available in the desired time frames due to the limited number of manufacturers able to offer it.

To help alleviate this shortfall, Motorola has cranked run rates of the 50 and 70 ns versions to the highest levels ever. Now these MCM2016H 16K SRAMS are available through distribution as well as from the factory.

And, in case you may have missed it, be aware that in addition to the industry standard 600-mil wide dual in-line 24-pin packages, Motorola offers a space-saving 300-mil wide

package with all the same pinouts and electrical specs inside. It saves a lot of board space.

Reviewing the part, the MCM2016H is fabricated in our silicon-gate HMOS II process to achieve the low power dissipation of 20 mA in standby, 120 mA active, and access times as low as 45 ns at the same time. The RAM stays in the power-saving standby mode as long as Chip Enable, which controls power down, is held high. Because the 2016H is fully static, no clocks or timing strobes are required.

Check □ I for information.



# MJH6282/11017 bipolar Darlington TO-218 series unique alternative to TO-3.

They're the first in TO-218 packaging to take advantage of what everyone knows is great about plastic TO-218s—lower cost and easier installation. And what's great about bipolar Darlingtons—Motorola sourcing.

It makes sense to save space, cost and time these days with PCB real estate becoming dearer and dearer.

And you can with the MJH- series of NPN/PNP complementary Darlingtons offering up to 160 W of power dissipation, replacing the old reliable, but more costly and hard to mount TO-3 in many sockets. You'll come

out even in performance but way ahead in costs.

Simple, easy to design with and proven reliable, the growing popularity of the TO-218 power package will get its biggest boost from these top performers. They offer orders of magnitude higher gain than discretes, as high as 18,000 at 10 A, switch inductive loads in nanoseconds, operate to 3.75 kVA RBSOA, handle up to 20 A continuous and cost as little as \$2.50 each.

Pricing ranges from \$2.50 to \$3.50 for the MJH6282 series and \$4.40 to

\$6.32 for the MJH11017 series — both in 100-up quantities.

Complementary Darlingtons afford the equivalent of 10 circuit components in two packages. And being complementary you can use them in pairs in audio amplifiers.

And go from milliamperes to amperes directly, compatibly, easily using IC-driven supplies.

Driver, output device, base-emitter resistors and output diode are all on one monolithic chip in one package.

And more efficient packaging equals lower price paid. Less is more with Motorola TO-218 Darlingtons.

Check  $\square$  L for information.

# Support MC68020 Development with HDS-400



The HDS-400™ microprocessor hardware/software development station provides low-cost emulation for the complete line of Motorola M68000 microprocessors including the 32-bit MC68020 MPU. The HDS-400, used in conjunction with a Motorola EXORmacs® development system, VME/10™ microcomputer system or a DEC VAX™ computer, provides tools for debugging and analyzing microprocessor system performance for both hardware and software.

The MC68020 emulator/analyzer uniquely combines the HDS-400

emulator module and the BSA personality module functions into a single enclosure, with a single cable/probe assembly to connect to the target system.

In addition to supporting higher clock speeds, the MC68020 emulator/analyzer gives unrestricted use of the full 4G-Byte available address space. Up to 16 breakpoints can be set in target RAM or emulation memory, even while the 4 longword instruction/data cache in the MC68020 is enabled.

An optional real-time bus state analyzer (BSA) may be integrated into the HDS-400, with personality modules to support each processor in the emulator system. Complex breakpoints and operation speeds up to 20 MHz with one wait cycle are supported by the real-time bus state analyzer with the MC68020 emulator/analyzer module.

With a processor-specific emulator, the critical functions and locations within the microprocessor can be

observed, greatly enhancing the efficiency of system debugging and shortening the product development cycle. Emulators for the MC68000, MC68008, MC68010 and the MC68020 allow designers access into the memory, CPU and registers of the microprocessor for debugging purposes.

The HDS-400 provides emulation for clock speeds of 12.5 MHz for MC68000 MPUs, 8 MHz for the MC68008 and the MC68010 and 16.67 MHz for the MC68020 allowing you to get to market faster with faster speeds.

Added MC68020 development ability proves that the HDS-400's versatility protects against obsolescence.

VAX is a trademark of Digital Equipment Corporation. HDS-400 and VME 10 are trademarks of Motorola Inc.

EXORmacs is a registered trademark of Motorola Inc.

Check ☐ M for information.



# MPX2050 transducer takes own temperature, keeps calm under pressure.

Stability without complexity best sums up the advantage of the unique new 0-7.5 psi MPX2050 pressure sensor family from Motorola.


Offering the industry monolithic, on-chip temperature compensation for the first time, the silicon piezoresistive transducer offers the designer an all-in-one chip combining computer-controlled, ion-implanted, laser-trimmed resistors with the high linearity, accuracy and ease-of-use Motorola's MPX- family has become renowned for.

Result of all this technology: an easier, lower-cost design job for you.

Stable and accurate, the MPX2050 utilizes the same, single-element, design used extensively in automotive, industrial and medical applications. Nominal output is set at 40 mV with 10 V supplied, more than sufficient for driving external measurement and circuitry.

Variation of pressure offset over temperature is just  $\pm$  1 mV.





Temperature effect on span is within 2% of full scale over  $a - 40^{\circ}$  to  $+125^{\circ}$  C operating range.

You can snap it into the economical, Motorola-developed, pressure-port housing that provides you with mounting flexibility and barbed hose connections.

Plus it's easy to mount (standard, 100-mil spacing), easy to connect (hoses slip right on), easy to customize (build your own ports), easy to measure (up to 90 mV output) and easy to apply. Easy to forget, too — years of use with no maintenance.

You don't have to recalibrate when replacing or interchanging, either. It's perfectly repeatable, unit to unit, device to device.

Prices are comparable to devices without temperature calibration so what are you waiting for? Send for data and see it do its own thing for you under pressure, easily.

Check □ N for information.

Coupon missing? Get information on any of the advertised products and systems by contacting your Motorola sales office or authorized Motorola distributor, or by writing Literature Distribution, Motorola Semiconductor Products Inc., P.O. Box 20912, Phoenix, Arizona 85036.

To: Motorola Semiconductor Products Inc., P.O. Box 20912, Phoenix, AZ 85036

### Motorola Reports

	ase send me information on:  A. MCM6257 256K DRAM
-	
	B. Dual optointerrupters
	C. Benchmark 20
	D. MC3479P stepperdrive
	E. HDS-200 development station
	F. Ultrafast rectifiers
	G. MC143403/04 Quad Line Drivers
	H. MOD fiber optics
	J. MCM2016H SRAM
	K. TO-220 Zeners
	L. Bipolar Darlingtons
	M. HDS-400 development station
	N. Pressure transducer
Th	is Coupon valid until June 3, 1985

Name	
name	
Title	
Company	
address	
City	
State	Zip
Call me. Phone	

# ROCKWELL SEMICONDUCTOR TECHNOLOGY CREATES THE NEXT GENERATION OF INTEGRAL MODEMS.

Our third-generation VLSI capabilities give you support at any level.

Building modems
into your product
line used to be a
complicated and
costly process. But
Rockwell International's
latest generation of VLSI
integral modems is changing all that

Today, our VLSI capabilities mean that we can support your design requirements at any level: you can order VLSI chip sets; standard cards with all data rates interchangeable; or custom cards designed to fit your specific shape, connector and software integration requirements.

In fact, we can offer a simple, economical solution to virtually any application requirement from 1200 to 9600 bps. Since our modems include both a microprocessor bus and an RS232C interface, they can be easily designed into computers, from micros to mainframes; plus G2-G3 facsimile machines, multiplexers, terminals and, of course, box modems.

What's more, Rockwell is the only supplier of fullduplex, dial 2400 bps VLSI integral modems. And all of our modems are as reliable as they are versatile. Based on our customers' experience with over a half million Rockwell integral modems in use around the world, we've been able to document an MTBF of 200,000 hours—nearly 23 years between service calls. Performance-wise, transmission is virtually error-free

over unconditioned or dial-up phone lines because our integral moderns offer auto-adaptive equalization.

We are the world's largest supplier of high-speed modern subsystems and devices. Ask your sales representative or distributor for a quote today, and you'll see that we have a distinct advantage in price and delivery lead times, too.

Rockwell integral modems. A generation ahead of all the rest.

### Rockwell Semiconductor Products Division

Rockwell International, P.O. Box C, MS 501-300, Newport Beach, CA 92660. Call toll free (800) 854-8099. In California: (800) 422-4230.



**Rockwell International** 

where science gets down to business

# Pilot Light.



The new Vivisun 20/20 switches make a pilot's mission safer by night and easier by day. A unique optics system eliminates the veiling glare and halo effect that would interfere with ANVIS night vision goggles. When voltages are trimmed to night vision goggle flying levels, Vivisun 20/20 switches can still be read with the unaided eye.

During the day, Vivisun 20/20 switches are readable in direct sunlight and deadface when not energized. They are also easy to install and have the lowest touch temperature and widest viewing

angle in the industry. Clearly, no other Mil-Spec switch can match it. And you can specify your Vivisun 20/20 switches with these options: Dustproof/Dripproof • Split Ground • P.C. Termination • EMI. For more information, write, phone or telex today.



#### AEROSPACE OPTICS INC.

3201 Sandy Lane, Fort Worth, Texas 76112 (817) 451-1141 • Telex 75-8461



MIL-S-22885/90

VISUN 20/20

# **U.S. MEETINGS**

IEEE First International Conference on Office Automation, Dec. 17–19. New Orleans Hilton, New Orleans, La. IEEE First International Conference on Office Automation, c/o Dr. Donald Kraft, Department of Computer Science, Louisiana State University, Baton Rouge, La. 70803; (504) 388-1495

1985 International Winter Consumer Electronics Show, Jan. 5-8. Las Vegas, Nev. Dennis Corcoran, CES, 2001 Eye St. NW, Washington, D.C. 20006; (202) 457-8700.

PC Fab Expo '85, Jan. 8-10. Sheraton Twin Towers Hotel, Orlando, Fla. Julia Wilson, PMS Industries, 1790 Hembree Road, Alpharetta, Ga. 30201; (404) 475-1818.

Automated Test Equipment West Conference (ATE), Jan. 14–17. Anaheim Convention Center, Anaheim, Calif. Morgan-Grampian Expositions Group, 2 Park Ave., New York, N.Y. 10016; (212) 340-9780.

Caldon West '85, Jan. 14-17. Anaheim Convention Center, Anaheim, Calif. Morgan-Grampian Expositions Group, 2 Park Ave., New York, N.Y. 10016; (800) 782-0009.

1985 Measurement Science Conference, Jan. 17-18. Marriott Hotel, Santa Clara, Calif. Darlene Diven, Lockheed Missiles and Space Co., PO Box 3504, Sunnyvale, Calif. 94088; (408) 756-0270.

**Uniform, Jan. 21–25.** Infomart, Dallas, Texas. Pemco, Inc., 2400 E. Devon Ave., Suite 205, Des Plaines, Ill. 60018; (800) 323-5155.

1985 Society for Computer Simulation (SCS) Multiconference, Jan. 24–26. Bahia Hotel, San Diego, Calif. SCS, PO Box 2228, La Jolla, Calif. 94038; (619) 459-3888.

Communication Networks Conference and Exposition, Jan. 28-31. Washington Convention Center, Washington, D.C. Louise Myerow, CW/Conference Management Group, 375 Cochituate Road, PO Box 880, Farmingham, Mass. 01701; (617) 879-0700 or (800) 225-4698.

4th International Symposium on Semiconductor Processing. Jan. 28-31. San Jose, Calif. Dinesh Gupta, Siliconix Inc., 2201 Laurelwood Road, Santa Clara, Calif. 95054; (408) 988-8000 or Thomas Kochaba, ASTM, 1916 Race St., Philadelphia, Pa. 19103; (215) 299-5560.

Mini/Micro West, Feb. 5–7. Anaheim Hilton Exposition Center, Anaheim, Calif. Electronics Conventions Management, 8110 Airport Blvd., Los Angeles, Calif. 90045; (213) 772-2965.

Conference on Optical Fiber Communication (OFC '85), Feb. 11-13. Town and Country Hotel, San Diego, Calif. Optical Society of America, 1816 Jefferson Place NW, Washington, D.C. 20036; (202) 223-8130.

IEEE International Solid-State Circuits Conference, Feb. 13-15. New York Hilton Hotel, New York, N.Y. Lewis Winner, ISSCC, 301 Almeria, Coral Gables, Fla. 33134; (305) 446-8393.

Integrated Machine Loading/Material Handling Systems Seminar, Feb. 19–21. Holiday Inn Livonia-West, Detroit, Mich. John R. McEachran, SME, 1 SME Drive, PO Box 930, Dearborn, Mich. 48121; (313) 271-1500, Ext. 382.


Automated Design and Engineering for Electronics Conference and Exhibition (ADEE), Feb 26–28. Anaheim Hilton and Towers, Anaheim, Calif. Cahners Exposition Group, Cahners Plaza, 1350 E. Touhy Ave., PO Box 5060, Des Plaines, Ill. 60018; (312) 299-9311.

Nepcon West '85, Feb. 26–28. Convention Center, Anaheim, Calif. Nepcon West '85, 1350 E Touhy Ave., Des Plaines, Ill. 60018; (312) 299-9311.

American Institute for Design and Drafting (AIDD) Exposition, March 3–8. Albert Thomas Convention Center, Houston, Texas. Philip Nowers, AIDD National Headquarters, 901 N. Washington St., Suite 509, Alexandria, Va. 22314; (703) 548-1263.

(continued on p. 29)


### MICRO POSITIONERS FOR MICRO ELECTRONICS



### Programmable, Repeatable, Ultra-High Precision.

- Full range of computer compatible linear, vertical and rotational positioners.
- X, X-Y, X-Y-Z modes with rotation.
- 0.1µ linear accuracy; 0.001° angular resolution.
- Ideal for wafer probing, dicing, scribing, resistor trimming, mask alignment and thick or thin film measurement.
- Computer controlled indexer provides full logic and drive input for unerring repeatable accuracy.
- Versatile design permits use for electronic and electro-optical applications.

Model CC1 Programmable Controller.



Send for Catalog 584.

SCIENTIFIC

110-20 Jamaica Avenue Richmond Hill, NY 11418 (212) 846-3700

CIRCLE 15

# EDI's Megabit DRAM

If memory density is a major concern, there is an even better solution than the new 256K monolithics.

### EDI's 256K Based Modules

Part #	Config.	Package	
41512	512x1	18 pin DIP*	
411M	1Mx1	22 pin SIP	
44256	256x4	22 pin SIP	

\*300 mil

EDI's Megabit DRAMs, in 22 pin SIPs, give you a greater than 4:1 space advantage over 256K monolithics. And you can have it now in 1Mx1 and 256Kx4 configurations.

CIRCLE 16

A pioneer in high density packaging techniques, Electronic Designs Inc. is

continuing to meet the requirements of advanced memory design.

If you need tomorrow's high density memory, whether DRAM, SRAM, or EPROM; commercial, military or custom, EDI has the solution . . . today.

For more information contact:

### **ELECTRONIC DESIGNS**



### U.S. MEETINGS

(continued from p. 27)

Interface '85, March 4-7. Georgia World Congress Center, Atlanta, Ga. The Interface Group Inc., 300 First Ave., Needham, Mass. 02194; (617) 449-6600.

Southcon '85 and Mini/Micro Southeast, March 5-7. Georgia World Congress Center, Atlanta, Ga. Electronic Conventions Management, 8110 Airport Blvd., Los Angeles, Calif. 90045; (213) 772-2965.

Integrated Services Digital Networks Exposition (ISDN '85), March 6-8. Bally's Park Place Casino Hotel, Atlantic City, N.J. Joan Barry, Information Gatekeepers Inc., 214 Harvard Ave., Boston, Mass. 02134; (617) 232-3111.

1985 ACM 13th Annual Computer Science Conference (CSC), March 12-14. New Orleans Marriott Hotel, New Orleans, La. Della T. Bonnette, Computing & Information Services, University of Southwestern Louisiana, Lafayette, La. 70504; (318) 231-6306.

Picosecond Electronics and Optoelectronics Meeting, March 13–15. Hyatt Lake Tahoe, Incline Village, Nev. Optical Society of America, 1816 Jefferson Place NW, Washington, D.C. 20036; (202) 223-8130.

International Computer and Telecommunications Conference (Comtel '85), March 18–20. Infomart, Dallas, Texas. Comtel '85, 5080 Spectrum Drive, Suite 707E, Box 17, Dallas, Texas 75248; (214) 631-6482.

Robotic End Effectors: Design and Applications Seminar, March 19-20. Holiday Inn Livonia-West, Livonia (Detroit), Mich. John McEachram, SME, 1 SME Drive, PO Box 930, Dearborn, Mich. 48121; (313) 271-1500, ext. 382

Second Annual International Conference on Artificial Intelligence for Robotics, March 21–22. Stouffers Concourse, Crystal City, Arlington, Va. Dr. Diener, IIT Research Institute, 10 W. 35th St., Chicago, Ill. 60616; (312) 567-4376.

1985 Trends and Applications Conference, May 21-22. Sheraton NW Washington, Silver Spring, Md. Mark Skall, National Bureau of Standards, Room A265, Technology Building, Gaithersburg, Md. 20899; (301) 921-2431.





### one-piece design defies rough handling

### Check these features:

- ✓ Each unit undergoes high-impact shock test
- ✓ Available from 1 to 40 dB
- ✓ DC to 1500 MHz
- √ Unexcelled temperature stability, .002 dB/°C
- ✓ 2W max. input power (SMA is 0.5W)
- ✓ BNC, SMA, N and TNC models
- ✓ Immediate delivery, 1-yr. guarantee

Precision 50-ohm terminations ... only \$6.95 (1-24) DC to 2 GHz, 0.25W power rating, VSWR less than 1.1 BNC (model BTRM-50), TNC (model TTRM-50) SMA (model STRM-50), N (model NTRM-50)

> finding new ways. setting higher standards

A Division of Scientific Components Corporation
World's largest manufacturer of Double Balanced Mixers P.O. Box 166, Brooklyn, New York 11235 (718) 934-4500 Domestic and International Telex 125460 International Telex 620156

CIRCLE 18

C 92 REV. A

#### over Freq. Range (Typ.) DC-1000 1000-1500 DC-1000 MHz 1000-1500 MHz DC-1500 MHz ±0.3 0.6 0.8 1.3 \*DC-1000 MHz (all 75 ohm or 30 dB models) DC-500 MHz (all 40 dB models)

Atten. Change, (Typ.)

### MODEL AVAILABILITY

Model no. = a series suffix and dash number of attenuation.

Example: CAT-3 is CAT series, 3 dB attenuation.

■ denotes 75 ohms; add −75 to model no

• denotes 50 ohms

ATTEN	SAT (SMA)	CAT (BNC)	NAT (N)	TAT (TNC)
1	•	•	•	•
2	•			
3	•		•	•
4	•			
5	•			
6	•	• =	•	•
7	•			
8	•			
9	•			
10	•	•=	•	•
12	•			
15	•			
20	•	•	•	•
30	•	•	•	•
40	•	•	•	•

PRICING (1-49 qty.): CAT (BNC)..\$11.95, SAT (SMA)..\$14.95 TAT (TNC)..\$12.95, NAT (N)..\$15.95

## **P**ERSONALLY SPEAKING

# Thin-film technology will redefine limits of Winchester disks



■hin-film technology may well be the best way to stay the growing appetite for external memory that plagues personal computers, high-resolution graphics workstations, local network file servers, and the host of other equipment that works with hard disks. Thus developing new approaches to disk coatings and head assemblies are top priorities for computer peripheral designers. Indeed, within the next two years we'll see many 5½- and 3½-in. disks turn from their current oxide coatings to sputtered or plated thin films. Further, thin-film heads by then will have begun to replace their conventional ferrite counterparts. Estmates have it that by the decade's end thin-film technology will drive disks' areal density from a present high of 10 Mbits/in.<sup>2</sup> to a whopping 50 Mbits/in.<sup>2</sup>—or

As always, there is at least one fly in the ointment: Thin-film deposition—particularly sputtered coating—is in short supply. Moreover, thin-film heads are notoriously difficult to mass-produce. Consequently, the changeover will have to be taken in two steps.

The initial move will be seen in coatings, but it's still unclear whether plated or sputtered surfaces will capture the lion's share of the new designs. Based on many of the drives scheduled for 1985, sputtering looks to be taking the lead. Plating is a wet process, so its yield is inherently lower than sputtering's. And sputtering appears to be the more controllable of the two approaches.

Hewlett-Packard, working with a 3½-in. 10-Mbyte Winchester disk, found that sputtering produced higher and more consistent yields. On the other hand, NEC, which has been going with plating for many years, says it

is still counting on mixing plated coatings and thin-film heads in its 1986 Winchester drives.

The second phase of the conversion, which should be well under way by 1988, demands that several challenges be met. The titanium carbide wafers that are used in thin-film heads are more difficult to work with than the silicon traditionally employed for semiconductors. All of the head's magnetic elements—coils, head arm, and slider—must be laid down on the wafer. Finally, very tight control of the head gap is crucial.

The move to thin-film technology carries another benefit: It guarantees that magnetic disks will be with us for some time to come. They have already survived challenges from alternative technologies—most notably magnetic bubbles and charge-coupled devices. And other developments should lock up their future, such as vertical recording and the work proceeding in VLSI to consolidate all of the electronic control circuitry.

Mortin Gold.

Martin Gold

# "Standard cells but I must be



## offer VLSI benefits, sure they'll work."

With Texas Instruments, you are.

Why? Because we commit to deliver standard-cell ICs that perform to your specifications.

Because TI's Standard Cell Integration System is carefully structured for producing functional prototypes on the first pass within minimum cycle time.

Because TI's 20 years of experience in IC design and fabrication are your assurance you will get what you want when you want it.

How? With TI's advanced design system incorporating comprehensive checkpoints, familiar TTL design rules, and convenient, in-depth support.

#### We do it right the first time

TI insists on multiple simulation and verification steps throughout the standard-cell design flow. They are the means by which we check and double-check the accuracy of your logic design and our implementation of it. They are one of our methods for doing it right the first time.

Finalization of your logic schematic involves simulation, testability analysis, test-pattern generation, and test-pattern grading. This can be done by TI or by you, using your in-house design tools or the computers at your nearest TI Regional Technology Center.

Chip layout can also be done by you using TI-provided specifications or by TI.

Following layout, TI performs a post-routing simulation which ensures that your performance specification is met. A schematic verification determines that your functional specification is met. And a design-rule verification makes sure that all geometric design rules are met.

The final simulation becomes, upon your approval, the benchmark by which all prototype units are tested.

The prototypes are shipped to you for in-system evaluation. At your go-ahead, we produce and deliver, typically within 8 to 12 weeks.

27-4980 ©1984 TI

#### Familiar design rules build confidence

TI's 3-µm CMOS standard-cell technology is as easy as TTL. You simply interconnect familiar SN54/74 functions using traditional methods.


You have the standard digital functions, as well as RAM, ROM, PLA, ALU, and linear functions. Design-for-test cells are included in the TI library to ensure thorough testability for each design. All cells are characterized over commercial and military temperature ranges.

As for your schematic, it can be hand-drawn on paper or generated by an engineering work station. Tl's standard-cell library is supported on leading work stations, such as Daisy, Mentor, and Valid, as well as on several PC systems. And TI supplies the translation software for automatic generation of the TI design-description language.

Rely on your Regional Technology Center for help

Each TI Regional Technology Center has on staff standard-cell specialists who will

Simulations and verifications performed by TI throughout the standard-cell design cycle help assure first-pass success.



CIRCLE 43

provide technical assistance, training, and guidance in TI standard-cell design procedures. Each Center is also equipped with the hardware and software tools you will need to complete your design.

You get results that pay off

TI's determination to do it right the first time is your assurance you will receive semicustom ICs that perform to your requirements. Doing it right the first time saves time and money, in addition to the savings you get with VLSI technology: Significantly fewer parts, because one standard-cell IC is the equivalent of hundreds of individually packaged chips. Reduced system weight, size, and power consumption. Lower assembly costs. Improvements in system capability, reliability, and quality.

When you team up with TI, we'll take into consideration the impact of all these factors on your system design in confirming that standard-cell ICs—or an alternate semicustom approach such as gate arrays—are best for you.

#### Call 1-800-232-3200, Ext. 105

Many more reasons for confidence in Texas Instruments as your standard-cell design partner are given in our brochure and detailed description of the design process. For copies of these, as well as our pocket selection guide and sample data sheets, call the telephone number above or circle the Reader Service Card number. Or write Texas Instruments Incorporated, Dept. SRS023E1, P.O. Box 809066, Dallas, Texas 75380-9066.



Creating useful products and services for you.

#### EASY ON.



## Sprague Type 195D TANITE® Tantalum Chip Capacitors can now be surface mounted automatically as easily as ceramic chip capacitors. They're supplied taped on either 8 mm or 12 mm reels for automatic placement and attachment to printed wiring boards or

extending from each chip identifies the positive terminal. Ideal for leadless applications, these space savers come in seven physical sizes. Capacitance values range from  $0.1 \,\mu\text{F}$  at 50 WVDC to  $100 \,\mu\text{F}$  at 4 WVDC. Write for

Engineering Bulletin 3539B to Technical Literature Service, Sprague Electric Company, a Penn Central unit, 347 Marshall St., North Adams, Mass. 01247.

SPRAGUE SPRAGUE

hybrid-circuit substrates. The tantalum wire nib

CIRCLE 19

#### **N**EWSPULSE

#### 32-bit CMOS microprocessor chalks up 5 MIPS

he new generation of 32-bit microprocessors will take a giant leap in speed with a CMOS chip that draws on a proprietary multitasking, multiprocessing architecture to execute an unprecedented 5 million instructions/s. Now in development at Hitachi Ltd.'s Central Research Laboratories (Tokyo), the chip, built with 1.3-µm design rules, packs demand-paged virtual-memory management, ROM, and RAM into 6.5 by 5.9 mm. Besides being code-compatible with the 68000-and as such, with existing 68000-based peripherals—it will run under Unix 4.2 and accept programs written in Pascal, C, and Fortran. Initial specifications for the chip, which will be housed in a surface-mounted package with more than 100 pins, spell out a clock rate of 20 MHz, a cycle time of 50 ns, and power consumption of 500 mW. First samples should appear some time in 1986.

#### Custom designs and fuse-programmable logic team up

Programmable logic devices normally do not fit into custom circuit design, but the combination of a high-level logic programming language and a sophisticated engineering workstation changes that situation. Valid Logic Systems Inc. (San Jose, Calif.) has bolstered its SCALDsystem I, II, and IV workstations with logic design software based on the Abel language, which was originally devised by Data I/O Corp. (Redmond, Wash.) for programming all types of fuse-programmable logic. Workstation users can now design fuse maps for programmable logic devices at the same time they enter the schematic, verify the timing, and simulate the logic of complex circuits. Abel actually does the job of compiling Boolean equations, truth tables, and state diagrams into fuse maps for any type of programmable logic, including PALs and PROMs.

#### 1/2-in. tape committee tackles serial recording

ome of the confusion over ½-in. tape cartridges may be resolved when an ad hoc standards committee rolls into action. As part of its charter, the HI/TC working group will define a serial recording format, as well as a device interface, for tape drives using the recently released IBM 3480 cartridge. The parallel recording scheme now used by the IBM drive is considered by some to be impractical for small computer systems. Among the companies represented in the committee are Computer Peripherals (a subsidiary of Control Data), Kennedy, Pertec Peripherals, Wangtek, and Xebec.

#### First silicon for transputer gets a complete checkup

he 32-bit transputer chip has not only seen the light of day but is now being tested. The T424, which is 85 mm<sup>2</sup> and contains more than 250,000 transistors, is getting the once-over at Inmos Corp. (Colorado Springs, Colo.). The company plans to have an evaluation board ready by midyear, by which time a full-fledged software development system—including compiler, debugger, and

#### **NEWSPULSE**

operative system—should be ready. Fabricated with a 2-\mu twin-well CMOS process, the chips internal memory has a cycle time of 50 ns. The transputer's sister chip, the 16-bit T222, is expected to appear in silicon within a few months.

#### DOD's software engineering institute finds a home


he U.S. Department of Defense's STARS (Software Technology for Adaptable Reliable Systems) project has taken an important step with the choice of Carnegie-Mellon University (Pittsburgh, Pa.) as the academic mentor for its proposed software engineering institute (Electronic Design, March 3, 1983, p. 49). As an essential component of the STARS initiative, the institute will develop a showcase software design environment. Niko Haberman, who presides over Carnegie-Mellon's computer science department, is expected to serve as the institute's acting director.

#### Ada compiler for Unix, Ultrix systems makes the grade

ollowing an exhaustive series of tests, the first commercial Ada compiler for ■ the VAX-11/700 series has been validated to comply with MIL-STD-1815A (identical to the ANSI Ada specification). The compiler, developed by Verdix Corp. (McLean, Va.), is meant for 11/700s running under Unix 4.2 BSD or Digital Equipment's Ultrix operating system. It was tested on a VAX—fitted with virtual memory—that executes 1 million instructions/s. The compiler processed about 1000 Ada statements a minute and cut through compiled code at 20,000 statements a minute. To facilitate developing programs, the compiler comes with library maintenance utilities, an error processor, a prelinker, and a symbolic debugger. The whole package, dubbed VADS (Verdix Ada Development System), needs about 1 Mbyte of physical memory to turn in its best performance.

#### Occam compiler works in Pascal machines

oving into mainstream computing, a single-pass Occam compiler produces up to 2000 lines of code per minute on any computer that can compile Pascal. The recursive program, developed by researchers at Brunel University (Uxbridge, Middlesex, England), compiles p-code for a stack machine. An interpreter then runs that code to simulate concurrent execution of up to 64 processes, switching from one process to another after every Occam statement. The compiler and interpreter both are written in Pascal.



#### ONE LOGIC PROGRAMMER.

When it comes to choosing the right programmable logic device for the right job, you should be the one to choose. Not your logic programmer.

That's why Data I/O's Programmable Logic Development System now supports more than 150 different logic devices from more than seven different semiconductor manufacturers—including the new CMOS logic and 32R16 Mega PALs®.

That's what we call choice. And you call freedom.

#### Logic design made easy.

Taking advantage of programmable logic has never been easier, especially with ABEL™, Data I/O's high-level design language.

ABEL turns your IBM® PC or VAX™ into a powerful logic design center, letting you express your designs in Boolean equations, truth tables, state diagrams or any combination... whatever works for you.

#### **Full-support options.**

Data I/O PLDS programming/ test adapters give you many device support choices. Bipolar, CMOS, new technologies and packages, PAL or IFL—you choose what you need today and ex-

#### Functional testing.

pand support tomorrow.

Three-step testing ensures

your programmed devices are functioning correctly. An automatic fuse verify confirms all fuses have been programmed as specified. A structured vectors test compares actual device output with expected results. And Data I/O's unique Logic Fingerprint™ test compares signatures of newly programmed logic devices with those of known-good masters.

#### Call toll-free 1-800-426-1045 for a demo or details.

If you're an engineer who likes to make choices, make your first choice a Data I/O.

CIRCLE 20

ABEL™ and Logic Fingerprint™ are trademarks of Data I/O Corporation, and VAX of Digital Equipment Corporation. IBM is a registered trademark of International Business Machines and PAL™ of Monolithic Memories, Inc.

Data I/O Corporation, 10525 Willows Road N.E., P.O. Box 97046, Redmond, WA 98073-9746. For immediate action, contact us directly, **CALL TOLL FREE**: 1-800-426-1045. In Washington, Alaska and Hawaii, call 206-881-6444. Europe: Vondelstraat 50-52, 1054 GE, Amsterdam, The Netherlands, Tel: (20) 186855. Germany MBH: Bahnhofstrasses 3, D-6453 Seligenstadt, West Germany, Tel: (6182) 3088. Japan: Ginza Orient Building 6-F, 8-9-13, Ginza Chuo-ku, Tokyo 104, Japan, Tel: (03) 574-0211.

DATA I/O

#### Announcing...

## A complete front-to-back your electronic design

### Now the price/performance leader in Printed Circuit Board CAD offers an advanced CAE Workstation—The CDX-9000.

Cadnetix now provides a design automation tool for every member of your design team. The CDX-9000 Workstation—Cadnetix proprietary hardware with all electronics built into one compact monitor housing. The Cadnetix Logic Design and Verification System—a complete design analysis package, with hierarchical schematic design, the CADAT<sup>TM</sup> 12-state logic simulator, a SCALD-based timing analyzer and a comprehensive technical publications package. And for program development, an open architecture and Berkeley 4.2 UNIX<sup>TM</sup> with a C compiler.


Together, the CDX-9000 CAE Workstation and the CDX-5000 Printed Circuit Board CAD Workstation provide a comprehensive electronic design tool set.

#### Error-free design is the goal and the Cadnetix tool set makes it feasible.

Start with flexible component creation and comprehensive component libraries. Add full support for hierarchical schematic design and a simulator that allows you to verify any portion of your design, at any stage of development. Automatic revision control and library management features ensure that you are always working with current versions of components and schematics. And, to keep your designs on track, the system has automatic forward and back annotation between the schematic and PCB designs and among all nodes in the network.

#### You are on the leading edge with the innovative Graphic Waveform Editor.

Cadnetix has significantly advanced simulation technology with a unique graphic approach. Simulator inputs are created graphically — output signals generated during execution are viewed graphically — and can be edited for use as inputs to



## solution for team.



other portions of your circuit design. No coding or repetitive textual input of data is required. The display format is familiar and easy-to-use, because it closely resembles a logic analyzer. And the waveform display can be used to view and edit outputs from any type of logic simulation.

#### Still the leader in PC board layout.

Think of the toughest PC board layout problem you've come up against. With the Cadnetix system, you can handle it. And with an ease of interaction that first time Cadnetix users find frankly unbelievable. You get fully automatic placement and routing. We support surface mount components, analog devices, and the upcoming fine-line geometries. In short, in one compact workstation, we give you more power and ease of use than anyone else in the market.

#### Tightly-coupled CAE/CAD in one practical, high-performance electronic design solution.

A total solution to your problem. Schematic entry, design verification and PC board layout in one easy-to-use system. The Ethernet™ Network and Cadnetix File and Peripheral Servers

to tie system resources together. And forward and back annotation to protect the integrity of your design. With proprietary Cadnetix hardware and the user-interface that made us famous, your imagination is the only limit to your design. And Cadnetix offers the workstation options (color or black & white) that you need to suit your design schedule and your budget.

need to suit your design schedule and your budget.
To find out more, call or write today. Cadnetix, 5757 Central
Ave., Boulder, CO 80301 (303) 444-8075.


CIRCLE 21



5757 CENTRAL AVENUE • BOULDER, CO 80301 • (303) 444-8075

CADAT is a trademark of HHB SOFTRON, Inc.
UNIX is a trademark of AT&T BELL LABORATORIES.
ETHERNET is a trademark of XEROX CORPORATION.

08406



## Choose Your Weapon.

When bugs attack, it's kill or be killed. You have to strike fast. Or your project ends up on the casualty list.

That's where we come in. Gould Biomation logic analyzers. The heavy artillery, if you will. The only analyzers to earn the reputation for helping you take on the toughest, deepest, most critical logic problems.

And now you can go to battle with the right weapon in hand.
Because we're supplying the whole

arsenal. Including the K205. A brand new analyzer that's unrelenting in its search to capture enemies of gate array, bit-slice and discrete circuit logic. And which, by the way, is easy to arm and use.

So bring your arms to bear. Check the weapon you're interested in. Then tear out the page, attach your business card and send it to our headquarters.

We'll fire back more information before the dawn's early light.



processor analyzer.

Provides the speed and width you need. Plus hardware/software integration tools. Noise margin analysis and tolerance compare.

Sophisticated triggering and microprocessor disassemblers.



that's faster than the system you're designing. Races along at 500MHz! For very high speed mainframe logic design.




K205. Our newest.
With Auto Save and
Tolerance Compare functions.
Plus more than enough
100MHz channels for in-depth
analysis of discrete logic.



standard general purpose analyzer, now with T12 remote communicator. Allows off-site remote diagnostics.


Gould Inc., Design & Test Systems 4650 Old Ironsides Drive Santa Clara, CA 95054-1279 Call toll-free (800) 538-9320. In California, call (800) 662-9231.







## Precise Time Measurements — Variable signal delay permits display of true time relationship between 2 signals. System: 7104 with two 7A29 1 GHz Amplifiers and 7B15Δ Delaying Time Base.



Logic Triggering — displays digital signals in true analog form for high-resolution time and amplitude measurements. System: 7104 with 7A42 Logic-Triggered Vertical Amplifier.



X-Y Phase Measurements — Phase matching to 250 MHz enables direct, wide bandwidth phase shift measurements with high degree of accuracy. System: R7103 with two 7A29 1 GHz Amplifiers.



Microchannel Plate CRT normalizes intensity so both low and high rep rates can be viewed simultaneously. System: R7103 with 7A29 1 GHz Amplifier, 7B92A Dual Time Base.

## Widest bandwidth, highest writing rate, most versatile oscilloscope in the world.

The Tek 7104 and rackmount R7103 are practical in more ways than you might expect. It is often the unexpected that makes their 1 GHz bandwidth, 20 cm/ns writing speed and configurability so valuable to R&D.

Those elusive pulses, glitches and single-shot events that only the 7104 can display are enough to make it the most practical oscilloscope you can buy.


The 7104's microchannel plate CRT achieves a writing rate (brightness) 1000 times that of conventional scopes—so you

can substitute direct observation for laborious, deductive measurement techniques.

Tek 7000 Series plug-ins let you continually reconfigure your system to match your current needs. Add the 7A29 Amplifier for maximum bandwidth to 10 mV/div. Add the 7D15 Universal Counter/Timer for time, period, width and frequency measurements to 225 MHz. Add the 7B10 Time Base for 200 ps/div maximum sweep speed. Or see the analog characteristics of high-speed digital signals with the 350 MHz, 4channel 7A42 Logic-Triggered Vertical Amplifier. And much more.

And now, with the new R7103 rackmount version, the world's highest bandwidth, highest writing rate oscilloscope is more versatile than ever.

Contact your local Tek Sales Engineer for a personal demonstration of the 1 GHz system you configure yourself. For the name of the Tek sales office nearest you, and for a free poster illustrating the Tek 7000 Series concept, call tollfree (800) 547-1512. In Oregon, (800) 452-1877. Or TWX 910-467-8708. TLX: 151754. In Oregon, call 1-800-452-1877.



Single Shot Measurements
—unmatched writing rate of
20 cm/ns provides bright
display even at 200 ps/div.
System: R7103 with 7A29
1 GHz Amplifier, 7B10 Time





Only Harris offers telecom designers a full spectrum of SLICs, CODECs and filters you can count on. Because we know that the difference between a successful loop installation and a lost customer can be traced to circuit reliability and consistency.

A comprehensive line of ICs—high-voltage PBX SLICs, low-voltage/low-power CMOS CODECs, filters, and COMBOs—gives you the Harris competitive edge throughout the subscriber loop.

Superior SLICs.

Harris SLICs combine many of the BORSHT functions on a single, dielectrically isolated chip: battery feed, overvoltage protection (with external components), ring relay driver, supervisory, and hybrid functions. Rugged enough to perform reliably in your most demanding loop environments, Harris SLICs are perfect for solid-state line interface circuits for analog or digital PBX/central office systems, replacing bulky transformer and hybrid systems.

Championship CODECs.

Featuring a fully TTL-compatible interface, Harris PCM CODECs incorporate on-chip precision voltage reference, auto-zero circuit, and sample-and-hold capacitors. Use them for PCM coding/decoding in digital PBX and central office telecom switching systems.

First-Rate Filters.

Using only 45 mW (600 ohms/0 dBm) of power, Harris PCM filters have no external anti-aliasing components and

are input-protected against static discharge. There's nothing better for telecom transmit and receive filtering or digital radio/speech synthesis voice filtering than Harris PCM filters.

For more information, write: Harris Semiconductor Analog Products Division, P.O. Box 883, MS 53-035, Melbourne, Florida 32902-0883 or call (305) 724-7418.

Harris Telecom ICs Product Summary

Part Number	Description	Highlights
HC-5502A	SLIC	Ring generator referenced to ground
HC-5504	SLIC	Ring generator referenced to negative battery supply
HC-5508	SLIC	Reconfigured and enhanced version of HC-5504
HC-5510/11	PCM CODECs	μlaw/A-law coding with signaling capabilities
HC-5512/12A	PCM Filters	Exceed all D3/D4 CCITT specifications
HC-5512D	PCM Filter	MIL spec
HC-5554/57	CODEC/Filters	μlaw/A-law COMBOs
HC-5541A	Dialer	Pulse-tone dialer
HC-55536/64	CVSD	Real-time speech processors
HF-10	UAF	Univ. Act. Filter, MIL Temp.



For your information, our name is Harris.

#### **N**EWSFRONT

## Oxide isolation process builds RAM controller chip that needs no wait states

Besides obvious benefits in throughput, an advanced controller chip works with moderate-speed dynamic RAMs.

ith microprocessor systems clipping along at 10 MHz or more, memory subsystems are forced to keep pace. Reaching those speeds without incurring wait states usually demands the use of high-speed components; both the dynamic RAMs and the controller logic. Now a merger between oxide isolation and clever design methods changes that: Together they produce a controller chip that operates at 10 MHz with no wait states. Moreover, the controller does not need dynamic RAMs that cycle blazingly fast; instead it can operate with cycle times of 150 ns, thus lowering the overall cost of the memory subsystem.

To reach such performance levels, National Semiconductor Corp. (Santa Clara, Calif.) entirely revamped the junction-isolation bipolar process with which it built its earlier 8409 dynamic RAM controller. The new process, based on oxide isolation, uses emitters that are about 70% smaller

than those in the earlier process. Consequently, it produces transistors that occupy an area of 1.25 mils<sup>2</sup>—about ½ the area of the junction-isolated transistors.

A washed emitter in the new structure eliminates any isolation spacing in the emitter region (see the figure). Junction isolation schemes usually insert a space to avoid emitter-to-base shorts when the metal contacts to the emitter are deposited. The oxide isolation approach turns the entire emitter into a contact, thus permitting the emitter region to be much smaller. Additionally, the scaling of the emitter is allowed because of self-aligned masking of the contact region to the emitter, which presents any misalignment.

#### Lower capacitance

Besides smaller emitters, the oxide-isolation process produces lower parasitic capacitances, which translate into higher operating frequencies for the transistors. Furthermore, by going with a thinner layer of epitaxial silicon and shallower junctions, National has produced sharper doping profiles, which further enhance transistor speed.


Unlike the earlier junction isolated process, the new one draws on a high-resistance epitaxial layer. In that way, designers can choose to reduce the size of the resistors or increase the value with no sacrifice of chip area. The latter choice means lower power consumption.

#### **Drops cycle time**

The transistor structure is not the only contributor to the RAM controller's speed. The architecture of the older chip has been significantly trimmed, lowering system cycle time and enhancing circuit stability. For instance, the placement of a voltage regulator and a delay line on the chip boosts the accuracy of the system's timing. The regulator controls the internal power supply seen by the inverters in the delay line, thereby eliminating any changes in propagation delay caused by variations in the external power supply. In addition, extra circuitry compensates for the effects of temperature on the resistors and other elements.

The single-chip controller halves the number of operating modes of the 8409 eliminating those rarely used. In addition, it sports a new feature: a control pin that sets

#### **NEWSFRONT**



To build its superfast dynamic RAM controller, National Semiconductor went from junction isolation (a) to oxide isolation (b), (4 times enlarged) yielding tighter packing densities and transistors that occupy about half the space of their predecessors. The older process needed overlapping spacing regions, the newer one self-aligns the contact region with the emitter.

the delay line to a row-address hold time ( $t_{\rm RAH}$ ) of either 15 or 25 ns. Since delay times differ with RAM organization, generation, and supplier, the ability to match the delay

time to the RAM is a big step toward system optimization.

Physically, the dynamic RAM controller drops right into the socket filled by the 8409.

Dave Bursky

### Two-processor board brings flexibility to voice applications

single-board subsystem calls on the resources of a generalpurpose processor and a digital signal processor to handle not only speech recognition and synthesis, but storing and forwarding of voice signals as well. The hardware and software flexibility of the board will permit future software packages to tackle such jobs as converting text into speech, and eventually the board could serve as a 1200bit/s modem. Designed by ITT Information Systems (Tempe, Ariz.), it can plug into a card slot in any IBM-compatible personal computer.

The trick lies in the programmability of the two processors. Since the board has its own 8088 processor, it can operate independently of the CPU in the host system. Thus, it can pull in files when it has to and eliminate many of the delays normally encountered when the host CPU is responsible for control.

The TMS320 digital signal processor performs most of the computations needed for matching templates and other functions. It has separate memory—PROM to store various routines and local RAM to hold parameters and data that must be accessed rapidly. The two processors communicate through a dual-port 512-byte RAM.

The three-tier software structure, designed specifically for this board, actually ties together the processors, the associated memory, and the logic. Typically it comes on a floppy disk and is loaded into a hard disk-based PC. Depending on the function desired, the appropriate routine and parameters are loaded into the local RAM on the board.

#### **Layered functions**

The software is divided into three basic layers (see the figure). The first resides on the disk and covers routines for vocabulary training, phone management, and I/O drivers. The middle layer encompasses the functional



## Introducing a high-quality RF source at a radically low price.



#### The Fluke 6060A general-purpose 1GHz signal generator.

This is Fluke's greatest price/performance breakthrough yet, created from 20 years of proven RF design experience. The 6060A is our newest, lowest cost, general-purpose generator.

General purpose because its broad frequency and amplitude ranges and modulation versatility offer the performance you need for virtually <u>all</u> RF design, development and testing applications.

General purpose because the 6060A meets these application needs with

—60 dBc non-harmonic spurious throughout its broad range. Fluke's years of designing and building RF instruments gives the 6060A the reliability you demand.

But the real breakthrough on our new 6060A is its price: **\$4500**\*

Because it is so much <u>less</u> than you might expect to pay for a comparable unit, the 6060A is the lowest-cost generator in its class.

Clearly, the 6060A signals a new era in generator price/ performance for the RF industry.

For more information about the innova-

tive 6060A, call **1-800-426-0361** or contact your local Fluke Sales Engineer or Representative.

#### Fluke 6060A

I IUNO OOOON	
Frequency range	100 KHz - 1050MHz
Amplitude range	+13dBm to -137dBm
Accuracy	±1.5dB
Harmonics	<-30dBc
Spurious	<-60dBc
Modulation	AM/FM
Radiated RFI	<1 µV at carrier frequency
IEEE-488 Interface, opt. 488 switch speed	<100 ms, typ.

IN THE U.S. AND NON-EUROPEAN COUNTRIES

John Fluke Mfg. Co., Inc. P.O. C9090, M/S 250C Everett, WA 98206 (206) 356-5400: Tlx: 152662 IN EUROPE:

Fluke (Holland) B.V. P.O. Box 5053, 5004 EB Tilburg, The Netherlands (013) 673973, Tlx: 52237



#### **NEWSFRONT**

routines—voice recognition templates and feature extraction procedures, synthesis, and so forth—that are downloaded to the board. The third layer consists of the routines needed by the TMS320 digital signal processor for recognizing speech, digitizing it, playing it back and also for controlling the telephone.

#### More robust


To perform voice digitization, ITT uses a scheme called residual excited linear prediction, which it feels is more robust than the more popular linear predictive coding technique. In this process, voice signals are sampled 8000 times per second, digitized into 8-bit samples, and then compressed, yielding a final data rate of 8 kbits/s. A word template requires about 1 kbyte of memory space.

As a speech recognizer, the card can handle a speaker-dependent vocabulary of 200 words, or a pooled-speaker vocabulary of 25 to 100 words, depending on the number of speakers. A vocabulary consisting of 200 templates can be matched in less than 300 ms, and that time can be shortened if smaller subsets

are used to build word files.

Initially, the system will come with programs that handle speech recognition, voice mail, appointment calendars, telephone directories, and automatic dialing and answering. The user will be able to "toggle" between the applications without having to exit from either routine. In the voice-mail mode, the system operates with a data rate of 9600 bits/s.

Aside from the two processors, the board consists of a local 128-kbyte RAM program and data space, separate PROM to hold the TMS



The voice recognition and synthesis processor from ITT Information Systems runs with three major software layers: a group of basic routines that reside on the personal computer's disk, another group that covers the general functions of the board, and the last group, which controls the operation of the TMS320 digital signal processor.

### **SYNC THE UNSYNCABLE**



It's time to get in sync with a revolutionary idea: High-density CMOS static memories that interconnect systems in ways never before possible. We call them BiPORT™ memories. Because unlike any other memory devices, they read and write at the same time.

The first in the series is the MK4501 FIFO, an asynchronous device that's organized 512 x 9 in a 28-pin DIP. It's the fastest, highest-density rate buffer available for interfacing fast processors with slower peripherals.

But that's only a glimmer of application potential. Now consider true parallel computing.

Quite simply, the MK4501 and future BiPORT memories enable you to synchronize processors with different clock rates so that they can communicate with each other. Without complicated arbitration circuitry. What's more, BiPORT memories are fully expandable by word size as well as depth.

All of which means that you can now create the equivalent of a much larger system. For a fraction of the cost.

The possibilities? As far as your imagination can take you. And all you have to do is get in sync. For more information, contact Mostek, 1215 W. Crosby Road, MS2205, Carrollton, Texas 75006 (214) 466-6000. In Europe, (32) 02/762.18.80. In Japan, 03/496-4221. In the Far East (Hong Kong), 296.886.

BiPORT is a trademark of Mostek Corporation.



#### **NEWSFRONT**

320 routines, the 512 bytes of dual-ported RAM, and the telephone line interface, as well as tone generation and detection circuitry. To pack all the circuitry onto a single card, ITT designers densely populates a six-layer printed circuit board that routes all the signals. Dave Bursky

#### **Pipelined structure** ups tape controller's transfer rate by 30%

pipelined architecture consisting of a FIFO buffer and three latches increases the bus communications rate of a Multibuscompatible tape controller card by 30%. Designed for streaming and start-stop 1/2-in. tape drives, the Multibus I board also attains a throughput high enough to accommodate cache tape drives.

The 16-bit latches allow the Tapemaster 1000 controller board, developed by Ciprico Inc. (Plymouth, Minn.), to exchange data with the tape drive at rates of up to 1.5 Mbytes/s. Latches 2 and 3 (see the figure) are used to match the bus data rate to the practical limits of the Multibus. The FIFO buffer stores data from the tape drive until the most efficient amount, as determined by the user, can be loaded onto the bus. When that level is reached. the card takes control of the bus and transmits the data at 4 Mbytes/s.

The controller board coor-

dinates bus and buffer cycles by putting latches on either side of the buffer, thus allowing data to move in overlapping steps. The latches hold the data as it flows from the 260-ns memory, preloading the data for transmission to the bus. Without the latches, wait states would have to be added to synchronize the cycles, thus degrading throughput.

To maximize communication with the host, the Tapemaster 1000 lets users determine how long it will control the bus. Programmable throttling, as this feature is called, lets users select either a time period ranging from 1 to 40 µs or the transfer of from 2 to 256 bytes. Thus, the user can send large data blocks by holding the bus for longer periods or send several short bursts of data.

#### Handles new drives

To exchange data with the new generation of tape drives, the system uses latch 1. Most tape drives currently have maximum bit densities of 6250 bpi and streaming tape speeds of 125 ips, so transfer rates of about 750 kbytes/s are acceptable. However, new drives with cache buffers can handle more data flow. forcing controller boards to roughly double transfer rates.

The pipelined architecture lets the controller simultaneously access system memory while it reads from or writes to the tape drive. An example is scatter-gathering. a task that lets the board read one data block from the tape drive and store it in non-

#### WHERE DO I LOOK FOR LEADERSHIP?

#### PMI North American **District Sales Offices**

Boston, Massachusetts (617) 655-8900

Chicago, Illinois (312) 885-8440 (800) 323-8755

Dallas, Texas (214) 341-1742 (800) 223-6147

Los Angeles, California (714) 666-0140

Philadelphia, Pennsylvania (215) 639-9595

Santa Clara, California (408) 727-6616

#### **PMI North American Authorized Distributors**

Anthem Electronics **Bell Industries Future Electronics** Gerber Electronics Hall-Mark Electronics Intek Electronics Ltd. Merit Electronics Corp. Pioneer Electronics Semi Dice Inc. Zentronics

Over 90 locations in North America.





**LEADERSHIP** Since 1969 Precision Monolithics has been a leader in the world of precision bipolar analog ICs.

We invented the DAC-08, the REF-01, the OP-07, the OP-27 and more. All industry standards. Soon we'll be bringing precision to the world of analog CMOS,


and again we'll establish new standards. Technological leadership is more than being the first.

It's being the best.

Precision Monolithics Inc. 1500 Space Park Drive, Santa Clara, California 95050, USA.

A Bourns Company.





This PTC thermistor—acting as a solid-state switch—has been wired to a circuit board as a defense against transistor destruction due to overheating. Bonded to a tab, the PTC measures surface temperature of the transistor, and when reaching the critical point, shuts off the drive circuitry to the transistor. After cooling, the PTC automatically resets itself.





Keystone Thermistors are distributed by
Allied Electronics Phone: 817/336-5401
Newark Electronics Phone: 312/638-4411

CIRCLE 27


#### **NEWSFRONT**

contiguous memory locations. This feature is one of the commands which can be called into play using the controller's ring buffering technique. The ring buffering commands, stored in firmware, include pointers which lead to the next consecutive data block. This frees the host to perform other tasks since it no longer needs to determine the next consecutive data block which must be written or read. Alternatively, the controller can read noncontiguous blocks

from system memory and group them into a single tape data block. These tasks, frequently called for in virtual memory applications, can be performed on-the-fly.

The pipeline also translates the 8-bit data coming from the buffer and tape drives into 16-bit words needed for Multibus systems. Though the board is controlled by an 8-bit microprocessor, it does not handle data because of its relatively slow speed.

Terry Costlow



A 1/2-in. tape controller board from Ciprico incorporates three 16-bit latches to form a pipeline that speeds data communication. The latches preload data for transfer to the bus or tape drive, thereby eliminating wait states.

## New 4-bit raster DAC sharpens graphics

(and it's in an 18 lead DIP)

## 125MSPS, guaranteed, "graphics ready," just \$15\*



Give yourself a head start with a monolithic DAC designed specifically for raster scan systems—the TRW TDC1034 4-bit,125 MSPS D/A converter. It directly drives CRTs to video compatible levels. Save on circuitry—no extra registering, buffering or deglitching. Save space—the 4-bit TDC1034 is an ultra-thin 18 lead DIP.

And you get terrific performance. This monolithic 4-bit DAC is ideal for either monochromatic or RGB color raster graphics (4096 colors!). Its high speed scans more pixels per picture to produce razor sharp high resolution displays. And because it's built with TRW's OMICRON-B™ 1-micron bipolar process, you get high reliability and low power consumption (600mW).

The low-cost 4-bit TDC1034 is your one chip solution to high volume production of

CAD/CAM work stations, computer graphics, and high resolution video. If your application needs all the options that an 8-bit, 24 lead DIP offers, consider the TDC1018—the first monolithic 8-bit, 125MSPS D/A converter.

Check these key performance features:

- Blank, sync and bright video controls
- Directly drives standard 75Ω load
- Inherently low glitch
- Registered data and control inputs
- Power supply rejection ratio>50dB
- Differential logic for maximum speed, minimum noise
- RS-343 compatible
- Low power dissipation
- Single -5.2V power supply
- 1/8 LSB linearity (4-bit TDC1034)
- 1/2 LSB linearity (8-bit TDC1018)
- ECL compatible data and control inputs

These DACs are available from Arrow Electronics, Hall-Mark, and Hamilton/Avnet.

#### Remember, you always get FULL SPEC PERFORMANCE from TRW LSI.

For a full data sheet or immediate information about our "graphics ready" DACs, call or write our Literature Service Department:

LSI Products Division, TRW Electronic Components Group, P.O. Box 2472, La Jolla, CA 92038, 619.457,1000

In Europe, call or write: TRW LSI Products, Konrad-Celtis-Strasse 81, 8000 Muenchen 70, W. Germany, 089.7103.115

In the Orient, phone: Hong Kong, 3.856199; Tokyo, 03.461.5121; Taipei, 751.2062


\*U.S. price in 1000s: TDC1034 CERDIP \$15; TDC1018 CERDIP \$36.00 © TRW Inc. - 1984 TRS-4116



**LSI Products Division** 

TRW Electronic Components Group

## Motorola's 256K ROMs or 50



### 

When you need the 256K ROM with state-of-the-art speed, Motorola has it—the 150 ns MCM63256.

On the other hand, you might be searching out the lowest-power 256K ROM available. Motorola has that, too—the 50 uA MCM65256.

#### Get a lot. Trade-off little.

Whether your requirements run to super speed or ultra-low power, Motorola satisfies them. And you don't make severe trade-offs to get the performance you need most.

The high-density HCMOS MCM65256 low-power leader's maximum power dissipation is only 50  $\mu$ A in standby with full rail inputs, 5 mA in standby with TTL inputs and just 50 mA, active. However it still offers a fast 350 ns access time, and just 100 ns max. from output enable.

Certainly speed is the biggest attraction of the high-performance N-channel HMOS MCM63256, yet maximum power dissipation is a low 15 mA, standby, and 100 mA active.

There's also a 200 ns version of the MCM63256, and matching high-speed 128Ks are available, too.

#### All in the industry-standard 28-pin family.


Beyond the ideal differences in their speed and power, these advanced-technology ROMs share many common operating characteristics and benefits, including availability now in the JEDEC-standard 28-pin dual in-line package.

They utilize late-process programming to minimize prototype turnaround, and they require no clocking on the chip enable because they're static. They operate from single +5 volt supplies, shift automatically into the power-down mode, and offer user-selectable address and mask-programmable chip and output enables.

#### Rewards offered.

You can buy 256K ROMs elsewhere, but you can't collect the rewards of top performance with fast turnaround at Motorola prices when you do. So reward yourself by ordering now through your Motorola sales office or authorized distributor.

At the least, before making a final decision, you owe yourself additional information. Write for it or send the completed coupon to Motorola Semiconductor Products Inc., P.O. Box 20912, Phoenix, AZ 85036.







### DIGITAL'S NETWORKING. AN OPEN WINDOW TO DYNAMIC MARKET GROWTH.

If you want to significantly enhance your OEM product offerings and enable your products to fit in easily with your customers' distributed computing environments, consider the advantages of Digital Network Architecture.

No other company offers a wider range of efficient networking options tailored to OEM reguirements. And no other company does so much to help you and your customers achieve the full benefits that networking can provide.


With Digital as your OEM supplier, you'll have the products you need to make local and wide area networking an essential part of your marketing plan. And that opens up an endless growth

#### **DIGITAL NETWORK** ARCHITECTURE, YOUR WINDOW TO THE **WORLD.**

Digital Network Architecture (DNA) is the most comprehensive communications strategy yet developed, and currently implemented in proven, deliverable products. It supports several communications technologies. And it can accommodate future standards as they emerge because DNA is implemented in a layered structure consistent with the ISO Open Systems Interconnect model.

As an OEM, DNA gives you tremendous marketing and product opportunities. You can incor-

path for you and your customers. porate the best price performance You can communicate with maincomponents in your systems.



frame systems. You can match the technology to the job. And, most importantly, you can keep pace with your customers' distributed processing needs as they

DECnet<sup>™</sup> software lets you link Digital's systems in both local and wide area configurations. It supports high-speed local area network communications using Ethernet. And it provides gateways to allow Digital's computers to communicate with other vendors' systems over private lines or packet switched X.25 networks. This means you can tailor your products to fit in with your customers' current and future networks.



#### BENEFITS FOR YOUR USERS. BENEFITS FOR YOU.

The benefits you and your customers get by incorporating Digital's networking capabilities are virtually unlimited.

First of all, your systems can incorporate recognized industry standards. Such as Ethernet (IEEE 802.3 specification), X.25, and others.

In addition, our growing set of network-based products, including a distributed database system, allow your single systems to easily grow into networks. Your applications can access remote data and other resources transparently, with no extra development required.

This means that, with Digital, your systems are in an excellent position to be widely used in your customers' computing environments.

#### ENGINEERED FOR SUCCESS IN MULTIVENDOR ENVIRONMENTS.

Your products need to communicate with equipment from different vendors. Ethernet was designed with this fact in mind. Today, Ethernet-based networks are proliferating across all application segments – such as CAD/CAM, ATE, factory automation and medical applications.

Digital's networking systems allow Ethernet to be part of a single-source solution for your OEM installations. And DECnet gateways provide highly functional links to other non-Digital communications environments.

In short, DNA and Digital's products do the most to ensure that your systems will fit in with both new and existing networks.

#### WE'LL BACK YOU WITH TRAINING AND SUPPORT.

If you're already a Digital OEM, you know the advantages of Digital training and support. It's second to none in the industry.

We can give you the skills to configure, market, install and service local and wide area networks effectively. We'll help you make the most of our networking products in your systems.

Digital representatives are

available for pre-sales consultation and installation assistance. And our world-wide service organization can provide all the on-site network maintenance your customers require.

#### BEST ENGINEERED MEANS ENGINEERED TO A PLAN.

The communications systems implemented as part of Digital Network Architecture, like all Digital hardware and software products, are engineered to conform to an overall computing strategy. This means our systems are engineered to work together easily and expand economically.

Every system we make – from the Professional™ 300 Series workstations, to our MicroVAX I™ supermicro, to our high-end VAX™ computing systems – can cooperate using DECnet software. Only Digital provides you with a single, integrated computing strategy, from chips to 32-bit systems, and direct from desktop to data center.

For more information about how you can make networking

from Digital part of your product line, send in the coupon below or contact your Digital Sales Representative or a Digital Authorized Industrial Distributor. Or call 1-800-848-4400, ext. 139.

Please send more information about Digital Network Architecture and DECnet

 I'd like the whole story about OEM networking opportunities with Digital.
 Please have your representative call today.


Name		
Title		
Company		
Address		
City		
State	Zip	
Telephone	Ext	
		ED 10/10/0/

Send to: Digital Equipment Corporation, 77 Reed Road, HL02:1/E10, Hudson, MA 01749.

THE BEST ENGINEERED COMPUTERS IN THE WORLD.



### From the innovative leader in high speed operational amplifiers...



## Three more revolutionary op amps that give you maximum performance with minimum design effort.

For designs that require high speed operational amplifier performance, the Comlinear 200 Series is your one-step solution.

#### The CLC200. Exceptional settling time. Superior thermal tail characteristics.

Consider first the new CLC200. Its DC to 100MHz -3dB bandwidth remains virtually unchanged over inverting and non-inverting gain settings of 1 to 50. Add to that a rise time of 3.6nsec and a settling time of 25nsec to 0.02% with <1mV thermal tail, and you can see why the CLC200 is the natural choice for any application involving high-speed pulsed information. Not only is the CLC200 fast, but it also has ample drive capability (±12V, ±100mA) to remain

oscillation-free even when looking into the high and widely varying capacitance of a flash A to D converter.

#### The CLC210. 60Vpp output.

If you're designing high-resolution displays you're probably resigned to designing your own custom driver amps as well. Not any more. The CLC210 is the second member of our new family. It features DC to 50MHz bandwidth, greater than 5MHz full-power bandwidth (at 60Vpp) and a powerful ±30V, ±50mA drive capability. Comlinear's drop-in ease-of-use lets you forget about re-inventing the amplifier, and concentrate instead on improving display technology. The CLC210's unparalleled full power bandwidth and high output voltage also make it an excellent choice for directly driving varactors in VCO control loops and phase-correction loops.

#### The CLC220. Speed and bandwidth redefines the state of the art.

For DC to 200 MHz, rely on the CLC220. With exceptional speed characteristics of 1.6nsec rise/fall times, 8000V/µsec slew rate, and 12nsec settling time to 0.02% (with <1mV thermal tail), the CLC220 defines the state of the art in high-speed operational amplifiers. Use it with ease and confidence in applications from data conversion, fiber optics, and more.

Look into the Comlinear 200 Series high performance operational amplifiers. All are priced below \$100 in 100-piece quantities. For the full story, call or write us today. Comlinear Corporation, 2468 East 9th Street, Loveland, CO 80537 (303) 669-9433.



#### **C**ONFERENCE PREVIEW

#### **Application-specific ICs** top the charts at February's ISSCC

Besides application chips, dynamic and static memories are the hot numbers; some analog favorites get an updated treatment.

s interest in application-specific circuits mounts, the density and speed of such chips is on the rise. The hottest of these ICs—memories and processors-can be seen at the International Solid-State Circuits Conference (New York City, Feb. 13-15). Also of major significance is the work that has been done to proliferate and boost the speed of 1-Mbit dvnamic RAMs and 256-kbit CMOS static memories devices considered rarities only a year ago.

More traditional circuits, of course, will not be left out in the cold, as the presence of an 8-bit, 500-MHz digital-toanalog converter shows. Other analog chips can also be seen. Additionally, the conference will play host to some of the latest in semicustom circuits and high-speed gate arrays will be unveiled.

Application-specific memories are showing up with an assortment of internal organizations, allowing engineers to choose the configuration best suited to their systems. One example is a dual-port RAM that is laid out as 64k by 4 bits.

From NEC Corp. (Kanagawa, Japan), the circuit is four times as dense as currently available devices and can be accessed in 35 ns. The memory handles graphics data from any node in a system. A 2k-by-9-bit circuit, developed by AT&T Bell Laboratories (Allentown, Pa.), demonstrates another possible layout.

#### **New tricks**

Some of the memories to be covered at the conference integrate untraditional functions. For instance, a 128-kbit EPROM from Intel Corp. (Santa Clara, Calif.) carries a built-in pseudorandom number generator, as well as the requisite encryption circuitry to generate a security key.

Processors, like memories, are increasingly being designed with specific applications in mind. A case in point is a video signal processor for facsimile machines. It joins a 4-bit flash analog-to-digital converter with an offset canceller to clip along at 5 MHz. The 2.5-µm CMOS chip, from Hitachi Ltd.'s Central Research Laboratories and its Device Development Center (both in Tokyo), weighs in with 25,000 transistors and 840 bits of RAM and can control a CCD image scanner.

Another CMOS processor, this one for a computer-controlled telephone, employs a 5-bit logarithmic a-d converter and 46-db programmable gain amplifiers. The circuit, designed by Bell Northern Research and Northern Telecom (both in Ottawa, Canada), controls half-duplex speaker microphone signals.

The work being done with floating-point arithmetic processors should be of great interest to designers assembling systems built around the new generation of 32-bit microprocessors. High-speed arithmetic can be had on a single chip or on a board-level subsystem.

One of two floating-point math chips hustles along at 14 MHz. This IEEE standard coprocessor is aimed at 32-bit microprocessors. It is fabricated with 1.75-µm twin-tub CMOS and handles single-, double-, and extended doubleprecision math, as well as 32-bit integer and 18-digit BCD operations. The processor is the creation of AT&T Bell Laboratories (Holmdel, N.J.).

Another processor, this one from Nippon Telegraph and

**Martin Gold** 

#### **CONFERENCE PREVIEW**

Telephone Public Corp.'s Atsugi Electrical Communication Laboratory (Kanagawa), is built with 1.2-µm n-well CMOS. The 80-bit device contains 15 kbits of memory and 50,000 gates and executes a staggering 5.6 million floating-point operations/s.

Dynamic RAMs capable of retaining 1 Mbit and CMOS static RAMs storing 256 kbits were just emerging a year ago. They are not the rarities they were then and they are getting faster as well. Most impressive is a dynamic RAM that can be accessed in 85 ns and that fits in a low-cost plastic package. The 43.2-

mm<sup>2</sup> chip, from NEC, adds an interconnection layer that enables it to be housed in a 300-mil plastic DIP.

Other 1-Mbit dynamic RAMs to come under scrutiny at the conference display some interesting new wrinkles. A 65-mm<sup>2</sup> chip from Mitsubishi Electric Corp. (Itami, Japan) is built around a shared sense amplifier and features a continuous nibble mode. The IC can be accessed in 90 ns and sports a test pin that allows it to be examined as if it were configured as 256k by 4 bits.

Joining a divided bit-line matrix and a 1.2-µm doublemetal CMOS process has yielded a 1-Mbit dynamic RAM that runs off 5 V and has an unprecedented array area-to-die ratio of 56.6%. Its creator, Mostek Corp. (Carrollton, Texas), also points out that over 80% of the total die area is repairable using laser-programmed redundant rows and columns.

Clearly, fast static RAMs have arrived as well, as can be seen in three 256-kbit CMOS memories. Two of the ICs boast an access time of 45 ns. One, from the Central Research Laboratory of Hitachi Ltd.'s Musashi Works (Tokyo), is a 32k-by-8-bit circuit

#### ISSCC '85's evening agenda

As is traditional, the ISSCC's evening panel sessions will attempt to shed some light on the more controversial issues surrounding the leading integrated circuit technologies. One of the hot topics at the upcoming conference will be the impact of VLSI chips on the coming generation of artificialintelligence computers. Other subjects that are likely to stir up some lively discussions are the limitations of submicrometer MOS, the future of custom and semicustom design, the challenges CMOS faces from high-speed LSI technologies, the role of CAE workstations, and the future of nonvolatile circuits.

Clearly, VLSI technology is one of the keys to creating machines specifically tailored to AI, which requires fast sorting of and searching through large data bases. These new computers will implement parallel processing in hardware and manipulate a range of data types.


The role that 32-bit microprocessors may play in AI-based computers will be analyzed by experts from the semiconductor industry, universities, and companies investigating artificial intelligence. VLSI's effect on AI will also be the theme of the conference's keynote address, which will be delivered by Raj Reddy, professor of computer science at Carnegie-Mellon University. This talk, and the presentations of other participants, will cover chips that could contain a hundred million or a billion elements sharing a common bus to a larger external memory. Obviously, the numerous processors in-

volved will not be identical. Some may work with dynamically alterable PLAs, others may carry out on-chip analog-to-digital and digital-to-analog conversions, and still others may contain network in-

The future of submicrometer MOS also will be given a good going-over. The technology has now reached the point at which design rules of 1 µm are possible. The question that remains to be answered is where to best concentrate industry efforts to achieve the projected twenty- to thirty-fold increase in device density that MOS now promises.

CMOS, meanwhile, is likely to be challenged on the high-speed front by such emerging technologies as gallium arsenide, aluminum gallium arsenide, and silicon bipolar. All are looking to demonstrate clear-cut performance advantages that will let them slip neatly into specific niches. This panel will discuss the potentials of these technologies in what is likely to be an era dominated by CMOS VLSI.

The explosion in workstations, CAD software and the proliferation of makers of gate arrays and standard cells reflect the tremendous impact of semicustom and custom ICs. One panel will look to the future of custom and semicustom designs, seeking to identify the tools that will be most useful in working with them. Another session will analyze the future of CAE workstations—from the user's point of view. Some of the questions to be addressed are the actual functions of the workstations, as well as their usefulness and their limitations.



In telecom application-specific IC's, Silicon Systems stands alone as the innovator in standard, semicustom, and full custom products. Not only were we the first to fully integrate Touch-Tone® receiver electronics onto a single chip, but we're also the company that has developed switched capacitor filter design to the present state-of-the-art. In fact, we are the telecom chip company with a proven ability that is unmatched for producing analog, digital, and analog/digital designs on a single chip.

Our present broad line of standard tele- for production at optimum yields. In fact, com application-specific circuits includes a family of high performance DTMF receivers, transceivers, and band-split filters; a selection of medium-tc-high-speed modems, speech synthesizer IC's, and switched capacitor filter arrays.

But beyond those standard IC's, Silicon Systems offers the industry's most advanced and complete semicustom and full custom capability. We wrote the book on innovative IC design. And we have the newest and most efficient, automated wafer fab

we're one of the few companies with both Bipolar and CMOS multi-process capability in the same wafer fabrication facility.

For more information on our DTMF's, modems, speech synthesizers, and switched capacitor filter arrays, send for

our Telecom Integrated Circuits brochure.



Silicon Systems, 14351 Myford Road, Tustin, CA 92680. (714) 731-7110.

®Touch-Tone is a registered trademark of AT&T.



CIRCLE 30 FOR PRODUCTION INFORMATION

CIRCLE 31 FOR CAREER INFORMATION

#### **CONFERENCE PREVIEW**

that consumes 200 mW when running at 10 MHz.

The second RAM, developed by Mitsubishi, draws a peak current of 45 mA. That low drain is obtained by using an address-transition-activated circuit combined with a three-level word-line circuit.

Although the third static memory—at 55 ns—is slightly slower than its two kin, it draws merely 10 mW on standby. The 40.77-mm² die, created by NEC, uses optimized polysilicon load resistors, buried isolation, and titanium polycide.

Other static RAMS will also be featured. One is a 4-kbit gallium arsenide device. The 1k-by-4-bit memory, from NEC sports 2.4-ns address access time for cache memory. Its power dissipation, however, is 1.1 W.

The world of analog circuits is not standing still. Proof of this can be seen in an 8-bit d-a converter with a conversion rate of 500 MHz, a 2-ns settling time, and 0.6-ns rise and fall times. From the Central Research Laboratory of Hitachi's Takasaki Works (Tokyo), the chip is fabricated with shallow-groove VLSI technology.

Also to be unveiled is a 150-W op amp with a continuous dissipation rating of 90 W and a peak rating of 800 W. The amplifier was jointly devised by Robert Widlar, an independent consultant and National Semiconductor Corp. (Santa Clara, Calif). The 35-V, 10-A device incor-

porates a class B output stage to avoid quasicomplementary problems.

The huge amount of work under way in semicustom circuits is also apparent at the ISSCC. These chips employ nearly every process technology, with emphasis on speed. For instance, an ECL gate array, from Siemens AG (Munich, West Germany), packs 9000 gates and boasts a propagation delay of 99.6 ps.

An ECL field-programmable array developed by National Semiconductor comes in with a total propagation delay of 3.6 ns at 1 W. Further, working with gallium arsenide, Oki Electric Industry Co. Ltd. (Tokyo) has created an array with 1000 gates and a 390-ps speed. □

#### Some highlights of ISSCC '85

#### Memories

#### **Dynamic**

85-ns 1-Mbit RAM in plastic DIP (NEC) 90-ns 1-Mbit RAM with multiple-bit testing (Mitsubishi Electric)

1-Mbit CMOS RAM with divided bit-line matrix architecture (Mostek)

Experimental 4-kbit RAM with 16 coded levels per cell (Hitachi)

#### Static

45-ns 256-kbit CMOS RAM with 200-mW power dissipation at 10 mHz (Hitachi) 55-ns 256-kbit CMOS RAM with 10-μw standby power consumption (NEC)

45-ns 256-kbit CMOS RAM with threelevel word line (Mitsubishi Electric) GaAs 4-kbit RAM with 2.4-ns address access (NEC)

#### **Nonvolatile**

25-ns 16-kbit CMOS PROM (Cypress Semiconductor)

95-ns 256-kbit CMOS EPROM (Hitachi) 256-kbit EEPROM with three polysilicon layers (Toshiba)

100-ns 256-kbit CMOS EPROM (Intel, Sierra Semiconductor)

64-kbit EEPROM with extended temperature range (Advanced Micro Devices)

#### Other

35-ns 256-kbit dual port RAM (NEC)
1-Mbit ROM with error correction circuitry (Mostek)

2k-by-9-bit CMOS dual-port RAM (AT&T Bell Laboratories)

Bell Laboratories)
128-kbit EPROM with built-in encryption circuitry (Intel)

#### Processors

#### Floating-point

80-bit floating point processor in 1.2-μm n-well CMOS running at 5.6 million floating-point operations/s (NTT)

14-MHz IEEE standard floating-point coprocessor for 32-bit microprocessors (AT&T Bell Laboratories)

#### Signa

NMOS pipelined image processor using quaternary logic (Tohoku University) digital signal processor with multiprocessing capability (Texas Instruments, ITT)

Programmable digital signal processor with 32-bit floating-point arithmetic (AT&T Bell Laboratories)

#### Semicustom arrays

80-ps 2500-gate bipolar macrocell array

100-ps 9000-gate ECL arrray (Siemens AG)

3.6-ns ECL field-programmable array (National Semiconductor Corp.)

390-ps 1000-gate GaAs array using superbuffered FET logic (Oki Electric)

#### **Analog circuits**

8-MHz 8-bit CMOS subranging a-d converter (RCA)

10-bit CMOS a-d converter with sample and hold (Intersil) 8-bit d-a converter with 500-MHz conversion rate (Hitachi)

150-W op amp (National Semiconductor and Robert Widlar independent consultant)

#### Other

4-chip Integrated Services Digital Network line termination set (Bell Telephone Manufacturing)

2.56-Mbit/s digital local loop transceiver (Bell Northern Research and Northern Telecom)


350-μW fifth-order low-pass switchedcapacitor filter (University of Califor-

480-by-400-element image sensor with a charge-sweep device (Mitsubishi Electric)

350-ps Josephson junction 4-bit parallel multiplier (NEC)

## CANDUAFFORD OTTOUSE INTEGRAL DEVELOPMENT TO SE

# SOURCE LEVEL DEBUG, YOUR DEVELOPMENT TEAM CAN WORK AROUND IT.



They can write and debug software the long, slow, expensive way. At the machine level. And finish late. Or never.

Or, they can write and debug at a high level. And avoid that risk. With Intel compilers and PSCOPE high-level language debugger.

Intel compilers come in a variety of languages, which means you can choose the best language for each project module. Each produces linkable code. That way, each engineer can work in a language he already knows, or use existing code with no rewrites. Saving training and coding time. Later, you can combine modules. Confident that they're compatible.

When you debug with PSCOPE, feedback is provided at source level. You can single-step, set breakpoints and trace execution flow at high level. You can even patch errors in the code as soon as you find them. With-

out recompiling. Then

recompile just once.


edit the source file and

At the hardware/software integration phase, Intel compilers are still working for you. They're specially designed to pass software information to the Intel I²ICE™ development tool. Insuring a smooth flow from program coding through code debugging and target system debugging to finished product.

Of course, all Intel compilers are tested and

retested. Time and again. So you don't have to waste your time tracking down compiler bugs.

Best of all, Intel's compilers and PSCOPE are just part of a fully integrated set of tools built to support iAPX microprocessor development from product conception to completion. So you can work on your product. Not your tools. Total support you can't get anywhere else.



Integrated tools that reduce development risks

Intel tools. Another great reason to choose Intel advanced technology microprocessors. Find out more about how to reduce your design risk. Call us today toll free at (800) 538-1876. In California, (800) 672-1833. Or write Intel Corporation, Lit. Dept. W-50, 3065 Bowers Ave., Santa Clara, CA 95051.

Then, tell your development team not to work late.



# IF YOU DON'T HAVE MULTI-USER DEVELOPMENT TOOLS, YOUR TEAM CAN STILL PULL TOGETHER.



Every which way.
Wasting time and money running around sharing data the old, inefficient, unreliable way. By hand. And foot.

With Intel's multiuser development tools, you'll never run that risk. Whether you work on a VAX,\* network your Intel

workstations or both, Intel tools can get your team together.

With Intel NDS-II networking, files are centrally stored. Work and information are easily shared through electronic mail.

Project coordination becomes easier and more efficient.

You can even stop worrying whether your investment is used to potential. Because the Network Resource Manager seeks out idle workstations and uses them. Keeping your tools and development team productive.


With NDS-II, you'll never run the risk of project members accidentally destroying or interfering with each other's software. Because program management tools and a hierarchical file system provide you with built-in file security.

If you're a VAX user, you can't find better cross-compilers than Intel's. They're engineered to produce the same quality code and debug records as the compilers on our own workstations. You can even connect your VAX to the NDS-II.

Last but not least, our newest multi-user tool,

Series IV. Use it as a twouser, stand-alone system, or as a powerful workstation on your NDS-II network.

Best of all, Intel's multi-user development tools are just part of a fully integrated set of tools built to support iAPX microprocessor development from product conception to completion. So you can work on your project. Not your tools. Total support you can't get anywhere else.



Integrated tools that reduce development risks.

Intel development tools. Another great reason to choose Intel advanced technology microprocessors. Find out more about how to reduce your design risk. Call us today toll free at (800) 538-1876. In California, (800) 672-1833. Or write Intel Corporation, Lit. Dept. W-49, 3065 Bowers Ave., Santa Clara, CA 95051.


And get Intel pulling for you.



<sup>© 1984</sup> Intel Corporation.

<sup>\*</sup>VAX is a registered trademark of Digital Equipment Corp.

## IF YOU DON'T HAVE I'ICE, YOUR PROJECT CAN STILL FLY.



Right out the window. Without our I¹ICE™development tools, your software may not work in the target environment. Or include all your specified features. With I¹ICE tools, you can make sure it will. Before the integration phase.

Intel's I2ICE devel-

opment tools provide in-circuit transparent emulation with integrated logic timing analysis, real-time trace and extensive breakpoint capability. At full component speeds. With no memory invasion and no change to existing interrupts. So what you see in the prototype is what you get in the final product.

Without I<sup>2</sup>ICE tools, your project could be held up indefinitely while you wait to integrate hardware and software. With these tools, your software debug begins by mapping program memory and I/O device behavior over to the emulation system. As functional hardware becomes available, memory and I/O are mapped back into your target prototype.

On top of that, you can take advantage of integrated logic timing analysis with iLTA, highlevel language debugging with PSCOPE, and optional high-speed memory. You're set up to solve even the most complex problems in record time.

There's even an installation and orientation

package, as well as workshops to help your development team become more productive, faster.

Most important of all, the I<sup>2</sup>ICE development tools are just one part of a fully integrated set of tools built to support iAPX microprocessor development from product conception to completion. So you can work on your product. Not your tools. Total support you can't get anywhere else.




Integrated tools that reduce development risks

Intel tools. Another great reason to choose Intel advanced technology microprocessors. Find out more about how to reduce your design risk. Call us today toll free at (800) 538-1876. In California, (800) 672-1833. Or write Intel Corporation, Lit. Dept. W-51, 3065 Bowers Ave., Santa Clara, CA 95051.

To make sure your project flies. Right.



### THE NEW ENGINEERING POLYMERS AND RESINS GROUP AT BADISCHE



"With the upswing in U.S. computer and auto sales, there is a need for new engineering plastics that we intend to help fill." Roger F. Jones, Managing Director...

"Many of you probably know Badische as a major U.S. producer of fibers, chemicals and plasticizers. But now we have added a new competitive line of quality engineering plastics.

"This market is an obvious choice for us. Our parent company, BASF, is one of the world's leading producers of nylon resins, acetal copolymers and PBTs. And the products we are marketing were developed with BASF high technology and performance—proven in the markets of Europe and the Far East." The new Badische engineering plastics line includes:

> ULTRAMID® nylon resins derived from PA 6, 6.6, 6.9, and 6.10—more polyamides than any other U.S. producer offers and featuring superior flame retardancy. They are used primarily in injection molding of electrical and automotive parts. ULTRAFORM® acetal copolymer, which has an ideal balance of strength, great rigidity and toughness, is used to make automotive and water handling parts. ULTRADUR® thermoplastic polyester, a PBT that is especially suited for electronic and automotive applications.

"The Group is staffed by veterans of the plastics industry, including our technically trained field force. But even more important than our expertise is our long-term commitment to the market."

### **Badische Engineering Polymers and Resins Group**

Ultramid®, Ultraform®, and Ultradur® are registered trademarks of BASF Aktiengesellschaft.



**Badische Corporation** Bridgeport, NJ 08014 Toll Free: 800-BC RESIN ber of the BASF Group BASF

### **N**EWS ANALYSIS

# Making logic programs execute in parallel is today's Al challenge

Fifth-generation hardware may already be defined, but getting the software to run in parallel is emerging as a tough problem.

apan's announced goal to produce a fifth-generation computer by 1990 has spurred artificial-intelligence researchers worldwide to a feverish pitch of activity. In all likelihood, their primary challenge will lie not in building machines containing many processors operating in parallel—as the hardware has generally been defined—but rather in programming those machines in parallel.


Architecture, algorithms, and languages all influence each other in parallel systems, since multiple processors must grind away at separate slices of a problem. That intimate relationship represents one reason that parallelism has yet to pay off in areas other than linear algebra. Scientific programs running on vectorized supercomputers can calculate a pipeline full of additions in one clock cycle, but programs that simulate human logic as the fifth-generation computers are expected to do—run sequentially for the most part.

The Japanese have targeted Prolog as the programming language of the fifth-generation computers. Because the language is not procedural, it is well suited to situations that prevent clear definitions of problems and solutions. Furthermore, it is a good compiler language, describes relationships well, and can be adapted to programming relational data bases.

Prolog does, however, have a significant drawback: Its basic mathematical operation, unification, is a sequential-not a parallel-process, which substitutes goals to make logic terms identical. Prolog converts formal logic, such as the phrase "All elephants have trunks," into a representation called a Horn clause—is an elephant (x)←has trunk (x). The equation reads as follows: For all x, if x has a trunk, then x is an elephant. Calculus notation is used, but as the process of reasoning proceeds in the program, that notation must preserve the truth.

But, the overall advantages of Prolog, are prompting companies and universities to explore ways of making its code—essentially, predicate calculus—parallel. One bit of unusual research looks for similarities between equations and logic languages. The concept, being tried out at the Research Institute of Electrical Communication at Tohoku University (Sendai, Japan), draws on algorithms that transform equationoriented programs into logic programs using an extended version of Prolog.

The university bases its premise on the fact that a logic language, Prolog and Lisp included, employs recursive functions and other mathematical operations that are



Logic clauses are connected via pointers in a directed structure. Here the arrow heads record the order in which the terms should interact. The clauses now take on the aspects of a data-flow graph. Note that constants are bound to variables: At the top of the graph, the constant bill is bound to the variable Y.

### **NEWS ANALYSIS**

special types. So, these particular kinds of problems can be formatted like an equation, and solved the way an algebra problem is solved — with reduction rules that match a left-hand expression to a right-hand one, and reduce each side successively until it can go no further.

Other avenues of research have identified two types of parallel logic programming structures in Prolog. OR and AND. OR problems find a value for the right-hand expression that will make the left-hand value true. Processing OR clauses in parallel is relatively easy, as one part of the problem does not depend on another part. But in an AND problem—like P:-Q, R, S—P is true only when Q, R, and S all are true.

One hardware-oriented scheme for extensive OR parallelism uses a number of processors constituting a parallel interface engine. That engine interfaces with two-level networks and uses TTL logic and some sophisticated control mechanisms.

To program the parallel interface engine, its developers at the Department of Electrical Engineering at the University of Tokyo essentially rewrote unification goals, or slices of OR clauses, and stored them independently in a pool. An optimization scheme subsequently reduced the pool's size. The university's results were conclusive: Test programs written in Prolog for a 256-node engine ran 170 times faster than did sequential Prolog versions

An alternative scheme

compiles logic clauses into single-execution graphs. Devised by the Department of Information and Computer Science at the University of California in Irvine, the technique essentially converts a logic program into a dataflow graph, which basically serves as the program. Data travels in arcs, and a node fires when the information arrives. Each node accepts. emits, and processes value tokens traveling asynchronously along the graph arcs. The tokens themselves identify devices for reassembling program parts.

The data-flow graphs are combined to form "templates," a sort of graphic family tree. Here, relationships between individuals, like "mother" and "father," are recorded as a list of assertions, and the problem might be as simple as understanding the question: "Who is the grandparent of Bill?" (see the figure).

The construct becomes a graph by representing the head of a clause—called its literal—as a directed arc. with arrows recording the order in which the terms are given. A simple assertion, "Bill's father is John." becomes more intricate as other clauses, connected by direction pointers, embellish the simple relationship. Terms are interpreted as nodes connected by arcs, producing the equivalent of a data-flow graph.

AND clauses are much harder to organize in parallel because they share variables. When variables (like X and Y) are shared, they must be bound to the same literal during execution. In this case, literals that share variables are grouped into clusters. In a relatively complex piece of restructuring, subtrees of clusters are filtered out for parallel processing.

A more restricted means of creating AND parallelism forwards information between literals that share the same variable. The processing scheme, devised by IBM Corp.'s Thomas J. Watson Research Center (Yorktown Heights, N.Y.), allocates terms for parallel or sequential treatment based on their type. For example, a ground term—that is, one containing no variables—would carry a type code preset by the compiler; terms with variables would carry other codes.

The scheme is developed to run on a tightly coupled parallel processor, with each element containing its own local memory and owning a copy of the entire program. Within each node are two expression stacks, a sequential stack and a parallel stack. User queries are read, converted into an execution graph expression, and placed on the sequential stack. As the processor draws on that stack for its next job, it tests for the subexpression type. If a subexpression proves suitable for parallel processing, it is placed in the parallel stack.

When the sequential stack finally empties, the processor executes the first expression from its parallel stack. Any idle processor "volunteers" to handle another's parallel

## An Analog and Digital I/O board for your IBM PC<sup>™</sup> at just \$295!\* Who does Molinari think he is?

Ho ho ho.


Don't laugh. We're not kidding. Data Translation is practically giving away a new single board plug-in that brings complete analog and digital I/O capabilities to your IBM Personal Computer.

Ordered in lots of 500 or more, you can enjoy full data acquisition capability for as little as \$295. And smaller unit orders also qualify for considerable savings... one unit is only \$495.

But what would you expect from an innovator like Data Translation? Whether you're working in laboratory research or industrial process control, our latest board can give you measurement and control capabilities at tremendous savings.

The DT2808 includes 16-channel 10-bit A/D, 2-channel 8-bit D/A, 16 lines of digital I/O, a programmable clock and direct memory access capability. And all of these functions are supported by PCLAB,™ our BASIC callable subroutine library running under PC DOS.™

A comprehensive user manual with many programming examples will get your application up and running fast.



\*500 pcs., \$495: quantity one



This easy to use, easy to program board is highly reliable, and of course, fully backed by Data Translation's service and support team.

The new DT2808. The lowest cost data acquisition for your IBM PC. And just one in a long line of software compatible analog I/O boards offered by the industry leader.

Data Translation.

Yes Virginia, there is a Santa Claus. He's president of Data Translation.

(617) 481-3700.

For more information, call one of our elves.

Data Translation provides a full family of analog and digital I/O boards with software support for the IBM PC.

DATA TRANSLATION

World Headquarters: Data Translation, Inc., 100 Locke Dr., Marlboro, MA 01752 (617) 481-3700 Tlx 951 646.
European Headquarters: Data Translation, Ltd., 430 Bath Rd., Slough, Berkshire SLI 6BB England (06286) 3412 Tlx 849 862.
In Canada: (416) 625-1907.
IBM PC, IBM Personal Computer and PC DOS are registered trademarks of IBM. PCLAB is a trademark of Data Translation, Inc.

### **NEWS ANALYSIS**

stack.

As one of its obstacles to parallel processing, Prolog uses logical terms whose structure cannot be changed. Thus when a variable is assigned in the first step, it must be referred to in the second and all subsequent steps; otherwise the machine does not know which variable has been assigned. To retain context in parallel, the variable could be replicated with each term, but these copies eat up memory and create storage problems. Literal substitution also raises communications overhead.

A software-oriented tack taken by the Royal Institute of Technology (Stockholm, Sweden) extracts parallelism through semantic domains, which describe the state of a definition interpreter. This approach, which uses a complicated unification algorithm, manages memory far more efficiently than does copying the variables.

To avoid a large number of non-local memory references, the Royal Institute created a model in which each parallel activity becomes a "process," and variables are stored in separate but formally specified context directories. So-called environment directories are linked to form a tree, with each one's processes being a "leaf."

Whenever a process begins,

a corresponding environment directory is dynamically created and linked to the parent directory, but no reference to context is fetched. The idea is reminiscent of demand paging, because contexts are fetched only when needed; but once fetched, they can be accessed by the parent directory. Thus, all "siblings" in a relational construct have access to the context.

Prolog's base in predicate calculus is actually settheoretical logic, the underpinning of relational theory. In fact, Prolog declarations look much like a record in a relational data base, a resemblance that Japan—and others hope to exploit. □



### **SWINGDUCTOR**

swinging chokes

a new and better way to **raise L** as you **lower I**(and vice versa).

Renco's new Swingductor<sup>TM</sup> is the first standard swinging choke ever that dependably and accurately swings from high inductance at low current to low inductance at high current — and back — with absolutely no outside help. So it's the simplest, most cost-effective way to make your power supply efficient from end to end. It's available from stock in 5 sizes (1.1" dia. x 1.5" width to 2.6" dia. x 1.5" width), with inductances from  $1.1\mu$ H to  $5600\mu$ H & current from 1.2A to 22A. Get complete data on how much each model swings with changing current so you can design your circuit around the inductance, rather than vice versa. It's all in our 46-page catalog which also includes full data on all the coils & transformers which we manufacture in the U.S.A. & ship worldwide. Call/write Marvin Scheck, 60 Jefryn Blvd. East, Deer Park, NY 11729. 516-586-5566. For engineering advice only, call toll-free 1-800-645-5828, from anywhere outside of NY State.

### RENCO ELECTRONICS, INC.



# THE BIGGEST LITTLE CHOKES AROUND

They handle higher currents — in smaller spaces — with no saturation.

They're our high-density power line chokes, Series RL-1256, with 265 standard values. 1  $\mu$ H to 47,000  $\mu$ H. Saturation currents to 155 Amps DC. Operating currents to 35 Amps AC.

The reason they can handle such high currents in such small space with no saturation — and with virtually no inductance variance — is the unique high saturation flux density ferrite material we use (plus, of course, our 30 years of inductance experience).

Simple to mount, they're perfect for switching regulators, power amplifiers, power supplies, SCRs, Triacs, speaker crossovers, RFI suppressors, and filters.

We design and manufacture in the USA and ship world-wide.
For our 46-page catalog of coils & transformers, call or write
Marvin Scheck, 60 Jefryn Blvd. East, Deer Park, NY 11729.
516-586-5566. For engineering advice or samples only, call toll free



A VERY PAST UPDATE ON MOS ROM DHYBLOPMENTS.

IFYOUTHINK
THAT SIGNETICS
ONLY WAKES-RUNGOF-IN-TE-WILL
PRODUCTS ITS TIME
YOUTURNED THE
PAGE

# A VERY FAST UPDATE ON MOS ROM DEVELOPMENTS.

We have nine different 150ns MOS ROM circuits—from 16K to 256K.

VLSI from Signetics
800-227-1817 Ext. 916 C





# The champ that can meet your challenge for any .085" centerline application.

The reason CHAMP connectors are specified for so many applications is simple. They do so much so well.

Like shielding IEEE 488 interconnects, eliminating solder in pc board mounting or interconnecting ribbon and jacketed cable.

With the innovative engineering of Accu-Plate selective plating and convenient mating hardware, every CHAMP connector gives you an extraordinary balance of value, technology and performance.

It's all based on our mass termination technology that leads the field in tooling and low applied costs.

All together, this line lives up to its name with no trouble. CHAMP.

For more details, call the CHAMP Information Desk at (717) 780-4400. AMP Incorporated, Harrisburg, PA 17105.

### AMP means productivity.


CIRCLE NUMBER 40



IEEE 488 versions, shielded or



Variety of configurations, hardware and assemblies for any requirement.



Compliant pin headers for solderless pc boards.

### Announcing the arrival of the world's first universal

### Standard Microsystems' HDC 9224 is so advanced it controls hard disks, floppy disks and even tape backup.

The new addition to Standard Microsystems' magnetic controller family is a single chip that controls Seagate-compatible hard disks, as well as IBM® compatible single- and doubledensity floppy disks.

A single chip that allows you for the first time—to include tape backup in a small computer without adding a lot of costly hardware and software.

A single chip so advanced its built-in DMA controller and ECC detect and correct errors with absolutely no processor intervention.


We've named this new addition the HDC 9224 Universal Disk Controller. But, you may call it one of the biggest breakthroughs in IC performance in a long, long time.

### The cornerstone of an intelligent subsystem.

The HDC 9224's ultraflexible

architecture makes it the true "next generation Winchester disk controller." With the addition of a few simple parts, you can use the HDC 9224 to build a high-performance, low-cost subsystem that controls up to four hard disks, floppy disks and tape drives.

The HDC 9224 easily interfaces to all popular ST506-compatible hard disk drives with up to 16 heads. Its flexible format command lets you select hard disk sector lengths up to 16 kilobytes and can be used with both



interleaved and non-interleaved sector formats.

The versatile HDC 9224 also controls all popular floppy disk drives, including the new 3.5-inch microfloppy. It can read and write, using industry-standard floppy disk recording formats, in both single and double density.

What's more, our popular FDC 9216 Floppy Disk Data Separator is fully compatible with the HDC 9224, and to further simplify your design tasks, we'll soon introduce two new companion chips—a Disk Buffer Manage-

ment Unit and a Hard Disk Data Separator.

### Available for immediate delivery.

Best of all, you can get the HDC 9224 when you need it the most. Today. In the near future, we also plan to announce a well-respected second source and several system-level board products for the PC-bus and other popular buses.

The HDC 9224 Universal Disk Controller is an n-channel, silicon-gate MOS/VLSI circuit fabricated with Standard Microsystems' COPLAMOS technology. It's available for immediate delivery in a 40-pin ceramic or cerdip dual in-line package.

For more information, contact Standard Microsystems
Corporation, 35 Marcus
Boulevard, Hauppauge, NY 11788.
(516) 273-3100.

 $\text{IBM}^{\otimes}$  is a registered trademark of the International Business Machines Corporation.



CIRCLE 35

# The Lundy UltraGraf is absolutely the fastest draw in the West or anywhere else.

This is the fastest, most intelligent 3-D computer graphics workstation available. The superlatives would seem to indicate a high price, too. But the Lundy UltraGraf workstation is surprisingly low cost considering its unmatched performance features.

At Lundy we don't develop technology for its own sake; we develop it to meet your needs. In the case of 3-D computer graphics workstations, you needed more speed, higher IQ, larger display and easier operation. UltraGraf delivers all four.

### The Lundy UltraGraf is first when it comes to speed and IQ.

Keys to UltraGraf's instant response are a high speed microcomputer and a high resolution vector display, both developed by Lundy.

Besides these features, we've designed more intelligence into the workstation, so UltraGraf places fewer demands on your host computer.

The result is unmatched interaction while freeing up your host computer to concentrate on other operations.

### $19 \times 15$ inches sets a new screen standard.

UltraGraf's 21-inch CRT has the largest viewing area—19×15 inches—in the industry. Fast vector drawing and mini-



Lundy UltraGraf sets 3-dimensional standards.

mum operator time produce easy-toread, flicker-free images. Spot size is only one ten thousandths of an inch, which produces remarkable crispness and clarity.

Furthermore, UltraGraf is easier to use. You send a picture only once, instead of resending over and over as

with many other systems. And you have local storage of all control functions for the interactive input devices. This provides maximum input flexibility, with minimum keyboarding.

### Lundy helps you see more in graphics.

When you take a close look at our graphics terminals, service, support, software, systems capability, enhancements—and our company—you'll understand why Lundy can help you see more in graphics now and in the long term.

For more information about our 3-D UltraGraf, or other CAD/CAM products, write Lundy Electronics & Systems, Inc., Glen Head, New York 11545, or call: (516) 671-9000.

LUNDY

Get the draw on sluggish productivity with Lundy's UltraGraf. Shown here are six views of a six shooter generated in just a matter of seconds.



### **VIEWPOINT**

### The quest for a standard 1/2-in. tape cartridge may well be unnecessary

### Raymond C. Freeman Jr.

Freeman Associates Santa Barbara, Calif.

f a standard is to emerge for 1/2-in. tape cartridges,' emphasizes Raymond C. Freeman, "it will almost certainly spring from the IBM e3480." He contends that IBM is already the clear-cut technological leader in high-performance 1/2-in. drives, giving it the needed authority to create a de facto standard. "In fact," he asserts, "manufacturers in a position to challenge this leadership have elected to wait and follow the company's lead."

As might be expected, Freeman's bold outlook is quite controversial. Some in the industry foresee a long hard climb ahead before standards emerge for 1/2-in. cartridges. Others believe just as fervently that manufacturers will endorse the smaller cartridge proposed by Digital Equipment and 3M. Despite such divergent opinions, Freeman sticks to his guns: "No one will successfully compete with IBM's package. It will be the standard for ½-in.

tapes for the next decade."

The 3480 cartridge, he explains, demonstrates how recording technology is moving in the same direction as computers and peripherals in general-toward smaller dimensions. Within its shell. which takes up only 4 by 5 by 1 in.. it stores more data than a  $10^{1/2}$ -in. reel of 1/2-in. group-code recorded tape (200 Mbytes formatted compared with 180 Mbytes unfor-



Since 1977 Raymond C. Freeman Jr. has headed up Freeman Associates, a consulting firm specializing in product and business strategies for manufacturers of storage peripherals. He also has worked at Applied Magnetics, Information Storage Systems, Honeywell Information Systems, and General Electric.

matted).

The cartridge comprises a single supply reel, with the take-up reel unconventionally mounted inside the drive itself. Its CrO<sub>2</sub> tape is split into 18 parallel tracks and has a density of roughly 19,000 bpi.

Though Freeman maintains that the IBM housing itself will be adopted as a standard, he readily admits that the drive—and even the type and composition of the tapemay be modified. Inevitably, he notes. OEM manufacturers will go with a serial or serpentine recording scheme, instead of taking the parallel path. Further, the special bias and head requirements of CrO<sub>2</sub> tape will probably make them opt for a more conventional coating.

As far as Freeman is concerned, other 1/2-in. cartridges, such as those proposed by Digital Equipment, MegaTape, and RossComp, are not really in the running to become standards. He backs his belief by pointing out that "in the high end of the industry, plug-compatible cartridge manufacturers have held off from making any commitments, waiting for IBM to make its move. Clearly, in the lower end also,

Stephan Ohr

### **VIEWPOINT**

they intend to follow its lead, thus effectively creating a standard.

"Their efforts will trickle down to the low-end OEMs who work strictly with serial recording and minis and supermicrocomputers." In fact, he believes that the high-end manufacturers will rapidly form a committee to adopt the standard, with makers of smaller drives quickly falling into line.

Freeman sees the 3480 tape drive as the "natural companion for 8-in. and high-capacity 5½-in. drives." In the long run, its greater storage area "will edge out ½-in. cartridges."

# Thin-film LCD technology could be the key to large-area flat panels

### Susumu Aizawa

Senior Managing Director Epson Corp. Nagano-Ken, Japan

wars," asserts Susumu Aizawa, "we'll see large-area liquid-crystal flat panels that display thousands of pixels side by side the CRTs now used with personal computers." The development, he states, may depend on devising active thin-film switching elements similar to those that are already at work in pocket-sized color LCD television receivers.

LCDs exhibit the lowest power consumption of any flat-panel technology and are the best bet for very slim fullcolor flat panels. "That's not to suggest," Aizawa concedes, "that there isn't still a lot of work to be done to boost

Martin Gold

display size, improve image quality, and cut manufacturing costs before LCDs with 80 characters and 25 rows become commonplace."



Since joining the Seiko Group's Epson Corp. in 1956, Susumu Aizawa has an impressive array of firsts. He developed the company's first analog quartz watch, its first digital printing mechanism, and its first thermal transfer printer. He holds a degree in precision mechanical engineering from Tokyo University.

To lick one of the problems associated with LCDs will require an approach different from the conventional passive one. Aizawa amplifies on this idea: "The present multiplexing schemes are limited to scanning 100 lines. When a greater number must be handled, the contrast ratio and viewing angle suffer." Active elements, on the other hand, enable at least 500 lines to be scanned.

Two structures are under investigation. One works with thin-film transistors mounted directly onto a glass substrate. The other goes with a bidirectional diode structure. Although the first is more familiar, it is the second that Aizawa sees as holding out the greatest promise.

These so-called metalinsulator-metal (MIM) LCDs consist of a thin layer of tantalum pentoxide sandwiched between tantalum and chromium. The device requires

# THE BIRTH OF THE ARRAY PROCESSOR AGE



ntil now, array processors have filled an important, but restricted, niche in the computing world. Analogic's AP500 has changed that. Because of its unique combination of flexibility, performance, and reasonable cost, the AP500 opens a vast number of computationally-intensive problems to array-processing power.

### THE ORIGIN OF THE **SPECIES**

As array processors have evolved, they have proven their worth in specialized, dedicated operations. In fact, Analogic's involvement with these devices started with such an application-a key subsystem in our invention of the first CAT-scan instant-image processor.

Building on this foundation, our engineers then developed the AP400 Array Processor, whose patented architecture set new standards for cost-efficient computing performance. The enthusiastic acceptance of the AP400 has resulted in one of the largest installed bases of any array processor-and continues today.

Now, the AP500 is here. It does not replace the AP400, rather it offers the user a new range of performance options for tackling increasingly complex problems in computer modelling, imaging, and design. With the AP500, state-of-the-art means more than computing speed. In continuing the tradition of

cost-effective computing performance and innovative design, our engineers have even given the AP500 standalone capability.

### THE NATURAL SELECTION

The AP500 meets or exceeds the performance characteristics of comparable array processors at 25% to 50% of their cost. It performs a 1024 pt. complex FFT in 4.68 ms, and a 50 X 50 matrix inversion in only 72 ms. Its other performance specs are equally impressive.

With 4 Mbyte of data memory, 384 kbyte of program memory, and high-speed

> bidirectional I/O capability, the AP500 can form the heart of a high-power computing work station. Its on-board co-processor means that it can even operate independently of a host computer for remote operations or applications which demand complex communication procedures, such as adding data block identifiers or handling packet protocols with incoming data.

We want to tell you more about using the AP500 to solve your problems. Just call Analogic's Computing Systems Group at

1-800-237-1011

Find out why the AP500 is ...

THE NATURAL SELECTION

**COMPUTING SYSTEMS PRODUCTS GROUP** 

Analogic Corporation, Audubon Rd., Wakefield, MA 01880, (617) 246-0300

### **VIEWPOINT**

only two or three masking steps and can be fabricated with sputtering techniques—keeping manufacturing costs down. Aizawa is quick to note that "the MIM LCD is quite suitable for large-area, high-contrast displays," pointing out that a 240-by-250-pixel array of 99 by 100 mm has already been created.

Turning to the more traditional structure, Aizawa explains that when the active element in a thin-film transistor turns on, data is written into a pixel. When the element turns off, a charge is stored within that thin film device that drives the liquid-crystal materials.

Working with active ele-

ments, the LCD driver circuitry can be integrated onto the same substrate as the LCD, keeping a lid on cost. The secret of the pocket-sized color LCD TV was the successful formation of 57,600 thin-film transistors on a glass plate. The resultant flat panel was only ½10 in. thick and 2 in. diagonally. It certainly could not have been produced with a CRT.

But, he adds, fabricating an array of thin-film transistors is no easy matter. It is created with processing techniques similar to those employed for 2- $\mu$ m VLSI devices and is thus subject to the same limitations. That translates into a wafer with a maximum diam-

eter of 6 in. In addition to the size restriction, assembling an active matrix array is quite expensive, so new active elements are being sought.

Aizawa is extremely optimistic about the future of flat panels, and about liquid crystals in particular. "By the end of the decade, I think we'll see flat panels that are the same size as today's CRTs and that resolve a maximum of 1000 by 1000 pixels—for graphics." The standard configuration will be a monochromatic 400-by-640-pixel array that shows 2000 characters. "By then," he concludes, "fullcolor and monochromatic arrays of 200 by 640 pixels will also be routine."□

# GET SET... FOR 16 & 32 BIT MICROPROCESSORS

WITH THE NEW ESP E12
SET PROGRAMMER



### **TECHNICALLY ADVANCED**

The First Set Programmer designed specifically for Engineering Applications ... with special instructions for splitting data into sets for both 16 and 32 bit microprocessors ... with approved capability for 512K EPROMS.

### HIGHLY RELIABLE

The reliability of the ESP family with over 2000 units installed . . . with complete device validation including the industry's only access time testing.

### **EASY TO USE**

Designed to connect to all common development systems and computers . . . with serial protocol "help" routines to solve interfacing problems.

### **COST EFFECTIVE**

A host of advanced features combined with the reliability of years of field experience . . . yours for a surprisingly modest price.

### ELECTRONIC SYSTEM PRODUCTS, INC.

1135—C San Antonio Road Palo Alto, California 94303 Telephone: 415 964 5338

EPROM Expertise



### UNITED CHEMI-CON KNOWS THE INS & OUTS



### OF SWITCHING POWER SUPPLIES

United Chemi-Con knows power supplies. Input and output. We were the first to design a complete line of aluminum electrolytic capacitors specifically to meet the exacting demands of power supply manufacturers.

**High ripple.** Up to four times the ripple current of standard capacitors.

**High capacitance values.** Scaled-down for high capacitance in a miniature case.

Low inductance. Long, slim design for output capacitors to reduce inductance where it counts.

**Wide temperature range.** Up to +85°C for input and -55 to +405°C for output series.

**Venting.** Vents designed for safety and a tight seal. **Plug-in mounts.** Snap-in or straight mounts on input series for PC boards.

For more on the ins and outs of power supplies, call or write for our new booklet, Understanding Aluminum Electrolytic Capacitors Part II, a basic guide to power supply applications.



Low profile, high capacitance, high ripple in a small can.




High capacitance in a low profile case size.



High ripple, up to 4 times the ratings of our general series.



High performance, low impedance in a miniature size.



Solvent-proof, low impedance, high ripple in a miniature size.



Low impedance, low ESR, long operating life in a small can.




Very high capacitance, very low ESR, long operating life.



Solvent-proof, miniature, a case as small as D4 x 7mm.



### UNITED CHEMI-CON INC.



New Cherry Pulse Width Modulators...pin for pin interchangeable with the PWMs you're now using.

Interchangeable PWM Control Circuit Numbers

Our PWMs are good enough to be your first choice. Already have a source? Try Cherry Semiconductor for the following reasons:

Cherry specializes in Bipolar ICs. Our many years of experience in Linear Bipolar Processing means improved performance and reliability. And we're geared for high volume, low cost production. We'll handle your needs fast. Competitively.

The Cherry lineup of PWM control circuits offers a solution for nearly every application. From a basic circuit with a minimum of extra features, to a sophisticated type with all the functional support and protection options you'll likely want, Cherry has it.

The next time you need PWMs, contact Cherry Semiconductor. We'll give you a real choice.

Intercha	Interchangeable PWM Control Circuit Numbers							
Industry Type	Cherry Semiconductor Type	Industry Type	Cherry Semiconductor Type					
NE5560 SE5560	CS-5560 N CS-5560 S	SG1527A SG2527A SG3527A	CS-1527A CS-2527A CS-3527A					
NE5561 SE5561	CS-5561 N CS-5561 S	TL593C TL594C	CS-593C CS-594C					
SG1524 SG2524 SG3524	CS-1524 CS-2524 CS-3524	TL594I TL594M TL595C TL595I	CS-594I CS-594M CS-595C CS-595I					
SG1525A SG2525A SG3525A	CS-1525A CS-2525A CS-3525A	UC1524A UC2524A UC3524A	CS-1524A CS-2524A CS-3524A					

Send today for complete technical data.

G: 1HRAY




SHIII CONDUCTOR

CHERRY SEMICONDUCTOR CORPORATION • 2000 South County Trail, East Greenwich, RI 02818 / (401) 885-3600

CIRCLE 41

# **MultiMod**<sup>™</sup> Multiple Output Switching Power Supplies. **The Proven Custom Alternative.**



### 300 to 1200 Watt Power Supplies With Up To 7 Outputs 2 to 48 VDC.

- Standard Off-The-Shelf Delivery
- VDE, IEC, CSA, UL Safety Specs
- FCC and VDE EMI Specs
- All Outputs Switching and Fully Isolated
- Field Selectable 115/230 VAC
- Efficiency Typically 75%
- Remote Sense
- Fully Regulated
- Extended Input Voltage Range: 90-132/165-265 VAC, 47-63 Hz
- Power Outputs at 50°C Derate Linearly to 50% at 70°C
- OVP with Crowbar & Inverter Shut-down
- Power Fail Signal
- Logic Inhibit
- Soft Start
- Brown Out of 85 or 160 VAC
- Reverse Voltage Protection
- 100% Burn-in
- Powertec's 19 Years of Proven Value

### MultiModular Construction **Using Standard Switching** Plug-In Modules.

MultiMod™ is a new concept in multiple output modular switching power supplies providing an alternative to costly customs. It allows you to choose your voltage/current combinations from a large selection of standard switching power supplies and standard auxiliary output modules, and we do the rest. The MultiMod switchers have 2 to 7 fully regulated outputs, which consist of one main output and 1 to 3 fully isolated plug-in output modules. These output modules are off-the-shelf standards which the designer can select as building blocks to provide his ideal voltage/current combinations. He is assured of dependable delivery of supplies which exactly match his unique requirements. And MultiMods operate with proven field reliability because they are put together

proven field reliability because they are put together with standard building blocks produced in high volume.

Main outputs use only pure switch mode design. All auxiliaries are also available as fully switching. Thus, the designer can be assured of maximum efficiency and minimum thermal stress. Post-linear regulated auxiliaries are also available. auxiliaries are also available.

Multiple outputs are available from 2 through 48 volts with modules rated from 12 to 1000 watts. Total output ratings available are 300, 400, 600, 850, 1000, and 1200 watts.

MM7 October 1984

### WERTEC

### Selector Guide-Multiple Outputs

See ValuSwitcher™ Family (19 Series) For Other Multiple Output Switchers.

The MultiMod™ is a new concept in multiple output switching power supplies providing 2 to 7 outputs. A building block approach using a selection of flexible "power packages" and standard plug-in output modules provides voltage/current outputs tailored to your specific requirements. The power supply is delivered totally assembled and tested, using the output modules you have selected to meet your needs.

- Select the "power package" that meets your total output power requirements (300 to 1200 watts) by referring to the "Power Package Selector Guide
- Select the output with the highest output power by referring to the "Main **Output Selector Guide**!
- · Select lower power outputs (auxiliary plug-in modules) by referring to the

- · Each power package accommodates one main output plus space for up to three one-space-wide auxiliary modules.
- · One-space-wide auxiliary modules are available with 1 and 2 isolated
- Column Two of the "Main Output Selector Guide" indicates the quantity of one-space-wide auxiliary modules that may be used with the main output
- "Auxiliary Spaces Occupied" column of the "Auxiliary Module Selector Guide" indicates the quantity of spaces each auxiliary module occupies (1 to 3 spaces).
- · See "Order Information" (Page 3) for more details

### **POWER PACKAGE SELECTOR GUIDE**

Model Package	Max. Power¹ 50°C		Max. No.	Number	Dimensions	
nation	Output Power <sup>1,2,3</sup>	Main	Auxs.4	Modules <sup>13</sup>	Outputs <sup>7</sup>	
6E	3005	2005	2005	3	1 to 4	2.75" x 7.62" x 11.75"
6F	400	250	200	3	1 to 4	5" x 7.62" x 11.75"
6JA	600	384	250	3	1 to 6	5" x 8" x 11"
6JB	600	528	250	2	1 to 5	5" x 8" x 11"
6L	850	768	360	3	1 to 7	5" x 8" x 14.83"
6M	1000	768	360	3	1 to 7	5" x 8" x 14.83"
6МВ	120017	1000	360	3	1 to 7	5" x 8" x 14.83"

### AUXILIARY MODULES SELECTOR GUIDE— SINGLE OUTPUTS

Module Appli-		C	output F			Load	Ripple	Aux.
Desig- nation <sup>11</sup>	cable Models <sup>12</sup>	Volts <sup>16</sup>		mps1,2	glad equipment of the contract	Regula- tion	& Noise % P-P	Spaces Occu-
			40°C	50°C	70°C	%15		pied8
F	6E, 6F	2	6	6	3.0	0.2	3.0	1
К	6J	2	8	7	3.5	0.2	2.5	1
F	6J	2	11	10	5.0	0.2	2.5	1
K	6L, 6M	2	9	8	4.0	0.2	2.5	- 1
F	6L, 6M	2	15	15	7.5	0.2	2.5	1
М	6J	2	50	50	25.0	0.2	2.5	2
A	6E, 6F	5	6	6	3.0	0.2	2.0	1
L	6J	5	8	7	3.5	0.2	1.0	1
A	6J	5	11	10	5.0	0.2	1.0	1
L	6L, 6M	5	9	8	4.0	0.2	1.0	1
Α	6L, 6M	5	15	15	7.5	0.2	1.0	1
В	6E, 6F	12	6	6	3.0	0.2	2.0	1
Р	6J	12	8	7	3.5	0.2	1.0	1
В	6J	12	11	10	5.0	0.2	1.0	1
P	6L, 6M	12	9	8	4.0	0.2	1.0	1
В	6L, 6M	12	15	15	7.5	0.2	1.0	1
С	6E, 6F	15	6	6	3.0	0.2	2.0	1
U	6J	15	8	7	3.5	0.2	1.0	1
С	6J	15	11	10	5.0	0.2	1.0	1
U	6L, 6M	15	9	8	4.0	0.2	1.0	1
С	6L, 6M	15	15	15	7.5	0.2	1.0	1
D	6E, 6F	24	6	6	3.0	0.2	2.0	1
Y	6J	24	4	4	2.0	0.2	1.0	1
D	6J	24	8	8	4.0	0.2	1.0	1
Y	6L, 6M	24	4	4	2.0	0.2	1.0	1
D	6L, 6M	24	10	10	5.0	0.2	1.0	1
G	6E, 6F	48	3	3	1.5	0.2	2.0	1
G	6J, 6L, 6M	48	5	5	2.5	0.2	1.0	1

### MAIN OUTPUT SELECTOR GUIDE

	Auxiliary <sup>13</sup>	Mai	n Outpu			Load	Ripple &
Model No.	Spaces Available	Volts <sup>16</sup>	Amps1,2,3			Regula- tion %	Noise % P-P
	Available		50°C	60°C	70°C	tion %	
6JA2-XXX-17	3	2	70	53	35	0.5	2.5
6JB2-XX-17	2	2	100	75	50	0.5	2.5
6L2-XXX-17	3	2	200	150	100	0.5	2.5
6M2-XXX-17	3	2	200	150	100	0.5	2.5
6E5-XXX-17	3	5	405	305	205	0.2	2.0
6F5-XXX-17	3	5	50	37	25	0.2	2.0
6JA5-XXX-17	3	5	60	45	30	0.2	1.0
6JB5-XX-17	2	5	90	68	45	0.2	1.0
6L5-XXX-17	3	5	150	113	75	0.2	1.0
6M5-XXX-17	3	5	150	113	75	0.2	1.0
6MB5-XXX-17	3	5	20017	113	75	0.2	1.2
6JA12-XXX-17	3	12	28	21	14	0.2	1.0
6JB12-XX-17	2	12	42	32	21	0.2	1.0
6L12-XXX-17	3	12	62	47	31	0.2	1.0
6M12-XXX-17	3	12	62	47	31	0.2	1.0
6JA15-XXX-17	3	15	24	18	12	0.2	1.0
6JB15-XX-17	2	15	34	26	17	0.2	1.0
6L15-XXX-17	3	15	50	38	25	0.2	1.0
6M15-XXX-17	3	15	50	38	25	0.2	1.0
6JA24-XXX-17	3	24	16	12	8	0.2	1.0
6JB24-XX-17	2	24	22	17	11	0.2	1.0
6L24-XXX-17	3	24	32	24	16	0.2	1.0
6M24-XXX-17	3	24	32	24	16	0.2	1.0

NOTE: 3.3 volts main outputs and auxiliary outputs are available upon request. Contact Factory.

### **AUXILIARY MODULES SELECTOR GUIDE—**

Module Designation 11 Applicable Models 12	Appli-	Output Ratings				Load	Ripple & Noise	Aux. Spaces Occu-
	cable				Regula- tion			
	Voits 10	40°C	50°C	70°C	%15	% P-P	pied8	
6JA 8	12	6/9 pk.	5/8 pk.	2.5	0.2	1.0	1	
н	R & & 6JB	12	6/9 pk.	5/8 pk.	2.5	0.2	1.0	1
	6JA	15	6/9 pk.	5/8 pk.	2.5	0.2	1.0	1
6JB	15	6/9 pk.	5/8 pk.	2.5	0.2	1.0	1	

- Maximum continuous output power may not exceed the product of rated current and voltage (measured at the output terminals) specified in the Selector Guide at indicated temperatures.
- 2. Higher peak current ratings may be obtained. Contact Factory.


  3. Maximum output power at 50°C of combined main and auxiliaries may not exceed the total package power indicated.

  4. The combined power for all auxiliaries may not exceed power rating
- 5. Higher current and power ratings attainable with moving air (6E only).
- 6. "M" Auxiliary: Substitute "operating load current" for "rated max."
  7. Number of outputs is determined by the output plug-in modules
- Numbers of spaces occupied by auxiliary module. Due to mechanical factors, 6JA and 6JB power packages are limited to no more than 2 "R" or "T" modules. Total number of outputs possible, including main, is
- or "1" modules, total number of outputs possible, including main, is therefore 6 and 5 outputs respectively. 9.6J, 6L, 6M: Factory strapped for 230 VAC input, 6E, 6F: Factory strapped for 115 VAC input. Customer may change input strapping. 10.Class 1 Non-SELV: Meets European safety requirements except in cases where a system does not provide for grounding, or where the



### Powertec Series 6 Specifications

See SuperSwitcher™ Family (9 Series) For Single Output Switchers From 400 to 1700 Watts.



### safety-agency-permitted components tied to case.

**Standard Options** 

\*\*Production Test

### P G 2 3 4 5-SXXXX **Custom Options & Modified Standards** 5: Parallel Option (Contact Factory) 4: Factory Wired 230 VAC (6E & 6F)9 3: CSA Logo14 2: Reverse Fan: 6J, 6L, 6M G: Power Good Option (6L & 6M only) P: Ball-bearing Fan D: Power Fail Option (all models) C: Cover Option: Applicable to 6E only, standard on others. B: EMI Filter-6E. 6F. 6J meet FCC 20780 Class A oL, or, of meet received that says. 6L and 6M (non-strappable 165-265 VAC input, version "3" only) meet FCC 20780 Class B and VDE 0871 Class A. X: Powertec assigned revision letter when applicable. 7: INPUT VOLTAGES (3 or 7)

3. 165 to 265 VAC (47-63 Hz); 6L, 6M only 7. 90 to 132 VAC (47-63 Hz) and 180 to 264 VAC (47-63 Hz) field selectable: 6E, 6F, 6J, 6L, 6M

Note: For 400 Hz operation contact factory.

### SAFETY and INPUT VOLTAGE (See "Order Information" above.)

### **AC INPUTS**

Brown Out—Regulates through short term line dips to at least 85 or 160 VAC

Inrush Current—Limited to 4X operating current to prevent nuisance tripping of protective circuit breakers and fuses.

Turn On Time-0.2 sec. max. for power up.

Undervoltage Inhibit—Protected against malfunction due to AC undervoltage operation.

### DC OUTPUTS

Adjustments—(  $\pm$  % of nominal voltage.) All Main Outputs: ± 10% 6J & 6M Auxiliaries; A, B, C, D, F, G: ± 10%. 6J & 6M Auxiliaries; K, L, P, U, Y: +5%, -2%. All 6E, 6F & "M" Auxiliaries: ±5%.

Line Regulation—6J, 6L, 6M: 5 mV or 0.1% over input range. 6E and 6F: ± 0.2% over input range.

Load Regulation—10 mV or 0.2% at any load up to 100% of rated load with remote sense connected; 0.2 mV/amp with internal sense; auxiliary modules with internal sense are 3 mV/amp.

**Dynamic Response**—A step load change of  $\pm$  25% of rated max<sup>6</sup> will cause a max. deviation of 3%. Output will recover to within 0.1% of nominal in 400 µsec.

Thermal Regulation—  $\pm$  0.02%/°C over operating range.

Ripple & Noise—See Selector Guide on page 2. Measured on 20 MHz scope via X1 probe having 4 inch maximum return lead.

Hold-up Time—Fully loaded outputs remain within regulation for 20 msec. minimum for the 6E and 6F following the last line voltage peak, measured from either 115 VAC or 230 VAC. Other values of hold-up are noted as follows:

### HOLD-UP TIME vs. INPUT VOLTAGE (6J, 6L, 6M)

V <sub>in</sub> CODE		7		3,	7	
NOMINAL VAC	90	115	165	180	208	230
HOLD-UP (msec.)	10	30	5	10	20	30

Efficiency—Exceeds 75% typically.

Loading vs. Temperature-100% rated load from 0 to 50°C. Derate linearly to 50% at 70°C.

Current Limiting—Foldback type, with automatic recovery upon removal of overload.

### **OVER VOLTAGE PROTECTION**

OVP Inverter Shut-down (Standard)—All outputs: Initiates inverter shut-down and latches supply off. Trip point at output terminals are factory set within the following windows:

NOMINAL OUTPUT	2V	5V	12V	15V	24V	48V
TRIP WINDOW	2.8-3.2V	6.5-6.9V	14-16V	17-19V	27-29V	54-57V

Remove AC input for 30 sec. to restore operation.

OVP Crowbar—An SCR crowbar across the output terminals short circuits output to protect load against excessive voltage. 6E, 6F, 6L, 6M have crowbar on main outputs. 6E, 6F auxiliaries and 6J, 6L, 6M low current auxiliaries (e.g. P) also have crowbar. All others have inverter shut-down

### REVERSE VOLTAGE PROTECTION

Main outputs protected up to rated load. Auxiliary outputs protected to 50% rated load.

### REMOTE SENSE

Separate sense terminals will accommodate a cable drop of 0.5 VDC. (See Note 1.) Internal circuitry protects load if sense lines are opened or shorted.

Margining: Fixed internal resistors can be installed to permit adjustments up to  $\pm$  10% for main output. Contact factory regarding auxiliaries.

### **POWER FAIL SIGNAL**

(Option)—Following the loss of AC input, a TTL compatible signal referenced to the negative terminal of the main output will change from high to low at least 2 msec. before the loss of output.

### POWER GOOD SIGNAL (Standard Option of 6L and 6M)

(Option)—A TTL compatible signal referenced to the main negative output terminal will change from high to low if the output voltage deviates more than  $\pm$  4% from nominal.

### LOGIC INHIBIT

6J, 6L, 6M: A TTL high signal referenced to the negative output terminal inhibits the output; a TTL low, or open input, enables the

6E, 6F: TTL low inhibits output.

Total Power Supply: Shut-down all outputs when main output is inhibited. Standard on all models.

Auxiliary Output: 6L, 6M: Total shut-down of individual output. 6J: Less than 1 volt.

### WARRANTY-1 year

possibility exists that an operator (maintenance personnel excepted) can come into physical contact with the power supply or its load

- 11. The Designation only represents the voltage and current output specs provided (NOT THE LOCATION). Powertec must determine the location of the auxiliaries. 12. Model (Power Package) in which the auxiliary module specifications
- 13. Number of one-space-wide spaces available for auxiliary modules.

  Corresponds to "Auxiliary Spaces Occupied" column of the Auxiliary
  Module Spaces Occupied Module Selector Guide.
- 14. CSA logo added upon request. Powertec has been granted self-certification status by CSA.

  15. When maximum auxiliary power is being used as shown in the Power Package Selector Guide, the load on the main output must be the following minimum percentage of the "Total Package Output Power" rating at 50°C: (6E: 8%), (6F: 6.5%), (6±) 10%), (6L, 6M: 7.5%). Lacking the above, auxiliary output voltages will decrease. Less minimum power on the main is required with reduced auxiliary loads.

  16. Other voltages available on special order.

  17. 40°C ratings. Hold-up time is 70% of specification. Minimum low line input voltage is 5% higher than specified.

  MM7 October 1984

Contact Factory to Obtain Powertec's Free Loose-Leaf Binder/Catalog to Which You May Add This and Other Product Brochures Which Are Published Monthly.


### MultiMod Package Specifications

See SuperSwitcher™ Family (9 Series) For Single Output Switchers From 400 to 1680 Watts.


See ValuSwitcher™ Family (19 Series) For Other Multiple Output Switchers From 50 to 400 Watts.


MODEL 6JA/6JB

# AIR FLOW FOR 6F ONLY 6F ONLY 2.35 MAX. 8F ONLY 1.50 1.5



NOTE: The locations for the specified auxiliaries must be determined by Powertec.





Contact Factory to Obtain Powertec's Free Loose-Leaf Binder/Catalog to Which You May Add This and Other Product Brochures Which Are Published Monthly.

MM7 October 1984

### **POWERTEC**

The Power in DC Power Supplies



### "Fine Line" Circuitry: When You Need Conductors Finer Than A Human Hair.

Miniaturization marches on. When round wire became too heavy and bulky, flat cable and flex circuitry were developed. Now, density requirements can be too tough even for conventional flex circuitry. So that's where "Fine Line" takes over.

What it is. Circuitry, as shown above, with lines and spaces of less than .010. Our current production capabilities range down to .003. That's "Fine Line."

Where it's used. Satellite circuits, high-speed computer interconnects, cryogenic infra-red detectors, thermal imaging sights, mother board/daughter

board interconnects, test equipment, and much more.

We're ready to work with you. Call your nearest Hughes rep, or phone us in Irvine. Our R&D people are at your service. Our circuitry is as fine as it comes. Today. The future? How about invisible conductors?

For more information phone Tony Piraino, 714-660-5788. Or write Hughes Aircraft Company, Connecting Devices Division, 17150 Von Karman Avenue, Irvine, CA 92714. In Europe, Hughes Microelectronics, Ltd., Clive House, 12-18 Queens Road, Weybridge, Surrey KT13 9XD, England.



# 1-800-5 Realism for your new entertainment

As an entertainment system designer, you know that today's electronics technology permits the generation of CRT-displayed graphics with all the fidelity of a first-quality color motion picture; but until now, not at a price economically feasible for low- and medium-priced entertainment equipment.

High-quality graphics generators have required a stack of printed circuit boards densely packed with SSI/MSI integrated circuits at a cost well beyond sensible budgets for low-cost microcomputer systems. This has caused the majority of graphics displays for popularly-priced entertainment systems to suffer from limited resolution and color selectivity.

### New high-quality graphics at a remarkably low cost.

Entertainment systems can be vastly improved now with design-in support and low-cost technologies from Motorola. For colorful, high-resolution graphics in home video and computer games where realistic computer animation is needed, there's Motorola's cost-effective Raster Memory System (RMS). This available-under-\$20 in-production-volume chip set at last makes

professional, quality graphics affordable for your next entertainment system.

Using only two chips, the RMS, under MPU control, converts a graphics program stored in memory into the complex video stream that can produce high-quality displays on the CRT. At an astonishingly low cost. No longer is expensive static display RAM needed. The RMS utilizes system memory comprised of industry-standard DRAM with capacities ranging from 16K to 1M bytes.

With the RMS you can select 32 colors from a universe of 4096 shades to use on a virtual accommodating and smooth scrolling screen.

With the advent of the RMS, graphics quality is now primarily dependent on the sophistication of the software, the amount of memory available and the power of the MPU.

### A range of MPUs for every entertainment application.

The RMS chip is designed to operate with a wide range of processors including three of Motorola's powerful MPUs: the 8-bit MC6809, the 8/16-bit MC68008 and the 16/32-bit MC68000.

Motorola's MC6809 MPU has the most complete set of addressing modes available on any 8-bit microprocessor today and interfaces with over fifty M6800 peripherals. In addition, you're never locked into a specific design with an upward source-code compatible instruction set.

The MC68008 MPU allows the design of cost-effective systems using 8-bit data buses while providing the system throughput benefits of a 32-bit microprocessor architecture. The performance of the MC68008 is greater than any 8-bit microprocessor and superior even to several 16-bit microprocessors.

The industry-leading MC68000 is a fully-implemented 16-bit microprocessor with 32-bit registers, a rich instruction set and versatile addressing modes.

With this line of compatible processors, you'll satisfy all the price/performance tradeoffs in your design requirements.

### Modulators and encoders give the big picture.

For supplying signals to color monitors, Motorola supplies a full line of modulators and industry-standard encoder circuits.

The MC1374 is a TV modulator circuit that packs an FM audio modulator, sound carrier oscillator, RF oscillator, and RF dual input modulator all on one low cost chip. It is designed to generate a TV signal



from both audio and video inputs. The MC1374's wide dynamic range and low distortion make it particularly well-suited for applications such as video tape recorders, video disc players, TV games and subscription decoders.

The MC1377 is a color television RGBto-PAL/NTSC encoder used to generate a composite TV signal from baseband red, blue, green and sync inputs. It is ideal for encoding signals from color cameras and graphics generators.

### Opening new markets with AM stereo.

Radio designers are noting the significant advantages AM stereo has over FM in range of coverage and fade resistance.

Motorola's CQUAM® (Compatible Quadrature Amplitude Modulation) AM stereo decoder is a complete one-chip full-feature AM stereo decoding and pilot detection system. It employs full-wave envelope signal detection at all times for the L+R signal, and decodes L—R signals only in the presence of a valid stereo transmission. The MC13020P needs no adjustments, uses no coils and has few peripheral components.

In the absence of a good stereo signal, CQUAM® produces an undegraded mon-

aural output for existing radios. When both channels are modulated the noise increase in stereo is a maximum of 3.0 dB... even less on program material.

Years of refinement have made Motorola's CQUAM® the leading contender in the race for a "world standard" in AM stereo systems. Even with four FCC approved competitors, Motorola's CQUAM® has captured more than 140 new AM stereo stations this year and leads in production with over nine major manufacturers.

### Talk engineer to engineer.

Motorola has tripled the number of application engineers it has throughout the U.S. and Canada.

Each has the expertise in emerging semiconductor technologies that can electrify your new entertainment design ideas. Call 1-800-521-6274 and discuss your applications. Any time between 9 A.M. East Coast and 5 P.M. West Coast time, weekdays. Toll free. Talk to our specialists. They'll discuss your applications and get you in touch with a field application engineer who'll in person describe in depth

The RMS system can simultaneously display any 32 colors from its palette of 4096 colors in adjacent pixels. The above illustration is a continuous tone artist's representation.

CQUAM is a registered trademark of Motorola Inc.

how Motorola products can bring new excitement to your entertainment designs at minimum cost.

### 1-800-521-6274


Wait'll you hear what we have in store for your new design. Be it in entertainment equipment, industrial or office automation, voice/data communication, or any other electronics-driven industry, we'll work with you at any level of chip, board or box integration through the industry's premier technical field organization.


A Motorola semiconductor field application engineer is in the right location with the right expertise to help you.

Call us on it.
One call. One source.
For all your
semiconductor
needs. Motorola
Semiconductor
Products, Inc.
P.O. Box 20912,
Phoenix, AZ 85036.

We're on your design-in team.







### Mil-Spec Approved Low Profile Resistor Networks

- Mil qualification approval per MIL-R-83401 in all pin styles, /07 (6-pin), /08 (8-pin), /09 (10-pin)
- Both pull-up (C) and terminator (G) configurations
- Tolerances: F(± 1%), G(± 2%) and  $J(\pm 5\%)$
- Temp coefficient // Resistance Range: K:  $\pm 100 \text{ PPM/}^{\circ}\text{C} // 47.5 \text{ to } 1 \text{ M}\Omega$ M:  $\pm$  300 PPM/°C // 10.0 to 1 MΩ

CIRCLE 135

### Low ESR Computer Grade Aluminum Electrolytic Capacitor-Series 3189

- Innovative non-DMF electrolyte & new construction techniques provide lowest ESR ever offered
- İmproved ripple current capability
- Operating life: 1000 hrs. at 85°C with full rated DC voltage
- Capacitance: 0.0032 to 0.76F
- Voltage range: 5 to 75 WVDC
- 38 std. case sizes from  $1\frac{1}{8}$ " to 3" dia. Operating temp:  $-40^{\circ}$  to  $+85^{\circ}$ C
- Offered in PCB mounting configuration or with std. screw terminals
- A 2000 hr. long life version (Series 3190) also available

### CIRCLE 136





### Commercial SMD (Chip) Resistor-Series 9C

- Ideal for use with high speed, automatic placement equipment
- Provides dramatic reduction of PCB real estate in new designs
- International std. size: 1.6 × 3.2 mm
- Power Rating: 1/8w @ 70°C
- Tolerance // Resistance // PPM/°C % Ω  $\pm 1$ 10 to 1M  $\pm 100$  $\pm 5$ 10 to 1M  $\pm 200$  $\pm 10$ 1.2M to 10M  $\pm 200$
- Zero ohm unit is also available
- Bulk or tape and reel packaging

### CIRCLE 137

Corporate Headquarters Columbia Rd., Morristown, NJ 07960 (201) 539-2000 TWX 710/986/7437

Reliability across the board Mepco//Electra A NORTH AMERICAN PHILIPS COMPANY

### INTERNATIONAL NEWSFRONT

### Array chip's eight cells build custom filters to eighth order and higher

In a method drawing on gate-array techniques, a switched-capacitor filter's properties can be spelled out during final metallization.

y specifying the sep-arate parts of a switched-capacitor filter during the final metallization stage of a prediffused and prewired structure, an eight-cell CMOS array can create virtually any type of a filter—as high as the eighth order. A cascaded arrangement of the arrays can produce even higher-order filters.

The array chip drifts less and holds tighter tolerances than comparable filters, many of which depend on external resistors for the required filtering characteristics. Furthermore, unlike software-programmable filters, which demand registers and decoders, the cells also occupy far less chip space. Perhaps the most rewarding aspect, it slashes design time to one-fourth the six to eight months required for totally custom filters.

Developed at Thomson Semiconductors (Grenoble, France), the array chip can be cascaded in combinations of two basic cells: one for filters with an odd number of stages. the other for filters with an even number.

### With or without


Each cell's inputs feed a CMOS transconductance operational amplifier and an integrating capacitor (see the figure). Inputs I<sub>1</sub>, I<sub>2</sub> and I<sub>3</sub> can be weighted or added to or subtracted from one another. By connecting two clock phases from the on-chip generator to switches input lines I4 through I6 (or I7 in even-stage filters), the inputs can be selected for inverting or noninverting integration, with or without a programmed delay.

A filter's cutoff frequency-ranging from a few hertz to about fifty kilohertz-is set by the ratio between the sampling frequency and the filter rate, both of which derive from an external oscillator. The internal clock generator is essentially a maskprogrammable divider that converts the external clock into the filter's internal one. Internal level shifters work with TTL clock inputs.

### Extra op amps

Two uncommitted op amps on the 8.5-mm<sup>2</sup> chip afford extra gain and output current. Alternatively, they can be used in prefiltering or postfiltering setups.

With the easily customized arrays, designers can create entire families of low-pass. high-pass and band-pass versions of Butterworth, Cauer. and Chebyshev filters. Thomson also plans to use the arrays for standard filters.□



To customize high-order switched-capacitor filters with an eight-cell array chip, designers can specify interconnections and capacitance value during final metallization of a cell for an odd number of stages (a) and for an even number (b). By connecting the chip's clock generator to switches, the outputs can be inverting or noninverting.

Mitch Beedie

Ferranti covers the small signal mosfet market from N to P.

Offering one of the most comprehensive ranges of small signal mosfets, Ferranti Semi-conductors covers the market with a complementary line of N & P channel devices.

Our advanced production techniques, coupled with years of semiconductor manufacturing experience, help us achieve excellent production yields. This, in turn, enables us to produce extremely cost-effective mosfets.

The benefits to our customers are highly competitive pricing, readily available products and short lead times.

Product specifications range from breakdown voltages (BVdss) of 20 to 350 volts and current handling capability (Id) of up to 4 amps continuous. And, due to the unique Ferranti mosfet design structure, low threshold, low leakage and high-speed devices are available as standard products.


We'd like to send you our free mosfet package, which includes a Product Selection Guide, Application Notes and a complete Small Signal Data Book. Call us at (516) 543-0200 or complete and return the coupon below.

# FERRANTI semiconductors

Yes, I'd like to receive your free mosfet package.



Name
Title
Company
Address
City/State/Zip
Phone ( )
Detach and mail to: Ferranti Semiconductors 87 Modular Avenue, Commack, NY 11725



### INTERNATIONAL MEETINGS

Cadcam International Show, Jan. 8-10. National Exhibition Centre, Birmingham, England. Peter Walker or Landy Hashimi, PWA, 32 Fitzroy Square, London W1P 5HH; (01) 388-9871.

Micro-Computer '85, Jan. 29-Feb. 3. Frankfurt, West Germany. Philippe Hans, German American Chamber of Commerce, 666 5th Ave., New York, N.Y. 10103; (212) 974-8856.

Middle East Electricity and Electronics Exhibition, Feb. 2-6. Jeddah Expo Center, Kingdom of Saudi Arabia. Len Bennett, Logistics, 237 Park Ave., 21st floor, New York, N.Y. 10017; (212) 551-3530.

AFIPS-Asia '84, Feb. 14-March 2. m.v. World Wide Expo, Tokyo, Osaka, Kitakyushu, Taipai, Hong Kong and Singapore. AFIPS, 1899 Preston White Drive, Reston, Va. 22091; (703) 620-8926.

Autotech Hong Kong '85, March 7-8. Hong Kong. Autotech Hong Kong '85, Hong Kong Productivity Center, 12th floor, World Commerce Center, 11 Canton Road, Tsimshatsui, Hong Kong; 3-7235656.

Componentes Electronicos '85, March 12-15. Mexico City, Mexico, March 19-22, Guadalajara, Jal., Mexico. Raquel Polo, United States Trade Center, Liverpool 31 Col., Juarez 06600, Mexico, D.F.; or PO Box 3087, Laredo, Texas 73044.

The Scottish Computer Show and Conference, March 12-14. Anderston Exhibition Centre, Albany Hotel and Holiday Inn Hotel, Glasgow, Scotland. Cahners Exhibitions Ltd., Chatsworth House, 59 London Road, Twickenham, London TWI 3SZ, England; (01) 891-5051.

China Tronic '85, March 14-19. Tianjin Exhibition Centre, Tianjin, Peoples' Republic of China. Asdale Exhibition Services, 109-111 Gloucester Road, 21st floor, Wanchai, Hong Kong; 5-8920511.

Comtel '85, March 18-20. Infomart, Dallas, Texas. Comtel '85, International Computer & Telecommunications Conference, 5080 Spectrum Drive, Suite 707E, Box 17, Dallas, Texas 75248; (214) 631-6482. Automatic Testing and Test Measurement '85, March 19-21. Rhein-Main-Halle, Wiesbaden, West Germany. Network Events Ltd., Printers Mews, Market Hill, Buckingham, MK18 1JX, England; (0280) 815226.

Networking '85, March 23-31. Tokyo, Japan. Brad Ketchum, INC. Publishing Corp., 38 Commercial Wharf, Boston, Mass. 02110; (617) 227-4700 or Aki Tsurukame, Pacific Catalyst Group, 650 Grand Ave., Suite 1004, Los Angeles, Calif. 90017; (213) 614-0049.

IEEE Infocom '85, March 25-28. Washington, D.C. Celia L. Desmond, IEEE Infocom '85, Room 1855, 160 Elgin St., Ottowa, Ont., Canada K1G 3J4; (613) 239-4510.

Bit '85 Computer Show and Conference, March 26-29. National Exhibition Centre, Birmingham, England. Cahners Exhibitions Ltd., Chatsworth House, 59 London Road, Twickenham, London TW1 3SZ, England; (01) 891-5051.

Comdex In Japan, March 26-28. Tokyo International Trade Center, Tokyo, Japan. Milton Berns, The Interface Group Inc., 300 First Ave., Needham, Mass. 02194; (617) 449-6600.


32nd International Electronics, Energy and Aerospace Exhibition (Riena), March 26–31. Rome, Italy. Riena, Via Crescenzio 9, 00193 Rome, Italy; (06) 6569343/4/5.

Internepcon/Semiconductor International, March 27-30. Korea Exhibition Center (Koex), Seoul, Korea. Cahners Exposition Group, 7315 Wisconsin Ave., PO Box 7007, Washington, D.C. 20088; (301) 657-3090.

Unix Systems Expositions '85, April 2-4. Palais des Congres, Paris, France. Networks Events Limited, Printer Mews, Market Hill, Buckingham, MD18 1JK, England; (0280) 815226.

Electronics and Electrical Engineering Exhibition, April 17-24. Hanover, West Germany. Hanover Fairs, PO Box 338, Whitehouse, N.J. 08888; (800) 526-5978 or (201) 534-9044.

### 2-way 90° Splitters



### 1.4 to 450 MHz from \$1295 (5-49)

IN STOCK ... IMMEDIATE DELIVERY

- over 50 models available
- · octave and narrow-band designs
- quadrature performance tightly controlled
- · hermetically sealed
- MIL-P-23971 performance\*
- one-year guarantee
   \*Units are not QPL listed

### 2-WAY 90° SPECIFICATIONS

- isolation 22 dB typ.
- avg. insertion loss 0.4 dB typ.
- 90° phase deviation <2 deg. typ.
- amplitude unbalance < 1.2 dB typ.

MHz	\$Ea.
1.4 – 1.7	12.95
3.0 - 3.8	16.95
5.8 - 7.0	12.95
7.0 - 8.0	12.95
9.0 - 11.0	12.95
12 – 14	12.95
12 - 16	16.95
20 - 23	12.95
25 - 50	19.95
40 – 70	19.95
55 – 90	19.95
80 - 120	19.95
120 - 180	19.95
150 - 250	19.95
250 - 400	19.95
350 – 450	19.95
	MHz  1.4 - 1.7 3.0 - 3.8 5.8 - 7.0 7.0 - 8.0 9.0 - 11.0 12 - 14 12 - 16 20 - 23 25 - 50 40 - 70 55 - 90 80 - 120 120 - 180 150 - 250 250 - 400

Eroa Bange

Call or write for 64-page RF Designers Guide or refer to EEM, EBG, Gold Book, Microwaves & RF Directories.

finding new ways ... setting higher standards

### Mini-Circuits

A Division of Scientific Components Corporation World's largest manufacturer of Double Balanced Mixers P.O. Box 166, B'klyn, N.Y. 11235 (718) 934-4500

C99-3 REV. ORIG.

# Did





you know..

that you can build a portable, battery-operated computer with built-in MODEM and LCD display that synthesizes speech, tells time, reads temperature, voltage, or MPH, drives your printer, relay, or robot's arm, times events, "sleeps" when it's not in use, and, lives in your briefcase!

### And you can get all the ICs from Hitachi.

- CMOS 4, 8, 16-Bit Microprocessors
- CMOS RAMs
- CMOS ROMs
- CMOS EPROMs

- CMOS Real Time Clock
- CMOS Programmable Timers
- CMOS Peripheral Interface ICs
- CMOS LCD Drivers

- CMOS Speech Synthesizers
- CMOS Gate Arrays
- CMOS A/D Converters
- CMOS Logic
- LCD Displays

San Jose, CA 95131 1-408/942-1500

If you're planning some new "dream" product design (perhaps a computer that fits in a matchbox), give us a call. We've been doing the "impossible" in CMOS for some time. For more information about the CMOS Family, contact your local Hitachi Representative or Distributor Sales Office.



CIRCLE 49

Gould AMI... Innovation and Quality in Semiconductors

# The wrong CAD software can really burn you up.




Do your best designers' best efforts sometimes go up in smoke?

Your trouble could be CAD software-too complex, too piecemeal, or too poorly integrated to do the job. But there's no problem with Gould AMI software-the industry's most comprehensive for gate array, standard cell and full custom designs.

### CAD software for the real world.

Gould AMI CAD software was developed in a



demanding design engineering environment—our own. It's fast and easy to help designers meet tough deadlines. And it provides a smooth flow of vital information into our silicon foundry.

It cuts error-causing tedium, too. Your logic description is entered only once, then retrieved as needed—even for converting from a gate array or standard cell to a full custom design. Displayed commands make schematic editing easy. And logic simulation, design verification, placement and routing are all automated.

### It's actually hard to make a mistake.

Hierarchical layout tools let you work on the circuit design in small, easy-to-manage blocks. "Correct-by-construction" software ensures that you detect and correct design rule errors as they occur. And you can generate test programs and functional test patterns in no time.

All you need is a DEC VAX™ or Prime® computer. You can even use Gould AMI CAD software to correct the lack of power you often find in popular workstations.

For details on bundled packages or individual programs, please call 408-554-2311. Or mail the coupon. Because if the job is having the right CAD software, Gould AMI is right for the job.

### Now, you're cooking! Tell me about your CAD:

- ☐ Software and macros for gate arrays.
- ☐ Software and cells for standard cell designs.
- ☐ Software for full custom designs.
- ☐ Training programs.
- ☐ Have a field engineer contact me.

Name

Title

Company

Address

City/State/Zip

Phone

Mail to: Gould AMI Semiconductors CAD Marketing 3800 Homestead Road Santa Clara, CA 95051

M/S

ED 12/13



AMI Semiconductors



### The Worldwide Series



We realize that sometimes you need to spec power supplies for products sold throughout the world. And that other times your spec calls out supplies for domestic markets only.

Wouldn't it be nice if you could specify the same quality you've come to expect from Standard Power linear supplies to meet both domestic and international applications—and save money in the bargain, too?

That's exactly what Standard Power lets you do with our SPW Series Worldwide linear power supplies. We redesigned our SLS Series supplies to meet the safety standards you need regardless of where your product will be marketed. These standards include VDE, UL, CSA, IEC and those of other major agencies around the world.

What's more, because of the redesign, we reduced our component and manufacturing costs and passed these savings along to you. So the SPW equivalent of our original SLS Series power supply costs you less and offers you more.

Valuable features of our SPW Series include worldwide AC input capabilities of

100/120/220/230/240 volts, line and load regulation of ± .05 percent each, output ripple of five millivolts peak-to-peak, remote voltage sensing, overvoltage protection on five-volt outputs and inherently low EMI/RFI noise levels.

Now you can spec Standard Power linear supplies for applications worldwide and buy them off-the-shelf from your local distributor.

Send now for our latest power supply catalog. Circle the reader service number or write to us on your letterhead.



### STANDARD POWER Inc.

A SUBSIDIARY OF


**Acme Electric Corporation** 

1400 So. Village Way • P.O. Box 15447 Santa Ana, California 92705 Telephone (714) 558-8512 • TWX: (910) 595-1760

CIRCLE 44

# Computers, Peripherals, Instrumentation, Communications, Medical Electronics...

Our switchers are as good as gold in all these applications and markets.



#### **SWS Series**



But it doesn't end there. For many years, Standard Power has designed and manufactured switching power supplies. In fact, our SWS Series of regulated switchers represents a third-generation power system—a design using a minimum number of components, with 100 percent burn-in, which means reliability. And that's critical to your system's reliability.

That's why Standard Power switchers keep showing up

in applications like process controllers, test equipment, telephone switching systems, such computer peripherals as drives, terminals, tapes and printers, document sorting equipment and machine tools.

The SWS Series includes 25 models—single, triple and quadruple outputs—in a power range from 150 to 250 watts. Each unit features line and load regulation at .2 percent each, built-in overvoltage protection and remote voltage sense on the main output, 20 millisecond holdup time and

UL recognition.

In addition, we were the first manufacturer to sell power supplies through electronic distribution. Today, more than 120 distributor locations stock our power supplies for off-the-shelf delivery. So go ahead and specify Standard Power . . . the quality switcher that's available.

To receive a free copy of our 32-page catalog, circle the reader service number or send us a note on your letterhead.



#### STANDARD POWER Inc.

A SUBSIDIARY OF

#### **Acme Electric Corporation**

1400 So. Village Way • P.O. Box 15547 Santa Ana, California 92705 Telephone (714) 558-8512 • TWX: (910) 595-1760

CIRCLE 47



Through advanced manufacturing technology, we're keeping an eye on quality without letting production costs get out of sight.

Look to Omron for the state-of-the-art in component manufacturing.

Our totally automated assembly lines are helping us produce more than 700,000,000 relays and

switches per year. Advanced computer monitoring systems are scanning continuously for the slightest variations between products at every stage of production. Through our advanced Q.A. systems, we're holding tolerances so tight that, in many cases, we've completely eliminated a customer's need for incoming inspections.

Our expertise in high-volume production of "standardized" components helps us hold the line on

costs. And those manufacturing efficiencies are reflected in the quality and cost-savings we pass on to our customers.

How an electronic component is made tells you a lot about performance, reliability and cost. That's why we'd like to show you a short video presentation of our manufacturing capabilities. Please call **1-800-621-6413**.

In Illinois: 312-262-7783.


# OMRON

snap-action, thumbwheel, illuminated, key. DIP switches - printed circuit board, general purpose, power, solid-state relays - photomicrosensors

**CIRCLE 48 FOR MORE INFORMATION** 

**CIRCLE 56 FOR VIDEO PRESENTATION** 

We're in control



## **Design-in a "SMART"** 110/300/1200 bps modem

#### **A Complete Communications Solution Built** into Your Product

Now you can design a "SMART" Bell 212A modem into your product by simply mounting one of Cermetek's CH1765 modem component modules on your printed circuit board. The modem is a complete low cost, communications solution - that includes such features as auto-dialing and autoanswering. The CH1765 has a FCC registered telephone line interface and needs only a UART or USART, an RJ 11C phone jack, and power (+5, +12, -12 volt) connection.

#### **Small Size and Compatibility are Key Features**

This complete modem mounts onto your board, taking only 16 square inches of space. The CH1765 is a Bell 212A compatible and will communicate with all

SMARTMODEM 1200 is a trademark of Hayes Microcomputer Products, Inc. ®Registered trademark of AT&T

Just call us at (408) 752-5000 for our nearest dealer location.

CERMETEK MICROELECTRONICS INC. 1308 Borregas Ave., Sunnyvale, CA 94088-3565

Dealer and distributor inquiries invited.

commonly used 110, 300 or 1200 bps modems. The CH1765 is also Hayes Smartmodem 1200™ compatible, allowing the user to select from an ever growing base of communications software.


#### **Easy to Use**

The CH1765 automatically adapts to such communication parameters as speed, parity, and use of rotary-type pulses or Touch Tone® for dialing. The CH1765 accepts serial commands from a terminal or computer keyboard to make the call. The nd additional information on the CHI Tob June vale. CA and a 3565 commands allow you to dial, answer, and hangup without the use of the telephone. In addition, the modem enables you to monitor a call's progress through different messages sand additional into mailor on the Cyf. 165 from the modem. The messages will tell you if the line is busy, ringing, a voice answered, or if you have made a successful connection.

CIRCLE 50

City State Street

# Build vs. buy.



# The data generator you don't have to add to.

Data Generator

# Total Traceability

**Another first from AVX** 

Now, every AVX SpinGuard is laser-inscribed with its lot code as well as a date code. That means total traceability on a commercial axial MLC—a feature previously available only on expensive military and hi-rel parts. And AVX brings it to you at no extra cost.

Total traceability: Another reason why AVX sets the standards for quality and reliability around the world.

To get your fully coded SpinGuards, contact AVX Customer Services at (803) 448-9411. Or call your local AVX Distributor.




SETTING NEW STANDARDS AROUND THE WORLD

CIRCLE 52

#### THE CHALLENGE:

Develop a volume production yoke with geometry tolerance of less than 1% requiring no recorrection after assembly.



When Lee Data design engineers were faced with the challenge of developing a high-line-rate, high resolution, IBM 3270-compatible

display terminal, they knew the deflection yoke would be a key component. They would require a yoke with geometry tolerance of less than 1% in production quantities. A yoke that would not require recorrection during final assembly in their plant.

So they turned to Discom. Taking advantage of Discom's thirteenplus years developing components that have continually raised the state-of-the-

art in display technology, Lee Data engineers were able to realize their objectives.

Using Discom's patented non-uniform conductor distribution process, Discom engineers developed a specially designed yoke to meet Lee Data's exacting specifications. Then Discom's full-capability prototype lab built prototypes for testing and evaluation.

And, when the design was finalized, and approved for production, Lee Data again turned to Discom. They knew Discom has the ability to produce, in quantity, yokes that consistently

In VDT applications, as well as avionics and large-screen graphics, Discom is helping the world's largest electronics manufacturers meet their design challenges. And often saving them time and money in the process. Circle the number below on the reader response card, or call (617) 692-6000 and challenge Discom.

and uniformly meet design specs.




Display Components, Incorporated 334 Littleton Road Westford MA 01886 CIRCLE 211

. . . challenging the limits of technology.

## LOW POWER, CMOS 8086 SINGLE BOARD COMPUTER

Replace Your iSBC\* 86/05 and get the Benefits of CMOS Technology Without Redesign



#### Compare these Key Features:

Bus Type CPU 5V Operating Current Operating Temperature Supplied RAM (Bytes) RAM Battery Back-Up On Board

Whether your application is an existing system upgrade or a low-power CMOS system design, DTI's CBC 86C/O5 will make your job easier. Full hardware and software compatibility with the iSBC\* 86/O5 allows you to gain the low power advan-

### INTEL iSBC\* 86/O5

MULTIBUS\* 8086 4.7 amps max. 0°C to 55°C 8K No

tages of CMOS without sacrificing system performance or your development investment. You even get fast nonvolatile memory on-board, and a full-spec MULTIBUS\* interface to maintain compatibility with existing systems.

#### ASK ABOUT OUR NONVOLATILE CMOS RAM FOR MULTIBUS AND LSI-11 TOO!

Above specifications taken from manufacturers' current published data.
\*MULTIBUS and ISBC are trademarks of Intel Corp.

#### DIVERSIFIED TECHNOLOGY CBC 86C/O5

MULTIBUS\*
80C86
200 milliamps max.
0°C to 70°C
16K
Yes (2.5 yrs. data retention)

For more information regarding the CBC 86C/O5 CPU board, or any of our other all-CMOS MULTIBUS\* boards, contact Bill Long, CBC Product Manager at (601) 856-4121.



P. O. Box 748, Ridgeland, MS 39157 Telex 585326

# New isolated TO-220 power transistor package from Panasonic.

Mounting a TO-220 power transistor used to require a heck of a lot of hardware. Spacers. Mica insula-tors. Bushings. Solder lugs. All adding up to considerable time and expense.

Now consider the new isolated TO-220 power transistor from Panasonic. With just a screw, washer and hex nut, you can accomplish the same thing. Forget about all the insulating hardware - it doesn't need any.

Its integral heat sink has a thin resin coating, providing thermal and electrical characteristics as good or better than standard TO-220 packages: up to 30K cycles at 0° to 90°C. And while SOA, transient thermal resistance and maximum collector power dissipation mum collector power dissipation are the same as equivalent transistors, the resin-coated flange

actually improves free air dissipation by about 17%.

A full range of isolated TO-220 power transistors is available in all the most popular values. Also available are isolated versions of the TO-3 plastic power transistor package. They're compatible with all standard designs. And their simplified mounting, coupled with competitive prices, adds up to big

savings in most any application.
With isolated TO-220 power transistors, you get optimum thermal protection . . . without all the hard-

For evaluation samples and design data, write or call today: Panasonic Industrial Company, Electronic Components Division, One Panasonic Way, Secaucus, N.J. 07094; (201) 348-5274.

You don't have to own a hardware store to mount them.

**Panasonic Industrial Company** 

# NOW THE SOLUTION TO IC NOISE IS RIGHT UNDER YOUR DIP



INTRODUCING MICRO/Q HIGH-FREQUENCY DECOUPLING CAPACITORS FROM ROGERS.



Rogers' new MICRO/Q™ capacitors get to the root of IC noise problems. Save valuable real estate. And let you increase IC density.

The first flat capacitor with the rectangular dimensions of standard DIP packages, MICRO/Q fits directly under ICs or sockets. Because it shares the same power and ground holes, there's no need to modify regular two-sided or multilayer boards. Use of outboard mounting holes is optional.

Specifically designed to optimize

the performance of today's fast-rise ICs by minimizing noise, the MICRO/Q capacitor's low-inductance design and high-frequency performance can reduce voltage and ground spikes up to 90%.

Available in all standard sizes or custom configurations, its low impedance and overall superior electrical performance will enhance the operation and reliability of virtually any board design. For all the facts, contact a Rogers MICRO/Q Product Specialist today at (602) 967-0624.



Rogers Corporation Q/PAC Division 2400 South Roosevelt, Tempe, AZ 85282 602 967-0624 Coming to our readers on January 10 . . . Electronic Design's

Annual Technology Forecast

## Fujitsu: World-Class Components



# Featuring special technology reports covering:

Computers

Semiconductors

Communications

Software

Test and measurement

Packaging and components

Also in this issue:

- Electronic Design's Annual Top 10 Contest
- A Special Interview Section
- A Domestic Reader Recall Survey

## World-Class Components Update:

RIFTBOARDS

Outstanding Operability, Sophisticated Technology And Unequalled Reliability Make Fulitsu The Only Keyboard Source You'll Ever Need.

Fujitsu keyboards are state of the art, featuring a low profile design that meets ergonometric & DIN standards for optimum productivity. A special "snapaction" keytouch permits a quick, rhythmical operation. Tactile feedback "touch" control for adjustable key-in response. Tilt angle adjustment for operator comfort. The result is a long life, World Class component for today's information age. Whether you need the hardware, the electronics or both, Fujitsu will manufacture the part or the entire package to your exact specifications.



Or if you have a design problem, Fujitsu will customize a solution with a technical wizardry unmatched in the industry.

For years, Fujitsu has been on the leading edge in developing breakthrough, problem-solving technology. Offering companies, worldwide, uncompromising quality and reliability—the result of Fujitsu's insistence on controlling, in house, every aspect of the design and manufacturing process. And delivering the highest level of service and absolutely competitives

Find out more about Fujitsu keyboards. Call or write today.

CIRCLE 59

**FUJITSU** 

World-Class Components
Part of Tomorrow's
Technology



Component Division Fujitsu America, Inc. 918 Sherwood Drive, Lake Bluff, IL 60044 (312) 295-2610 Telex: 206196 TWX: 910-651-2559 **TECHNOLOGY REPORT** 

# Transforming a simulated IC into silicon demands tools that unravel design decisions

This, the second of two reports on computeraided engineering tools, picks up with the physical realization of application-specific ICs. The first part, which ran in the Nov. 15 issue (p. 128), explored design capture, simulation, and timing verification. With the notable exception of some silicon compilers, IC design tools fall into two groups: those that help synthesize a chip's electrical design and those that help transform that design into silicon. The latter include software packages for automatic space allocation and routing, verification tools that check the layout against the simulator's net list, and circuit extractors that determine circuit parasitics and reannotate the simulation model with the corrected values.

The first IC design phase is completed when the circuit works properly on a simulator. Before the second phase can begin, however, a decision must be made on how to build the circuit in silicon. Usually the decision favors the least

**Max Schindler** 



expensive alternative (Fig. 1), but the chip's specifications may dictate a costlier choice.


For example, if speed and chip size demand it, gate arrays must yield to standard or even custom cells. Economic considerations alone call for full-custom chips only in quantities of more than 50,000, but because only custom ICs can fully exploit advanced production technology, popular general-purpose chips will continue to be hand-optimized for another decade.

According to industry estimates, silicon compilation should become the best design choice for quantities under 10,000, but the technique is too young for hard and fast conclusions. Transistor density ranges somewhere between gate arrays and standard cells,

although some designs have densities reaching 85% of custom chips.

For most OEMs, the alternatives narrow down to gate arrays or standard cells. Depending on the design and the technology, the crossover point between gate arrays and standard cells should be expected between a few hundred and a few thousand copies. But designers must keep in mind that gate arrays can rarely use all their gates — usually they provide only enough routing space to connect about 80% of them. When the designer is forced to go to the next larger size, silicon use can drop to 40% or so. Furthermore, if high speed is essential, more expensive double-metal arrays may be needed because they accommodate shorter routing paths. Some arrays also consist of uncommit-







ted transistors rather than gates; they permit the user to find the fastest combination for a given need.

For smaller systems, a type of hybrid technology is emerging as another alternative. It employs unpackaged ICs that are bonded to ceramic substrates. Space requirements average onetenth of those for equivalent circuit boards, while costs run lower than those for gate arrays. Via Systems Inc. (North Billerica, Mass.) offers the SystemNode 120H especially for hybrid designers, and AutoMate Design Automation Systems (Palo Alto, Calif.) has developed an interface that adapts its hybrid design software, which normally runs on Data General hardware, to Daisy workstations (Fig. 2).

Because the software for pc board and hybrid design is quite similar to that for gate arrays, the same CAE systems can often be used for all three techniques, and even for standard-cell designs, as long as the cell shape remains fixed. However, because their connecting points are predetermined, hybrids and pc boards have another advantage: Designers need not worry about distributing bonding pads around the chip's periphery.

#### Down the auto route

Automatic routing packages usually consist of several programs for different levels of complexity. Usually, critical signals are routed first, which sometimes poses

a problem in arrays having a single layer of metal, where contacts are often placed in fixed locations. The usual channel-routing algorithms also run into trouble with arrays that have no channels but that interconnect directly atop the active areas.


#### Start with the pins

Another algorithm used in first-pass routing starts with both pins to be connected and then searches in the X and Y directions until a connection is formed or an obstacle encountered. In the latter case, the "line search" algorithms retrace and try again in a direction perpendicular to the one just tried.

Remaining connections are completed by a "maze router" which propagates imaginary "waves" from one point to another, along rectangular approximations to polar coordinates. When the target point is reached, the router determines the wiring path along the unoccupied grid points that it found as the "wave" propagated.

#### Rip it up

If the maze router cannot find a path, the rip-up-andretry program goes into action. After removing the blocking connection, this algorithm first routes the connection that was blocked and then tries to find another path for the link it ripped up. If that fails, it restores the original connection and asks for human intervention. The Cadisys software developed by Mentor Graphics Corp. (Beaverton, Ore.) permits




1. The best implementation of a logic chip is usually the one with the lowest cost. Standard cells and gate arrays now run neck to neck, but silicon compilers could make custom chips quite competitive.

such intervention either before or after autorouting—in the first case to assure preferred placement for the most critical cells, in the second to complete routing. Gould AMI Semiconductors (Santa Clara, Calif.) reports that Cadisys usually completes 95% of the networks in a typical 500-network circuit on single-metal gate arrays.

Because nearly all gatearray vendors offer layout support, the user can transfer the electrical design to the supplier if his or her own CAE system cannot handle routing. For example, LSI Logic (Milpitas, Calif.) executes its 400,000-line software on a mainframe that handles 5 million instructions/seasily outrunning worksta-

tions. The lack of a circuit description standard complicates this step, but translation software from one supplier's net list to another's is usually available (see "EDIF Standard Running on Fast Track," p. 123).

Standard-cell design has been following gate arrays into today's singly powerful workstations. A system like



2. Hybrid technology links ICs in a manner similar to pc boards, but the interconnections are produced on ceramic substrates, to which the ICs are then bonded (magenta pads).



the Daisy Logician can indeed handle complex circuits (Fig. 3). But lack of in-house CAE need not deter an engineer standard-cell design and layout can usually be done at a foundry's design center or on a simple workstation that acts as a terminal for the foundry's mainframe. In fact, with the number of standardcell makers now at about 20, workstation users cannot expect to have even the major suppliers' offerings in their libraries. Still, the choices continue to proliferate—about half the standard-cell makers have not only parts with the common 3- to 5-ns gate delay, but also 1- to 2-ns parts. Others also list a line of cells with gate delays between 10 and 15 ns.

#### No experience needed

RCA Corp.'s Solid State Division (Somerville, N.J.) is one company that vows to turn engineers into standardcell designers—in three days. In cooperation with Hamilton Avnet (Culver City, Calif.), a distributor of electronic components, the company plans to open 12 design centers within a year to assist designers throughout the country. By the way, several companies, including Texas Instruments Inc. (Dallas), RCA, and NCR Corp. (Dayton, Ohio), include analog cells in their libraries.

RCA's design process is straightforward (Fig. 4a). A user can develop the circuit on a workstation running a program that converts the design into the RCA format—for example, the Daisy Logician.

After downloading, RCA's Mimic simulator goes over the circuit once more to make sure it complies with RCA requirements and to add fault coverage. If testability is inadequate, the user is notified. A separate fault coverage analyzer and the Scoap testability routine, the latter from Sandia National Laboratories (Albuquerque, N.M.), are available on RCA's workstations.

Under Mimic, rise and fall delays are expressed as functions of load capacitance, thereby assuring accurate timing. Components can either be called up from the library or described in the Mimic language (Fig. 4b).

After format conversion, the APRA automatic placement and routing system takes over. It either runs automatically or accepts preplacement inputs to improve density or keep critical signal paths short. Algorithms that automatically handle such preplacement may soon emerge, if work at Sandia Laboratories and elsewhere is successful. The designer can add circuitry from a Calma workstation, in which case a program called Critic performs a comprehensive electrical-rule check.

#### Working in concert

The next step—design verification—is perhaps the most critical in the whole design process. A program must check the final schematic for correctness and determine the actual interconnect loading for another simulation run. At RCA, this program is

called Concert (Connectivity Certification) because it actually checks the current net list against the one on the Mimic file. Photomask generation then completes the design process.

An ideal system would go even further. Mitsubishi Electric Corp., for example, has developed in its Itami and Karakura laboratories the software to reconstruct the complete circuit from photomask patterns-not an easy job in any case. However, as fabrication technique approach the submicron region, parasitics become critical enough to warrant the extra

Mitsubishi calculates gate. diffusion, and junction capacitance from both the parallel and the perpendicular overlap of the (double-metal) geometry adjacent to each transistor. Toshiba Research and Development Center (Kawasaki) follows much the same path with its timing verifier, Mactis.

A circuit extractor, as such programs are called, was also developed at the Massachusetts Institute of Technology (Cambridge). Dubbed EXCL, it uses field equations to compute both resistance and capacitance. Not surprisingly, calculations for even a 100-transistor circuit, decomposed into 1500 rectangles, take about a minute on Digital Equipment's System

Such precautions will become especially important for cells with user-defined parameters, which are used, for example, by VLSI Tech-

#### **EDIF** standard: running on the fast track

While the number of players in the lucrative field of CAE keeps growing, more and more time-the engineer's, the CPU's-is spent converting one supplier's formats into another's. Recognizing the urgency of the problem, the leading contenders are delegating some of their brainpower to come up with the Electronic Design Interchange Format.

EDIF represents not so much a language in the sense of hardware definition languages, but a format that accommodates specific languages. It will cover all levels of application-specific IC design, from functional definition to geometric description. Version 1, though, specifically addresses gate arrays and standard cell, including macro libraries and technology information.

Logic and circuit models, macrocell layout, schematic symbols, and base arrays (including plug and socket information) all must be relayed in program form from the foundry to the user, before the design can start (Fig. A). The designer, on the other hand, must send the foundry-or a remote computer, if the design exceeds 3000 to 8000 gates-net lists and layout information (Fig. B).

Behavioral description will be tackled later, as will some aspects of full-custom IC design. After all, IC makers all have their in-house standards and few others design custom ICs at present.

The EDIF heavyweights did not start with a blank slate: The University of California at Berkeley's Lisp-like CIDF (common interchange desciption format), Daisy's Gail (gate-array interface language), and Texas Instruments' Tidal (TI design automation language) represented de facto standards for which a common denominator had to be found. Work on the EDIF has advanced so rapidly

that some companies are planning to adapt the asyet-unendorsed standard as early as next year. Right now, no official standards body has announced plans to review EDIF, but chances are that the IEEE will turn the current EDIF proposal into an official standard.


```
(Cell NAND2
 (View Topological Logic
  (Interface
   (Declare (INPUT PORT a b) (OUTPUT PORT z))
   (Body (Figure Group SchematicSymbol)
    (shape (20 0) (arc(40 0) (60 20) (40 40)) (20 40))
    (circle (60 20) (70 20))
   (PortImplementation a (Figure Group SchematicPort
                            (Path (0 30) (20 30))))
   (PortImplementation b (Figure Group SchematicPort
                            (Path (0 10) (20 10))))
   (PortImplementation z (Figure Group SchematicPort
                            (Path (70 20) (90 20))))
   (Permutable a b)
   (Instance Nand2Primitive)
   (View Physical
    (Declare INPUT PORT a b) (OUTPUT PORT z)
    (Body (Figure Group MetalBlockage (Rectangle...)))
    (PortImplementation a (Figure Group Poly...))
    (PortImplementation b (Figure Group Poly...))
    (PortImplementation z (Figure Group Poly....))
    (Permutable a b)
    (Figure Group Metal (Path...) (Polygon...)...)
    (Figure Group Poly (Path...) Path...)...)
                         (A)
   Netlist
    (Contents
    (Instance Nand2 N1)
    (Instance Nand2 N2)
    (Joined N1:z N2:a)
    (Joined N2:z N1:b)
                          (B)
```



nology Inc. (Santa Clara, Calif.) and Harris Corp. (Melbourne, Fla.). The latter calculates capacitance from layout geometry but uses the value only as lumped loading at each node.

For the currently employed 3- to 5- $\mu$ m line widths, lumped capacitances have proven adequate, but below a micrometer, the rise and fall delays of the basic gates can change enough to necessitate simulating the real, distributed structure-no mean feat when tens of thousands of components are involved. The problem will become even more serious with silicon compilers, because no approximate geometry is known before the actual layout.

As compiled cells and even those that have their parameters defined by the user approach the complexity of custom cells, conventional layout software may have to be supplemented with custom layout techniques like compaction and ploughing. Compaction fits cells into a given space by compressing an originally loose layout to a desired aspect ratio. Ploughing makes space for, say, a via, by pushing aside existing lines under observation of the de-



3. Integrated workstations like Daisy's Logician can handle highly complex circuits from logic design to detailed layout. The ability to view several design steps in different windows helps the system engineer tackle the design of small circuit segments even at the mask stage.

sign rules (Fig. 5). This technique, like many other IC design advances, was developed at the University of California at Berkeley and gives routing algorithms some much needed freedom for standard and custom cells. Incremental design rule checking, essential to that technique, is accomplished by running the appropriate routine in the background during routing.

An experimental technique, stemming from AT&T Bell Laboratories (Murray Hill, N.J.), is known as virtual-grid symbolic layout. A program dubbed Mulga assembles cells that were defined in an intermediate language and laid out on a preliminary grid. The user describes a floorplan symbolically, and the program matches up adjacent cells by changing their preliminary (or virtual) grids.


#### **Meet Freddy**

From Europe comes another layout system that will shortly be distributed by Racal-Redac (Westford, Mass.). Running on a VAXbacked dedicated workstation, but scheduled for transfer to Apollo computers, the software was originally developed by Inmos Ltd. (Bristol, England) to design the transputer and has been nicknamed Fat Freddy. The user describes a circuit at a high level for two data bases, one graphical and the other functional. That duality flows throughout the hierarchical decomposition, down to the transistor level, where each

physical component is checked against its functional definition and its simulated behavior. Because the system uses a transistor model with 25 second-order parameters. it can accurately reflect even such secondary characteristics as the drain pull effect.

Although meant for fullcustom design, the software can certainly handle standard cells in an integrated environment. On the other hand, it comes so close to a silicon compiler that it will ease the transition for those wishing to switch from silicon compilation to custom design.

Assuming a chip design has passed all verification steps. an integrated CAE system should be able to produce a pattern-generation tape. This step, however, is sometimes performed by the foundry



4. A foundry's CAE system for standard cells closely resembles those used on workstations, but the support of only one manufacturer's thoroughly tested cells simplifies matters (a). Cells are described here in the Mimic language, as demonstrated with a Johnson counter (b).



from net-list information, especially in the case of gate arrays. Often the deciding factor in establishing the designer-foundry interface rests not so much on technical consideration but on who will assume rsponsibility for the accuracy of the tests that determine whether a chip is labeled good or bad. Because production-quality automatic test equipment can cost over \$1 million, the customer only performs spot checks. Of course, the foundry's tests are only as good as the test tape; if the tape comes from the customer's CAE system, the foundry cannot be held responsible.

Furthermore, as CAE sys-

tems proliferate, foundries cannot be expected to support all the different formats the workstations use, and at least one of them-Gould AMI Semiconductors — will only accept those from the major CAE suppliers. The company points out that only highspeed (10-MHz) test programs can find timing deficiencies. But they are hard to debug (eight weeks is not unusual) and, if faulty, can reject a good product, leading to additional delays.

#### To a fault

Low-speed programs, on the other hand, which stem from less sophisticated CAE stations, cannot be sped up:

5. Ploughing is a layout algorithm that simplifies local rerouting. Once a plough is inserted in, say, a set of interconnections, it can move them all while observing geometric design rules.

Test vectors that occur within the same cycle in a low-speed system may fall into different cycles in a faster system.

Truly integrated CAE software develops test vectors as a by-product of simulation and at least one-the Logician—actually integrates test generation with the circuit design and verification steps. Acting as a small expert system with knowledge about test procedures, the Daisy fault simulator program, DFS, warns the user early in the design cycle if the testability of his or her design might jeopardize future production. It not only tries out its test patterns by inserting faults in the design but also generates reports about the outcome of its scrutiny.

However, the currently used fault models—primarily stuck-at, bridge and open faults-are no longer adequate for VLSI chips, especially those implemented in CMOS. Stuck-at-open faults (where a gate output remains at logic 0 regardless of input) manifest themselves differently in CMOS from stuck-atclosed, so that the common but unspecified stuck-at mode becomes inadequate for gatelevel circuit tests (see "Some Caveats in the Workstation Search," p. 128).

#### **Risky assumption**

Furthermore, most fault simulators assume that a single stuck-at check will catch multiple faults. That is not necessarily true when a single critical path is checked. because in complex chips it may be deeply buried in the



Would you hire an entire band when all you need is one instrument? Of course not.

So why use a whole orchestra of computers when all you need is one to develop software for virtually any type of micro-processor?

The secret? Avocet's family of cross-assemblers. With Avocet cross-assemblers you can develop software for practically every kind of processor — without having to switch to another development system along the way!

### Cross-Assemblers to Beat the Band!

#### **Development Tools That Work**

Avocet cross-assemblers are fast, reliable and user-proven in over 4 years of actual use. Ask NASA, IBM, Xerox or the hundreds of other organizations that use them. Every time you see a new microprocessor-based product, there's a good chance it was developed with Avocet cross-assemblers.

Avocet cross-assemblers are easy to use. They run on almost any personal computer and process assembly language for the most popular microprocessor families.

#### Your Computer Can Be A Complete Development System

Avocet has the tools you need to enter and assemble your soft-ware and finally cast it in EPROM:

EPROM Programmers let you program, verify, compare, read, display EPROMS but cost less because they communicate through your personal computer or terminal. No personality modules! On-board intelligence provides menu-based setup for 34 different EPROMS, EEPROMS and MPUs (40-pin devices require socket adaptors). Self-contained unit with internal power supply, RS-232 interface, Textool ZIF socket. Driver software (sold separately) gives you access to all programmer features through your computer, lets you download cross-assembler output files, copy EPROM to disk.

Model 7228 Advanced Programmer
—Supports all PROM types listed. Superfast "adaptive" programming algorithm programs 2764 in 1.1 minutes.

Model 7128 Standard Programmer — Lower-cost version of 7228. Supports all PROM types except "A" versions of 2764 and 27128. Standard programming algorithm programs 2764 in 6.8 minutes.

Avocet	Target		CP/M-86
Cross-assembler	Microprocessor	CP/M-80	IBM PC, MSDOS**
XASM04 NEW	6804	\$ 250.00	\$ 250.00
XASM05	6805	200.00	250.00
XASM09	6809	200.00	250.00
XASM18	1802/1805	200.00	250.00
XASM48	8048/8041	200.00	250.00
XASM51	8051	200.00	250.00
XASM65	6502/65C02	200.00	250.00
XASM68	6800/01, 6301	200.00	250.00
XASM75	NEC 7500	500.00	500.00
XASM85	8085	250.00	250.00
XASM400	COP400	300.00	300.00
XASMF8	F8/3870	300.00	300.00
XASMZ8	Z8	200.00	250.00
XASMZ80	Z80	250.00	250.00
XMAC682 NEW	68200	595.00	595.00
XMAC68K NEW	68000/68010	595.00	595.00

Model 7956 and 7956-SA Gang Programmers — Similar features to 7228, but program as many as 8 EPROMS at once. 7956-SA stand-alone version copies from a master EPROM. 7956 lab version has all features of stand-alone plus RS-232 interface.

**EPROM**: 2758, 2716, 2732, 2732A, 2764, 2764A, 27128, 27128A, 27256, 2508, 2516, 2532, 2564, 68764, 68766, 5133, 5143. **CMOS**: 27C16, 27C32, 27C64, MC6716. **EEPROM**: 5213, X2816A, 48016, I2816A, 5213H. **MPU (w/adaptor)**: 8748, 8748H, 8749, 8749H, 8741, 8742, 8751, 8755.

7228	Advanced Programmer	\$ 549
7128	Standard Programmer	429
7956	Laboratory Gang Programmer	1099
7956-SA	Stand-Alone Gang Programme	r 879
GDX	Driver Software	95
481	8748 Family Socket Adaptor	98
511	8751 Socket Adaptor	174
755	8755 Socket Adaptor	135
CABLE	RS-232 Cable (specify gender)	30

Convert assembler output to other formats for downloading to development systems and target boards. Also useful for examining object file, changing load addresses, extracting parts of files. Converts to and from Intel, Motorola, MOS, RCA, Fairchild, Tektronix, TI, Binary and HEX/ASCII Dump formats. For CP/M, CP/M-86, MSDOS, PCDOS......\$250

**68000 CROSS-ASSEMBLER** — With exhaustive field testing completed, our 68000 assembler is available for immediate shipment. XMAC68K supports Motorola standard assembly language for the 68000 and 68010. Macros, cross-reference, structured assembly statements, instruction optimization and more. Linker and librarian included. Comprehensive, well-written manual.

To find out more, call us toll-free. 1-800-448-8500

(in the U.S. Except Alaska and Hawaii)

VISA and Mastercard accepted. All popular disc formats now available --please specify. Prices do not include shipping and handling -- call for exact quotes. OEM INQUIRIES INVITED.

\*Trademark of Digital Research \*\*Trademark of Microsoft



Sales and Development: 10 Summer Street P.O. Box 490, Dept. 1284 ED Rockport, Maine 04856 (207) 236-9055 Telex: 467210 AVOCET CI

Corporate Offices: 804 South State Street Dover, Delaware 19901



logic and thus hard to observe. For that reason, IC design techniques that simplify testing are gaining support.

A technique known as level-sensitive scan design partitions a chip and inserts register latches that capture the state of the signal path at the interface. Several IBM laboratories have cooperated in the development of a chip partitioning aid that formalizes the divide-andconquer approach, but it is limited to logic systems that can be described as networks.

At AT&T Bell Laboratories, a system called Titus takes a similar approach. It inserts scan paths for designs of 2000 to 5000 gates in a few hours, then automatically generates test vectors. The lab reports a 10% to 15% increase in chip size and a 5% loss in speed. However, scandesigned chips elsewhere have been known to waste up to 40% of their area on test circuitry.

In practice, the logic designer still must rely on common sense and experience when adding logic dedicated to easing the test burden. A software system that simplifies the chore and amounts to a more grandiose form of Daisy's fault simulator has been developed at the Siemens Research and Technology Laboratories (Princeton, N.J.). Called Idas, it contains the Cadat logic and concurrent fault simulator; Hector, the actual testability analyzer; Pretest, which predicts testing costs; and Atwig, an automatic test pattern generator. All run on a Daisy workstation.

One more component, Edit, acts as the interface with the user, highlighting in different colors the observation and control paths. In addition, it automatically inserts flipflops in areas where fault coverage is rather low, as determined by Hector's heuristic analysis.

#### Bottleneck in the making

Despite such efforts, the preparations for chip testing are rapidly turning into a bottleneck for applicationspecific ICs. When software tools make it possible to design VLSI chips in days. spending weeks if not months to test and debug that design is clearly not acceptable. The best bet to resolve the problem may well lie in fully integrated CAE systems that actually cover all the design functions—including fullspeed test design and actual prototype testing-without costing a million.

One such system has recently been introduced by Mentor Graphics. It consists

#### Some caveats in the workstation search

Because a CAE system's fault simulation capability is both important and hard to observe, it typifies the difficulties in acquiring a CAE workstation. For each of the software components, the buyer must not only be ready to ask many questions but also be prepared to sample a range of circuits, designed to increasingly stress the system's abilities

In addition to these major concerns, there are lesser ones that users of simulation packages must worry about. Some simulators, for instance, cannot handle system components running at different clock speeds. Others cannot manage variations in rise and fall time, and a few are even limited to one or two IC technologies.

Because each CAE system dis-

plays even the same simulator's output in a different way, it is essential to investigate the user interface. This is especially true because some displays have particular trouble with buses. Others cannot be caoxed into displaying functions that are not preprogrammed, even if the manufacturer is willing to part with the source code. In fact, even getting a gate-level net list can be excruciating or impossible. A good simulator should enable the user to view a circuit at different hierarchical levels and to make some changespreferably without switching between editors that require different commands. Better still, if simulation runs as a background task when a circuit is being redesigned, the user can experiment more efficiently.

# Put the best of three worlds on one desktop.

Now you can have the powerful Tektronix PLOT 10 graphics command set that you've always wanted, but use the host of your choice—IBM or DEC. And just by typing a single switch-host command on any one of Tek's all new CX4106, CX4107 or CX4109 terminals.

They're all plug compatible with both host environments. One coax to a standard IBM 3270 controller or a conventional RS-232 plug to your DEC, (or other ASCII host), is all you need to make the most flexible connection in graphics.

Then, for fast and familiar graphics data handling the new CX Series terminals come with an IBM-style keyboard. Screen output will be just as familiar as keyboard layout. 32-line 3278/3279 alphanumeric emulation is built in. So is VT100 applications capability. And so is push-button support for Tek's color transparency or hard copy copiers.

All the graphic quality features of the original 4100's are there, too, as well as full compatibility with PLOT 10 IGL, GKS, and TCS programs. Along with popular third party software such as SAS GRAPH\*, ISSCO's DISSPLA\* and TELL-A-GRAF\* and Precision Visual's DI-3000\*.

So don't wait to put the best of 3 worlds—TEK, DEC, and IBM—on one desk. Contact your Tek sales engineer or call 1-800-547-1512. In Oregon 1-800-452-1877.

DISSPLA and TELL-A-GRAF are the registered trademarks of ISSCO.
SAS GRAPH is a registered trademark of SAS Institute Inc., Cary, N.C.
DI-3000 is a registered trademark of Precision Visuals, Inc.
DEC and VT100 are trademarks of Digital Equipment Corporation.
IBM is a trademark of International Business Machines Corporation.
Display Graphics courtesy of PDA Engineering.



Copyright 1984 Tektronix Inc. HDT-104.

OEM prices and leasing programs (U.S. only) are available.


CIRCLE 61



of a software package, an Apollo node like the DN 300, and an extra chassis for the test hardware—a 160-channel pattern generator and

logic state analyzer and 16 data acquisition channels). The hardware verification system not only permits the user to design testability into

ICs and pc boards but actually to run developed test patterns at clock speeds up to 10 MHz (Fig. 6). Because the user is working with the same



6. Mentor's hardware verification system (HVS) serves either as a test pattern generator that highlights changes and problems (top left) or as a logic analyzer for a prototype (center). The user programs the pattern clocks according to current needs.

# Our new function generator makes frequencies 30 times easier to hold.

The typical function generator lets you dial in frequencies with  $\pm 3\%$  accuracy. Our new Model 21 doesn't have a dial. Instead, a 3 1/2-digit display shows you settings over the  $100\mu$ Hz to 11 MHz range. And the accuracy equals the display resolution—an impressive  $\pm .09\%$ , thanks to a built-in counter and a digital memory circuit.

Push the Stabilizer button and that accuracy becomes long-term stability.

But that's only the beginning, because Model 21 is the most important new function generator design in the last 20 years.

For instance, it has digital synthesis of waveforms [including haverwaves and ramps] below 1.1 kHz, with 1000 horizontal points and 250 vertical points per cycle. You can stop a wave at any point, hold it, then resume.

Or you can use the generator's output as a 1000:1 frequency divider for ultra-low frequency generation.

Sine, triangle, and square waveforms are available at all frequencies, and they can be triggered or gated.

Ālot of capability for an instrument just a little over 3 inches high—and just a little under \$1,000\*. For details on how you can get your hand on one, contact:
Wavetek San Diego, Inc. 9045 Balboa Ave., P.O. Box 85265, San Diego CA 92138. Tel. [619] 279-2200;TWX 910-335-2007.
\*U.S. price.

CIRCLE 62 FOR DEMONSTRATION CIRCLE 63 FOR LITERATURE





graphics interface format and operating procedures as during earlier stages of the design, test generation and execution do not disrupt the continuity of the engineering cycle.

#### Better relations needed

While testability and testing are the most obvious shortcomings of present CAE systems, the most pernicious may well turn out to be the data-base organization. Completely hidden from the user, data-base management nevertheless determines the performance and the expandability of any data-intensive computer application.

Because hierarchical decomposition is widely accepted as the best approach to digital system design, most data bases in CAE systems are hierarchical, like Unix files. However, each component at most levels in the hierarchy has several aspects: A transistor, for example, has electrical attributes as well as geometric ones. One solution was mentioned in connection with the Inmos and RCA design systems—a dual data base with a 1:1 relationship among its components.

More often though, designers resort to a network schema, which can model interrelated hierarchical schemas. The price is a high processing overhead, because network nodes are interconnected via pointers that must be updated every time a relationship changes. On the other hand, homogeneous relational data bases are essentially flat, because each

tuple—or record—contains a subsystem in each of the relation's attributes.

Texas Tech University (Lubbock) has worked out a schema that combines homogeneous and heterogeneous relations (where each item contains a subitem in only one of the attributes). While preserving relational algebra, this approach adds flexibility to the data base, since each item can be broken down either into subitems that must be ANDed (all must be present) or into others that can be ORed (only one need be present).

Because the data base is hard to change once a system has grown to substantial size. CAE system designers should start off with the most flexible concept they can find. Artificial intelligence has produced data model that fits the bill, because a class system-such as Smalltalkaccepts hierarchical object organization with inheritance rules while permitting the object to be seen with other views (also called attributes, flavors, or properties).


One reason for the absence of such data bases from CAE systems is their link with the Lisp language and its reputation for slow execution and large memory. However, alternative languages exist. Mainsail, for instance, has its origins in the Stanford artificial intelligence language (Sail) and Mainsail is extendable, portable, and permits dynamically binding. Intel uses it for its in-house CAE.


For these reasons, the CAE system under development at Cericor Inc. (Salt Lake City, Utah) is worth a closer look. It is called actor-based because each process requests actions from the data base that are specific to that task. The design guidance task, for example, which automatically checks loads, also displays errors culled from the data base while returning node-related results. As can be expected, Cericor's AI-inspired system pays a lot of attention to a consistent and cooperate user interface.


#### **Dreaming of PC**


The need for an extensive and extendable data base, as well as the need for high throughput, has so far eliminated personal computers from candidacy for integrated CAE systems. Simulation and fault generation in particular have proven prohibitive for 8088-based machines like the IBM PC -generally the preferred personal computer for engineering tasks-but the 80286based IBM PC AT may change that. Daisy, whose Personal Logician has been capturing schematics for some time, has adapted the program to the PC AT and plans to extend it to simulation—an ambitious goal if the system is to digest more than a few dozen gates.

FutureNet Corp. (Canoga Park, Calif.) is taking a different—and perhaps more effective—approach. By adding a 16032-based coprocessor board that runs the Cadat simulator, the system packs the muscle of a full-fledged workstation where it counts the most.









For 15 years, Calma's been the big fish in a microscopic pond the intricate world of computer aided IC layout.

Now we're going into business on a much larger scale — PCB layout.

#### **INTRODUCING T-BOARDS** A BIGGER HELP.

Our new T-BOARDS™ software can give you more help than any other PCB layout software.

What other system, for instance, can give you fast automatic interactive routing of up to eight layers simultaneously.

And automatic interactive placement.

And on-line connectivity and clearance checking.

And a full color view of multiple layers.

And correct-by-construction methodology.

All in one package.

T-BOARDS is capable of handling 32"x 32,"32-layer boards, and features pop-up menus, real-time checks to make sure layout mirrors design, and 1 mil precision.

#### BIGGER AND BIGGER HELP.

T-BOARDS alone can cut your workload down to a manageable size.

But it doesn't stop there.

When brought into Calma's full TEGAStation environment, you'll have a complete front-end workstation system for schematic capture, advanced simulation and testability analysis — all using just one database.

#### SERVICE AND SUPPORT— MAYBE THE BIGGEST HELP.

For 15 years, Calma's been putting a comprehensive service and support organization in place.

In 60 places, for that matter. All over the world. We offer a variety of service

plans, hardware and software support, education programs — even a hotline.



Error lockout and dynamic checking.



Red rectangle shows clearance violation.

#### **BIG COMPANIES HAVE** BIG ADVANTAGES. ONE OF OURS IS GE.

PCB layout systems are a long range commitment.

No way do you want the company you're buying them from to fold in the short run.

Calma's been here for 15 years an institution in this mercurial business.

General Electric, our parent company, has been here over 100 years. And firmly believes electronics is the foundation for the next 100 years.

Giving Calma the resources and commitment to be here much


Which, if you plan on future growth in total automation, makes a big difference.

Call (800) 626-2001 extension 801 for specifics.





# We pack CMOS ROMs so densely something gets squeezed:



# ...the price.

	Part Number	Organization	Access Time (ns)	Operating Current (mA)	Standby Current (µA)	JEDEC Package	50K Price
<b>ESGIS</b>	CDM53256*	32Kx8	250	12	50	28 pin Type B	To be announced
FIZEK	CDM53128	16Kx8	250	10	50	28 pin Type B	\$3.00
EGALS	CDM5364	8Kx8	250	12	50	24 pin	\$2.50
#64K	CDM5365	8Kx8	250	12	50	28 pin Type B	\$2.50

<sup>\*</sup>Available first quarter 1985. Patterns accepted 12/84.

#### Now, CMOS ROMs at NMOS prices.

RCA has broken the price barrier. For the first time, you can buy CMOS ROMs from RCA for the same price as NMOS ROMs.

Our new space-efficient chip cuts manufacturing cost. Using a new and smaller space-efficient silicon chip, RCA has made CMOS ROMs the same size as most NMOS ROMs—even smaller than many. We shrank geometries down to  $3\mu$  and arranged memory cells in a NAND-stack configuration that uses the small space more efficiently. Our costs go down, so your price goes down.


#### Faster than NMOS, too.

At a maximum access time of 250 ns, RCA ROMs are even faster than many NMOS types. Cheaper and faster? Well, you'd expect the breakthrough in CMOS ROMs to come from the inventors of CMOS.

#### Pin-for-pin compatibility.

RCA ROMs feature the same pinouts as competitive NMOS and CMOS ROMs or PROMs. They are input and output compatible with CMOS or TTL logic. So now it's easy to give your existing design the advantages of CMOS technology...lower power consumption, wider temperature range, etc.

Pack your pattern to your RCA sales office today. Squeeze your ROMs, before your competition squeezes you. To put CMOS advantages in your design, call your local RCA sales office for a price quote today. For technical brochures and ordering information call toll-free 800-526-2177.




If you would like an RCA salesp detailed information on price, d erations, please send this coup Box 2900, Somerville, NJ 0887	elivery and technical consid- ion to: RCA Solid State,
End product application:	
What size ROM required?	
Name:	
Title:	Phone:
Company:	
Address:	

Call: Hamburg, 49-4106-6130; London, 44-03-2785511; Paris, 33-3-946-5656; Hong Kong, 8-52-3-723-6339; Sao Paulo, 55-11-210-4033.



#### **TURNING YOUR PC INTO A** FASTER TOOL FOR MODERN TIMES.

This is the 3rd in a series of technical papers from Zilog, designed to give engineers new insights into Zilog microprocessors—what advantages they provide for particular products and why they are the choice among engineers who need optimum performance.




IBM® and other compatible PC computers are fast enough for general home and office use. But, for hardware and software development applica-

tions, the gears turn slowly.

What you need is a faster "gear" to co-process with the Intel 8088 inside IBM's PC. Like Zilog's Z8001® CPU. Now, there's a way to increase throughput for the IBM PC—as well as test the performance of the Z8001 CPU for your high-performance applications with a Z8001 CPU-based board called the "Trump Card" from Sweet Microsystems. And it proves dramatically how powerful Zilog's 16-bit CPU really is.

The new device is a peripheral board that plugs into any expansion slot on an IBM PC or compatible PC computer. Trump Card is addressed as an I/O device that communicates through the expansion bus. It is powered by Zilog's Z8001 CPU.

The Trump Card increases the computational power of the IBM PC, and provides maximum performance with a minimum of board space.



The Trump Card, shown from the front. The left side of the board contains 512 K-bytes of type-4164 dynamic RAM; the right side contains the Zilog Z8001 and an interface to the IBM PC I/O-expansion bus.

## Z8001 COMPILER BASIC IS 80 TIMES FASTER THAN IBM INTERPRETIVE BASIC.

Essentially a monolithic minicomputer central processing unit, the Z8001 CPU is characterized by an instruction set more powerful than many minicomputers. As the programmer sees it, the Z8001 contains sixteen 16-bit general-purpose registers (for addresses or data) that may also be used in groups to form as many as eight 32-bit registers or four 64-bit registers. The low-order halves of the registers may be used for byte operations, thus the Z8001 CPU is able to manipulate data in 8-, 16-, 32-, and 64-bit pieces.


The Z8001 CPU, running at 10 MHz, can execute the same programs 4 to 10 times faster than the Intel 8088. What's more, the Z8001 CPU, with its large 8-megabyte memory range, makes the Trump Card's 512K bytes of memory easy to design with. (To use this memory in the card, you simply load a BASIC, CP/M-80, or C program from PC-DOS and

type "RUN")

Apple II	Apple III	TRS-80 Model II	IBM PC	IBM PC (with Trump Card)
224	222	189	190	2.4

A comparison of execution times (in seconds). Running on IBM's interpretive BASIC, a Sieve program takes 190 seconds to execute. Running the same program under TBASIC on the Trump Card Compiler takes only 2.4 seconds.

The eight addressing modes are register, indirect-register, direct-address, indexed, immediate, base-address, base-indexed, and relative-address. The instruction set utilizes data types ranging from single bits to a 32-bit long word. What's more, the processor executes 110 distinct instruction types that, when permuted by all the addressing modes and data types, create a set of more than 400 instructions.



A Z8000 CPU functional block diagram of the internal structure of the Zilog Z8000 family of high-performance microprocessors.

## ALL THE PROPER SUPPORT FOR 512K BYTES OF MEMORY.

The wide range of software written for the Z8001 CPU is proven by all the programs you can run on the Trump Card. With the Z8001-based Trump Card, you can run the following software on your IBM or other compatible PC:

BASIC Compiler – TBASIC is PC BASICA-compatible. Most instructions are implemented without modification.

CP/M-80 Emulator—Allows you to run CP/M-80 Z80 assembly language programs directly. Just download your Z80 programs and run them.

C-Compiler — The industry standard version of C is available.

Debugger—Intended to aid in program development, you can examine and change memory and register contents and more.

Screen-editor—Has many word processing features, including ASCII text file development. Multilevel Language Compiler—Allows

Pascal-like control and data types, arithmetic expressions with automatic or specified allocations of registers, and more.

RAM Disk—Can allocate 128K to 387K bytes of on board memory to function as an intelligent RAM disk.

#### COPROCESSING IS JUST PART OF THE STORY.

The Z8001-based Trump Card is just one example of a successful application design for the Z8001 CPU. But there's far more to the Z8000 family than this.

Today, Z8000 CPU's are used in a wide range of applications, from industrial and medical products to computers and graphics imaging machines. And Zilog stands behind every application with service and software support that makes your Z8000-based products get to market on time.

Find out for yourself how much power Zilog packs into every Z8000 CPU by turning your IBM PC

into a faster tool for modern times.


To get your own Trump Card and complete instructions, call Sweet Microsystems at (401) 461-0530.

For information about the Z8000 CPÚ, send for our complete overview or call our Literature Hot Line at 800-272-6560. For seminar dates and locations, or information on Zilog training, call 408-370-8091. Or write: Zilog, Inc., Technical Publications, 1315 Dell Avenue, MS C2-6, Campbell, CA 95008.

The Z80, Z8000, Z8001 are registered trademarks of Zilog, Inc. CP/M is a registered trademark of Digital Research Inc. IBM is a registered trademark of International Business Machines Corporation.

**Zilog** Pioneering the Microworld. an affiliate of EXON Corporation

CIRCLE 65



The remarkable efficiency of the HEXFET-II can bring significant benefits to all low voltage and battery powered applications.

Designers who are really into power MOSFETs will realize the fantastic cost savings now possible.

Learn the importance of this new development by contacting us for full data.

You can't afford not to.

#### NEW HEXFET-II LOW VOLTAGE MOSFETS ARE ALL SINGLE CHIP DEVICES!

HEXFET-II	V <sub>DS</sub>	RDS(ON)	ID @ 25°C
Part No.	(Volts)	(Ohms)	(Amps)
IRF050	50V	.017Ω	72A
IRFZ40	50V	.028Ω	51A
IRFZ42	50V	.035Ω	46A
IRFZ30	50V	0.05Ω	30A
IRFZ32	50V	0.07Ω	25A
IRFZ20	50V	0.10Ω	15A
IRFZ22	50V	0.12Ω	14A

**TECHNOLOGY DRIVEN** 

# International Rectifier

WORLD HEADQUARTERS: 233 KANSAS ST., EL SEGUNDO, CA 90245, U.S.A. (213) 772-2000. TWX 910-348-6291, TELEX 472-0403 EUROPEAN HEADQUARTERS: HURST GREEN, OXTED, SURREY RH8 9BB, ENGLAND, TELEPHONE (088 33) 3215/4321, TELEX 95219

## **D**ESIGN ENTRY

# Monolithic controller builds PC network without toil or trouble

A controller chip puts CSMA/CD within the reach of personal computer networks, keeping a lid on parts count and simplifying software development.

ffice automation promises to dramatically boost productivity. Personal computers are a step in that direction, and a giant one at that, forming a base of distributed intelligent machines. The next crucial advance is to link them in a network, so that each machine shares peripherals and information.

The 82588 is the first single-chip controller designed to join personal computers over a local network. Essentially a slave peripheral, the chip is fitted with a CSMA/CD controller, two logic-based collision detection mechanisms, and an encoder and decoder for both non-

return-to-zero inverted (NRZI) and Manchester data encoding. Adding a simple transceiver line


## Joseph Mazor and Robert Galin, Intel Corp.

Joseph Mazor is a design manager for local-area network products at Intel's design center in Haifa, Israel. He is a participating member of the IEEE 802.3 working group for 1-Mbit's star networks and holds a BSEE from Technion, The Israel Institute of Technology.

Since mid-1980 Robert Galin has been planning strategy for Intel's peripheral components operation in Santa Clara, Calif. He has a master's degree in engineering from the University of Michigan. driver or an RF modem lets the controller implement all of the major hardware functions required by a local-area network.

Most of the chip's major duties, such as encoding and collision detection, can be programmed to meet the protocols of a particular network. And although its flexible system interface allows it to be employed with any popular microprocessor, the controller is optimized to work with the iAPX-186 and the iAPX-188 without TTL glue.

For the most part, local networks specifically designed for personal computers suffer from one of three major deficiencies. First, many are



#### Cover: PC network controller

proprietary, forcing users to buy from one manufacturer. Second, with few exceptions, they lack collision detection, and therefore limit a network's efficiency for large offices (see "A LAN for All Reasons," below). Finally, industry-standard networks were originally designed for minicomputers. Thus, they are too expensive for personal machines. What is specifically lacking is an access scheme that is both efficient and cost-effective. In the past, carriersense multiple access with collision detection met the first requirement, but not the second. Conversely, approaches like collision avoidance meet the second specification but not the first.


In contrast, the controller was designed with low-end systems in mind and makes possible inexpensive but efficient local networks in three ways. For the OEM, it reduces component count, board space, and development time. For the end user, its 1- or 2-Mbit/s data transfer rate (lower than that of networks based on minicomputers) allow the integration of controller, encoder-decoder, and collision detection functions, which lowers component cost. Also, lower bit rates imply cheaper, twisted-pair cabling that covers longer distances without expensive repeaters (Fig. 1).

The controller works with emerging stan-

#### A LAN for all reasons

The recent proliferation of personal computers in the workplace has led designers to realize that a single approach to local networks cannot answer all needs. A network for engineering workstations would be too expensive for personal computers. Instead, a network needs to be built as a hybrid, with portions within individual departments appropriate to the cost and performance needs of the applications they serve (see the figure).

To that end, there are four separate—though not competing-CSMA/CD network specifications in various stages of development. The first is Ethernet, which with its 10 Mbits/s data rate is best suited to local networks built around minicomputers or as a backbone connecting smaller clusters of networked personal computers. Another approach, dubbed Cheapernet, is a reduced-cost implementation of Ethernet that works well with personal computers in research and engineering settings where 10 Mbits/s performance is necessary. A third approach, IBM's recently announced PC network will connect personal computers that are located up to 5 Km apart. Being a broadband network, it has the advantage that it can carry several services (video and data) over a single coaxial cable. Finally, Starlan is a proposed IEEE 802.3 standard that is a 1-Mbit/s baseband system. It inexpensively links devices, such as personal computers, through already installed twisted pair wires used for telephones. Its major use is for the office environment where low cost and ease of wiring is extremely important.



dards for personal computer networks like American Telephone and Telegraph's Starlan (1-Mbit/s baseband) and the IBM PC network (2-Mbit/s broadband). The controller also can be coupled with an off-chip data encoderdecoder to handle up to 5 Mbits/s when higher throughput is needed.

#### At your command

The IC communicates with a host using a set of 16 high-level commands (Fig. 2). The Transmit, Retransmit, Configure, and Diagnose commands free the CPU from overseeing every step of each task that the controller undertakes. Instead, after the processor invokes a command. it is free to take on other jobs. The high-level commands simplify writing and debugging software for the controller and the network.

Another of the controller's important features is its efficient memory structure for receiving frames. A network carries a large number of relatively short control messages, like Open, Close, and Acknowledge, that direct its operation. In fact, typically 75% of all network messages may be less than 100 bytes long. As a result, a storage system that breaks memory down into large, equal-sized blocks would be vastly inefficient. Each block would be able to accommodate the largest possible frame but would be only partially filled most of the time. The controller avoids this problem by using a sophisticated approach that allocates multiple buffers to a frame.

Rather than retain a frame in a single, sequential block, the chip stores it in a number of smaller buffers. A 100-byte buffer, say, could hold a short frame, and multiple 100-byte buffers could store longer ones. To link individual buffers, the host processor creates a chained list of pointers that indicate where in memory the data is held. This multiple-buffer approach keeps the amount of memory needed to store received frames to a minimum, an extremely important consideration in personal computers, where RAM is at a premium.

#### Aboard the chip

The controller itself consists of two main sections: a parallel system interface with the host and a serial interface to the network. Two builtin 16-byte FIFOs, one for transmitting and one


for receiving, link the two (Fig. 3).

The first block consists of a bus interface unit and a group of registers. The bus interface contains an 8-bit data bus. It is responsible for all communications with the system CPU. In conjunction with an external DMA controller, the new chip takes care of all reading and writing to memory—at up to 4 Mbytes/s—as well as all CPU interrupts. Two DMA channels are recommended, one for transmitting and the other for receiving.

The parallel section also comprises three sets of registers: one for storing configuration information, one for writing commands to, and one for reporting the chip's status. To make rapid changes in the controller's operating parameters, the processor enters a block of data into RAM, and that data is loaded by DMA into the registers (Fig. 4).

#### Serial side

The chip's serial interface contains the CSMA/CD controller and converts parallel data into serial form, and vice versa. It also assembles each frame as specified by the configuration registers, computes the cyclic redundancy code (CRC) for each transmission, and




1. The 82588 local-area network controller connects directly to a network (through a driver or modem) without the need for an expensive transceiver tap. Intended for relatively low data rates of 1 to 2 Mbits/s, the chip allows networks to be built with twisted-pair wires instead of coaxial cables.

#### Cover: PC network controller

backs off and reattempts transmissions in case of a collision.

Since most of its major features are completely under user control, the IC's data-link controller subsection gives an enormous degree of freedom to the system developer. And the chip is right at home in a wide variety of networks. For baseband transmission, it handles end of carrier (IEEE 802.3) framing; for the IBM PC network it accommodates high-level data link control (HDLC) framing. Both techniques include a 32-bit CRC for error detection. The data controller also can be programmed with the length of the address field, station priority, framing, minimum frame length, spacing between frames, and slot time.

The two collision detection methods increase the controller's range of possible applications as well (see "Collision Insurance," p. 148). The code-violation detection mechanism is most



2. The controller's command register is fed commands from the host CPU, which the chip executes for one of its two channels. The pointer field within the register identifies which status register is to be read, and the interrupt acknowledge field resets the controller's interrupt line to the CPU.

useful in short-topology networks, such as a serial backplane. The bit-comparison technique is employed in systems with separate channels for transmission and reception, like a broadband network. Both can be used simultaneously to ensure reliable operation.

The chip presents a rich assortment of diagnostic and management functions: internal and external signal loopback paths, channel activity indicators, optional capture of all frames (regardless of destination address), and timedomain reflectometry for locating faults in the network cable. Moreover, the controller's Dump command gives the designer access to the contents of all of the chip's registers, which helps debug system software.

#### The time is right

A clock timing generator on the chip's serial side determines the data rate. It will accept up to a 16-MHz crystal for data transfers to 2 Mbits/s. (The parallel side has its timing set by the system's master clock.) The data encoder and decoder, also on the serial side, can transmit and receive information in any one of three formats: Manchester, differential Manchester, and NRZI. Manchester is used in Starlan. NRZI encoding is for broadband systems.

The transmit and receive FIFOs enable the parallel and serial sections of the controller to exchange data. These registers, each 16-bytes deep, improve data throughput between the controller and the host CPU. The controller's programmable FIFO threshold can be finetuned to a particular system's bus latencies.

The controller and the CPU talk to each other through main memory and the controller's onchip registers. The processor uses the Chip Select (CS) line—along with the Write or Read signal—to gain the controller's attention. The controller communicates with the CPU over the Interrupt (INT) line. In addition, the two share an 8-bit data bus.

#### Two transfer types

Two types of transfers can take place via the bus. The first is a command and status transfer; the second, a data transfer. The former is always performed by the CPU. To initiate a Transmit or Configure command, for example, the processor issues the command to the controller. At the completion of the command the controller issues an interrupt and the CPU reads the chip's status.

The host reads each of the four status registers, from the same port, in round-robin fashion. Any parameters or data associated with a command are transferred between the main memory and the controller using DMA. Data transfers, unlike command and status transfers, are requested by the controller and are most often carried out by an external DMA controller.


#### **Dual DMA**

The controller is fitted out with a pair of DMA channels, each with a Request and Acknowledge line. Typically, one channel receives data and the other transmits information and carries the chip's initialization and maintenance routines. The channels are identical,

though, and can be used interchangeably. When the controller needs to transfer data to or from memory, it activates the DMA request lines and the DMA controller. When it is finished, it interrupts the CPU, which then reads the status of the controller to confirm the operation.

In order to transmit a frame, the CPU first prepares a data block in memory, which contains the network address to which the frame is to be sent and the information to be transmitted. The CPU programs the DMA controller with the address of the block, along with other control information. It then issues a Transmit command to the controller's command register.

At this point, the controller monitors the network link to determine whether the line is free. If it is, the IC starts transmitting the frame by inserting the preamble, beginning-of-frame flag, and the source address and fetching bytes from memory, loading them into the FIFO, and



3. The controller's two main blocks are linked by two 16-byte FIFO registers. The parallel section comprises a bus interface unit that connects the controller to the host and a register subsection that accepts commands and delivers information on the controller's status. The serial section contains a data-link controller subsection, decoder and encoder circuits, collision detection logic, and a serial-timing generator.

#### Cover: PC network controller

sending them out over the network. While the controller is sending the frame, it calculates a CRC, which it appends to the end of the data field. If a collision is detected during transmission, the controller sends out a jamming pattern and interrupts the CPU. The processor can then issue a Retransmit command, which works in the same way as the Transmit command, except that the chip keeps a record of the number of collisions that are detected. At the end of a transmission, the controller updates all of the status registers and sends an interrupt to the CPU, indicating that the transmission is complete.

When it is not transmitting a frame or doing housekeeping, the controller continually checks the network for any messages addressed to it.


#### Calling all nodes

The controller can be addressed in one of three ways: individual addresses to one node. multicast addresses to a group of nodes, and broadcast addresses to all of the nodes in the network. Two types of reception are possible as well. In the "promiscuous" mode, the controller accepts any frame that is transmitted on the network regardless of its address. In the other, the device accepts only multicast and individual addresses that correspond to its own. The latter typifies normal operations.


Before enabling the receiver, the CPU makes a memory buffer available and programs the DMA controller with the buffer's starting address. The received frame is then transferred to memory. This is known as single buffer reception, since the entire frame is sent to a continuous buffer.

When a frame is received, the network controller records the number of bytes that were written into the memory buffer in a status register. Also, the controller records the status of the reception—whether it was successful or not-and affixes that information to the received frame. Then the controller issues an interrupt to the CPU to indicate that reception is finished.

In networks where the size of the frame is not fixed, the controller's multiple-buffer scheme



4. The controller's four status registers fall into two categories. The first, which consists of three registers, indicates an operation's status. The second contains a single register and keeps tabs on the chip's internal operating activity. The operation status registers confirm that a particular command has been executed and store any result, if one is produced.



©1984 Allied Corporation

## Slip into something comfortably.

#### Interconnect up to 400 or more Bendix® B³ contacts with ease.

Your search for reliable, high density, low insertion force printed circuit board connectors is over.

Our unique Bendix® Bristle Brush Bunch (B³) connectors mate with 1.5 ounce insertion force per



contact position. That's a 70 to 90% reduction versus conventional pin and socket contacts, which minimizes the risk of connector or PC board damage during mating or unmating.

B<sup>3</sup> contacts are made of multiple strands of high tensile strength wire that are bundled together to

form a brush-like contact. Intermeshing two of these multi-strand wire bundles forms a gas tight connection with superior electrical characteristics including redundant current paths, minimal constrictive resistance and uniform current densities. B³ contacts maintain their electrical stability over 20,000 mating and unmating cycles.

Bendix B<sup>3</sup> connectors are available in 2, 3 and 4 row contact configurations on .100 inch centers with 10 to 100 contacts per row.

Mother board, daughter board and PC board versions feature front removeable contacts with straight and 90° PCB stud or solderless wrap terminations.

Input/output versions, have rear removeable/ rear release crimp contacts for 22 to 28 AWG wire.

Polarization keys offer 256 combinations. For more information, technical data and prices

Call 1-800-323-7299.

Amphenol Products world headquarters: Lisle, IL 60532



#### Cover: PC network controller

makes effective use of the memory. In multiple buffering, the controller alternately receives the contents of a given frame from one of the two DMA channels. This dynamic allocation of memory buffers makes particularly efficient use of available storage when frames are of widely differing sizes.

Before multiple-buffered reception begins, the CPU allots one buffer to the controller. As the controller starts receiving the buffer's contents, it interrupts the CPU and requests that

#### Collision insurance

The efficiency of CSMA/CD was demonstrated in a 1979 study of Ethernet that linked about 120 host computers and network servers. The investigation showed that a network using some form of collision detection had a throughput of 98%, compared with 37% in systems that deferred while there was traffic on the channel, and 18% in those with no collision-regulating provision at all. Until recently, though, the relative sophistication of such collision detection schemes as CSMA/CD precluded them from low-ends networks.

The 82588 can be programmed in two ways to implement CSMA/CD collision detection. Both are logic-based. In code-violation detection, the controller looks to see if incoming bits violate Manchester or NRZI enoding standards. If that is the case, they are assumed to have been damaged by a collision. The second method, bit comparison, is useful in networks with separate transmission and reception channels such as Starlan or the IBM PC network. In this scheme, the device compares its transmitted CRC signature with that of the received signal while a transmission is taking place. Monitoring the network in this manner allows the chip to immediately backoff and try again when a collision is detected, without having to wait for an acknowledgement from the received mode. Hence, total data throughput is significantly increased.

the next buffer in the sequence be assigned. The processor responds by loading the second DMA channel with the information in the next buffer. In this way, the controller can immediately switch over to the second channel as soon as the first buffer is full. When channels are switched, the controller again interrupts the CPU to request another buffer, and information on that buffer is loaded into the unused channel.

The process of alternating between channels continues until the entire frame has been loaded. By the time that is accomplished, the received frame has been spread over a number of buffers, and the CPU has created a description of the buffer-chain in memory.

Connecting the controller to any of the industry's leading microprocessors is a straightforward task because the chip's system interface adapts easily to any processor that works with standard data bus and control signals. The chip works with no wait states on an 8-MHz system bus. Further, a system based on the chip and one of the 80188 and 80186 family of microprocessors exacts a minimum component count (Fig. 5).

#### **Easy interface**

In a system centered on the 8-bit 80188, for instance, the controller connects directly to the microprocessor's 8-MHz clock and data bus and to its Read, Write and Chip Select control signals. Although the controller needs two DMA channels to operate, these, too, are supplied directly by the processor. And the CPU's interrupt controller can service the interrupts generated by the controller.

The controller's flexibility allows the same system configuration to be used in a number of different physical layer interfaces. In a Starlan network or in a serial backplane, the controller would feed a line driver. In an IBM PC network, the controller would connect to an rf modem. In terms of hardware, only the actual physical link to the network need be changed in order to switch between these applications. All other necessary variants are easily implemented by commands that can be built into the system's firmware.


For baseband systems running at 1 Mbit/s and using unshielded twisted-pair or coaxial cable, the only external components needed are



#### Cover: PC network controller

an RS-422 driver and receiver and, possibly, one or two pulse transformers. The last supplies dc isolation. Together, these few components can fit onto an area that is 6 cm on a side. In contrast, traditional data-link controllers and their associated TTL glue and other logic demand an area that is at least 15 cm on a side.

In a Starlan configuration, the controller links to the network through low-cost RS-422 transmitter-receivers, one connected to Transmit Data, TXD, pin and the other to the Receive Data, RXD, pin. Each transmitter-receiver is joined to a separate pulse transformer and then to corresponding transmit and receive twistedpair. Each station is connected to a hub over the two twisted pair drop cables, up to 800 ft. in length. Within the hub is a corresponding pair of transformers and RS-422 receiver-transmitters for each station. Transmitted signals from a number of nodes are ANDed on a short (less than 1m) bus and returned back to the controller through the receiver pair. The trans-



5. A minimum number of components marks the interface between the controller chip and an 80188 microprocessor. The controller IC links directly to the processor's 8-MHz clock, and Read, Write, and Chip Select control lines. Even the two DMA channels and the interrupt functions are handled by direct connections between the microprocessor and the LAN controller chip.

## D.A.T.A. BOOKS are like having 18 researchers at your fingertips...



#### but much easier to manage.

If you're an electronics engineer, chances are you've already heard about D.A.T.A.BOOKS. You may even be among the thousands of engineers who use one or more of our 25-plus publications daily.

Whatever information you need for your projects, D.A.T.A.BOOKS have it. Electrical specs...logic drawings... package design...device replacement...manufacturing sources... and more. D.A.T.A.BOOKS reference over 852,000 types of products from nearly 1,000 major manufacturers worldwide.

Our information is complete, accurate and up to date because we contact these manufacturers continually to get the technical data you need to complete your project faster and more efficiently. We know the information you require because

we've been in the business since 1956.

Inside D.A.T.A.BOOKS, you'll find easy to use standardized performance specifications, block drawings, alternate sources of supply, functional equivalence data, manufacturer locations and more.

You'll save time and money by contacting *only* those manufacturers you really need to for the best price and availability.

Your time is much too valuable to waste calling manufacturers and paging through out-of-date catalogs when you can have D.A.T.A.BOOKS do it for you!

Publications include — Integrated Circuits: Digital ICs, Linear ICs, Interface ICs, Memory ICs, IC Functional Equivalence Guide, Microprocessor ICs, Microcomputer Systems, Modules/Hybrids and Audio/Video

ICs. Discrete Devices: Transistors, Diodes and Thyristors. Special Devices and Directories: Optoelectronics, Power Semiconductors, Power Supplies, Microwave, Master Type Locator, Microprocessor Software and Applications Notes. Discontinued Devices: Digital and Audio/Video, Interface and Memory, Linear, Transistors, Diodes, Thyristors, Optoelectronics, Microwave and Type Locator.

Call or write us today. Or contact the D.A.T.A.BOOKS representative nearest you.

Toll-Free (800) 854-7030 Inside CA, call (800) 421-0159

#### (D.A.T.A., INC.

P.O. Box 26875 9889 Willow Creek Road San Diego, CA 92126

D.A.T.A.BOOKS Representative Listings: **EAST**: Motion Engineering, MA (617) 485-2144; Astrorep, NY (516) 422-2500, NJ (201) 826-8050; Motion Technology, DE/MD/DC/VA (800) 482-6318; Stegman Blaine, PA/WVA (513) 729-1969. **SOUTH:** Motion Technology, NC (800) 532-6849, TN/SC/GA/AL/FL (800) 482-6318; Blackburn Associates; TX/LA/AR/OK (214) 692-8885, TX (713) 463-1354. **MIDWEST:** Stegman Blaine, OH/KY (513) 890-7975, (216) 871-0520, (513) 729-1969; Enco Marketing, MI (313) 642-0203; JHS Associates, IL/IN/WI (312) 741-9070. **WEST:** Dynatech, CO/UT (303) 773-2830; Applied Controls Northwest, WA (206) 775-2999, (509) 922-1762, OR (503) 257-7408; Leddy Associates, No.CA/NV/HI (415) 969-6313; Varigon Associates, So.CA (213) 322-1120, (714) 855-0233, (619) 576-0100. **CANADA:** Tech-Trek, (416) 674-1717, (604) 273-1800. **INTERNATIONAL:** (619) 578-7600 or TLX: 910530606.

#### Cover: PC network controller

mitting controller performs collision detection on the received data.

For broadband systems, such as the IBM PC network, NRZI-encoded data passes through an rf modulator and demodulator. In this case, the RTS and Clear to Send (CTS) signals from the controller are modem handshake signals. Here, the transmit and receive signals are modulated at different frequencies, or channels. A frequency translator on the network receives the signals from all the nodes and retransmits

#### **Program 1. Sending the message**

TRANSMIT: PROCEDURE (CHANNEL, BUFFER\_LEN, BUFFER\_ POINTER): DECLARE CHANNEL BYTE; DECLARE BUFFER\_LEN WORD; DECLARE BUFFER\_POINTER POINTER; TX\_BUFFER\_588(00) = BUFFER\_LEN MOD 256; TX\_BUFFER\_588(01) = BUFFER\_LEN / 256; TX\_BUFF\_PTR =, BUFFER\_POINTER; TX\_CHANNEL = CHANNEL; TX\_BUFFER\_LEN = 2048; /\* TEMPORARYSTORAGE \*/ /\* MAX. FRAME SIZE \*/

CALL DMA\_LOAD (TX\_CHANNEL, 1, TX\_BUFFER\_LEN, TX BUFF PTRI OUTPUT (CS\_588) = 4 OR SHL (TX\_CHANNEL,4); TRANSMIT \* RETURN:

END TRANSMIT:

#### Program 2. Try, try again

RETRANSMIT: PROCEDURE:

PARAMETERS FOR THIS COMMAND ARE TAKEN FROM THE TEMPORARY STORAGE USED DURING THE LAST TRANSMIT COMMAND \*/

CALL DMA\_LOAD(TX\_CHANNEL,1,TX\_BUFFER\_LEN, TX\_BUFF\_PTR):

OUTPUT (CS\_588) = 12 OR SHL (TX\_CHANNEL,4);

/\* RETRANSMIT \*/ RETURN:

END RETRANSMIT;

#### **Program 3. Mission accomplished**

RCV\_ENABLE: PROCEDURE(CHANNEL, BUFFER\_PTR);

DECLARE CHANNEL BYTE; DECLARE BUFFER\_PTR POINTER;

CALL DMA\_LOAD(CHANNEL,0,2048,BUFFER\_PTR); OUTPUT(CS-588) = 8 OR SHL (CHANNEL,4); RETURN:

END RCV\_ENABLE;

them at the system's receiving frequency. The receive and transmit channels of the IBM network each fits into the bandwidth of a 6-MHz TV channel.

Software for the controller is much simpler and easier to implement than for traditional data-communication chips. One reason is the controller's high-level commands, which speed software development, as well as offload the CPU. Another reason is the controller's ability to handle complete frames without the processor's assistance.


In a PL/M-86-language procedure for transmitting a frame, the CPU prepares a block in memory by loading the DMA controller with the starting address of the block and its byte count (Program 1). The central processor also enters the DMA parameters into temporary storage so that they can be reused in case a collision occurs. After loading the DMA controller, the processor issues the Transmit command to the controller. If the channel is clear, the frame is sent. Otherwise, the chip automatically defers to any activity on the data link and then transmits its signal. Ultimately, the controller interrupts the CPU, which determines from the status register whether or not the transmission was successful.

If a collision occurs, the CPU invokes the Retransmit procedure (Program 2). In this procedure, the DMA controller is reloaded with the parameters (taken from temporary storage) and the Retransmit command is issued. On receiving it, the controller again attempts to transmit the frame, but only after a back-off time (which begins counting on the last collision) has run out.

Finally, to receive a frame, the CPU prepares a buffer in memory, loads the DMA controller. and enables the receiver (Program 3). When a frame arrives, it is deposited into the memory using a DMA operation. Then the CPU is interrupted, letting it know that it can now determine the length and status of the received frame.

How useful?	Circle
Immediate design application	541
Within the next year Not applicable	542 543

## 13 Small, Smart Solutions For Data Entry & Display



**Microterminal:** small, smart, tough . . . easy to install . . . simple to interface and operate - the logical, space saving substitute for bulky, fragile CRT's!

Rugged and water resistant for in-plant use - uncomplicated keyboards plus bar code wand and mag stripe reader options are perfect for factory data collection. Priced for OEM's and styled to enhance control consoles.

Serial ASCII (110 to 19,200 baud), RS-232-C, RS-422 and 20mA current loop communications. Only 8.5" x 4.5" x 0.6" and priced from \$192.00.\* Request new full line Microterminal brochure.

**Data Acquisition and Control Systems Division** 3631 E. 44th Street, Tucson, AZ 85713 (602) 747-0711

Model	Alpha Display Characters	Baud Rate	Data Buffers: Characters	Keyboard	Function Keys(3)	Features	Supply Voltage
TM71	16	110-19200	320(1)	Alpha	14	Full feature	+5VDC
TM77	16	110-19200	320(1)	Numeric	14	Larger keys	+5VDC
TM71-I/O	16	110-19200	320(1)	Alpha	14	TTL I/O	+5VDC
TM77-I/O	16	110-19200	320(1)	Numeric	14	Larger keys	+5VDC
TM71B TM71MS	16	110-19200	320(1) 5 x 50(2)	Alpha	16	Bar Code Wand	+24VAC/ DC
TM77B TM77MS	16	110-19200	320(1) 5 x 50(2)	Numeric	16	Mag Stripe Reader	+24VAC/ DC
TM71M	16	110-9600	320	Alpha	14	Military	+5VDC
TM70	12	300 & 1200	36	Alpha	8	Low cost	+5VDC
TM76	12	300 & 1200	36	Numeric	8	Larger keys	+5VDC
TM25	8	300	8	Numeric/ Hex	7	Low Cost	+15VDC
TM27	8	300-4800	8	Numeric/ Hex	6	Low Cost, polled	+8 to +12VDC

1) Two 80-character input buffers - two 80-character output buffers. - 2) 5 x 50-character buffers also included for bar-code and magnetic-stripe reader data. 3) User programmed.



**Tomorrow's Solutions Today** 

(205) 882-0316, (206) 455-2611, (213) 991-8544, (214) 681-5781, (215) 657-5600, (216) 729-3588, (301) 628-1111, (301) 251-8990, (303) 663-4440, (305) 365-3283, (305) 395-6108, (312) 832-6520, (313) 474-6533, (314) 291-1101, (315) 699-2671, (315) 853-6438, (316) 942-9840, (317) 636-4153, (319) 373-0152, (404) 447-6992, (408) 559-8600, (412) 487-8777, (505) 293-8555, (602) 746-1111, (607) 785-3191, (612) 884-8291, (614) 764-9764, (617) 444-9020, (713) 988-6546, (714) 835-0712, (716) 544-7017, (716) 889-1429, (801) 467-2401, (805) 496-7581, (813) 885-7658, (913) 342-1211, (914) 964-5252, (919) 722-9445, **CANADA**: (403) 230-1341, (416) 678-1500, (514) 731-8564, (613) 722-7682

## Introducing three new 2465 Special Editions.



DMS

CTS

## Now Tek tops the scope that topped them all!

These specially configured, specially priced measurement packages based on the 300 MHz 2465 deliver capabilities well beyond what you're used to now. Quicker measurements. More precision. More value. They bring unprecedented manual/programmable efficiencies to a spectrum of measurements in manufacturing, design or service applications.

At the top is the 2465 DVS with integral GPIB interface, DMM, Counter/Timer/Trigger-Word Recognizer and Video measurement capabilities.

The GPIB interface lays the groundwork for a programmable semiautomatic measurement package with extended capabilities. Result: you use computer power and human pattern recognition to best advantage in your test and measurement applications.

The Counter-Timer-Trigger (CTT)-Word Recognizer combination, also programmable, is ideal for measuring frequency, period, pulse width, time between events and more—automatically. And for the first time in a portable scope—Boolean triggering.

The 17-bit Word Recognizer probe, enabling you to count, trigger and determine the frequency of word occurrences, is a valuable tool in digital applications.

The fully programmable 4½ digit, autoranging DMM provides dc and ac (RMS) volts and current, dBm, dBV, resistance and temperature. All measurements can be averaged and smoothed for CRT display or bus transmission.

For television waveforms, including "high definition," the 2465 DVS enables easy display of any line or field regardless of protocol. Other unique features are a back-porch clamp and CRT readout of the triggering field and line numbers. The step, frequency and phase response, and overdrive recovery are comparable to waveform monitors.

The GPIB, a talker/listener, provides programmability for the scope and all its extended measurement capabilities. It can transfer readout displayed measurements and accept operator prompting messages.

The 2465 DMS and 2465 CTS are special editions with different feature sets. The 2465 DMS provides all the capabilities of the DVS except TV. The 2465 CTS provides all the features of the DVS except TV and DMM.

These new 2465 Special Editions are based on everything that made the 2465 the

		2405 5440	2405 050
Features	2465 DVS	2465 DMS	2465 CTS
GPIB	STD	STD	STD
Counter/Timer/Trigger- Word Recognizer	STD	STD	STD
P6131 (4 probes)	STD	STD	STD
DMM	STD	STD	
TV	STD		
Rackmount*			★ 25 F28

\*Available at time of order and can be configured with the other capabilities.

NOTE: Extended measurement capabilities may be ordered on either the 150 MHz 2445, or 300 MHz 2465 oscilloscopes.

#### world's most popular high performance portable scope.

You get auto level "hands-off" triggering. True four channel capability with 300 MHz bandwidth at the probe tip. Δ-Time delayed sweep accuracy up to 0.5%. On-screen vertical and horizontal cursors. Extensive CRT readouts, including time, voltage, phase, ratios and trigger level.

Plus, the industry's first 3-year warranty on all parts and labor, including the CRT.

See refinements in productivity, automation, accuracy and performance like you've never seen before. Call your Tek sales engineer today for a demo. For literature call the Tek Literature Center toll-free at 1-800-547-1512. (In Oregon, 1-800-452-1877).



# When you need fast, easy selection of magnetic cores for switching power supplies,

Common Mode Filter	In Line Filter	Driver	Output Transformer	Power Filter Inductor
Ferrite toroids Ferrite shapes (ungapped)	Molypermalloy powder cores 50 Ni-50 Fe powder cores Gapped ferrites	Bobbin cores Ni-Fe tape wound cores Ferrite toroids	Ferrites (a) pot cores (b) shapes (c) toroids  Ni-Fe tape wound cores  Amorphous tape wound cores  Cut cores (a) Ni-Fe (b) Amorphous (c) Ni-Fe laminations	Molypermalloy powder cores 50 Ni-50 Fe powder cores Gapped ferrites Cut cores


## We deliver the widest product choice – useful design data – the best application engineering – all from a single source: MAGNETICS.

It's a jungle out there in the switched mode power supply and regulator design world. Higher frequencies. Smaller sizes. Greater efficiencies. Better semiconductors. And choices, choices, choices in magnetic core materials and geometrics.

You know the impact the proper choice of core material will have on your power supply cost and performance. There's only one house that can provide you with the full

range of your magnetic core needs-and world class design data and application engineering to go with it-MAGNETICS.

Let us show you. It will cost you nothing. Tell us the problem you face or describe your need. We'll provide you with core information, back it up with application engineering and supply sample cores if needed. Write: MAGNETICS, P.O. Box 391, Dept. ED-6, Butler, Pennsylvania 16001.



MAGNETICS. The Promise Keepers.



#### **D**ESIGN ENTRY

## Controller chips pair up in S interface for ISDN systems

Two CMOS LSI chips, the chief building blocks of a system terminal and a PBX line card, simplify implementation of the S interface for ISDN links.

he emergence of all-digital telephone networks using packet- and circuit-switched data schemes will open the door to many new telecommunication services, including electronic mail, banking, alarm signaling, and the transfer of information via telex and facsimile facilities.

Already the International Telephony and Telegraphy Consultative Committee (CCITT) has recommended standards for an S interface on the premises of subscribers to the Integrated Services Digital Network (see "Interface Standard Ensures Compact Subscriber Networks," p. 158). This microprocessor-controlled interface to the ISDN will give subscribers simultaneous access to two 64-kbit/s voice or data channels and one 16-kbit/s control channel. Voice-band signals are to be digitized at the subscriber's terminal and transmitted over one of the 64-kbit/s channels. It will be possible to link all three channels to a main computer for central handling over pulse-code-modulated (PCM) highways.

#### Alan Clark, Advanced Micro Devices Inc.

Alan Clark, currently ISDN product marketing manager at AMD in Sunnyvale, Calif., joined the company in March 1983 as a development engineer. Before that, he designed microprocessor-based control systems for power stations at Babcock-Bristol Ltd. in the United Kingdom. He holds a BSc in mathematics and physics and a PhD in digital signal processing from the Polytechnic of Central London.

Although it will be some time before system specifications are completely defined, help in implementing the S interface is at hand in the form of two CMOS chips: the Am7930 digital subscriber controller and the Am7931 digital exchange controller. They are the first LSI circuits to meet the CCITT's basic design criteria for ISDN terminals and private branch exchange (PBX) line cards.

The subscriber controller chip is the heart of either a basic or an advanced ISDN terminal driven by an 8-bit microprocessor; it gives the customer access to the data-handling facilities on the S interface. For PBX design, the exchange controller chip is used to build the required number of S interfaces on the line card (one chip for each interface). Residing on the PBX line card itself, the device provides the exchange information function for one ISDN subscriber line.

Both chips allow full-duplex data transfer at 192 kbits/s over four wires between the subscriber's terminal equipment and the PBX line card. These ICs support the point-to-point and point-to-multipoint connections described in the CCITT recommendations, with the data framed on the 64-kbit/s voice and data (B1 and B2) channels and the 16-kbit/s control and data (D) channel.

The main blocks of the subscriber controller chip are a line interface unit, a data link controller, a multiplexer, a main audio processor,

#### ISDN controller chips

and a microprocessor interface (Fig. 1a).

The line interface is connected to the fourwire S interface by a pair of isolating transformers, one for transmission and the other for receiving. The transmitter, which has a binaryto-pseudoternary encoder and a line driver, receives the B channel data from the multiplexer and the D channel data from the data link controller. It then couples these signals to the Sinterface.

The unit's receiver recovers data and timing from the S interface; it also presents data from the B channels (via the multiplexer) and the D channel (via the data link controller) to the subscriber. The receiver, in essence performing a function inverse to that of the transmitter, converts pseudoternary-coded signals into binary before delivering them to other blocks within the IC.

Data processing is coordinated by the data

#### Interface standard ensures compact subscriber networks

The CCITT's proposals for an interface standard ensure that a small set of ICs can meet the requirements of an evolving telecom network as it moves toward an all-digital state. Two main subscriber configurationspoint-to-point and point-to-multipoint-have been recommended for use with the Sinterface, which is a four-wire module operating at 192 kbits/s (48-kbit data/control frame structure).

In the point-to-point setup, one telephone or terminal is connected via an S interface to a line card in the local exchange through cables no longer than 1 km. The point-to-multipoint configuration


may join up to eight telephones or terminals with one S interface, and cable runs to the local exchange are 150 meters or less.

The function of the terminal equipment is virtually identical in both configurations. With the network terminating equipment, however, there is a difference; whereas some equipment would be tied into a single terminal on the subscriber's premises, in larger installations it would be in PBXs using multiple terminals.

In the latter case, network terminating equipment 1 (see the figure) would connect to the transmission line on one side and present the standard S interface

at point T on the other side. Network terminating equipment 2 would be optional and would provide line termination for network terminating equipment 1. Terminals that operate with existing standards (like the RS-232) would attach at reference point R and use a terminal adapter for interface buffering.

The transmission line (for which there is yet no standard) would connect either to the line terminator or to a central office line card. The transmission line media, which vary from country to country, could be two-wire, four-wire, fiber-optic, microwave or satellite linkups.



link controller, which extracts the D channel information from the Sinterface and transmits the microprocessor-generated D channel information over the Sinterface. The controller also performs bit checking and frame checking for error detection, and it generates various detec-

tion flags when necessary.

In operation, the system's master, or external, microprocessor initializes the data link controller and performs the higher-level protocol processing. A random-number generator in the data link controller provides an address for the subscriber controller chip when the IC is powered up for operation on the S interface. When the chip is receiving, data flows via the D channel from the line interface unit through the microprocessor interface. This flow reverses when the chip is transmitting.

The device's protocol permits terminals in the point-to-multipoint configuration to access the D channel in an orderly way. When two or more terminals attempt to access the D channel simultaneously, one will always be successful in completing transmission of its information. This procedure also permits the terminals to operate in a point-to-point configuration.

#### Selective response


The data link controller will recognize 1- or 2-byte addresses and the first 2 bytes in a longer address. This allows the user to program the chip to respond only to selected addresses. In this way the terminals interrupt their respective microprocessor only when their preprogrammed address is received. The data link controller can also be programmed to bypass the address-decoding phase and to pass the entire packet to the microprocessor.

As the data link controller receives the D channel information from the line interface unit, it alerts the external microprocessor by generating suitable interrupts (if there is no interrupt mask). The microprocessor determines the source of an interrupt by reading the interrupt register, and it then accesses the appropri-

ate error or status registers.

The circuitry to access the subscriber controller's programmable, status, and error registers, as well as its transmitting and receiving buffers, is all in the microprocessor interface block. This section has the logic to interface the chip to an external 8-bit microprocessor. Controlling the multiplexing of the B1 and B2 channels to and from different sources is the job of the programmable multiplexer. Possible source and destination pairings include the line interface unit, the main audio processor, the microprocessor interface, and the serial port, with the port providing a serial interface to external peripherals.

Generating suitable audio responses and



1. The Am7930 digital subscriber controller for telephone systems contains circuitry for accessing the S interface defined by the CCITT (a). This device is on the subscriber's premises. The Am7931 digital exchange controller provides the S interface and line termination functions for the subscriber controlier (b). The IC is on the private branch exchange (PBX) line card.

#### ISDN controller chips

tones is the responsibility of the main audio processor block. In addition to digital filtering circuits, it has digital-to-analog and analog-todigital converters. It will drive a handset earpiece or a loudspeaker, and its analog input accepts a handset mouthpiece, a separate microphone, or both.

The multitone generator in this block can provide a one- or two-tone signal with programmable frequency, amplitude, and cadence. One or more tones can be summed into the transmission (and side-tone) paths to create a dual-tone multifrequency generator. Or the tones can be summed into the receiving path to provide indication at the loudspeaker output of dialing, busy, or ring-back conditions.


Two correction filters, one in each transmission and receiving path, can be programmed to modify the frequency characteristics. Thus they compensate for any imperfections in audio response of the microphone, earpiece speaker or loudspeaker. They can also be used to add preemphasis or postemphasis or both to match user preferences.

Except for the exclusion of the main audio processor and the inclusion of a time-slot assigner, the main blocks in the exchange controller chip are the same as those of the subscriber controller (Fig. 1b). There are, however, some operational differences within the blocks of the exchange controller.

First, the line interface unit can be operated in two modes: adaptive timing for pointto-point applications and fixed timing for point-to-multipoint. The mode is selected by an internal register that the local external microprocessor programs.

Also, the exchange controller's multiplexer can route data from the microprocessor interface and the B1, B2, and D channels to the timeslot assigner. The multiplexer performs these operations in addition to the routing options specified for the multiplexer in the subscriber controller chip. When the D channel is routed to the time-slot assigner, it bypasses the data link controller. Hence the central computer has direct access, over the dual PCM highway, to the B1, B2, and D channels to or from the S interface, as well as to the local external microprocessor.

Significantly, the exchange controller chip is compatible with the Am7901A subscriber line



2. The data frame structure with which the subscriber and exchange controllers communicate over the S interface operates at 192 kbits/s. During each 48-bit (250-µs) frame, two voice/data streams and one control/data stream are sent from the network terminating equipment to the terminal equipment. The identical format controls communications between terminal equipment and network terminating equipment after a check for line contention has been performed by the terminal equipment (D to E bit query). The CCITT ISDN recommendation gives a full definition of frame structure and bit polarities.

audio-processing circuit (SLAC) used in analog line cards, because both parts support a dual PCM interface. Therefore digital line cards can replace analog line cards on a one-to-one basis within the same PBX. The practical advantage is that an analog system can be gradually modified to an all-digital one. Most importantly, because of the backplane compatibility between the exchange controller chip and the subscriber line audio processing circuit (vis-à-vis the dual PCM highway), systems can be developed that connect the S interface point to analog trunk lines. This configuration befits public telephone communication.


#### Picking the right slot

The exchange controller's dual PCM interface has independent control of the transmission and receiving paths. The frame synchronization signal identifies the beginning of the frame and establishes a reference point for all time slots. The dual PCM interface can operate at up to 8.192 Mbits/s and therefore will be able to accommodate 256 time slots at 64 kbits/s. During each frame, two 64-kbit/s B channels (8-bit time slots) and one 16-kbit/s D channel

(2-bit time slot) may be transferred to or from the dual PCM highway (Fig. 2). Time-slot assignment and highway selection is under program control of the line card microprocessor.

The on-chip time-slot assigner allows a number of the exchange controllers to be connected together and to the PBX backplane. The assigner can be programmed by the microprocessor to transmit or receive data to or from the B or D channels over the PCM highway. Or it can be programmed to send or receive data from the microprocessor. The local microprocessor may thus communicate with the central computer over the dual PCM interface.

When suitably configured with other available chips to create a simple PBX, the subscriber and exchange controller chips can be used in applications ranging from a simple voice telephone to a sophisticated voice/data terminal. In its simplest form, an ISDN terminal using the devices requires a microprocessor and keypad. The microprocessor scans the keyboard and constructs the signaling messages for the D channel. The only other circuits required (Fig. 3) are the Am7936 subscriber power controller and the Am7938 quad exchange power



3. In PBX applications, the minimum set of chips required for subscriber access over the S interface comprises a digital subscriber controller, a digital exchange controller, a subscriber power controller, a quad exchange power controller, and two 8-bit microprocessors. The rudimentary connection shown establishes standard telephone service.

#### ISDN controller chips


controller, plus two bipolar high-voltage ICs to supply the required voltage and power levels over the Sinterface.

In the PBX application, a 40-V input to the S interface from the quad exchange power controller is converted by the subscriber power controller into a 5-V dc output, enough to power the ICs in the terminal equipment. One quad exchange power controller can drive up to four S

The subscriber controller chip can be used in a variety of terminal equipment, from simple voice-only setups and hands-free phones to a full workstation (Fig. 4). To connect ISDN circuits to existing equipment, the chip's serial or microprocessor ports can be used to access the CCITT's R interface point, which can be any interface—for instance, an RS-232.

Multiple exchange controller chips may be used on one PBX line card to provide the required number of Sinterfaces. One microprocessor can control up to eight S interfaces and can be linked to the line card's backplane via an Am8530 serial communications controller that connects to the parallel microprocessor bus. Or the microprocessor can communicate with the line card over the dual PCM highway of an exchange controller.

For practical implementation of an S interface on the ISDN, consider a telephone capable of supporting one analog line (one two-way conversation) and an RS-232 data link (Fig. 5). Ideally all the ICs would reside in the telephone, with a standard RS-232—compatible connector



4. The voice-only phone (without the digital signal processor block or a display) is the ISDN equivalent of the standard analog phone. A digital signal processor may be interfaced to the serial B port for echo cancellation and voice encryption, yielding secure hands-free operation (a) with on-hook dialing. In voice and data workstations, the subscriber controller chip combines with a number of peripherals, including memory, UART, CRT controller, and a microprocessor all connected to the same microprocessor bus (b).

# GEARED FOR SPEED. Siliconix's SD5000 ANALOG SWITCHES AND SD210 FETs Deliver Lightning Speed For Video And Audio Switching.

Today's video, audio and data acquisition systems demand high-speed switching capability. Our SD5000 and SD210 families provide the solution.

These versatile devices are monolithic arrays of single-pole, single-throw analog switches. Available as a single-channel FET (SD210-215) or four-channel IC (SD5000-5002), they feature low  $r_{\mbox{DS}(\mbox{on})}-70\Omega$  max—and low input/output capacitance with virtually no crosstalk. And they can pass audio and video signals beyond 500MHz.

Fabricated using Siliconix's sturdy polysilicon-gate DMOS process, the SD5000 and SD210 bring you faster, more stable switching than their metal-gate competitors—with no distortion. But the best part is they're available now. In stock. And in volume. For more information send us the coupon. Or call (408) 988-8000 ext. 2066. Siliconix's SD5000 and SD210. Because the performance shift is on.

Corporate Headquarters, 2201 Laurelwood Road, M/S 5, Santa Clara, CA 95054 European Headquarters, Morriston SWANSEA SA6 6NE, United Kingdom Far East Headquarters, Hong Kong Nippon-Siliconix, Tokyo, Japan.



(408) 988-8000


Siliconix incorporated, P.O. Box 4777, Santa Clara, CA 95054 I'm ready to shift my system performance into high speed. Please send me: (ba) SD5000 data sheet. (bb) SD210-215 data sheets. (d)  $\square$  IC data book. ☐ MOSPOWER design catalog. (f) Small Signal FET design catalog. ☐ CMOS Gate Array brochure. ☐ Have an applications engineer call me. Name Position Company\_ City\_ State Phone ( Expiration date 6/30/85

#### ISDN controller chips

built into the side of the telephone set.

The subscriber power controller provides an isolated 5-V dc output to power ICs required for telephone functions even when local power is lost. The isolation prevents a ground loop between the terminal equipment and the PBX line card when a locally powered terminal is connected to the telephone set.

The microprocessor—in this example, an Am80C51—programs and controls the ICs in the terminal equipment, as instructed by commands generated by the PBX line card, keypad, or RS-232 link. This configuration allows the microprocessor to use its standard 8-bit bus. Port 3 of the microprocessor provides bus control signals (like read and write) and port 0 handles the 8-bit address/data bus. Port 2 handles the high-order addresses (A<sub>8</sub> to A<sub>15</sub>) to the digital subscriber controller, the serial communications controller, PROM and RAM, and the keypad control. Both interrupt outputs of those controllers tie into the two microprocessor input interrupt pins on port 3, so that the microprocessor can service interrupts from the ICs separately. In addition, with a PAL device, port 1 on the microprocessor delivers the Chip Select



Practical terminal equipment applications for controller chips include a telephone that supports one voice line and one data link simultaneously. Memory devices—which should be large enough to accommodate expanded system telephone functions—contain the operating protocols and software for system initialization.

#### **Type TF Ultra-Precision Film Resistors from Caddock:** Absolute Tolerances to ±0.01% with TC's to 5 PPM/°C and Resistance Values from 1 kohm to 125 Megohms.





#### Caddock's Tetrinox® resistance film technologies achieve unique ultra-precision resistor performance.

Tetrinox®—Caddock's advanced resistance film technology-combined with high-thru-put manufacturing technologies, results in a unique approach to the production of ultra-precision resistors.

The Type TF resistors utilize these tech-

nologies to provide a highly producible ultra-precision resistor with low temperature coefficients, high stability and an extended resistance range.

#### Resistance values up to 125 Megohms provide a new design element.

The exceptionally wide range of resistance values from 1 kohm to as high as 125 Megohms make the Type TF Ultra-Precision Resistors ideal for new design opportunities.

And in existing designs, Type TF resistors are widely used to replace ultra-precision wire-wound resistors. For purposes of price comparisons

with ultra-precision wire-wound resistors, here are representative Type TF prices in 2500-unit quantities:

Model No.	-	Toler- rance	TC	Unit Price
TF 020 R-	1 k	-0.01%-10	PPM/°C	\$2.67
TF 020 R-	10 k	-0.01%-10	PPM/°C	\$2.67
TF 020 R-	100 k	-0.01%-10	PPM/°C	\$2.93
TF 020 R-	1 Meg	-0.01%-10	PPM/°C	\$4.94
TF 626 R-	10 Meg	-0.01%-10	PPM/°C	\$6.47

The high producibility and unit-to-unit consistancy of Type TF resistors also assures 6-to-8 week delivery on even large production quantities, and many resistance values are available from stock.

#### **Seven Absolute Tolerances from** ±1.0% to ±0.01%.

For maximum design flexibility, Type TF resistors are available in seven resistance tolerances

> $\pm 0.01\%$ ,  $\pm 0.025\%$ ,  $\pm 0.05\%$ ,  $\pm 0.1\%$  $\pm 0.25\%$ ,  $\pm 0.5\%$  and  $\pm 1.0\%$

This wide range of absolute tolerances gives circuit designers optimum price-performance characteristics in all applications.

#### **Three Temperature Coefficients** of 5 PPM/°C. 10 PPM/°C and 15 PPM/°C.


The choice of three Absolute Temperature Coefficients - 5 PPM/°C, 10 PPM/°C and 15 PPM/°C - in all models and values of Type TF resistors permits each circuit's requirements to be achieved on an efficient performance versus cost basis.

These temperature coefficients apply over

the temperature range of -15°C to +105° C, referenced to +25° C.

#### Type TF Resistance Range from 1 kohm to 125 Megohms

Model Number Wattage @ +70° C.		Maximum Continuous	Resis	tance	Dimensions	
Radial Leads	@ +70°C.	Oper. Voltage	Min.	Max.	Length	Height
TF 020 R	0.33	300	1 K	2 Meg	0.75 ± .020	0.375 ± .020
TF 050 R	0.75	1400	10 K	10 Meg	1.50 ± .020	0.50 ±.020
TF 626 R	0.33	300	2.01 Meg	35 Meg	0.75 ± .020	0.375 ± .020
TF 656 R	0.75	1400	10.01 Meg	125 Meg	1.50 ± .020	0.500 ± .020




#### Thin-profile Type TF resistors save installation space.

The thin profile of the Type TF resistors make them an ideal replacement for the largebodied wire-wound resistors.



And the radial leads of the Type TF resistors also simplify their installation into PC boards. **Custom Type TF resistors** with special performance and configurations can achieve optimum cost-effectiveness.



tolerance, temperature coefficient and resistance value that are available in the standard radiallead Type TF Ultra-Precision Film Resistors.

Discover how easily these problem-solving resistors can improve the performance and reliability of your equipment, too. For your copy of the latest edition of the Caddock 24 page General Catalog, and specific technical data on any of the more than 150 models of the 13 standard types of Caddock High Performance Film Resistors and Precision Resistor Networks, just call or write to -

Caddock Electronics, Inc., 1717 Chicago Avenue, Riverside, California 92507 • Phone (714) 788-1700 • TWX: 910-332-6108



#### ISDN controller chips

signal (CS) to the ICs and a clock to the serial communications controller.

The amount of memory (PROM and RAM) needed depends on the sophistication of the terminal equipment. The PROM contains the LAPD (Link Access Protocol Type D) protocol, keypad, and initialization routines for the subscriber and communications controllers. The number of programs in the PROM—and hence its size—will grow as the local terminals that need the RS-232 link increase and as telephone functions are added to the system (for example, call forwarding, call holding, and automatic redialing). Therefore the PROM area should be upwardly compatible to accept EPROMs of 16 to 64 kbytes. The RAM is used by the microprocessor to store temporary information and to adapt the data rate of the information passed between the RS-232 link and the Sinterface.

The subscriber controller chip is connected to the telephone earpiece, ringer, microphone, and hookswitch, and, via the S interface to the PBX line card. The serial port on the device connects to one of the serial ports of the serial communications controller. The other serial port on that controller, connected to the differential line drivers and receivers, provides an RS-232 link to a local terminal from the connector on the side of the telephone set.

On power-up, the microprocessor in the terminal equipment enters a reset routine stored in the PROM. This routine initializes the subscriber and communications controllers, then disables them, and the microprocessor then scans the keypad (via the keypad controller) for activity. The terminal equipment can now begin transmitting and receiving to and from the Sinterface, RS-232 link, and telephone handset. It can be activated by the PBX line card over the S interface or locally, from the keypad or when the handset is lifted.

If the telephone handset is lifted, the subscriber controller chip will interrupt the microprocessor, which interrogates the device's interrupt register and establishes that a voice connection has been requested. The microprocessor then transmits a data packet over the D channel to the PBX, requesting that a B channel be made available for the telephone conversation. (This transmission is over the S interface via the on-chip data link controller.)

At this point the PBX processes the packet and responds by transmitting a corresponding packet from the line card over the Sinterface to the terminal equipment. The packet indicates which B channel can be used for the voice link, and the packet is passed by the subscriber controller, via its data link controller, to the microprocessor. The microprocessor decodes the packet and programs the chip to connect its main audio processor to the designated B channel on the S interface. With the telephone link thus established, the subscriber will hear the dial tone and be able to dial the telephone num-

The microprocessor scans the keypad for the number being dialed, then transmits it to the PBX on the D channel. The PBX decodes the number and makes the connection. The subscriber will hear the connected telephone ringing, and conversation can begin when the phone is answered via the designated B channel.

The microprocessor and the PBX line card interact similarly when a local terminal is connected to the RS-232 port and the subscriber requests data transmission via the keypad. Unlike voice transmission, however, the microprocessor in this case will program the subscriber controller to route the designated B channel to the serial port, thus providing a link to the serial communications controller. The microprocessor will also program that controller to process the data going to and coming from the subscriber controller's serial port.

#### A voice from beyond

On the other hand, when the PBX initiates a voice transmission, the subscriber controller will interrupt the microprocessor and pass the D channel data from the line card to the microprocessor. If the line card is requesting a voice connection, the microprocessor instructs the subscriber controller to activate the telephone ringer and make the B channel link, so that conversation can begin when the telephone is answered.

If the PBX requests a data link to the RS-232 interface, the microprocessor will program the subscriber controller accordingly, route the designated B channel to the chip's serial port, and monitor the data transfer. Since the Sinterface can support two 64-kbit/s B channels, Pay less for more.



#### Get RCA quality and performance.

OEM designers and systems integrators can now utilize the many performance features of RCA communication terminals, at most attractive prices.

The RCA APT (All-Purpose Terminal).

Professional quality RCA APT terminals are designed for remote data base timesharing by telephone line and direct computer-connected applications. They feature a built-in 1200-baud or 300-baud direct-connect modem, an RS232C interface for high speed modem and other accessories, and a parallel printer port for hard copy. Menu controlled operation and a "programmable personality" can match specific requirements for each data base.

VP5801 APT, \$559\*.

Built-in 1200-baud direct-connect modem. Full 60-key typewriter-style keyboard with 16-key calculator keypad. Auto-dial (tone or pulse) of up to 26 stored numbers for voice or data base calls. Programmable sequences initiated automatically after log-on. Two user keys for selection of printer or other operating modes; four programmable function keys, shiftable for a total of eight functions. APT can be programmed to match the communications requirements and control commands of many other (and more expensive) terminals. Briefcase size  $(17" \times 7" \times 2")$ , lightweight (under 4 lbs.) and memory backup (minimum 48 hrs., without batteries) enhance portability. Many other user-friendly features.

VP4801 APT, \$348\*.
All other features of the VP5801, except with 300-baud modem.

VP3301 Interactive Data Terminal, \$307\*.

58-key flexible membrane keyboard with finger positioning overlay includes two definable user keys. Full RS232C interface for direct modem and computer connection. Six switch-selectable baud rates from 110 to 19.2 kilobaud. Full color graphics and reverse video.

40 character × 20 lines or 20 × 12 display formats. Video output for 525-line color or standard mono-

chrome monitor. Size: 13.1" × 7" × 2". Weight: approx. 5 lbs.

To order, call toll-free 800-722-0094. (In PA, 717-295-6922.) For more information, call 800-233-0187. Or write: RCA Data Communications Products, New Holland Avenue, Lancaster, PA 17604-3140.

\*OEM quantity price, minimum 25 units.



Data Communications Products

VP3301 IDT, \$307\*

APT with optional display monitor.

#### **ISDN** controller chips


voice and data links can be made and run simultaneously.

Whenever a data link is made, from either the subscriber or the PBX line card, the data flows from the local terminal via the RS-232 link through the subscriber controller into the RAM on the microprocessor bus. The data is stored in the RAM and retransmitted on the microprocessor bus through the other serial port on the communications controller. Then it enters the subscriber controller's serial port and passes through the S interface on the designated B channel.

For data coming from the S interface, the

data is transmitted through subscriber controller's serial port into the communications controller, then into the RAM via the microprocessor bus. When the data is collected in the RAM, it is retransmitted over the microprocessor bus through the other communications controller serial port, then onto the RS-232 link, and finally to the local terminal.

When the SCC is in the HDLC (High-level Data Link Control) mode, packet data can be transmitted to and received from the local terminal over the S interface via the B channels. Use of the RAM for temporary storage of data coming from and going to the local terminal al-



6. The exchange controller chip is ideal for establishing a PBX, as shown on a section of the line card (only one S interface). The microprocessor would be common to all exchange controllers. The quad exchange power controller can provide power for up to four S interfaces.

## NEW PRODUCT NEWS FROM TELETEK

Systemaster II. Responding to market demand for speed and increased versatility, Teletek is proud to announce the availability of the next generation in 8-bit technology — the new Systemaster II! The Systemaster II will offer two CPU options, either a Z80B running at 6 MHz or a Z80H running at 8 MHz, 128K of parity checked RAM, two RS232 serial ports with on-board drivers (no paddle boards required), two parallel ports, or optional SCSI or IEEE-488 port. The WD floppy disk controller will simultaneously handle 8" and 51/4" drives. A Zilog Z-80 DMA controller will provide instant communications over the bus

between master and slave. Add to the DMA capability a true dedicated interrupt controller for both onboard and bus functions, and the result is unprecedented performance.

Systemaster II will run under CP/M 3.0 or TurboDOS 1.3, and fully utilize the bank switching features of these operating systems.

TELETEK

4600 Pell Drive Sacramento, CA 95838 (916) 920-4600 Telex #4991834 Answer back — Teletek

CIRCLE 77

SBC 86/87. As the name indicates, Teletek's new 16-bit slave board has an Intel 8086 CPU with an 8087 math co-processor option. This new board will provide either 128K or 512K of parity checked RAM. Two serial ports are provided with individually programmable baud rates. One Centronics-compatible parallel port is provided. When teamed up with Systemaster II under TurboDOS 1.3, this 5MHz or 8MHz multiuser, multi-processing, combination cannot be beat in speed or feature flexibility!

Teletek Z-150 MB. Teletek is the first to offer a RAM expansion board designed specifically for the Z-150/Z-160 from Zenith. The Teletek Z-150 MB is expandable from 64K to 384K. Bring your Z-150 up to its full potential by adding 320K of parity checked RAM (or your IBM PC, Columbia, Compaq, Corona, Eagle, or Seequa to their full potential). The Teletek Z-150 MB optionally provides a game port for use when your portable goes home or a clock/ calendar with battery backup! Evaluate the Systemaster II, SBC

86/87 or Teletek Z-150 MB for 30 days under Teletek's Evaluation Program. A money-back guarantee is provided if not completely satisfied! All Teletek products carry a 3-year warranty.

(Specifications subject to change without

notice.)

In Europe:
Kode Limited
Station Road
Calne, Wiltshire
SN11 OJR England
tel: 0249-813771
telex: 449335
In Canada:

TELETEK TIMES BIRM

AND Z-150 MB

MAE Microsystems 8255 Mountain Sights, Ste. 150 Montreal, Quebec

H4P1W1 Canada tel: 514-341-1210

I'm interested in information regarding:

- Systemaster II
- ☐ SBC 86/87 ☐ Z-150 M
  ☐ Evaluation Program
- ☐ Teletek's S-100 Board Line

Name \_\_\_\_\_\_ Company \_\_\_\_\_ Address \_\_\_\_



# Even if your components are out of this world KSM has a speedy way to fasten them down

Even when you *know* you've got the right components for tomorrow's automated products, you also know it doesn't mean a thing if you can't put it all together in a cost-effective way.

There's where KSM stud-welding systems can help. We can give you the specialized fasteners and tools to secure all components with speed and dependability.

Pins, studs, precision welding systems — it's all here, ready to zero in on your particular fastening requirements.

In addition, our engineers will work with your engineers in solving any fastening problem.

For more complete information or literature, phone or write . . .



KSM Fastening Systems, Inc.

301 New Albany Road Moorestown, NJ 08057 1-800-257-8181 • In NJ 609-235-6900

#### **DESIGN ENTRY**

#### **ISDN** controller chips

lows these operations to occur at different rates. With this capability, data can be transmitted through the system at a fixed 64 kbits/s, required for the B channel, regardless of the rate at which it was originally received.

#### **Extending the highway**

Another example shows a portion of a typical PBX line card architecture and the connections and ICs associated with one S interface (Fig. 6). The microprocessor is common to all the exchange controller chips on the line card, and the quad exchange power controller provides the power for up to four S interfaces. The decoder provides the necessary chip select signals.


There are several possible routes for the B and D channels through the exchange controller chip. The B channels from the S interface, for example, can be routed directly to the microprocessor on the line card or over the dual PCM highway via the exchange controller.

Such a line card configuration is very flexible. When a packet on the D channel is received from the terminal equipment, the exchange controller can pass the packet off the line card directly over the dual PCM highway. Alternatively, it can pass the packet, via its on-chip data link controller, to the microprocessor for processing on the line card.

Conversely, when a packet is transmitted over the S interface to the terminal equipment, it can pass directly to the exchange controller from the PCM highway or from the microprocessor on the line card. In the latter case, the packet is passed through the on-chip data link controller before being transmitted.

The microprocessor can communicate with the host computer controlling all the line cards in the PBX by transmitting and receiving data over the PCM highway (via an exchange controller). As an option, a serial communications controller can be interfaced to the microprocessor bus, so that communication can take place between the line card and the host computer over the controller's HDLC link.□

How useful?	Circle
Immediate design application	544
Within the next year	545
Not applicable	546



The Pascal-2 system is available on Digital's VAX, MicroVAX; PDP-11/RSX, RSTS, RT-11, UNIX, TSX-Plus; and Professional Computer running P/OS, RT-11.

## We put a lot of ourselves into Pascal-2. Pascal-2 is the only language compiler that provides a uniform development environment across the full line of Digital system.

Everything we know about software development is built into Pascal-2. We created a straight-forward, robust compiler with rugged predictability that has already become a legend. Pascal-2 has proven its performance and its reliability in more than 2,000 installations in 36 countries.

Pascal-2 on VAX Now Pascal-2 can give you that same performance on the Digital Equipment Corporation's VAX, the premier software development computer system.

Pascal-2 provides the strength and flexibility essential for real utility in scientific, engineering, business, and industrial applications.

Using the advanced capabilities of this optimizing compiler, your development cycle will be shorter and your applications more efficient.

#### See us at DEXPO West Booth 2836

Digital, PDP, VAX, VMS, RSTS, RT-11, RSX, Professional 350 and PlOS are trademarks of Digital Equipment Corporation. UNIX is a trademark of AT&T Bell Laboratories. TSX-Plus is a trademark of S&H Computing, Inc. Pascal-2 is a trademark of Oregon Software.

Pascal-2 is the only language compiler that provides a uniform development environment across the full line of Digital systems from the Professional 350 to the VAX. All versions of the compiler provide identical language features, with the same interface for the operating system and hardware, and the same set of language extensions.

As a result, your application can be moved easily from one environment to another.

The Pascal-2 System Development Package for the Digital VAX and MicroVAX includes an optimizing Pascal compiler; an interactive, sourcelevel Debugger; a Profiler that pinpoints execution bottlenecks; and other utilities to aid program development.

If you would like to put Pascal-2 to work on your VAX, call us at 1-800-874-8501.

Software

6915 S.W. Macadam Avenue Portland, Oregon 97219

CIRCLE 79



## There's always a way out with The High Density Plus Backplane System.

Introducing High Density
Plus One; the latest in the High
Density Plus Backplane System

family.

We developed High Density Plus™ because the world of VLSI can be a frozen wasteland for the ill-equipped design engineer.

If you're using ECL, Schottky TTL, CMOS, gate or standard cell arrays, High Density Plus will help you meet interconnection needs better than any available product.

And High Density Plus One goes one step further.

#### Five Rows in the Space of Four

High Density Plus One features five rows of contacts in a four-row space. The special fifth row of contacts can be used as

a low inductance ground. Or for power distribution. Or in combination, allowing the designer to use virtually all the contacts within the standard four rows for signal transmission.

It's just

the ticket for CMOS-based VLSI designs requiring high-speed signal integrity and increased interconnection density. The low-inductance fifth row of contacts minimizes ground noise and is positioned to provide maximum EMI shielding.

#### A Complete System

The High
Density Plus
family is designed to be
integrated with
Teradyne's multilayer printed circuit technology,
power busing
systems, and
STRONGHOLD®
cardcage.


Completely modular, the system is based on a

building block approach that lets you customize designs to best meet your needs, whether you need five, four, or three rows of contacts.

Our engineers stand ready and able to help tailor-make your system. If you need the whole system completely assembled and tested, or just individual components, we have what it takes to get you out of any jam.

#### The Leader in Interconnection

Come to Teradyne. The leader in meeting the backplane-based interconnection requirements of high-speed, high-density LSI and VLSI.



Don't delay. We created High Density Plus to get cornered designers out of tight spots. Call Brenda Blaine, (603) 889-5156, ext. 372, for our product brochure. Or write Teradyne Connection Systems, 44 Simon Street, Nashua, NH 03060.



Connecting problem . . . and solution

CIRCLE 80

output /1	ELECTRONIC MEASUREMENTS TOS 40205	1	TRIPLE OU	TPUT POWER SI						
output /2	10S 40205	TOS 20205	- 00	TPUT POWER S	linn.					
output 13	3-7 @ 3A	3.7	LPT 7202FMVI		OPPLY COMPAR	ISON -				
max output power	0-20v @ 0-2.5A	3-7v @ 3A	0-7v @ 3.2A	MPS 620M	HEWIET	CHAR	T			
outputs isolated	0-40v @ 0-1.25A	0-20v @ 0-2.5A		0-6v @ 5A	HEWLETT PACKARD 6236B	HEIAH -				
serial operation	118W	0-20v @ 0-2.5A	0-20v @ 0-1A	0-20v @ 0-1A	0-7v (ii 3A	6237B	DYNASCA	7		
parallel	all	118W	0-20v @ 0-14	0-20v @ 0-1A	0.20v @ 0.5A	0-21v (1 1 20	1650	SORENSEN SLT 52 Series		_
parallel operation	ves	all		€€ 0-1A	0.5A	0.5A	SV ( 5A	SET 52 series	SORENSEN SLT 02 Series	SYSTRO
Output mode 1	all outputs	Ves				2 0.5A	0.25V (1 0.5A	0-5 @ 0-5A		SYSTRO DONNE TL 8-
Output mode 2 & 3	CV CF	all				W	0-25V @ 0.5A	12 & 15v @ .5A	12 & 15v @ 1A	0-8 @ 3
a ogramming 12-	CV CC		-			ım zero	50W	- 12 or - 5 or - 15v at .05A	- 12 or - 5 or - 15 @ 1A	+32 @
lage set 1			A STATE OF THE PARTY OF THE PAR			- Zero	all	40W	ROM 1A	
Voltage set 2 & 3						d	ves	a s comm zero	2 & 3 comm zero	98W
current set 1	O Sire						ves	no	no zero	2 & 3 comm
current set 2 & 3	<b>WIE</b> AS	TRONIC JUREMENTS INC.	Voltage land				CVCF		no	no
panel meter 1	ir i		0-40 V				CVCL	CVCL	CVCL	no
panel meter 2 %	10 20	30	4			pot	no	CVCL	CVCL	CVCL
simulth read voice	89.50.75	Mary 1	AND THE REAL PROPERTY.				fixed	no	no	CVCL
simulth read Am		1.005 A POR	A DESTRUCTION OF THE PARTY OF T			300	sing, turn pot	sing, turn pot	sing, turn pot	no
aguiation load a		Section S	Current					sing, turn pot	sing, turn pot	1 turn coar & fine
regulation load a	1	ing CC	1			.3	fixed	fixed	fixed	& fine
regulation load z	0		2.16			3	select 1,2,3	no	fixed	fixed
ripple (p-p) 1	DS Medicando						select 1,2,3	по	no	ves
ripple (p-p) 2	Enter Stone Sharete	The state of the s	Voltage				no	no	no	Ves
ipple (p-p) 3		CV	Voltage 0 20 V				<150mv	.03 + 5v	no	Yes
olation in/out 2500 val		755				THE WORLD	.1%	196	.03 + 5v	.02% or s
9. @ output 500 v		20 7					50 mv	1% 50 my	196	.02% or
(nom) 47-400	42	01					50 my	50 my	50 mv	3 m
h area sq. ft. 7" x 11" x	1	O C	2.5 A				not specia	1800 vec/min	1500 V8C/min	ne son
1 pci 5 yrs.		CC.	The same			12.5" × 8"	50-60 Hz 4" x 10" x 14"	800 VBC 47-440 Hz	800 vdc	94
	2				TO BE SHOWN TO	Vr.	1 97	1.9" # 5.0" # 6.7"	3.9" × 8.1" × 8	a.   a. m
					3040	DESCRIB	\$ 500 prox	9 974	SAGO	-

### COMPARE THE FACTS

### AND THE CHOICE OF SELECTING TRIPLE OUTPUT POWER SUPPLIES GETS EASY

#### FOR INSTANCE —

- 20% to 65% more output power than any comparable unit
- Excellent ripple and regulation
- Works in series and parallel modes for higher current and voltage outputs
- Any output may be grounded providing for either polarity
- Convenient metering & multi-turn pots
- 2 models: 3-7v @ 3A, 0-20v @ 2.5A & 0-40v @ 1.25A or 3-7v @ 3A, 0-20v @ 2.5A & 0-20v @ 2.5A
- All of this, and more, in less than 0.4 sq. ft. for \$575.00

Choosing the best triple output lab supply isn't as easy as it looks ... so here's a little help from Electronic Measurements. We'll send you a Free COMPARISON CHART so you can prove to yourself why the EM Series not only outperforms all the rest, but offers the lowest dollar per watt in the industry.

For your Free Comparison Chart – CALL TOLL FREE (800) 631-4298\* or contact:



405 Essex Road, Neptune, New Jersey 07753
\* In New Jersey, Alaska, Hawaii and Canada, call (201) 922-9300

#### **D**ESIGN ENTRY

## Built-in Basic interpreter turns controller chip into versatile system core

An extended set of Basic statements and operators transforms a chip into the foundation for a wide range of embedded real-time systems.

ingle-chip computers have been popular for some time now, especially in embedded applications. But the phrase "computer on a chip" takes on a whole new meaning with the appearance of a software package that implements a version of Basic in silicon.

The 8052AH-Basic controller is aimed primarily at data acquisition, test instrumentation, and process control. Further, it is right at home in virtually any embedded environment

and monitoring system.

Unlike so-called Tiny Basic interpreters, the chip's MCS Basic-52 software package is a full Basic interpreter. In addition, it can manipulate strings and handle logical operators (AND, OR, exclusive-OR, and NOT) and floating-point arithmetic. It is also able to accept and deliver numbers in floating-point, integer, or hexadecimal formats. Counted among its other features are built-in EPROM programming, mnemonic access to all on-chip I/O resources, and a builtin real-time clock with a resolution to within 5 ms. Moreover, its complete function library of routines can be accessed in assembly language (see the table, opposite). And the package supplements Basic's standard instructions with commands designed specifically for embedded systems. The package resides in the 8-kbit ROM of the 8052AH-Basic chip. Apart from the software, it is identical with the 8052AH and so features 256 bytes of RAM and three multiplemode 16-bit timer-counters.

Although Basic is held in low regard by many computer scientists, one fact cannot be denied: It is by far the most popular microcomputer language. Not only is virtually every personal or home computer capable of running it, but the language has become a de facto standard for many applications, including laboratory and

#### John Katausky, Intel Corp.

John Katausky is technical marketing manager for Intel Corp.'s microcontroller operation in Chandler, Ariz.

#### Summary of Basic-52's features

Commands	Statemen	nts	Operators		
RUN LIST NEW NULL RAM ROM XFER PROG1 PROG2 FPROG1 FPROG1 FPROG2	BAUD CALL CLEARS CLEARS CLEAR1 CLOCK0 CLOCK1 DATA READ RESTORE DIM DO-WHILE DO-WHILE DO-UNTIL END FOR-TO-STEP NEXT GOSUB RETURN GOTO ON-GOSUB IF-THEN-ELSE	ONEXT1 ONTIME PRINT PRINT PHO.# PH1.# PUSH POP PWM REM RETI STOP	ADD (+) DIVIDE (/) EXPONENTIATION (**) MULTIPLY (*) SUBTRACT (-) LOGICAL AND (.AND.) LOGICAL OR (.OR.) LOGICAL NOT ABS () INT () SGN () SQR () RND LOG () EXP () SIN () COS () TAN () ATN () = ,>,> =, <,<=,<>PI	CBY () DBY () XBY () GET IE IP PORT1 PCON RCAP2 T2CON TCON	

Boldface statements have been added specifically for embedded systems.

#### **Basic controller**

office automation. Its popularity is easily explained by its simplicity and ease of use. A programmer can execute, edit, and debug short programs in minutes, without having to worry about compilation, linking, and locating.

#### **Building up Basic**

Like any language, Basic has its drawbacks, but the 8052AH-Basic's software package addresses many of them by beefing up its instruction set. These enhancements address three general areas: First, sophisticated programmers dislike the fact that Basic is an unstructured language. Because GO TO statements can be placed anywhere in a program, understanding and debugging it can become quite a chore. For that reason, the package contains the more structured DO-WHILE and DO-UNTIL statements, as well as the standard FOR-NEXT and IF-THEN-ELSE. These extensions furnish better ways to control the flow of a program.


Second, the fact that Basic uses global variables forces subroutines to use the same names for variables as the main program employs. Generally, this is an inconvenience because

variables may need to be redefined every time a subroutine is called up. The package's function library, however, includes PUSH and POP statements that allow the user to pass variables to subroutines on a stack, making it easy to redefine variables in a subroutine. Additionally, PUSH and POP can be used to pass parameters to and from user-supplied assembly language routines.

Finally, interpreted Basic is usually a slow language. Although this is a legitimate complaint, many applications can still be adequately served by it. The package's fast token-based interpreter, though, puts an end to the problem, turning in execution speeds that compare quite favorably with those of popular 8- and 16-bit personal computers.

#### A quick turn around the pins

As mentioned, the software is stored in an 8052AH controller chip, which is itself housed in a standard 40-pin DIP (Fig. 1). Some of the pins' uses are predetermined. Of the four ports on the standard 8052AH, only port 1 still serves as an I/O port on the Basic version. Since the



1. The pin assignments of the 8052AH (a) and the 8052AH-Basic controller (b) differ primarily in that the second does not use lines  $AD_0$  to  $AD_7$  and  $A_8$  to  $A_{15}$  as ports 0 and 2, respectively. Further, the Basic version needs  $\pm 5$  V on pin 31 to enable the 8052AH to execute from internal ROM.

8052 AH-Basic requires external memory, Pins 32 through 39 and 21 through 28, which formerly served ports 0 and 2 respectively, are now used for their alternative function: addressing and exchanging data with RAM and ROM. Pins 10 through 17, which formed port 3, are putting in their time at their assorted alternative duties—with some slight revisions. The only other changes involve pin 31,  $\overline{\rm EA}$ , which is now tied to  $V_{\rm CC}$ , and port 1, whose pins have acquired a second set of functions.

#### Port 1 in detail

To start with, pins 1 and 2 of port 1 (P1.0 and P1.1) can also be used to clock and trigger timer-counter 2. Pins 3, 4, and 5 generate all timing and other signals necessary to program just about any EPROM or EEPROM—a simple way to save and retrieve programs without uploading or downloading. Pin 6, together with the INT<sub>0</sub> pin (pin 12), gives the user the option of implementing direct memory access. Finally, pin 7 takes care of direct serial output to a peripheral, such as a printer. All that needs to be done in this case is to invoke the LIST# com-

mand or the PRINT# statement.

In addition, the syntax of Basic-52 permits the user to read and write directly from and to port 1. For instance, the statement:

#### PORT1 = 55H

would place the hexadecimal value 55 on the appropriate pins, while:


#### A = PORT1

would assign the value of variable A to the port 1 pins. Furthermore, some of the language's commands and statements manipulate those pins so that they furnish a number of useful and unique features. For example, P1.2 can also serve as an output for the pulse-width modulate (PWM) statement. Executing it generates a pulse train of varying duration, frequency, and duty cycle on the pin.

The statement:

#### PWM 50, 100, 1000

creates 1000 cycles of a signal that, assuming a 12-MHz clock, is high for 50  $\mu$ s and low for 100  $\mu$ s. The PWM statement also can generate audi-



2. A simple system based on the 8052AH-Basic microprocessor requires just three additional chips plus the serial-port driver. Port 1 could be used, for example, to sense switches, drive indicators, or a power printer.

#### **Basic controller**

ble feedback in process control and security systems.

To pin 9 (Reset) falls the job of initializing the system. It also furnishes power on reset when an external 8.2-k $\Omega$  resistor is connected from this pin to ground and a 10-µF capacitor is connected to V<sub>CC</sub>.

Under the software package, all of the pins that formed port 3 are pressed into service in their alternative functions. One of the interrupt pins, INT<sub>0</sub>, now also handles DMA requests (pin 12), and the pins for transmitting and receiving data (pins 11 and 12) now handle serial inputs and outputs to the console. Their activities are integrated into a Basic application program. For example, an interrupt on the  $INT_1$  pin (pin 13) can be handled by the ONEXT1 statement:

#### 10 ONEXT 1 1000

which forces a GOSUB to line 1000 every time the INT<sub>1</sub> pin is pulled to a logical 0. In the called subroutine, the user can process the interrupt, then use a RETI statement to exit from the interrupt handler.

To turn the Basic chip into a complete system, the user need supply only external RAM and serial port drivers (Fig. 2). The RAM requirements are few: At least 1 kbyte must be present, and it must start at external memory location 0 and be contiguous and completely decoded. After reset, the package determines how much memory is present in the system and initializes it, then waits for the user to type in a space character. That character establishes the baud rate automatically.

Although this system is quite useful, it does not represent an ideal embedded controller. Fortunately, adding just a little more hardware is all that is needed to construct one complete with automatic self-starting, EPROM and EEPROM programming, and simple programfile management (see "EPROM Saves the Program," opposite).

Once the desired type of EPROM is in place, starting up the system involves no more than entering either the PROG2 or FPROG2 command. Both commands preserve the baud rate information in exactly the same way as PROG1 or FPROG1 does. In addition, though, either causes the first program stored in PROM to ex-

#### **EPROM** saves the program

EPROM and EEPROM programming is certainly one of the most powerful features of the MCS Basic-52 software package. And it is simple to use; only three of the 8052AH-Basic microprocessor's control pins are needed to call it into play. In brief, after the user enters a program, it is stored in RAM, starting at location 512. When the user types PROG PROG or FPROG, the program that is stored in RAM is programmed into an EPROM or EEPROM whose address is 8000<sub>16</sub>.

To start the process, the CPU first writes a logical 0 to the Program Enable pin, P1.5, thus supplying the higher voltage required to program the EPROM. Next, the processor reads the appropriate RAM location, starting at 512, and saves the byte of information.

Then, the CPU sends out the appropriate loworder PROM address to pins ADo to AD7 and sets the ALE Disable pin to 0. That latches the loworder PROM address permanently into the system address latch-74LS373 (see the figure). Only one AND gate is required to do this. The processor then writes the high-order PROM address to pins A<sub>8</sub> through A<sub>15</sub> and the data to pins AD<sub>0</sub> to AD<sub>7</sub>. Finally, a 0 is written to the Program Pulse pin. Depending on the PROM used, that pin is held low for either 1 or 50 ms. After it returns to a logical 1, the CPU verifies the contents of the programmed PROM and then writes a 1 to ALE Disable.

The process continues until the entire Basic program is saved in PROM. When programming is complete, the CPU writes a 1 to the Progam Enable pin, leaves the programming routine, and returns to the Basic command mode. To prevent accidental programming during power-up, OR gates should be used (top left in figure).

The foregoing description of the programming naturally leads to two questions.

The first concerns the duration of the 0 state. A 50-ms pulse is required to program most standard EPROMs. The 1-ms pulse, on the other hand, permits the software package to program Intel's latest generation of high-density EPROMs, working with the company's programming algorithm, dubbed INTELigent. To apply it, the user simply types FPROG instead of PROG. The algorithm requires that the V<sub>CC</sub> on the EPROM be increased to 6 V. One economical way to accomplish this is with a DIP relay. The software package also allows the user to specify programming pulses of any length.

The other question centers on the accuracy of the programming pulse versus that of the system clock frequency. To eliminate any dependency on the system clock the package actually calculates all critical timing parameters from a user-supplied variable XTAL After a reset, the package assumes a system clock frequency of 11.059200 MHz unless told otherwise. If the user enters the statement:

#### YTAI = 12000000


a 12-MHz system clock is assumed and the proper PROM programming time calculated. The real-time clock pulses and the band rate for the line printer output port are also determined. This ability gives the designer the freedom to choose the desired system clock frequency without having to worry about the internal timing of the Basic software.

Another useful aspect of the software's PROM programming capabilities is that it stores up to 255 programs in an EPROM. PROM size, of course, limits the possible number of programs. Every time PROG (or EPROG) is typed, the software responds

with the file number that has been assigned to that program. To call up a given program, the user simply types ROM X, and the package finds the appropriate one. Typing RUN starts program execution.

Suppose the user discovers an error in a program that is stored in EPROM—normally bad news because such programs cannot be edited. However, the package allows a program to be transferred from EPROM to RAM by typing XFER. Once XFER is entered, the program may be edited like any other. Typing PROG again saves the edited program.

Additionally, after reset, the software package waits for a space character, from which the baud rate is derived, to be entered on the serial port. As an option, the package can be made, on receiving the command PROG1 or FPROG1, to save the serial-port baud rate information in PROM. The next time the processor is reset, the package can sign on directly without the need to enter a space character.



## **DESIGN ENTRY**

#### **Basic controller**

ecute directly after reset, bypassing a RUN command. In fact, even the console is no longer needed in some embedded systems. Programs can be written and debugged with the aid of a terminal, and when the programmer is satisfied with the results, the hardware can be embedded in the design and the terminal disconnected.

#### On call

Aside from the features already noted, the package contains a host of others that are very attractive for embedded systems. The CALL statement, for instance, accesses assemblylanguage routines directly from the package, a handy way in which to meet speed requirements. Better still, assembly-language programs can take advantage of a complete library of routines that reside in the package. The user gains access to this library simply by placing a specific op code in the accumulator and then sending a CALL to location 30<sub>16</sub>.

Suppose, for example, that the assemblylanguage routine reads a 16-bit value, and the user would like to calculate the value's square root and send it to a particular location. Assuming that the user supplies the 16-bit integer to the high- and low-byte registers,  $R_2$  and  $R_0$ , respectively, the calculation can be made simply (Program 1). All told, over 60 routines can be invoked by assembly-language programs.

The software package also controls all of the system's I/O memory resources. To make things simple, all of these operations are symmetrical. For example, the operator DBY in the statement:

## A = DBY (0FEH)

assigns the value located at OFE<sub>16</sub> in the chip's internal memory to variable A. The statement:

$$DBY (0FEH) = 22H$$

places  $22_{16}$  in internal memory location OFE<sub>16</sub>. The same symmetry holds for the interrupt registers, IE and IP, as well as the timers and the timer configuration registers.


Other special instructions are particularly

### Program 1. Getting to the root of a variable

MOV A, #9AH; Load accumulator with op code for placing Register pair R2:RO onto argument stack CALL 30H

Execute the operation MOV A, #1FH CALL 30H MOV A, #1H CALL 30H Specify square-root routine Execute the operation

Specify truncation and integer conversion Execute the operation



3. With the help of an address decoder, the I/O on a system built around the Basic chip can be expanded at will. One such setup converts analog into digital and digital into analog signals, and supplies a parallel I/O port for a console.

# Welcome to the New Valley

You're looking at lowa — home of the Electronic Technology Corporation.

We design test and deliver semicustom integrated circuits Very seel. The ald Silicon Valley really spirkered when we took their heet design. re design, test, and deliver semicustom integrated circuits. very well.

The **old** Silicon Valley really snickered when we took their best design

The **old** Silicon Valley really snickered when we took their best design

The **old** Silicon Valley really snickered when we took their best design The **old** Silicon valley really snickered when we took their best design technology — plus software for gate arrays, linear arrays, standard cell and full custom — and but it out here in Cedar Ranids

Custom — and put it out nere in Legar kapids.


Maybe they didn't want to admit that when 1600 electronics staffs take they didn't want to admit that when 1600 electronics staffs take.

The in the old Silicon Valley commercial secrets det spilled. rechnology — plus surrware for yare analys, micel full custom — and put it out here in Cedar Rapids.

wayoe they gidn t want to admit that when row election valley, commercial secrets get spilled. Tall Corn. Low Overhead. The old Silicon Valley probably didn't realize that our Midwestern operating costs are about half theirs. (They'll find out when we give our competing hids So will you!) Or that those lower costs that our Midwestern operating costs are about that theirs. [They it find out when we give out competing bids. So will you.] Or that those lower costs when we give out competing bids. So will you.] Or that those lower costs when we give out competing this worthwhile to someone with less the many we can make a semiclistom this worthwhile to someone with less the when we give out competing bids. So will you.) Or that those lower costs when we give out competing bids. So will you.) Or that those lower costs than mean we can make a semicustom chip worthwhile to someone with less than mean we can make a semicustom the old Silicon Valley.)

10 ICs in their design. (Not 25, like in the ones who need semicustom microchins in But you know. And you're the ones who need semicustom. JICS IN THEIR design. [INOT 25, like in the old Silicon Valley.]
But you know. And you're the ones who need semicustom microchips in the form to stay ahead

order to stay ahead.



Then we don't just take your schematic and turn it into chips. We study it. If necescosts. No surprises. sary, we'll recommend ways to improve your circuits' performance in the semicustom environment. **Before** the layout stage.

It's just the way business is done in lowa.

Talk to an engineer. You can talk directly to ETC engineering by dialing our Engineering Hot-Line, 319/395-0747. A design engineer will be ready to talk with you. About semicustom technology, about applications, or about your project if you'd like. No obligation, just straight talk. Go ahead. And get up to date on the New



2037 N. Towne Lane NE Cedar Rapids, Iowa 52402 Phone 319/395-0567

Engineering Hot-Line 319/395-0747 Rush more information about ETC. ☐ Have a representative contact me.


My business card is attached

Your Midwest Source for Microcircuits. And Straight Talk.



#### **Basic controller**

helpful for the designer. Thus BAUD sets the baud rate for the line printer port. If the designer wants to transmit at 1200 bauds, he or she simply enters BAUD 1200. CLEARS is used to reset all of the package's stacks, and CLEARLI resets all interrupts, except the real-time clock. CLOCK1 enables the real-time clock, just as CLOCKO disables it. The value of the clock can be read or assigned by using the TIME operator. ONTIME generates an interrupt when the TIME operator reaches or exceeds a specific value. ONTIME works in much the same way as the aforementioned ONEXT1 statement. Finally, the statements PHO and PH1, when used to-



4. To function as an autopulse dialer, the Basic chip needs only a single-pole, single-throw, normally closed relay and an npn transistor to drive it.

Prog	ram 2. Placing a call with the software package
10	REM MCS BASIC-52 AUTO TELEPHONE DIALER
20	STRING 200,20 : REM ALLOCATE MEMORY FOR STRINGS
30	REM NAMES ARE STORED AS FOLLOWS -
40	REM NO. OF DIGITS IN NAME - NAME -
	PHONE NUMBER
50	REM THE "E" REPRESENTS THE END OF FILE
60	\$(1)="3JOE1234567E"
40	\$(2)="4BILL2345678E"
50	\$(3)="3ANN3456789E"
60	INPUT "WHO WOULD YOU LIKE TO DIAL - ",\$(4)
70	FOR I=1 TO 3: REM LOOP TO FIND MATCH
80	REM READ THE NUMBER OF DIGITS AND STRIP
	OF ASCII BIAS
90	FOR J=1 TO (ASC(\$(I),1) .AND. OFH)
100	IF $ASC(\$(4),J) = ASC(\$(I),J+1)$ THEN NEXT J ELSE NEXT I
110	CLEARS : REM CLEAR THE STACK TO ELIMINATE
400	THE I INDEX
120	REM I COUNTS THE NAME, J THE PHONE NUMBER
130	CLOCK1: REM TURN ON THE REAL TIME CLOCK
140	DO : REM NOW LOOP TO DIAL
150	C = (ASC(\$(I),J) .AND. OFH)  IF C = O THEN C = 10
160 170	FOR Y = 1 TO C : T = TIME
180	PORT1 = PORT1 .AND. OFEH : REM OPEN THE LINE
190	IF TIME < T + .04 THEN 190: REM LOOP FOR 40 MS
200	PORT1 = PORT1 .OR. 1 : REM CLOSE THE LINE
210	IF TIME < T + .1 THEN 210 : REM LOOP FOR 60 MS
220	NEXT Y
230	J=J+1: WHILE ASC(\$(I),J)<>ASC(E)
240	END
240	ENU

gether, ensure that outputs are given in hexadecimal notation. PHO suppresses leading zeros, and PH1 always prints out four hexadecimal digits.

Building a functioning system around the Basic chip is a snap. The designer can link to virtually any standard peripheral chip simply by assigning some location to the peripheral in the 64 kbytes of external address available to the 8-bit device.

## Addressing I/O

In fact, the software actually reserves the chip's upper 8 kbytes of memory (from 56 to 64 kbytes) for I/O. Accessing external peripherals is accomplished by using the XBY, or address, operator. For example:

#### A=XBY (0FFF0H)

reads a peripheral or external memory location that has been decoded for address OFFFO16 and assigns its value to the variable A. Similarly:

$$XBY(0FFF0H) = 55H$$

writes 55<sub>16</sub> to a peripheral or memory location that has been decoded for address OFFFO<sub>16</sub>. A system consisting of an analog-to-digital and a digital-to-analog converter plus an 8255 parallel port, all connected to the software package. is typical of process control, environmental monitoring, or energy management applications (Fig. 3).

An autopulse telephone dialer also demonstrates the versatility of the software package (Fig. 4). This application takes advantage of the logical operators as well as the real-time clock and string operations (Program 2). Such dialing could play an important role in many process control and remote environmental-monitoring systems where information must be periodically sent to a master computer over a phone link. Variations on the general software scheme could be devised to address a wide variety of automatic dialing and automatic answering settings.□

How useful?	Circle
Immediate design application	547
Within the next year	548
Not applicable	549

## WREN\_SUPER-PERFORMING 51/4" WINCHESTERS IN 21 TO 86 MEGABYTE CAPACITIES.



THE WREN"

High Technology from Control Data delivers a 5-1/4" Winchester with truly outstanding performance and reliability. Compare for yourself. Call our Information Hotline 1-800-828-8001 or write OEM Product Marketing, HQN08H, Control Data Corporation, P.O. Box 0, Minneapolis, MN 55440. Also available through your Arrow or Kierulff distributor.

**GD** CONTROL DATA

The HP 1630G Logic Analyzer for today's 16-bit designs.

## Hardware and software solutions design and test cycle.

With up to 65 channels of state analysis, the HP 1630G is the new standard for system design engineers working on complex new 16-bit microprocessor-based products. Plus, you can configure 8 of those lines for 100 MHz timing analysis to get a logic analyzer with investigative power and versatility for virtually all your needs.

## Three new software overview modes let you nonintrusively monitor software and hardware performance and interact in real time.

The HP 1630G significantly expands on the hardware and software performance capabilities already introduced in the HP 1630A/D family members. In addition to time histograms that show execution-time distribution, and

label histograms that show address activity, the HP 1630G gives you three new modes: program flow, time positional, and linkage measurements. Program flow measurement lets you monitor program activity based strictly on opcode accesses. Time positional measurement lets you measure the number of occurrences of an event per unit time. Linkage measurement measures the relative frequency of the activity between specific modules.

## Time tagging gives you added insights into system functions.

In the state analysis mode, time tagging measures the time elapsed between each stored state. Make detailed absolute time measurements between states and known physical events. Or, use it to measure the total time from the trigger point to a particular state. Because time tagging is a single-pass activity, it is well-suited to helping you identify inline sections of code that take longer to execute than anticipated.





HP-IB: Not just IEEE-488, but the hardware, documentation and support that delivers the shortest path to a measurement system.

HP 1630A

## throughout your 16-bit

## Floppy disc interface and popular 16-bit microprocessor support.

On-board non-volatile memory keeps one instrument setup and your current disassembler instantly available at power-up. For even greater storage, the HP 1630G features direct compatibility with a number of HP disc drives such as the HP 9121S/D (the HP 9121D is illustrated). In one convenient 3½" floppy you can now store data, state listings, timing diagrams, alternate disassemblers, and instrument setup configurations. For added flexibility, the HP 1630G supports all popular 8-bit, as well as the following 16-bit microprocessors: 68008, 68000/68010, 8086, 8088, 80186/80188, 80286/80288, Z8001 and Z8002.

## Our HP 1630G upgrade kit protects your previous HP investment.

If you've already invested in an HP 1630A or HP 1630D, but you feel you need the added capabilities of the HP 1630G, an upgrade kit is available.

Compare the HP 1630G. At \$12,100\* it's even HP-IB programmable for fully automated measurements. To find out more about the HP 1630G or its companions, the HP 1630A/D, call your local HP sales office listed in the telephone directory white pages. Ask for the electronic instruments department.

CIRCLE 82

\*U.S.A. list price only.





## **100 WATT SWITCHER** 100 KHz

**Advanced Design Cost Cutter** 

## Model RH101...the newest, the smallest, the best, for the least.

ACDC's new ADCC is probably the smallest 100 watt op frame switcher having MOSFET 100KHz technology. Check these additional features, then check with us. When you compare the features with the price, you'll understand why we call it the "Advanced Design Cost Cutter."

• Designed to meet IEC380/VDE0806

• Two mounting surfaces

• Field selectable 115/230VAC

• Fully protected OVP, overload and short circuit over temperature and

- short circuit, over temperature and

- reverse voltage
   Crowbar standard
- · Computer tested with data sheet on
- Wireless construction
- Reduction in heat, weight, size and omponent count through MOSFET
- ology r, AC cycled, high temp burn-in
- off-the-shelf" through ACDC distributors

Write for our catalog.

## **D**ESIGN ENTRY

## Chip duo allows transfer of controller electronics to smallest disk drives

With the disk drive electronics now packed in tiny packages, placing controller boards in the host computer is a has-been approach.

ost personal computers have to control at least one floppy-disk drive, and usually the controller electronics for the drive are on a plug-in card. Moving the controller components into the drive would free an expansion slot in the computer, but eversmaller disk drives severely restrict the area for the drive circuitry itself, let alone added control electronics. Instead of the standard 5½-in. height for drives, designers now face 3½-in. versions, like the Sony floppy.

Two chips give the designer considerable leverage in overcoming the impossible. With the pair—the SSI 570 and the SSI 580—a designer can squeeze all the electronics for a disk drive into less than 2 in. The space thus made available can be used to move a controller into the disk drive.

For example, an SA400 type of disk drive can interface with a host computer in a much simpler manner with the two chips, which incorporate most of the required circuitry (Fig. 1). Both

Dan Brown and Al Morton, Silicon Systems Inc.

Dan Brown gained extensive experience in IC design before becoming computer products marketing manager at Silicon Systems in Tustin, Calif. He obtained his BSEE from the University of California in Irvine.

Al Morton is applications engineering manager at the same company and was previously a field applications engineer at Harris Semiconductor and Texas Instruments. His BSEE and MSEE are from California State University in Fullerton.

satisfy the interface characteristics of all lines between the host and the drive, supply all interconnections with the read/write heads, and provide an interface with an on-board microprocessor

When used with an 8048 microprocessor and a spindle-motor speed controller, the chip set makes up virtually all the circuitry required in a floppy-disk drive. The SSI 570 replaces the traditional MC3470 and MC3471, several 7414 input gates, and a handful of diodes. The SSI 580 replaces several SSI and MSI logic circuits, programmable logic arrays, integrated fuse logic devices, or gate arrays.

The SSI 570, known as the data path chip, provides the complete read/write and erase functions in a 28-pin package. It includes the write data flip-flop, as well as a write current source that can be set externally.

Erasing can follow either "straddle" or "tunnel" methods, which employ different erase heads. With the straddle method, the erase gap straddles the write gap; with the tunnel method, the erase gap follows the write gap. For tunnel erase heads, the SSI 570 erase current can be delayed at turn-on and turn-off to coincide with the position of the written information. The read data path—from the head to the read output—is characterized by low noise  $(5 \,\mu\text{V rms})$ , high gain  $(1000 \,\text{V/V})$ , and minimal peak shift (0.3%).

The SSI 580, which also comes in a 28-pin

## Disk drive control chips

package, is a special-purpose I/O port expander for an 8048 or similar microprocessor. It processes system data and controls the width and delay of the index sensor input. The inputs of all host interface lines have hysteresis, and the outputs meet the high-current (48-mA) and open-collector specifications required by the SA400 interface.


#### **Easy layout**

The designer still must use a few passive components to build a low-pass filter and to set the timing. However, there are no critical analog interconnections or layout problems, since that wiring is internal to the SSI 570. Since each chip occupies less than half an inch on a side in surface-mounted packages, the inherent space savings are obvious.

The controller board supplies a function needed by many magnetic media recording schemes. It turns data being sent to the drive into a serial stream, using modified frequency modulation (MFM) to encode it (see "Matching the Message to the Medium," opposite).

The read signal processing circuits on the data path chip consist of two differential preamplifiers, a summing amplifier, a postamplifier, an active differentiator, a zero-crossing detector, a time-domain filter, and an output one-shot (Fig. 2). When reading (R/W high), these circuits amplify and detect the read signals to produce uniform digital output pulses.

Each preamplifier input—for example, +HD<sub>1</sub> and -HD<sub>1</sub>—is connected, in parallel with a write current driver, to each read/write



1. An SA400 type of floppy-disk drive and its interface with a host computer typically require that some of the interface electronics be placed on a plug-in controller board within the computer.

head. The inputs are protected from the large voltage transitions that occur during writing. The output of the selected preamplifier, defined by the state of the Head Select pin  $(HS_0/HS_1)$ , is

fed to the summing amplifier.

The summing amplifier's outputs  $(+A_0,$  $-A_0$ ) are ac-coupled to the postamplifier through an external filter network. The input amplitude to the postamplifier (at pins +In, -In) should be maximized to reduce peak shift, meaning that the low-pass filter should have minimal attenuation in its passband. (Bessel or Thompson filters are typically used for their linear phase characteristics.) The passband corner is usually set above the third harmonic of the maximum frequency.

The postamplifier, which requires no external bias connections, can adjust the amplitude of a signal before sending it on to the differentiator. Maximum postamplifier gain is achieved with infinite impedance across gain pins G<sub>1</sub> and G<sub>2</sub>. (An additional frequency- or phase-compensation network may also be em-

ployed here.)

The response characteristics of the differentiator are determined by an external capacitor (or more complex series network) between  $D_1$  and  $D_2$ . The capacitor chosen should allow for a current of 2 mA peak to peak at maximum amplitude and frequency. If the internal  $50-\Omega$ resistance is insufficient to provide roll-off at 10 times minimum frequency, an external series resistor can be added. To attenuate higher frequencies, a series RLC network can be used, but the capacitor should still be selected as just described.

The peaks of signals entering the differentiator from the postamplifier become the zero crossings of the differentiator's output signal. A detector provides a unipolar output for each positive or negative zero crossing of the

differentiator output.

#### The time-domain filter

To enhance peak detection, spurious inflection points between true signal peaks are suppressed with a time-domain filter. The filter rejects detected zero crossings if they are not sufficiently separated in time. The time period is set by an external RC network at the TD pin.

Uniform data output pulses, presented at the

## Matching the message to the medium

Since the data that can be stored in a disk is limited by the number of flux transitions that can be produced on the magnetic surface, a selfclocking encoding scheme is often used to pack the most raw data into the flux transitions. The most popular scheme for floppies—though not necessarily the most efficient one-is modified frequency modulation (MFM) as follows:

If the serial stream of binary data is visualized as a sequence of bit cells, the rules for MFM recording can be summarized as follows:

- There is a flux transition for each 1 bit at the bit
- There is a flux transition between each pair of 0 bits.
- There is no flux transition between the bits of a 10 or a 01 combination.

In current floppy-disk drives, a controller tackles the encoding before the data is sent to the drive. What the drive receives is a serial stream of digital MFM-encoded data, which is then used to clock a toggle flip-flop. Each toggle on the output of the flip-flop causes the current to flow in a different leg of the read/write head, creating a change in the polarity of the magnetic field and therefore causing a flux transition. In the read mode, that recorded flux transition passes near the read/write head, inducing a low-level signal. Each flux transition corresponds to a pulse in the original data stream.

The challenge lies in faithfully replicating the original data stream. The key parameter is the spacing between the peaks of the detected signal. The signal is first amplified, then filtered to remove the unwanted frequency components. The low-frequency or dc components cause a signal offset, which becomes an asymmetry (or peak shift) in the output pulse position. The high-frequency components (noise) can cause jitter in the output pulse timing, which breaks up into small random varia-

tions in the zero-crossing location.

Differentiation changes the signal peaks into zero crossings. A comparator can detect the zero crossings, from which a bidirectional one-shot produces the data output pulses. Since the input to the differentiator is anything but a pure sine wave, the comparator may see "zero crossings" that do not indicate true flux reversals, but rather that are a result of noise or distortion in the signal processing path. However, valid zero crossings generate pulses from the comparator that are longer than a known minimum. If all pulses of less than that duration are ignored, some protection is afforded against false zero crossings. The SSI 570 data path chip employs this time-domain filtering scheme.


## Disk drive control chips

Read Data Pulse pin (RDP), are provided by the output one-shot, which is triggered by the output of the time-domain filter. The duration of the output data pulse is determined by an external RC network at the PW pin. The output one-shot is inhibited when the device is in the write mode.

The SSI 570's write circuits (Fig. 2 again) consist of two differential write current drivers operated by a flip-flop divider stage, a center tap voltage reference, two erase current switches, and control circuits for head selection and erase timing.

In the write mode (R/ $\overline{W}$  low), these circuits send controlled write and erase currents to either of two read/write heads. The value of the write current is set by an external resistor connected between the  $R_w$  pin and ground. Write current can be boosted 30% to compensate for the varying radial speed between the inner and outer track on the disk. This calls for a high input to the Current Boost pin (CB). The erase current is set by the external  $R_{\rm EC}$  resistors in series with the erase coils and the erase current switches at pins  $E_0$  and  $E_1$ .

The center tap voltage reference, V<sub>CT</sub>, is a



2. The SSI 570 creates a read and write path between the floppy disk and the host computer. The detection and filtering schemes that accept or recover raw data from the disk are electronically similar to the methods used by standard multichip designs.


## Set your design imagination free.

## The Interconics Challenge:

You design the large circuit board you've always wanted — we'll produce it!

Our superior capabilities mean you can now design circuits as large as you want, with densities never before possible on large boards. Boards four feet wide by six feet long with 7-mil lines and guaranteed 10-mil edge-to-edge tolerance are nothing new to us. We routinely work with a host of substrates and laminates. And we hold tight tolerances, even on unstable materials.


High-density, large circuit boards are only the start of the Interconics story. We also produce micro-strip, stripline and phased array antenna circuits and large flexible circuits better than anybody in the world.



#### Interconics Large Circuit Capabilities

Characteristic	Value
Maximum circuit size	Up to 50" wide; length limited only by avail- ability of materials
Line width	7-mil lines routinely produced on 48" boards
Dimensional tolerand Line width and	ce
spacing	±10%
Line position	±5 mils over 48"
Line straightness and parallelism	±2 mils over 48"
Front-to-back registration	5 mils

Let us show you what we've already achieved in producing innovative circuit designs. Simply call 1-800-328-9086 (In Minnesota 612-228-6512) or write: Interconics Information Center, P.O. Box 64223, St. Paul, MN 55164. We'll send you a 4-color brochure with all the technical details.



A UNIT OF **BMC** INDUSTRIES, INC.

CIRCLE 84

## Disk drive control chips


switched source that supplies both the erase head and the write head current. In the write mode, the reference voltage is near the V<sub>DD</sub> supply, minimizing power dissipation. In the read mode, the voltage is lowered to a value suitable for biasing the preamplifier inputs. To prevent undesired writing or erasure during power-up (or from a power-supply fault), the voltage reference is delayed until the supply voltages are within their operating ranges.

The write currents are controlled by two switching differential current drivers. When the data path chip is in the write mode, those drivers change output states at each negative transition of the Write Data In pin (WDI). The

output impedance of the drivers is very high. External resistors connected across each read/write head damp the write current.

The erase current is activated when the write mode is selected, but its application may be delayed. The turn-on delay is created when the erase capacitor, C<sub>E</sub>, is charged through the erase delay resistor, R<sub>ED</sub>. Similarly, the erase current, after leaving the write mode, is held for a time by the discharge of C<sub>E</sub> through the series  $R_{ED}$  and  $R_{EH}$ , which is the erase hold resistor. (For straddle-erase applications, CE can be omitted, causing the erase current to be applied concurrently with the write current.)

The SSI 580 I/O port expander has one 4-bit



3. The SSI 580 is a special-purpose I/O port expander that complements the data path chip when both are used with an 8048 microprocessor. Ports A and B are 4-bit input ports; port 2 is a 4-bit bidirectional port.

## Microprocessor programming made simple.

"Keep it simple" was the principle of the 14th Century English philosopher William of Occam and it has even more validity today. Faced with the problems of sophisticated computer systems, designers have found that ever more complex programming languages are further complicating their tasks. Until now.

## Occam. Created for system design and implementation.

When we started designing our new VLSI family of 10-MIP transputers, we built on William's simple philosophy. To take advantage of the possibilities opened up by the transputer, we needed to create a language capable of properly addressing parallelism and multiprocessor systems.

With the ability to describe concurrency (whether timeshared or real) and to handle message-passing at the lowest level of the language, all aspects of a system can be described, designed and implemented in occam. From interrupt handling through signal processing to screen editors to artificial intelligence. And on.

But occam is not limited to our

transputer family. It provides an efficient, responsive implementation language for systems built on today's microprocessors. It also opens up future possibilities with its performance-enhancing multiprocessor capabilities. And INMOS now offers a product to let you exploit occam's total capability in your system.

## Simplify your job with the Occam Programming System.

The Occam Programming System (OPS) gives you the tools for complete VAX / VMS software development. This package includes an integrated editor / checker, an optimizing VAX compiler and full documentation. This gives you a supportive environment for the development of occam programs

for execution on the VAX. Cross-compilers for 68000 and 8086-based systems will also be available.

What's more, the occam programs developed and proven on the OPS will give you a head start for work with the INMOS transputer. Extensions to the OPS will be available which will allow occam programs to run on the transputer.

And if you have a requirement to program the transputer in other popular high-level languages, other extensions will include compilers for C. Fortran, and Pascal.

### Get started today.

Contact us for our information pack on occam, the Occam Programming System and the transputer. You'll be surprised how simple your life can be.

For quick response, call us at (303) 630-4000 or write: Occam, P.O. Box 16000, Colorado Springs, CO 80935.

inmos. and occam are trademarks of the Inmos Group of Companies





## Disk drive control chips

bidirectional port, port 2, and two 4-bit input ports, port A and port B (Fig. 3). Port 2 consists of pins P<sub>20</sub> through P<sub>23</sub>. The pins for port A consist of Disk Select (DS), Write Gate In (WGATE IN), Motor On (Motor On), and Direction Select (DIR). Port B consists of DS and three sensor inputs, one for the index, another for write protection, and the last for track 00.

An 8048 microprocessor communicates with the I/O port expander over bidirectional port 2, with timing provided on the Programming pin (PROG) from the microprocessor. Information is transferred in two nibbles: the first contains the op code and port address and the second, the four-bit I/O data. A high-to-low transition on PROG clocks in the op code or address, and a low-to-high transition reads or writes data as directed by the op code.

### Reading and writing

In the read mode, the microprocessor can read each of the two 4-bit input ports via port 2. The processor loads the read op code and port address on pins  $P_{20}$  and  $P_{22}$  in the falling edge of PROG. When the op code and address are decoded, the appropriate input port is selected,

	221	oou rea	ad and write mo	ues	
Mode	op code (P <sub>22</sub> )	Address (P <sub>20</sub> )	input (plus on chip manipulation)	Output	
			DS	P <sub>23</sub>	
			index sensor latch	P <sub>22</sub>	
	0	0	Write protection sensor	P <sub>21</sub>	
			Track 00 sensor	P <sub>20</sub>	
Head			DS	P <sub>23</sub>	
			WGATEIN	P <sub>22</sub>	
	Ū	1	Motor On	P21	
			DIR register	P <sub>20</sub>	
			(P <sub>23</sub> ·WR PROT se <u>nsor)</u> + (DS· WGATEIN	WGATE	
			(P <sub>22</sub> DS)	TRACK 00	
write	1	U	(P <sub>21</sub> ·DS)	Ready latch rese	
			P <sub>20</sub>	Index	
	1	1	(see text)	INTR	

and port 2 is configured as an output port (see the table). This operation is terminated by the rising edge of PROG, which returns port 2 to the input mode.

In the write mode, the microprocessor passes system parameters to the I/O port expander for logic manipulation and transmission to the host system. The write op code and address are passed on the high-to-low transition of PROG. On the low-to-high transition, data on port 2 is loaded into the circuit.


The Interrupt signal (INTR) is the output of a D flip-flop, which is reset every time the Step command is issued. The command forces INTR low, thereby interrupting the 8048 and causing it to execute an interrupt service routine. Typically that routine obtains information on the direction the heads should move and on the status of the track 00 sensor, and the information is used to generate phase-control signals for the stepper motor. Note that indeterminate operation will result from holding the Index Sensor Latch reset.

The  $T_1$  signal, which drives the counter input on an 8048 type of microprocessor, changes state whenever the host sends a step command.  $T_1$  and the  $\overline{DIR}$  register input from port A monitor head position, so that a Current Boost command can be given to the data path chip when a specific track is reached.

The Index pulse width and delay are programmed by resistors and capacitors connected to the  $R/C_w$  and  $R/C_D$  pins, respectively. The WGATE output controls the change between read and write modes of the data path chip.

Since the chip set is intended to squeeze the floppy disk's electronics into as small an area as possible, the ideal situation would be to free enough space to put a disk controller on the same board. A suggested floppy-disk drive reduces circuit space (Fig. 4) by using a multilayer board and surface-mounted active and passive components (the 8048 is available as a surface-mounted device). The circuit meets all the controller signal requirements of the SA400 type of interface (Fig. 1 again). The chip set needs only half a square inch, and the rest of the circuitry, approximately 1 in. Thus the disk drive electronics fit in less than 2 in.

The reduction in IC count is obvious. Surrounding the data path chip are the passive



## High quality. Low price. New KEMET® AXIMAX™ capacitors give high-volume users the best of both.

Now KEMET ceramic capacitors come in a new, economical package that puts punch in your production. But not in your poolest.

production. But not in your pocket.
Low-cost AXIMAX capacitors are axial-leaded, conformally-coated units with the same superior construction you've come to expect from all KEMET capacitors, whether solid tantalum, multi-layer ceramic, or precision thin-film. But at a budget-pleasing price.

In four case sizes with COG (NPO) ultra-stable, X7R stable or Z5U general-purpose dielectric, AXIMAX capacitors offer over 138 capacitance values from 10.0 pF to 1.0  $\mu$ F, in 50 and 100-volt ratinas.

They're assembled with high-temperature solder that maintains lead integrity.

And their wide-range selection and performance let you use them everywhere quality counts—such as bypass and decoupling circuits for telecommunications, data processing,

automotive and entertainment systems.

New KEMET AXIMAX ceramic capacitors are available now in 2,500 and 5,000-unit taped reels, and conform to EIA specification RS 296D—ready for high-speed, automatic insertion. With exclusive EPIC delivery, direct from inventory.

For lead-taped engineering samples, contact: Union Carbide, Electronics Division, Components Department, P.O. Box 5928, Greenville, SC 29606. (803) 963-6348. TWX: 810-287-2536. Telex: 57-0496.

Union Carbide in Europe: Phone Geneva, 41-22-396511; Telex: 845-911302.

Union Carbide in Asia: Phone Hong Kong, 852-372-31211; Telex: 780-45162.

Or call your local KEMET representative or distributor.

UNION

ELECTRONICS DIVISION COMPONENTS DEPARTMENT KEMET offers you more in the '80s.

See EEM for KEMET capacitors general catalog.
KEMET is a registered trademark of Union Carbide Corporation.

## Disk drive control chips


components needed for filtering, timing, damping write current, setting write and erase current, and setting gain. The I/O port expander chip is supported by three optical sensors for the Track 00, Write Protect, and Index pins and by four passive timing components. The 8048 microprocessor needs a crystal for clocking, and it delivers commands to a stepper motor through external power transistors. The spindle motor brings the floppy disk up to speed when turned on by the microprocessor.

The I/O port expander is a bipolar chip, meeting the 48-mA drive requirements of the SA400 interface. But if the controller is incorporated in the drive, or placed very close to it, there will be no cable and thus no need for high

currents and hysteresis. Then an SSI 580 type of circuit could be made in CMOS and used with an 80C48 microprocessor to reduce the drive's power requirements.

A further benefit could be derived from the change to CMOS if the designer combined 80C48 and SSI 580 functions on a single chip. That solution would reduce the required circuitry to two ICs, a handful of passive parts, opto-sensors, power drivers, and a crystal. □

How useful?	Circle
Immediate design applicati	ion 550
Within the next year	551
Not applicable	552



4. With the data path chip and the I/O port expander, all the electrical requirements of the SA400 floppy-disk drive interface (shown in Fig. 1) can be met with just one 8048 microprocessor and a handful of discrete components. The chip set can be fit into 2 in.2, thus allowing the plug-in disk controller card circuitry to be moved into the disk drive.

## High-performance CMOS Static RAMs. There's never been a better deal.




#### The Game

High performance. Reliable delivery. And a fair price. When it comes to CMOS Static RAMs, the stakes are too high to gamble on anything less.

#### **Our Hand**

That's why S-MOS offers the two most popular CMOS Static RAM types for large volume users: the SRM 2064 64K (8K×8) and the SRM 2016 16K (2K×8). Pin-compatible with 6264 and 6116 device families, respectively, they're designed for performance that meets or exceeds other vendors' premium grade products. But at prices equivalent to their standard grades.

Take our powerful 64K CMOS SRAM. It features an access time of just 150ns,



The S-MOS system

SRAI	M CON	MPARI	SON C	HAR	r	
16K (2K×8) 150ns	OPERAT CURF (TYP)		STAND CURP (TYP)			DBY (3) RENT MAX
LEADER'S STD, 6116	35mA	70mA	5mA	15mA	20μΑ	2000μΑ
LEADER'S LP, 6116	30mA	60mA	4mA	12mA	2μΑ	50μΑ
S-MOS' STD, 2016	20mA	35mA	.3mA	2mA	1μΑ	50μΑ
64K (8K×8) 150ns						
LEADER'S STD 6264	60mA	110mA	1mA	3mA	20μΑ	2000μΑ
LEADER'S LP 6264	60mA	110mA	1mA	3mA	2μΑ	100μΑ
S-MOS' STD 2064	25mA	40mA	1.5mA	3mA	2μΑ	100μΑ
(1) AVERAGE: MIN DI	UTY CYC		= VIH, CS = VIH (16)		(64K)	
(2) $\overline{CS1} = VIH OR CS$ $\overline{CS} = VIH (16K)$	2 = VIL	(64K)				
(3) CS1, CS2 ≥ VCC CS ≥ VCC (VDD)			≤ 0.2V (6	4K)		

Based on published data sheet parameters

worst case. Plus power consumption that's a mere 25mA operating;  $2\mu A$  standby.

What's more, the device utilizes 2-micron selectox silicon gate CMOS technology. It's a proprietary process that optimizes speed and power while cutting production costs. So while you're increasing performance, you're also saving money.

The SRM 2016, like its 64K counterpart, cuts down on energy consumption and has an access time of just 150ns.

Both SRAMs feature industry-standard

pinouts and a choice of either plastic flat pack, cerdip, or plastic DIP packaging.

#### **Our Raise**

For outstanding reliability, our SRAM parts are 100% burned-in and temperature tested. And they are fabricated by Suwa Seikosha, one of the world's largest, most automated CMOS LSI manufacturers.

And remember, these premium devices are delivered at a price that's equivalent to the competition's standard grade. Now that's one sweet deal.

#### Our Call

So when the chips are down and you need more, stand pat with S-MOS. We've got a full house of 64K and 16K CMOS Static RAMs ready for immediate delivery.


S-MOS Systems.

Nothing beats a winning hand.



S-MOS Systems, Incorporated 50 West Brokaw Rd., Bldg. 7 San Jose, CA 95110 (408) 993-1212

## Better Instruments for Better Communications



### The "Personal-Sized" MS610A Spectrum Analyzer

Although compact, the "personal-sized"

MS610A is a full-fledged spectrum
analyzer with a frequency range of
10kHz - 2GHz. And it's so easy to
operate! Just specify reference level
and frequency span, then hit a pair of
handy front-panel pushbuttons. Now
other functions are automatically
coupled to span and reference,
internally setting resolution bandwidth,
sweep time and input attenuation for
optimum accuracy.
Another better communications
instrument from Anritsu.



Anritsu means communications.

We began building telephone and radio equipment more than 50 years ago. And although we've expanded into other fields since then, we've remained true to those first electronic roots.

In fact, the Anritsu name is now known around the world as synonymous with communications. From public telephones to sophisticated, state-of-the-art



optical and digital transmission systems, Anritsu communications products are highly regarded for both unequalled reliability and technical excellence.

With such wide-ranging experience in all phases of communications, it's no surprise that our electronic measuring instruments are superior, too.

Anritsu builds the electronic instruments that keep electronic and fiber optic communications operating at the knife edge of efficiency. From the simple measurement of voltage and current to complete high-level analysis of both analog and digital circuitry, Anritsu instruments are built by experts in communications. And Anritsu instruments are built to be used.

Whether it's an Anritsu electronic voltmeter, a network analyzer or a complete GPIB-based automatic test system, you'll find a basic field-proven ruggedness built in. And you'll find controls that actually make sophisticated measurements simpler to perform.

At Anritsu, we're striving toward still better instruments. And better communications.

ANRITSU ELECTRÔNICA COMÉRCIO LTDA.

Av. Passos, 91-Sobrelojas 204/205-Centro, 20.051-Rio de Janeiro-RJ, Brasil Phone: 221-6086, 224-9448 Telex: 2131704 ANBR

**ANRITSU AMERICA, INC.**128 Bauer Drive, Oakland, NJ 07436, U.S.A. Phone: 201 337-1111 Telex: 642-141 ANRITSU OKLD

ANRITSU EUROPE LIMITED
Thistle Road, Windmill Trading Estate, Luton, Beds, LU1 3XJ, U.K. Phone: (STD0582)418853 Telex: 826750 ANRSEU G
ANRITSU ELEKTRONIK GmbH


Uhlandstrasse 9, 4000 Düsseldorf 1, F.R. Germany Phone: (0211)682424 Telex: 8584904

**CIRCLE 88** 



10-27, Minamiazabu 5 chome, Minato-ku, Tokyo 106, Japa Phone (03) 446-1111/Telex: 0-242-2353 Cable: ANRITDENKI TOKYO

## THE Q/PAC POWER DISTRIBUTION CAPACITOR. A SMALL REVOLUTION IN PCB PACK AGING TECHNOLOGY.



Now there's a way to achieve ultraefficient power distribution and high capacitance with the same space-saving component: Q/PAC® from Rogers.

A small revolution in PCB packaging technology, Q/PAC power distribution capacitors improve and simplify all aspects of board design. Rugged and easy to install, they eliminate on-board power traces. And provide noise suppression unmatched by conventional discrete decoupling capacitors.

What's more, since Q/PAC saves valuable real estate by replacing both power traces and discrete decoupling caps, there's more space for signal routing and interconnecting IC's.

So you can increase density on dependable twolayer boards—and avoid expensive multilayer.

The simple, cost-effective way to package high-density, low-noise logic, memory and other boards, Q/PAC power distribution capacitors feature low impedance, low dissipation, low inductance and excellent electrical performance. They're available in capacitance values up to 0.04 µf/in. in lengths up to 16". With 2 or 3 conductors in either vertical mounting or horizontal under-the-DIP constructions.

To find out more about how Q/PAC can revolutionize your packaging possibilities, call a Rogers Q/PAC Product Specialist today at (602) 967-0624.



Rogers Corporation Q/PAC Division 2400 South Roosevelt, Tempe, AZ 85282 602 967-0624

## **D**ESIGN ENTRY

# On-chip EEPROM holds changing register data for 8-bit microcomputer

With a 32-byte EEPROM built into its main registers, a microcomputer chip lowers the risk of losing essential data, whether in multiprocessor or stand-alone setups.

hough some microcomputers incorporate electrically erasable PROM, they use it only for control and application programs, which rarely undergo changes. Ideally, systems should be able to apply that nonvolatile storage to the critical immediate data with which their main registers work.

Making a 32-byte EEPROM part of the main data registers, as does the 16E57 microcomputer chip, permits critical data to be placed in nonvolatile storage with no concern about loss during a scheduled or accidental power outage. Besides that as its main asset, the microcomputer can slip easily into multiple-processor systems or stand on its own.

## Frank Gruppuso, Ranjit K. Verma, and John E. Burgess, General Instrument Corp.

As manager of logic design engineering at General Instrument's Microelectronics Division in Hicksville, N.Y., Frank Gruppuso works with semicustom, microcomputer, and digital signal-processing products. He holds an MSEE from the Polytechnic Institute of New York.

Ranjit Verma manages the worldwide applications organization, supervising support activities for microcomputers and semicustom, digital signal processing and standard logic products. He has an MSEE from the State University of New York at Stony Brook.

Product line manager John Burgess is responsible for the worldwide marketing and strategic planning for 8-bit microcomputer products. He received an MBA from the University of Rhode Island. A self-contained oscillator generates the clock frequency, which is determined by an external crystal or ceramic resonator. The oscillator's output is internally divided by eight to set the instruction cycle time of the microcomputer. Thus, a 2-MHz crystal gives an instruction execution time of  $4 \mu s$ .

The EEPROM is organized as 32 byte-wide words in a file register format. It operates in five modes: programming, erasing, bulk erasing, writing, and reading. The 21 V required for programming and erasing is derived on chip from the main 5-V supply and is completely transparent to the user.

In addition to its EEPROM, the microcomputer contains a mask-programmable control ROM, organized as 512 words by 12 bits. Also on chip are a RAM, arranged as 32 words by 8 bits and set up as a register file to store internally generated data, and 20 bidirectional I/O lines that afford the primary means of user access to the microcomputer.

Like the EEPROM and RAM, I/O is organized into groups of registers that appear to the CPU like any other group of on-chip registers. This arrangement grants the CPU a great deal of flexibility, since there are no specific user I/O instructions.

In keeping with the microcomputer's talents as an efficient control processor, its instruction set permits the user, directly or indirectly, to address, set, reset and test, or skip the status of

## **EEPROM-equipped microcomputer chip**

any register bit or I/O line.


An 8-bit data bus connects the processor's main functional elements: a file of 32 addressable 8-bit registers; the user-defined program ROM containing 512 words that are each 12 bits wide; and of course an ALU (Fig. 1).

## A register file concept

The file breaks down into operational and general-purpose registers. The former include F<sub>1</sub>, a real-time clock counter (RTCC); F<sub>2</sub> the program counter; F<sub>3</sub>, the status register; and the I/O registers. General-purpose registers hold data and control information under the command of the instruction set.

The program ROM contains instructions for all on-chip logic functions. Microinstruction sequencing is controlled through the program counter, which automatically increments when it is executing in-line programs. Program control operations are initiated by Bit Test, Skip, Jump, and Call instructions or by loading computed addresses into the program counter. The two-level stack handles subroutine nesting. The instruction decoding and control block receives the 12-bit instruction word from program memory, decodes it, and issues the appropriate control signals for the desired action.

Status register F<sub>3</sub> stores the condition of the most recent ALU operation. Bits in that register are set or cleared either by bit-level program instructions or by a Move instruction. An 8-bit up-counter, F<sub>1</sub>, times or counts external events. Under program control, it can be set to any 8-bit binary value and thereby facilitate counting of 256 external events, either predetermined or undetermined. The contents of the real-time clock counter—that is, the number of events counted—can be interrogated under program control.



1. Among the resources of the 16E57 single-chip microcomputer is a 32-word-by-8-bit EEPROM that gives the device nonvolatile, user-programmable storage. The chip's registers are connected by an 8-bit data bus to an ALU. Included on chip is a 512-word-by-12-bit program ROM.

File selection register  $F_4$ , an addressable 5-bit register, indirectly addresses the register file. Although a full address can be written into this block from the internal data bus, only the low-order 5 bits are relevant to  $F_4$ . During indirect addressing, the microcomputer accesses the contents of the register pointed to by  $F_4$ .

The 20 bidirectional I/O lines are organized into three register groups for interfacing with external devices. Registers  $F_6$  and  $F_7$  are 8 bits wide,  $F_5$  is 4 bits wide. All I/O registers are handled by the ALU in the same manner as any internal register. For example, an I/O port can be incremented and forced to count by direct command. To perform a counting operation, the ALU need not continually increment or decrement its accumulator and transfer the information to an I/O register. The I/O registers are essentially internal devices with pins that interface with the outside world.

An I/O port interfaces with either the input to a TTL circuit or the open-collector output of such a device (Fig. 2). When the microcomputer puts out data through the port, the data is latched and the output pin is connected directly to the TTL input. But when data is being received by the processor, the port latch is first set to a high level under program control. That turns off transistor  $Q_2$  and allows the TTL open collector to be pulled up by  $Q_1$ , a transistor that can source a minimum of  $100\,\mu\text{A}$ . Thus, the TTL device either forces the latched output line low or keeps it high.

#### The ALU's register

The ALU contains one temporary working register—the accumulator, dubbed the W register—plus the gating logic needed to perform Boolean and arithmetic operations on data stored in the W register or in any file register. The various operations use one or two 8-bit operands. One of them is fetched from any of the file locations, or it may be a literal within the instruction. If needed, the other operand is held in the W register.

Using the operations singly or in combination, the ALU can add, subtract, multiply, and divide the 8-bit operands. It also performs BCD arithmetic, mask operations, and bit and field manipulations. Typically, the microcomputer executes an instruction in just  $3 \mu s$ .


Resident data memory consists of 64 bytewide words that are addressed in three register banks (Fig. 3). The first bank consists of 32 registers:  $F_0$  through  $F_7$  (octal)—among them the I/O registers, the program counter, and the real-time clock counter—plus registers  $F_{10}$  through  $F_{17}$ , which are general- and special-purpose RAM for storing program data. The 32 EEPROM registers are addressed as two banks of 16 each— $F_{20}$  through  $F_{37}$  (also octal)—which are chosen according to the states of two bank selection bits, ESEL 1 and ESEL 2, which are located within status register  $F_3$ .

The first bank is selected when ESEL 1 is a logic 1 and ESEL 2 is a logic 0. The second bank is chosen with the reverse logic levels. All the preceding registers, from  $F_0$  through  $F_{17}$ , are addressable, regardless of the states of ESEL 1 and ESEL 2.

### The EEPROM compared

The 32 nonvolatile EEPROM registers operate very much like the general-purpose file registers. First, ESEL 1 and ESEL 2 are set for the appropriate bank and then the operation instructions—Erase/Write, Erase, Write, Read—are executed. To address the EEPROM registers, the ESEL bits are set to 10 or 01. If both bits are either 0 or 1, the standard registers are addressed.

The nonvolatile registers differ from the standard types in that only a logic 1 can be written to bit positions. To store a data pattern, the EEPROM must first be erased to all logic 0s and then 1s written to the appropriate bit positions. A program operation is performed automatically when either of the two banks is selected,



2. Users interface with the microcomputer through 20 bidirectional I/O lines, one of which appears here. The I/O ports are fully TTL-compatible.


## **EEPROM-equipped microcomputer chip**

and a MOVWF (Move W to F) instruction is executed on registers F<sub>20</sub> through F<sub>37</sub>. Erasing and writing take about 20 ms each, but they are automatic and transparent to the software.

Any one EEPROM register can be erased by selecting either bank and then executing a CLRF instruction on F20 through F37. An entire bank of registers can be erased in a single 15-ms bulk operation. To do so, ESEL 1 and ESEL 2 are set to logic 1 and an ERAL instruction is executed on F<sub>20</sub> through F<sub>37</sub>.

To write into an individual EEPROM register, first a bank is selected and then an IORWF f, 1 (Inclusive-OR W and F) instruction is executed on F<sub>20</sub> through F<sub>37</sub>. If the register earlier was erased to 0, register W will be copied correctly into the register. If not, only the 1s will be written. To write a 1 to an individual register bit, the BSF instruction may be used. Data is read at the instruction cycle time of the microcomputer, or in this case, about  $3 \mu s$ .

The microcomputer can perform other



3. The microcomputer's register file is divided into operational registers (F<sub>0</sub> through F<sub>17</sub>) and working registers (F<sub>20</sub> through F<sub>37</sub>). The EEPROM registers are selected only when ESEL 1 and ESEL 2 are in opposite logic states; when the bits are in the same state, the operational registers are selected.

## Silicon General's Advanced 1524 B Pulse Width Modulator.

# A new R<sub>x</sub> for making power supplies smaller.

## Powerful capabilities make the 1524B a true 4th Generation PWM.

Seven years ago Silicon General invented the 1524 PWM, the industry standard control circuit for switching power supplies. It was an instant success. Today, almost 60% of all power supplies incorporate devices from the 1524 family.

Now we've created the new industry standard.

The 1524B features higher voltage outputs, lower input voltages and better line regulation of your power supply. It puts more functions on a chip than ever before, making your system more reliable and permitting even smaller power supplies.

## Pin-for-Pin compatible with the 1524.

In most applications, just by unplugging your present 1524 and plugging in a 1524B you can substantially enhance your overall system performance. Consider these unique features:

 $5V \pm 1\%$  low drift bandgap reference eliminates initial output voltage adjustment and exhibits line and load regulation 5 times better than the 1524.

R from SILICON GENERAL

Undervoltage lockout with hysteresis prevents turn-on jitter and allows operation from a fixed 5V supply.

	:	:
		:
•	*	*
	•	

Key Feature present and improved over 
Feature present

Wider current limit common mode range gives you the option to sense either directly in the supply output line or in the return line.

High speed shutdown protects output devices during a fault condition.

Excellent external sync. capability eliminates erratic triggering problems.

Full double pulse suppression logic prevents power transistor failures caused by double pulsing and ensures glitch-free controller output.

Dual 60V, 100 milliamp transistors allows you to design with higher input voltages and more current drive.

7-40V *input capability* permits wider range of system operation.

Impressive? We've been bringing power down to size for over seven years. Now the 1524B continues our tradition of technological leadership. The 1524B PWM is available off the shelf and in volume.

For information write Silicon General, Semiconductor Division, 11651 Monarch St., Garden Grove, CA 92641. (714) 892-5531. TWX: 910-596-1804. Telex: 69-2411.

Solutions for Data Conversion and Power Management.




## **EEPROM-equipped microcomputer chip**

system tasks while programming is in progress. The Busy bit in status register  $F_3$  is a read-only bit that is polled by the software to determine whether programming is complete before attempting other operations on a EEPROM register. A logic 1 in that bit location indicates that programming is taking place. If another operation is attempted before the bit goes low, the microcomputer suspends execution.

#### A streamlined command set

Each instruction in the microcomputer's set is a 12-bit word that follows a powerful yet easy-to-use command structure. The single



4. Tailoring the programmable microcomputer chip to a specific job, such as a keyboard encoder, is relatively simple. The keys, arranged in an 8-by-8 matrix, connect directly to the chip's bidirectional I/O lines. Software in EEPROM directs routine scanning, encoding, and debouncing.

12-bit instruction word provides several unique characteristics. Fetching the entire instruction word all at once greatly simplifies the microcode and enhances throughput by not requiring multiple fetches from program memory. The machine is also fault-tolerant. Should the program counter accidentally jump to a random location, the program will resume by always executing instructions and never data bytes, as would be the case if memory were organized in 8-bit data bytes. For simplicity, all instructions are single words and are confined to the microcomputer; that is, the instructions are not intended to address external memory chips or peripheral devices.

The basic repertoire of 36 instructions is divided into four groups: byte-oriented register file operations, bit-oriented ones, literal and control operations, and byte-oriented EEPROM file register operations. Each instruction is further divided into an op code. which defines the command type, and one or more operands that provide additional operational characteristics.

For byte-oriented operations, f is a designator that specifies which of the 32 file registers the instruction will use. The destination designator, d, indicates where the result is placed. If d is 0, the result goes to the accumulator; if it is 1, the result returns to the file register specified in the instruction.

In bit-oriented instructions, b designates the number of the field bit affected by the operation. For control operations, k is an 8- or 9-bit constant; for operations on literals, it is a literal value. In addition to the basic instruction set. an extra set of about 40 commands—actually a superset—is upwardly compatible with the basic commands.

Because of its on-board EEPROM, the 16E57 can be easily customized for use in a variety of specialized control applications. Often those applications are similar except for certain information that varies from job to job. Keyboard encoders, for example, perform a like function in most terminals, but must handle slightly different function key assignments, serial port parameters, and other system attributes.

Rather than use different encoders, a generalized keyboard encoder can be built with the 16E57. Variable or specialized key attributes

## OUTSTANDING UNDER COVER PERFORMANCE

WITH CHOMERICS MOLDED-IN-PLACE EMI/EMP GASKET / PANEL ASSEMBLIES

Electronic enclosure shielding performance is greatly enhanced when cover panel EMI gaskets are vulcanized directly to the flange surface instead of adhesive-bonded. A molded-in-place conductive elastomer gasket permits the optimum seal profile to be formed. Eliminating the adhesive interface maximizes EMI/EMP shielding and environmental sealing.

### **GASKET IS CRITICAL**

Shielding effectiveness. Low resistivity. EMP survivability. Vibration resistance. Stability over time. Corrosion resistance. These are all necessary properties for gaskets used in demanding applications. Concern for gasket quality and performance is critical to enclosure design. It cannot be just an afterthought, as it often is with panel fabricators. We invented, developed, and perfected conductive elastomer technology. We produced our first molded-in-place cover

gasket over 10 years ago. Our corrosion resistant CHO-SEAL® 1285 elastomers provide over 90dB of shielding effectiveness and excellent performance in airborne, shipboard, and ground environments.

## SIMPLE INSTALLATION

Covers with vulcanized CHO-SEAL gaskets simplify your manufacturing operation by eliminating parts and reducing documentation and inventory requirements. Pre-fabricated cover/gasket assemblies eliminate the inconsistent and expensive adhesive-bonding operation. And, because of increased reliability and fewer parts, field maintenance is simplified.

#### YOUR COVER OR OURS

Chomerics has the manufacturing capabilities to fabricate complete assemblies—from machining to molding to surface finishing. Or,


we'll vulcanize CHO-SEAL gasket materials to covers supplied to us. We can also vulcanize non-conductive or COMBO® gaskets for dual-seal applications, where enhanced corrosion protection is required.

To find out how well we perform under cover, request a free copy of our "Molded-In-Place EMI/EMP Gasket/Panel Assemblies" brochure by circling the inquiry number or calling 617-935-4850.

## CHOMERICS SHIELDING TECHNOLOGY

THE LEADER IN SHIELDING INNOVATION, DESIGN, AND TESTING TECHNOLOGY

77 Dragon Court Woburn, MA 01888 TEL: (617) 935-4850 TWX: 710-393-0173



CIRCLE 91

## **EEPROM-equipped microcomputer chip**

are simply stored in the chip's EEPROM. Aside from the cost advantage, the single-chip approach adds programmability to the end product.

#### A system overview

When programmed for keyboard duty, the chip must scan, detect, debounce, encode, and buffer key closures (Fig. 4). The keys are arranged in a 8-by-8 matrix and are connected directly to the chip's I/O lines. The key closures, coded in ASCII, are sent to the control processor.

A software command interpreter enables the control processor to read and write to the EEPROM under control of the 16E57. Such a design frees the control processor from the

#### Program 1. Sample code for writing data into EEPROM register Desired EEPROM bank selected FSR = Destination of byte to be written Count = Number of bytes to write Next Call **GETBYT** Get data byte from system bus Put data byte in working register MOVE DATA,W MOVWF 0 Save in EEPROM DECFSZ Count See if done yet Goto Wait No-wait for ready bit Goto Save Last file-exit Wait **BTFSC** Status, Busy Wait for busy bit to be cleared Goto Wait INCE **FSR** ; Destination pointer to next location Goto Next

F	rogram functi	2. San on key	V	ole code for putting out alues from EEPROM
	MOVLW	Bytes Count		Put number of data bytes in counter
	MOVLF	Pointer		Get address of character string
	MOVWF	FSR		Put address into indirect register
Next	MOVF	0,W		Pick up data byte
	MOVWF	Keynum	:	Put in file to be output
	Call	Output	:	Send file
	INCF	FSR		Point to second byte
	DECFSZ	Count		Decrement counter of Bytes - skip if finished
	Goto	Next		

need to supervise the EEPROM's 20-ms erase/write timing specification. Also, the time to read data from the control processor and to program an EEPROM location does not interfere with key scanning or encoding. Instead, onchip control logic performs an EEPROM program operation automatically, without bothering the keyboard encoding software.

A crystal or ceramic resonator must be added to the microcomputer chip to create a keyboard encoder. In operation, ports RB and RC of the chip—under software control—continuously scan and read a 64-key mechanical contact keyboard. The shift and caps lock keys appear as separate inputs to the RA port, with software performing the control key function on a defined key in the matrix. Internal pull-up resistors maintain a valid logic 1 on the ports dur-

ing read operations, thus negating the need for

external resistors.

Once a key is verified, debounced, and encoded, the key code is transmitted synchronously through one pin of the RA port to the bus interface logic. The clock signal is supplied through another pin of the RA port. In the same manner, commands and data from the control processor are sent over the serial data wire to the 16E57. In its simplest form, the serial-toparallel interface is controlled by the microcomputer and an 8-bit bidirectional shift register.

The microcomputer scans the keyboard matrix by first selecting one of the eight rows and then reading the eight columns. If no keys are depressed in any row, the next is read. As the scan proceeds, a count is kept of the number of

keys that have been checked.

When a key closure is detected, debouncing data is pulled from an EEPROM file and used by the debounce-delay timer. During the debouncing period, the clock line (pin RA<sub>1</sub>) is checked for commands arriving from the host. After debouncing, the closure is verified and the count, generated during the scan, serves as an offset in a look-up table containing the various key codes.

If only one key has been depressed, the autorepeat timers are read from EEPROM and entered into the repeat-timer run registers that are used for counting down. The modified ASCII or other maskable codes are then sent to

### **DESIGN ENTRY**

## **EEPROM-equipped microcomputer chip**

the system bus.


The bit corresponding to that key in the run bit map is set, indicating that the key has been registered. The next time the key is scanned, the bit map will be checked to see if it has already been sent to the host.

There are two methods for reading and writing EEPROM files in the keyboard application. The first is used by the control processor for such information as the terminal and user identification numbers, 50- or 60-Hz operation, serial port characteristics, and other system attributes. The process is initiated by pulling the clock line low and thus placing the 16E57 in its programming mode, so that it can read a command from the bus. A single-byte command is needed for setting the EEPROM's pointer byte count and starting location.

If the command indicates that data must be written into EEPROM, the first data byte from the system bus will be written into the location indicated in the command word. If only one byte is written, an EEPROM write-acknowledgment code is sent to the control processor. For several bytes, a check will be made to see if the Busy bit has cleared, indicating that 16E57 has completed writing at the location. The additional bytes of data are then written. After the last byte has been written, a verification code is returned to the control processor (Program 1). When an EEPROM file is read, the value at the location indicated by the file number is put out onto the bus.

Another program procedure designates specific keys for code-conversion chores. The feature is very handy for assigning a special character or character string to a specific function key. With that programming (Program 2), when the 16E57 detects the simultaneous closure of the Control, Shift, and Function key, the sequence of characters entered is written to the EEPROM and assigned to the function key. The next time the function key is depressed, the microcomputer will transmit those characters to the control processor.□

How useful?	Circle
Immediate design application	553
Within the next year	554
Not applicable	555



## **Extremely** Fast Switching, **Low Barrier** Schottky Diodes

- Low Capacitance < 1.0 pF @ 0V
- Low Barrier < .30 V @ 1 mA
- Low Leakage < 100 nA @ 10V
- **Guard-Ring Protected**
- Very Fast − < 100 psec lifetime

TRW Microwave offers new guard-ring, fast switching Schottky diodes for wave shaping, A/D converting, clamping, and general purpose switching. These replace A2S835 (HP 5082-2835), 1N5711/12.

PART NUMBER	CASE	V <sub>BR</sub> VOLTS	C <sub>TO</sub> pF	1 mA V <sub>F</sub> max VOLTS	IF min @ IV, mA
A2S830	Glass	20	1.1	0.32	50
A2S836	Glass	10	1.0	0.34	50
A2S832	Glass	15	3.5	0.30	200
A2S032	Chip	20	1.2	0.32	50
A2S033	Chip	10	0.9	0.34	50
A2S035	Chip	15	4.0	0.30	200

Also from TRW Microwave's Semiconductor Group . . .

- Schottky chips and glass package diodes -1N5711, 1N5712, 1N5165
- PIN Diodes 1N5719, equivalent to HP 5082-3188
- Planar Back and Tunnel Diodes
- JAN, JANTX also available

TRW Microwave, 825 Stewart Drive, Sunnyvale, CA 94086. Telephone: 408.732.0880 TWX: 910-339-9207



**TRW Microwave** 

©TRW Inc. 1984

## More Room ... More Multibus Cages.

ONLY FROM ELECTRONIC SOLUTIONS!



We have more models than all our competitors combined. Choose a cage with:

3, 4, 5, 6, 7, 8, 9, 12,14, 15, 16, 20, 24 OR 26 SLOTS

for the right solution to your problem. We have models with either 0.6" or 0.75" card centers and can even accommodate wire-wrap cards.

All models are electrically and dimensionally interchangeable with Intel's iSBC-80® Cages.

#### More Room

You get more room for extra cards without increasing overall size. because our design gives you greater inside dimensions.

## More Reliability

All cages are constructed of sturdy, durable anodized aluminum with a single mother board backplane . . . a concept that increases reliability and minimizes interconnections.

#### THREE YEAR WARRANTY

## More Information?

CALL OUR TOLL FREE NUMBER

(800) 854-7086

In California Call Collect: (619) 292-0242

## Electronic Solutions

9255 Chesapeake Dr., San Diego, CA 92123 (619) 292-0242 Telex II (TWX): 910-335-1169

Fully Multibus Compatible, Terminated Mother Board.

## **MULTI-CAGE**

Note: Multi-Cage is a registered trademark of Electronic Solutions Multibus, trademark of Intel.

CIRCLE 93

# SWITCH

As the electronics industry advances, you can't afford to be left behind. The obvious choice for efficiency is switch mode. And the obvious choice for switch mode power supplies is...

Permag, the world's largest dis-

tributor of permanent magnets, magnetic assemblies, switch mode power supplies and linear ferrites, offering the most sophis-

ticated fabrication procedures and the most comprehensive engineering expertise you can find.

To Switch Mode Power Supplies
And To Ferrites From

PERMAG

400 Karin Lane, Hicksville, NY 11801

Please send your latest Linear Ferrites Catalog.

Have salesman call

Name

Company

Address

City

State

Phone

## POWER SUPPLY SPECIFIERS

See Deltron's New Linear Power Supply Catalog

IF YOUR
COPY
IS MISSING,
CIRCLE
THE NUMBER
BELOW.



TOLL FREE: 800-523-2332

P.O. BOX 1369 WISSAHICKON AVENUE NORTH WALES, PA 19454 PHONE: 215/699-9261 TWX: 510/661-8061

INTERNATIONAL UNIT:

DELAIRE CO. DUBLIN, IRELAND TELEPHONE: (01) 851411 TWX: 30442 DEL EI PREFIXES: UK (0001) INT. + 353 (1)

CIRCLE 94

## We're a *POWET-TWO* in WORLD CLASS LINEARS .

- 15 to 250 Watts
- Up to 200,000 hours MTBF
- UL, VDE, ĆSA, IEC Safety FCC, VDE EMI
- **Worldwide Input**
- 1 to 3 Outputs
- **3 Year Warranty**

Deltron inc. | POWER SUPPLIES

## Voltage/Current Ratings - World Series and Regular Models

SINGLE OUTPUT

REGULAR MODEL	WORLD SERIES MODEL	VOLTAGE VOLTS	CURRENT AMPS	CASE
VQ5-3C	W100A	5	3	Α
VQ5-6C	W101B	5	6	В
VQ5-9C	W102C	5	9	С
VQ5-12C	W103D	5	12	D
Q5-18C	_	5	18	F
Q5-27C	_	5	27	G
VQ12-1.7	W104A	12	1.7	Α
VQ12-3.4	W105B	12	3.4	В
VQ12-5.7	W106C	12	5.7	С
VQ12-6.8	W107D	12	6.8	D
Q12-10.8		12	10.8	F
Q12-17.1	_	12	17.1	G
VQ15-1.5	W108A	15	1.5	Α
VQ15-3	W109B	15	3	В
VQ15-4.8	W110C	15	4.8	С
VQ15-6	W111D	15	6	D
Q15-9.5	_	15	9.5	F
Q15-14.4	_	15	14.4	G
VQ24-1.2	W112A	24	1.2	A
VQ24-2.4	W113B	24	2.4	В
VQ24-3.6	W114C	24	3.6	С
VQ24-4.8	W115D	24	4.8	D
Q24-7.2		24	7.2	F
Q24-9.9		24	9.9	G
_	W116A	48	0.5	Α
	W117B	48	1.0	В
_	W118D	48	3	D

All 5 Volt single output units have a built in fixed crowbar overvoltage protector. World Series multiples also have this type of built in crowbar on output #1 when its voltage is specified as 5 Volts only. Crowbar protectors are optionally available on other models and are selected from the chart below.

Voltage Range	0-15 Amp	15-36 Amp	
6-15	CB41	CB51	
15-30	CB42	CB52	

#### **DUAL AND TRIPLE OUTPUTS**

Corresponding ratings separated by slash marks are alternate field selectable ratings for the designated output.

STANDARD MODEL	WORLD SERIES MODEL	OUTPUT #1		OUTPUT #2		OUTPUT #3		CASE
		VOLTS	AMPS	VOLTS	AMPS	VOLTS	AMPS	CODE
CP20800	W208A	5/12/15	.4/1/.8	5/12/15	.4/1/.8	_	_	1/DA
CP20900	W209B	5/12/15	.7/1.7/1.5	5/12/15	.7/1.7/1.5		_	2/DB
CP21000	W210C	5/12/15	1.5/3.4/3	5/12/15	1.5/3.4/3	_	_	3/DC
CP20500	W205C	5	2	12	4	_	_	3/DC
	W214A	5	2	24	.5/1.7p		_	1/DA
CP20000	_	5	3	5	3	_	_	1/DA
CP20100	_	5	6	5	6	_	_	3/DC
CP20200	_	5	2	5/9-15	.3/.6		_	1/DA
CP20300	_	5	3	5/9-15	.6/1.3	_	- 1	2/DB
CP20400		5	6	5/9-15	1.2/2.5	_	_	3/DC
CP20600	_	5	1.5	12	1.8/3.2p	_	_	2/DB
CP20700		5	.8	12	1.1/1.7p	_	_	1/DA
CP21100	_	18-20/24	.4/.6	18-20/24	.4/.6	_		1/DA
CP21200	_	5	.5/.7p	12	.9/1.8p		_	1/DA
CP21300		5	3	24	1.2	<del>-</del>	_	2/DA
CP300000	W300A	5	2	5/9-15	.2/.4	5/9-15	.2/.4	1/TA
CP301000	W301D	5	3	5/12/15	.4/1/.8	5/12/15	.4/1/.8	4/TD
_	W318D	5	6	5/9-15	.7/1.5	5/9-15	.7/1.5	4/TD
CP302000	W302E	5	6	5/12/15	.7/1.7/1.5	5/12/15	.7/1.7/1.5	5/TE
CP303000	W303E	5	8	5/12/15	.7/1.7/1.5	5/12/15	.7/1.7/1.5	5/TE
CP304000	W304F	5	12	5/12/15	.7/1.7/1.5	5/12/15	.7/1.7/1.5	6/TF
CP313000	W313F	5	6	12	1	24	4	6/TF
CP308000	W308E	5	3	5	.6	24	5/6p	5/TE
CP305000	W305G	5	12	5/12/15	1.5/3.4/3	5/12/15	1.5/3.4/3	7/TG
CP306000	_	5	1	5	.5	24	1.5/1.7p	4/TD
CP307000	_	5	2.5	5	.5	24	3/3.4p	5/TE
CP309000	_	. 5	9	12	.8	24	.5/4.5p	5/TE
CP310000	_	5	2	12	.4	12	.4	1/TA
CP311000	_	5	1.7/2.2p	5	.15/.2p	24	.2/3p	4/TD
CP312000	_	5	3	5	.6	24	4	5/TE

CP Models can be fitted with a crowbar OVP option on one or more outputs. A code number 1 in any of the positions following the root 5 character model designator defines this option.

## Specifications - World Series and Regular Models

Input

100, 117, 220, 230, 240 VAC ±10%, 47-440 Hz. Derate output current 10% for 50 Hz. operation. Consult factory for 400 Hz. operation. Regular models 115/230 VAC ±10%.

Output

See table of models. Outputs are adjustable ±5%.

**Operating Temperature** 

0°C to 50°C full rated, derate linearly to 40% at 71°C. Single output regular models derate to 50%.

Storage Temperature

-20°C to 85°C.

**Dielectric Withstand Voltage** 

World Series Models
Input to ground - 3750 VAC
Input to output - 3750 VAC
Output to ground - 500 VAC

Regular Models
1250 VAC
1250 VAC
300 VAC

Leakage Current

5 microamps typical line to ground. Regular models 20 microamps.

Creepage Distance

Greater than 6 mm line connected metal parts to dead metal.

Line Regulation

±.05% for a 10% line change.

**Load Regulation** 

±.05% for a 50% load change.

Ripple & Noise

1 mv rms, 5 mv p-p.

**Peak Currents** 

Numbers after a slash mark followed by a lower case "p" are surge ratings that units deliver for approximately 500 milliseconds.

**Temperature Coefficient** 

0.03% per °C.

Stability

±0.1% typical for 8 hours after warm up.

**Recovery Time** 

30 microsec typical for full line changes or 100% load increase.

**Remote Programming** 

1000 ohms per Volt approximately.

**Remote Sensing** 

Built in capability with loss of sense protection.

**Overload & Short Circuit Protection** 

Adjustable auto-recovery foldback current limiting; time delayed with a second foldback loop in units with surge current capability.

**Reverse Voltage Protection** 

Provided on outputs and pass elements.

**Overvoltage Protection** 

All 5 Volt models have built in fixed crowbar. Optional fixed crowbar OVP for other models.

Interface

Input solder lugs, output barrier block terminals.

Mounting

3 to 4 mounting surfaces, 5 orientations.

Mechanical

Refer to drawings for dimensions, parts locations and weight.

Vibration & Shock

Per MIL-STD-810C

## World Series Models Meet Worldwide Safety Requirements, Regular Models Meet UL, CSA Requirements.

UL UNDERWRITERS LABORATORIES, INC. UL 1012 — Power Supplies

**UL 478** — Electronic Data Processing Units and Systems

CSA CANADIAN STANDARDS ASOCIATION
CSA 22.2, No. 143-1975 — Office Machines
CSA 22.2, 154-1975 — Data Processing
Equipment

IEC INTERNATIONAL ELECTRO-TECHNICAL COMMISSION

IEC 380 — Safety of Electrically Energized Office Machines

IEC 435 — Safety of Data Processing Equipment

VDE VERBAND DEUTSCHER ELECTRO-TECHNIKER

> VDE 0730, Part 2P — Business Machines VDE 0804/3.77 — Telecommunications and Electronic Data Processing Equipment

BPO BRITISH POST OFFICE TECHNICAL GUIDE No. 26


ECMA EUROPEAN COMPUTER
MANUFACTURERS ASSOCIATION


**ECMA - 57** — Safety Requirements for Data Processing Equipment


CEE INTERNATIONAL COMMISSION ON RULES FOR THE APPROVAL OF ELECTRICAL


**EQUIPMENT CEE 10, Part 2P** — Specification for Business Machines.


## Dimensions - World Series and Regular Models (inches/mm)














Note: Flap cutout may be missing on regular models



P.O. BOX 1369 ■ WISSAHICKON AVENUE, NORTH WALES, PA 19454
PHONE: 215/699-9261 TWX: 510/661-8061
REPRESENTED BY:

International Unit: **DELAIRE**, SALLYNOGGIN ROAD, DUN LAOGHAIRE, CO. DUBLIN, IRELAND
TELEPHONE: (01) 851411 PREFIXES: UK (0001) INT. +353 (1) TWX: 30442 DELT EI

## 188 variable RF coils. At very affordable prices.



If you need variable inductors in the range from .05 uH to 1100 uH, no one gives you a wider selection than Coilcraft. And no one gives you lower off-the-shelf pricing!

Coilcraft tuneable RF coils are designed to meet MIL specs. They feature compact 10mm or 7mm packaging, optional shielding, and one-piece construction for maximum stability.


For special inductance or Q values, we'll custom-build coils to your specifications and still save you money!

For all the details on Coilcraft tuneable RF coils or our other inductive devices, call 312/639-6400.

**Experimenters Kits.** Choose kits covering the range from .0425 to 1.5 uH or from .70 to 1143 uH. Kits include shielded and unshielded samples along with detailed specifications. Each costs \$60, applied against your first order. Call 312/639-6400 to order.



**Chip Inductors** 



**Current Sensors** 



**Power Inductors** 



**Axial Lead Chokes** 

Coilcraft
1102 Silver Lake Rd., Cary, IL 60013

CIRCLE 231

## ebreathers from Gould e competition

Great leaps in raw performance are rare in the computer world.
Usually, changes occur in increments of half-a-MIP or so. Now real Firebreathers roar into the arena, quadrupling the best the competition has to offer.

#### With scorching speed.

These creatures don't run a little faster. Running real production code supplied by VAX™ users, our PowerNode™ 9000 benchmarks at 4.5 times faster than the VAX 11/780...at a comparable price! Even our second-in-line

PowerNode 6000 runs 1.5 times faster. But with all this power and speed, the PN6000 has a dainty footprint...60% less than the VAX 11/780.


Even the hottest firebreather won't fly if it's hard to run. Ours are UNIX\*-based, so ease of use and compatibility become part of the power. Plus we offer the "Compatibility Suite", application software packages which are consistent across our entire Gould PowerSeries product line... the widest range of UNIX-based systems in the world.

We know these claims sound outrageous. Make us prove them. Give us your benchmarks and production code. We'll show you

Gould Inc.,
Computer Systems Division
Distributed Systems Operation
6901 West Sunrise Boulevard
Ft. Lauderdale, FL 33313
\*UNIX is a trademark of AT&T Bell
Laboratories

MPowerNode and PowerSeries
are trademarks of Gould Inc.

MVAX is a trademark of Digital
Equipment Corp.



#### **D**ESIGN ENTRY

## Associative memory calls on the talents of systolic array chip

A monolithic systolic array puts its on-chip memory to good use, first searching out the desired information and then processing it.

This is the fourth in a series of articles dedicated to the first commercial systolic array processor chip. The series began with the cover article in the Oct. 31 issue (p. 207) and has continued in every consecutive issue.

classic problem for designers. Theoretically, one of the simplest ways to get information is to match the memory contents with the desired key, much as an instructor calls upon pupils to volunteer an answer to a question. However, processors traditionally force programmers to call memory using addresses. That scheme often makes for relatively slow processing. Searching through a set of numbers for the one with the highest value, for instance, typically forces a von Neumann processor to examine each member in the set at least once.

An alternative is an associative memory system, which matches some part of the desired data within memory instead of requiring addresses. Known by a host of names, including content-addressable memory, data-addressed memory, parallel search memory, and search

associative memory, the technique has been called into service a number of times in various applications. But such systems are usually fairly large and expensive.

The Geometric Arithmetic Parallel Processor, or GAPP, takes a new approach to this long-standing dilemma. The first systolic array processor chip, the device is not only well suited to associative memory but can be configured in a comparably small system as well. Further, since it performs logical and arithmetic operations, it also serves as an associative processor that works on the data found in a memory search.

The chip carries 72 single-bit processors that run in parallel as a single-instruction, multipledata path system. Each processor element is fitted out with 128 bits of dedicated RAM. Also vital to associative memory is the IC's global broadcast function, which lets users transmit data, such as the search word, to all of the processor elements simultaneously.

The tremendous speed advantage of parallel processing over conventional methods is demonstrated in the relative time needed to perform associative memory searches. Searching for a single number in a set with N members, a traditional processor running an algorithm that lets it look just once at each number takes up to N cycles to locate the desired data. The associative processor, in contrast, needs M cycles, where M equals the number of bits in the target

#### Lyle Wallis, NCR Microelectronics

Lyle Wallis is an applications engineer at NCR's Microelectronics Division in Fort Collins, Colo. He holds a BSEE from the University of Missouri at Columbia and an MSEE from the University of California at Berkeley.

#### Systolic array chip


information. The device interrogates the memory entries in parallel, and once the proper information has been found, it can be either processed by the associated processor or passed directly to the host.

An associative memory unit can be broken down into two main components: an associative array and an associative array controller (Fig. 1). The arrangement is similar to traditional memories, which consist of an array of addressable cells and a controller.

#### Other functions

In addition to managing the memory, the controller also handles sequencing. It contains two registers: one holds the data that the host is looking for, called the "comparand"; the other contains a mask, which screens out unwanted bits during processing.

The associative array comprises a group of cells, each of which generally holds a single



1. An associative memory consists of a controller and an array of memory cells. The first section manages the second and stores the target word-or comparand—and the mask, both of which come from the host. The tag bits attached to each cell denote what data is located at any one.

word. Each cell has a tag bit to notify the controller when its data matches the sought-after word. When there is a match, the tag bit is set and that cell is termed a responder. If the desired data is not in that cell, the tag bit remains unchanged and the cell is dubbed a nonresponder.

Every cell within an associative array also performs three tasks—compare, write, and read. The first and most fundamental task simply compares the masked target data with the contents of the cells, setting the tag bit if there is a match. The second then writes a data word to the responding cells. Read, the final function, shifts the contents of the responding cells to the output bus. If there is more than one responder, the output is the bit-by-bit logical OR of all the responding cells. These three functions are carried out only on data in the responding cells; nonresponding cells are untouched.

This architecture can easily implement the associative memory and handle associative processing tasks. The feature set of the systolic array chip performs all the operations needed to form an associative array, and when coupled with a programmable control circuit, it also serves as an associative processor.

#### **Maintaining control**

The GAPP chips themselves form the associative array. However, since these devices do not have any control features, an external controller must be used to sequence the array and to oversee the target-word and the mask register. It consists of a control store, address sequencer, and host computer (Fig. 2).

The associative array can be built in various sizes, since the chips can be ganged together to create larger arrays. Because each processor element within a grid of chips is a serial processor, word widths greater than one bit must be emulated serially. The on-chip RAM lets the elements handle a variety of word widths, as well as multiple words and multiple tag bits since every RAM location is individually addressable. Further, there will be some RAM left over that can be used as a scratchpad or for storing arithmetic operands and other data.


Input and output for the full array are handled via the communications (CM) bus. Input usually comes from traditional processors in word-serial and bit-parallel form. However, because processor elements accept only word-parallel and bit-serial data, incoming information must be reformatted. This job, often referred to as corner turning, can be implemented with GAPP devices or with special parallel-to-serial circuitry.

#### Doubling up

The north/south (NS) register of the chip pulls double duty, acting both as a place to store the tag bit and as an area to carry out various functions. The tags of all the processor elements can be quickly sent to the controller using the global output signal (see first article in series, ELECTRONIC DESIGN, Oct. 31, p. 207, for definition of global output). Several GAPP chips can then be combined in a wired-OR configuration to generate a responder signal for the control unit.

The control section can be set up in a number of ways, but the most effective is to use a programmable controller. Whatever route is taken, though, the controller remains responsible for generating instructions and addresses for the array and for sampling the output of the responder detection circuit. The control store receives its list of instructions from the host. Bit serial data can quickly be sent to all processor elements using the global input, which is easily accomplished by employing the op code lines to command the C register to load either a 1 or a 0.

Programming the associative processor is different from programming a conventional processor with RAM. That is due both to the different type of search involved and to the array's architecture. In operation, the instructions supplied by the control unit to the associative array are mnemonics for the chip. The control-



An associative memory controller (highlighted) consists of a control store, which holds commands coming from the host, and a sequencer. The sequencer can use data from responders to branch to another part of a program.

#### Systolic array chip

ram(tag):=c, ns:=c;

ler language in the algorithms used by the chip employs a syntax similar to that of the Clanguage. References to the bits in the mask and target-word registers take the form of a bit number. The register's MSB is assigned a 0, and the LSB is designated M-1, where Mequals the word length. The RAM associated with each processor element is similarly labeled, with the

#### Program 1. Making a comparison /\* Compare function \*/ /\* Load the NS and EW Registers\*/ if (value ==0) ew:=0, ns=ram (addr), c:=1; else c:=1; ew:=c, ns:=ram (addr); /\*EXNOR into NS reg\*/ ns:=ram (temp),ram(temp):=sm; /\*AND result with TAG\*/ ew:=ram(tag),c:=0, ns:=ns;c := cv/\*place results in RAM and NS\*/

#### /\* TAG exists in NS \*/ /\*load tag into R\*/ c:=0, ew:=0: ram(R):=sm; /\*Loop for every bit in the word\*/ for(i=0; i < M, i++) $if(mask(i) == 1)then{}$ /\*Load ew and ns with the values to be compared\*/ if (comparand(i) = = 0)then ew:=0, ns:=ram(cell+i); c:=0; else c:= 1: ew:=c, ns:=ram(cell+i), c:=0; /\*EXOR operands\*/ ns:=ram(temp), ram(temp):=sm; /\*Update R bit and tag\*/ ew:=ram(R): c:=0;c := cy;

Program 2. The match game

contents of the data word appearing in locations "Cell" through "Cell + M-1". Response bits are stored in additional RAM locations and are typically used by the algorithms.

#### Time for our program

Since, as noted, a system consisting of GAPP chips is bit-serial, the most effective primitives are 1 bit wide. The bit-wide comparison primitive (Program 1) loads the comparand bit into all of the processor elements using one instruction, an important technique for parallel data input. This is accomplished by using the set 0 instruction of the East/West (EW) registers and the set 1 instruction of the C register.

The compare algorithm also makes use of a time-saving scheme concerning the tag bit. Since the NS register, which normally retains the tag bit, is needed for many other tasks, the bit is simultaneously written to a RAM location reserved for the tag (last line of Program 1). At the completion of any function that reports results by marking the responders using the tag. the tag bit also appears in the NS register.

In each of the responding cells, the compare algorithm sets the tag bit if the value residing at a given RAM address (addr) matches the value sent from the host. This address can be any number between 0 and 127.

The algorithm starts off by first loading the NS register with the value stored at addr. At the same time, the EW register is loaded with the value sent from the host. Next, the EW and NS registers are exclusive-NORed, and the result is placed in the NS register, where it is ANDed with the tag bit. The result of the last operation is placed in both the tag location and in the NS register. Although this describes a 1-bit search, it could easily be invoked repeatedly to operate with larger words.

#### Five or six cycles


Only five cycles are needed to compare a 0, six to compare a 1. In all of the examples, the assumption is made that the controller can keep the associative array operating at maximum speed at all times, so that no wait stages are required.

Primitives such as compare increase the power available for larger programming tasks and also simplify the programmer's chores. The

ram(R):=c, ns:=c;

### COMPLEMENTARY DMOS:

THE PERFECT FIT FOR YOUR HIGH VOLTAGE INTERFACE



Supertex has added high voltage. N and P channel DMOS power FETs to our popular low voltage, complementary product line. Available in both commercial and military grades, this complete family of complementary power FETs ranges from 20 to 600 volts.

Supertex High Voltage DMOS FETs are ideally suited for your low level logic to high voltage interface. They feature low threshold voltage, low input capacitance and fast switching times. Our high voltage products are used throughout the world in many applications, most notably telecom-

munications, ATE, solid state relays and flat panel displays. For more information regarding Supertex's DMOS FET line, please ask for DMOS Marketing: (408) 744-0100.



Leadership in CMOS and DMOS Technologies 1225 Bordeaux Drive Sunnyvale, CA 94089 (408) 744-0100 TWX 910-339-9388



BVDSS Min (V)	RDS (ON) Typ (ohms)	ID PULSED** Max (A)
200-350	7-13	1.5
350-600	1.8-4.5	5.0
350-500	25-45	0.5
350-600	6-15	2.0
350-500	4-5.5	3.0
350-500	45-75	0.25
350-500	14-25	1.0
200-400	250	75mA
200-400	550	40mA
	200-350 350-600 350-500 350-500 350-500 350-500 350-500 200-400	Min (v) Typ (ohms)  200-350 7-13 350-600 1.8-4.5 350-500 25-45 350-600 6-15  350-500 4-5.5 350-500 45-75 350-500 14-25  200-400 250

\*Available 4th quarter 1984. All other products available in production quantities.

\*\*Max. ID will depend on package type and voltage rating.

#### Systolic array chip

ease of using primitives can be seen in the exact match function, which differs from the compare primitive only in that the latter emulates a bit-parallel machine by operating on a word bit by bit.

As in the foregoing example, the responders are searched for an exact match to the masked target-word register, with matches indicated by setting the tag bit. Specifically, a response bit is maintained at location R in the RAM (Program 2). If R is set, that particular cell contains a possible match to the broadcast data. If R is clear, that cell does not contain a possible match. At the end of the algorithm, all cells marked as possible matches are determined to be exact matches for the full word. This approach takes 5.5M+2 cycles, with M again representing the number of bits being compared. (This rate assumes that the number of 1s and 0s is equal.)

The write primitive is also handled with a bit-wide scheme. It, too, can be repeated for larger words. In this algorithm, the tag bit is restored to the NS register near the end of the

#### **Program 3. A writing lesson**

```
Write function *
/*Load contents of addr into ew*/
ew:=ram(addr), c:=0;
/*produce AND of not(tag), assumed to be in NS, with
contents of addr*/
c := bw:
ram(temp):=c, c:=1;
/*load value into ew, tag assumed to be in NS*/
if(value = = 0)
  ew:=0, c:=0;
 ew:=c, c:=0;
/*AND value and tag*/
/*Load intermediate values in anticipation of OR*/
ns:=c, ew:=ram(temp), c:=1;
/*perform OR and restore tag*/
c:=cy, ns:=ram(tag);
ram(addr): = c;
```

program to ensure that multiple invocations will proceed smoothly. The restoration is combined with an OR operation, so no added cycles are demanded.

#### First, load the cells

The write algorithm begins by placing a Boolean value into each of the responder cells (Program 3). Since the chip treats all locations equally, some care must be taken to write only to the responders. To be sure that the nonresponding cells are not modified, the tag bit for each responder must first be inverted and then ANDed with the data in RAM.

Once this is done, the tag of the original responders is ANDed with the new value. The results are then ORed together; this effectively blocks the nonresponders from accepting the new value. The data is then written into the addr of the responders.

As mentioned, these primitives can be used as building blocks for more complex tasks. A limit search, for example, finds the set of responders with a value greater than, greater than or equal to, less than, or less than or equal to a particular number. All of this can be done with just the compare and write algorithms. Basically, all the responders are designated as greater than, equal to, or less than the desired value. Once that is done, it is simple to select any combination of sets.

#### Call and response

The three response bits, X, Y, and Z, all are held in RAM (Program 4). The first either indicates equality or denotes an undecided state that requires further processing. The second designates greater than, and Z signifies less than. Initially, all responding cells are set to the undecided state, or 100. If the MSB of the target number is a 1, then all the undecided elements have a 0 as their MSBs will be marked less than. If the target's MSB is a 0, all the elements that show a 1 as their MSBs will be marked greater than. This sequence continues through the full number of bits making up the target, and at the end of the word, those cells in which all bits are undecided are determined to be equal to the desired number. The limit search takes 24+29M cycles.

Once a responder or class of responders is

#### 10T7216/7217 HIGH SPEED 16x16 BIT PARALLEL CMOS MULTIPLIERS MILITARY -55°C to +125°C Voc = 5v ± 10%, TA = Power Supply Current Icc (mA) Clocked Multiply COMMERCIAL $Voc = 5v \pm 5\%$ , $T_A = 0^{\circ}C$ to $70^{\circ}C$ Time t<sub>Mc</sub> (ns) 100 Power Supply Current Icc (mA) 80 ALL DEVICES AVAILABLE IN 64 PIN DIP, 68 PIN LCC, AND 64 PIN FLAT PAK Clocked Multiply Time t<sub>Mc</sub> (ns) 65 75, 90, 140

In the past you probably didn't even consider using multipliers in your system design for obvious reasons: high power consumption, heat build-up, low reliability, large power supplies, elaborate cooling schemes, and more... Now all that's over.

#### IDT'S HIGH SPEED 16x16 BIT CMOS MULTIPLIERS.

Thanks to our unique leading edge CEMOS™ technology, our IDT7216/7217 multipliers run incredibly fast at extremely low power levels. Now, for the first time, the tremendous performance advantages of the digital signal processing design approach become viable in such diverse systems as video image enhancement, high-speed color graphics, speech synthesis, voice recognition, telecommunications, pattern generation, robotics control, data communications, radar, sonar, countermeasures, medical systems...

How about your system?

LOW POWER. Our IDT7216/7217 multipliers feature ½12 the power consumption of equivalent ECL or bipolar products. Look at the chart—we're not talking almost 5 watts. The cool running of CMOS significantly enhances system reliability, increases packing density and reduces the need for large power supplies and cumbersome cooling apparatus. No need for auxiliary air or liquid cooling. And our IDT7216/7217 multipliers allow the use of LCCs that weigh only ½10 as much and take up less than ½ the board space of dual-in-line packages.

HIGH SPEED. The speed of bipolar. These advantages are made available without sacrificing speed. Look at the chart. Commercial speeds of 65ns (15MHz). Military speeds of 75 ns (13MHz).

**RELIABILITY.** Our military parts are 100% screened to MIL-STD-883, Method 5004. Commercial versions differ only in burn-in time and electrical test temperatures.

**AVAILABILITY.** All speed, power and package options are available off-the-shelf.

**DSP FAMILY.** Our 16x16 multipliers are the first of a family of high-performance CMOS DSP circuits. An exciting series of high speed/low power devices are in development for introduction later this year. They will continue to make your job easier.

**EVALUATION SAMPLES.** Write us about your application on your letterhead and we'll send you an evaluation sample of our IDT7216/7217 multiplier.

**CMOS SOLUTIONS.** We also supply the world's fastest CMOS 16K static RAM family, 64K static RAM modules and memory support logic products. And that's just the beginning.

**MAY WE BE OF ASSISTANCE?** Call or write today for complete information on our 16x16 bit multipliers and our other CMOS system solutions.

Integrated Device Technology, Inc. 3236 Scott Blvd., Santa Clara, CA 95051 (408) 727-6116 TWX 910-338-2070

CEMOS is a trademark of Integrated Device Technology, Inc.



**Integrated Device Technology** 

#### Systolic array chip

identified, it is often important to interrogate the array to read its values. The most obvious way to accomplish this is to shift the contents of each cell out via the CM bus. The data words would have to be prefaced by the tag bit, so that the external circuitry can determine which of the words are responders. Obviously, this approach operates on both responders and nonresponders, but this will not matter in many applications.

Nevertheless, there are two drawbacks to this method. First, if a large array is chosen to increase throughput, the time needed to shift all the data out can be significant (see the table below). Second, the requisite external circuitry

#### Program 4. In search of limits /\*Mark all elements as undecided\*/ WRITE(X, 1); WRITE(Y, 0); WRITE(Z, 0); /\*Loop through all bits\*/ for(i=0;i< M,i++)/\*Reset Tag\*/ ns=0: if(comparand(i) = = 0)/\*locate all undecided cells\*/ COMPARE(X, 1); /\*locate greater than cells\*/ COMPARE(cell+i, 1); /\*mark responders as greater than\*/ WRITE(X, 0); WRITE(Y, 1); /\*locate all undecided cells\*/ COMPARE(X, 1); /\*locate less than cells\*/ COMPARE(cell+i, 0); /\*mark responders as less than\*/ WRITE(X, 0); WRITE(Z, 0);

Loading or read	ling time for	a single-bit	plane
Dimensions of array (processor elements)	Total number of processor elements	Total number of GAPP chips	I/O shift time (µs)
48 × 48	2304	32	4.8
132 × 132	17,424	242	13.2
516 × 516	266,256	3698	51.6
1032 × 1032	1,065,024	14,792	103.2

inherent to this scheme is substantial. However, in tasks like image processing, where large portions of the data are of interest, this still might be an effective technique.

#### A question of comparison

A second approach simply employs the compare instruction to read the value of a bit using the responder signal. Comparing addr with a 0 effectively shifts the data in along with the responder signal, where it can then be shifted into the target-word register. A compare between the addr and 1 shifts the inverted data in with the responder signal. If there is more than one responder, the OR of all the data bits is positioned on the responder signal.

This method can be called into play when it is necessary, for instance, to establish the numbers of pixels that are at their maximum values. The algorithm for determining which of the words in memory has the highest value uses the responders first as decision-making data and then to read the maximum value. The first two steps of the following algorithm effectively amounts to an instruction that sets all the tag bits:

```
for (i=0; i< M, i++)
/*search for undecided cells*/
SET;
COMPARE(R, 1);
COMPARE((CELL+i), 1);
if (RESPONDER)
    WRITEN(R,0);
```

The program first scans all the memory cells. looking at the most significant bits. If any cell has a 1 in that position, it is noted that it holds the highest value. All the cells with 0s are marked as storing less than highest. When the bits are all processed, the cells containing the highest value at each bit are determined to contain the maximum word value. This will take 14 cycles for each bit of the data.

#### Cutting down on overhead

The program uses the compare algorithm whether or not the data is to be read out. It is possible, though, to read the contents of a cell without incurring the overhead associated with the exclusive-OR used in a comparison. The



#### Systolic array chip

third read does just that, employing the responder signal supplied by the associative array to read the value of the responding cells. Doing so places the data in the responding cells at addr in the NS register. The routine:

```
/*Load ns with TAG*/
ns:=ram(tag);
/*Load ew with data*/
ew:=ram(addr), c:=0;
/*AND tag and data*/
c := cy;
/*Place results in NS*/
ns:=c:
```

makes good use of the fact that the tag bit is stored in memory, so it can be used consecutively a number of times. The read is called up by logically ANDing the tag at ram (tag) with the data at addr and then placing the results in the NS register.

A read of this type would be desirable whenever it is necessary to address portions of the array individually at a unique address—as with a conventional memory—instead of by the content of memory. This is done by loading the data words over the CM bus so that each elements holds a unique number in its RAM. An exact match search (using either primitives or the larger program) could then be executed and the cell contents read. On a grid of systolic arrays 516 elements on a side, the exact match would take a maximum of 114 cycles and the read would take  $4 \times M$  cycles.

#### Easing into associative processing

Once an associative memory has been built from GAPP chips, it is relatively simple to enhance it to create an associative processor. The primitives and techniques detailed permit a full range of searches, which can be combined with arithmetic or logical operations to further increase the system's capabilities.

As simple as it sounds, one of the functions most useful to associative memories is counting, or simply summing the number of responders. Its importance can be seen in a limit search, in which it might be vital to know how many bits fall within a set of limits. Doing so relies on the chip's ability to perform serial arithmetic, keeping track of the number of cells that have the tag bits set.

A related function, called first, lets users process the bits on an individual basis. Once it is determined that there are multiple responders, it becomes important to turn off all but the desired one, so that the others are not altered when the operation takes place.

One technique is to propagate a marker in the northwest corner cell of the array and carry it eastward along the top row until the eastern edge of the array is reached. It can then drop down a row and move in the opposite direction, continuing with its serpentine route across the full array. Since the marker resides in only one cell at a time, only that cell is on, so it is the only one being addressed at any given time. Sampling the responder after each shift of the marker makes it possible to know when the first responder has been reached. Another technique would be to prioritize multiple responders with the unique PE address.


A final algorithm takes advantage of some of the processor element's logical functions to calculate the number of bit positions by which the corresponding digits in each cell differ from those of the desired value. This number, or Hamming distance, forms the basis of numerous error correction codes. The algorithm:

```
/*Store Zero in COUNT field of all Candidates*/
for (i=0, i< M; i++)
   WRITE(COUNT+i, 0);
/*Compare all bits*/
for(i=0;i< M;i++)
   SET:
   COMPARE(CELL+i,COMPARAND(i));
   ADDONE:
```

is effectively a search for no match, which is followed by incrementing a count field in all responders. Once the Hamming distance is determined for each word in the associative array, a least-value search can be performed on the count field to find the word with the smallest distance. Every time no match is found, the counter is incremented by one.□

How useful?	Circle
Immediate design application	556
Within the next year Not applicable	557 558

## A NEW APPROACH TO INSTRUMENTATION AMPLIFIERS.




Introducing an easier approach to instrumentation. The new LTC1043. This dual precision CMOS switch circuit lets you build simpler instrumentation amps with performance previously impractical at the board design level.

Using the LTC1043, a few external capacitors, your favorite precision op amp, and two resistors to set gain, you'll have an instrumentation amp that rivals any IC, hybrid, or module currently available. And it even works on a single 5-volt power supply.

The LTC1043 consists of precision CMOS (LTCMOS™) charge balanced switches. As an

CIRCLE 99



LINEAR

LINEAR TECHNOLOGY CORPORATION 1630 McCarthy Boulevard, Milpitas, CA 95035-7487 PH: (408) 942-0810 instrumentation front end, it alternately connects a capacitor to a differential input signal and then to an output amplifier, extracting lowlevel signals from large common mode inputs.

The new LTC1043. It's a classic example of how smart technology can save you time and money. For 20 more unique applications of the LTC1043, including signal conditioning circuits, high accuracy voltage multiply or divide, sample and hold, F/V and V/F converters, and switched capacitor filters, contact us today.

LTCMOS is a trademark of Linear Technology Corp.

## **Signal Conditioning**

Here's How You Do It All—Easily:



#### To Amplify



**OPA111:** World's best JFET monolithic op amp with dielectric isolation—a super combination of low noise, low bias current, low drift, high O.L. gain—never before achieved.

- • Low noise
   1μV rms max

   • Low bias current
   1pA max
- Low offset voltage/drift... 250μV max, 1μV/°C max

Circle reader service no. 100



**INA101:** A high accuracy monolithic instrumentation amplifier.

- $\bullet$  Low offset voltage/drift . . 25 $\mu$ V max, 0.25 $\mu$ V/°C max
- Low nonlinearity . . . . . 0.002% max • Gain range . . . . 1 to 1000V/V

Circle reader service no. 101



**OPA201:** Innovative low power monolithic op amp has two separate precision input stages (selected by TTL signal). Use in synchronous detector designs and for simplified autozeroing systems. A new extremely versatile, circuit "building block."

- - Circle reader service no. 102

**OPA27/37:** Precision grade op amps offering ultra-low noise. For transducer and pre-amp applications

- Low noise . . . . . . . . 2.7nV/ $\sqrt{\text{Hz}}$  at 1kHz  $0.07\mu\text{V}$ , p-p, 0.1 to 10Hz
- Low offset voltage/drift. . 25μV max, 0.6μV/°C max
- High speed . . . . . . 1.9V/µsec (OPA27),
   11.9V/µsec (OPA37)

Circle reader service no. 103

#### To Condition



#### **To Transmit**



#### To Isolate



**ISO100:** Optically coupled monolithic isolation amplifier offers low drift, wide bandwidth and achieves isolation at lowest cost per channel avail-

0.07% max
c, 1µV/°C max
750VDC min
2500VDC

Circle reader service no. 104

3656: Both signal and power isolation are provided by this 1" by 1" by 1/4" IC package.

Innovative transformer coupling has 3-port isolation.

Isolation test	8000VDC min
Continuous isolation	3500VDC min
<ul> <li>Leakage 0.5μA max</li> </ul>	at 120V, 60Hz
Isolation mode rejection	125dB at 60Hz

Circle reader service no. 105

XTR100: 4-20mA two-wire current transmitter includes matched tracking current source to provide bridge excitation. Small enough to mount in thermocouple well.

Instrumentation amplifier input:
Low offset voltage/drift 25μV max, 0.5μV/°C max
Nonlinearity 0.01% max
• Wide supply range +11.6V to +40V

Circle reader service no. 106

MPY100: Precision monolithic analog circuit performs four-quadrant multiplication, division, square root, and squaring.


Circle reader service no. 108

**4302:** Multifunction converter can multiply, divide, square, exponentiate, root, sine, cosine, tan<sup>-1</sup>, etc. mathematical functions accurately.

Versatile .													E	0	$= V_Y (V_Z/V_X)^m$
Small size															. 14-pin DIP
				r	٠,	.,		e.	,,		١,				rvice no 100

DIV100: This analog divider is 100% tested over its full 40:1 denominator range.

•	Low error															(	).	2	5%	r	n	a	X
						_					4	_	_	_	_						4	1	n



REF10: High stability +10V reference is fully specified over its complete temperature range.


•	Low drift				. ,		,				1ppm/	°C max
	Very low noise											

Circle reader service no. 111

#### Plus...

A/D and D/A converters, sample/ hold, power amplifiers, rms-to-DC converters, peak detectors, oscillators, and filters that give you solutions to your signal conditioning design problems.

#### **To Convert**



VFC320/VFC62: High linearity—monolithic V-to-F converter; operates to 1MHz.

- 12 to 14 bit linearity
- Open collector output/active pull-up.
- 20ppm/°C max gain drift

Circle reader service no. 107



**Putting Technology To Work For You** 

(205) 882-0316, (206) 455-2611, (214) 681-5781, (215) 657-5600, (216) 729-3588, (301) 628-1111, (301) 251-8990, (303) 663-4440, (305) 365-3283, (305) 395-6108, (312) 832-6520, (313) 474-6533, (314) 291-1101, (315) 699-2671, (315) 853-6438, (316) 722-0104, (317) 636-4153, (319) 373-0152, (404) 447-6992, (408) 559-8600, (412) 367-1011, (505) 293-8555, (602) 746-1111, (607) 785-3191, (612) 884-8291, (614) 764-9764, (617) 273-9022, (713) 988-6546, (714) 835-0712, (716) 544-7017, (716) 889-1429, (801) 467-2401, (805) 496-7581, (813) 885-7658, (818) 991-8544, (913) 342-1211, (914) 964-5252, (919) 722-9445, CANADA: (403) 230-1341, (416) 678-1500, (514) 731-8564, (613) 722-7682

### DESTINATION: TRISTAR

#### A foundation for delivering semiconductor memories

Tristar premiers two new semiconductor memory products. The first examples of a long term dedication to excellence and market support. Engineered by minds whose first concern is the needs of a discriminating marketplace.

#### 64K Dynamic Ram

Tristar's KM4164A, featuring our first high density MOS Memory product, is now available for volume

delivery. The smallest die in the industry. Its design is fully optimized for high speed, high performance applications. With access times of 150 & 200 ns, the device is designed with a 256-4ms refresh cycle that provides easy upward compatibility with 256K DRAM.

#### **16K EEPROM**

Our 16K EEPROM is another beneficiary of the quality and yield of Tristar's and Samsung's class 10 fabrication facilities. The KM2816A is an industry standard for nonvolatile memory, providing the flexibility needed for micro-

processor-based systems to take advantage of real time changes in the operating software or data accumulation. On-board address and data latches. auto-timed byte write, auto erase before write, and 5 volt-only operation lead the list of special features of Tristar's 16K EEPROM. Additionally, twoline control eliminates bus contention, and the KM2816A also conforms to the JEDEC byte wide pinout standard.

#### Commitment to excellence


To create these products, we placed ourselves under stringent criteria.

Local engineering to assure perfection not only in technology, but in application as well. A class 10 fab line at Samsung's facilities in Korea assures the quality and yields that our customers have every right to demand. And throughout the process, superior service from the semiconductor industry's most dedicated professionals.

Tristar's memory products are available, in quantity, now. If you are looking for a memory supplier whose benchmark is excellence, come to Tristar. Your technology resource.



Santa Clara, CA 95054 (408) 980-1630



## THE COGITO HALF-HEIGHTS.





#### **DESIGN SOLUTION**

## Add-on circuit monitors trickle-charging system


#### Kenneth J. Ciszewski

Design Engineer 1929 Hurstgreen St. Overland, Mo. 63114

ealed lead-acid batteries, especially those employed in standby power systems, are too expensive and important to be supervised by a simple trickle charger. A circuit that keeps tabs on both the

battery and the charging system is a simple form of insurance against the loss of power and data due to an undercharged battery.

The circuit (Fig. 1) checks the charging system for a high-voltage condition, which would indicate an improper charger setting or the failure of the pass transistor. It also sets off an alarm if a low voltage is detected or if the battery fails to charge. The latter would suggest that the battery is disconnected, its wiring or



1. When added to a commercial trickle charger, this circuit monitors the condition of both the battery and the charger, keeping the user apprised of any faults.


terminals broken, or that it possibly has an open cell.

An operational amplifier, the LM334, forms the core of the circuit's three basic sections. These consist of a differential amplifier, A<sub>1</sub>, whose output is fed to comparator A2, plus a separate window comparator made up of  $A_3$  and  $A_4$ .

As long as the voltage output of the charger is between preset limits (here 22 and 28 V dc), no fault is indicated. If the voltage drops too low or goes too high, the appropriate LED lights. A common pull-down signal also is supplied for linking to an audible alarm, such as a Sonalert.

The voltage input to the comparator is halved by a voltage divider consisting of two 47-k  $\Omega$  resistors. Consequently, the window comparator's voltage references are simply set to one-half of the desired high and low limits (in this case, 14 and 11 V).

The voltage waveform across the charger's current-limiting resistor varies in amplitude, depending on whether the charger is connected



2. The sawtooth waveform across the charger's current-limiting resistor changes in amplitude to reflect the status of the battery. The level when the battery is connected (a) drops when a cell opens or the wiring is broken (b). A differential amplifier senses the difference to warn an operator of the fault.

to the battery or not (Fig. 2). First, A<sub>1</sub> senses the voltage, and A2 then compares A1's output with a fixed reference that is set by a 15-V zener diode and a 100-k  $\Omega$  potentiometer. When the peak value of the charger's sawtooth waveform exceeds the reference, A2 charges capacitor C through transistor  $Q_1$  and diode  $D_1$ . That, in turn, drives transistor Q2, keeping transistor Q3 turned off.

If the battery fails to draw sufficient charging current, the comparator no longer charges the capacitor and Q<sub>3</sub> both turns on a fault LED and furnishes a common fault signal, through diode D<sub>2</sub>, to the alarm. Transistor Q<sub>4</sub> inhibits the fault signal when no voltage is applied to the positive sensing input of the differential amplifier. That saves standby power when the battery is not being charged because of a power outage.

The window comparators' voltage references are set to the nominal values shown in the schematic by using a high-impedance voltmeter to monitor the voltage on the wipers of potentiometers  $R_1$  and  $R_2$ .


The inputs to A<sub>1</sub> are protected against voltages in excess of 32 V dc by 10-k Ω voltagedivider resistors. To adjust that amplifier, its sensing inputs must be shorted and potentiometer R3 set for a 0-V dc reading at the amplifier's output. When the entire circuit is properly adjusted, the battery is connected to the charger and the differential and the singleended sensing inputs attached to the currentlimiting resistors and the charger outputs.

By carefully watching an ammeter connected to the points shown, the battery should be allowed to charge until the current reaches the minimum value specified by the charger manufacturer. Then, potentiometer R<sub>4</sub> should be adjusted so that the battery-disconnect and failure-to-charge LED goes out. To test the circuit, one lead of the battery should be momentarily disconnected to emulate a fault. The LED should turn on but go off again when the lead is reconnected. If the charging current is again allowed to fall to its minimum value, the batterydisconnected LED should remain off.

A lamp-test switch connected to -24 V dc helps check the LEDs. When the switch is pressed, all the LEDs should turn on and the alarm should sound.

## BRAND-X or POWER-ONE FLEX?

"An Unfair Comparison"



#### You Shouldn't Compare Apples and Oranges

We apologize for our unfair comparison. But when it comes to POWER-ONE's new FLEX-Series D.C. power supplies, there really isn't anything comparable on the market.

Based on II pre-designed case sizes, with power ratings from 10 to 400 watts, the FLEX-Series dramatically simplifies the development of custom power supplies. You can specify the exact output ratings and options you want... at a fraction of the cost and time of a full custom design!

#### **Built to Your Exact Requirements**

With the FLEX-Series you pay only for the features you specify. And using our "Total Package" concept there's no additional assembly labor, no extra parts to buy. As for options, you name it. Virtually any output voltage and current combination is available. There's connectors, fans, covers, front panel assemblies; there's power fail monitoring, high surge current capabilities and much, much more.

#### Safety Approved Worldwide

The FLEX-Series is certified to the world's toughest safety agency requirements. Which means

you can take delivery of an internationally approved power supply, built to your exact specifications, in the shortest leadtime in the industry!

#### Call for a Quotation

Whatever your quantity needs — large or small — the FLEX-Series will save you time and money. Plus, it's POWER-ONE proven. So call today for a FLEX-Series quotation. Or get the full FLEX-Series story in our new 1985 Catalog. You'll agree that all other custom power supplies are nothing more than BRAND-X when compared to the flexible FLEX-Series.

"Innovators in Power Supply Technology"



#### POWER-ONE LINEAR PRODUCTS

740 Calle Plano • Camarillo, CA 93010-8583 Phone: (805) 987-8741 or (805) 987-3891 Call Toll Free from California: (800) 421-3439 Outside California: (800) 235-5943



















#### Gate and instruction place nonmaskable interrupt under software control


#### **Vittal Rao**

Engineer Digital Systems Section ISRO Satellite Centre Airport Road, Vimanapura PO Bangalore: 560 017 India

f an application needs one more interrupt than is normally provided by an 8085 processor, the expense of an 8259 programmable interrupt controller may be unwarranted and unnecessary. A AND gate plus one of the processor's instructions can do the trick.

Most microprocessors have a nonmaskable interrupt, called Trap on the 8085. That pin cannot be masked by the designer but the simple AND-gate circuit (see the figure) places it under software control.

The gate's inputs connect to the external device and the processor's serial output data (SOD) line. The output goes to the Trap pin. By



The AND gate helps place the 8085 processor's nonmaskable interrupt pin under software control.

executing the Set Input Mask (SIM) instruction, the interrupt can be alternately enabled or disabled. If an interrupt occurs, the processor can branch to the NMI vector—24<sub>16</sub>.

#### **Routines extend 8051** math—to negative numbers

#### Israel Yuval

Electrical Engineer ADA (Israel) PO Box 2250, Haifa, Israel


wo routines extend the Multiply (MUL) and Divide (DIV) instructions of the 8051 microprocessor to signed numbers. In the routines, negative values are represented by

their two's complement.

As defined by Intel, a MUL AB instruction multiplies an unsigned 8-bit integer in the accumulator by the contents of register B. The loworder byte of the 16-bit product is left in the accumulator and the high-order byte in B.

DIV AB divides the unsigned 8-bit integer in the accumulator by the integer in register B. The accumulator receives the integer part of

#### WINCHESTER, FLOPPY AND TAPE Il on one board



Our OMTI 5400 SCSI (SASI) controller offers Winchester, floppy and tape support all on a single 5½" footprint PC board. By using our proprietary VLSI chip technology, we were able to squeeze all these functions onto a board size that most controller companies are still using for single function controllers. This means increased capability and improved cost-effectiveness in your application.

As a forward-looking OEM, you want multifunction SCSI (SASI) data controllers that meet your needs today and can meet the challenges of future developments in peripheral device technology. As you would expect, we've applied our new technology to meet these challenges in a whole family of SCSI (SASI) data controllers, the OMTI Series 5000.



#### **UNBEATABLE FLEXIBILITY**

Our OMTI Series 5000 family of SCSI (SASI) controllers supports industry standard ST506/412 5¼" fixed and removeable Winchester disks, 5¼" and 8" floppy disks and QIC-02 compatible to streaming tape. Each controller is SCSI (SASI) compatible to protect your software from change as you add next generation disk and tape technologies. And they are all second-sourced to guarantee availability.

#### **HIGH PERFORMANCE**

The Series 5000 controllers provide consecutive sector, noninterleaved data transfer and multisector buffering between host and peripherals. In addition, our data buffer supports simultaneous transfers between Winchester and streaming tape for fast image backup operation. No other manufacturer offers you performance like this!

#### **EASY TO USE**

Our high-level SCSI (SASI) command set off-loads your host CPU. Only one command is required to completely backup or restore Winchester data to and from tape, all without host intervention. Separate host-initiated commands allow selective file backup and restore. A sophisticated 32-bit ECC and automatic error retry means that reliable data is always available to the host. Finally, automatic Winchester flaw management handling prevents disk defects from corrupting your system.

To learn more about the OMTI Series 5000 data controllers, please contact us for additional information.




Scientific Micro Sustems. Inc.

339 N. Bernardo Avenue, Mountain View, CA 94043 (415) 964-5700

CIRCLE 115
SALES OFFICES: Seattle, WA (206) 883-8303; Boston, MA (617) 246-2540; Atlanta, GA (404) 296-2029; Morton Grove, IL (312) 966-2711; Melrose Park, IL (312) 345-5320; Arlington, TX (817) 429-8527; Laguna Hills, CA (714) 643-8046; Greensboro, NC (919) 292-8072; Mountain View, CA (415) 964-5700; Philadelphia, PA (215) 860-8626. DISTRIBUTORS: United States-Arrow Electronics, Inc. (516) 694-6800; Canada-Allan Crawford Associates Ltd. (416) 678-1500; International-Prima International (408) 732-4620.

LOC	OBJ	LINE	SOURCE			
		1				ENTS OF ON-CHIP RAM ADDRESSES MUL1 AND MUL2
		2 3				REGATIVE VALUES ARE REPRESENTED BY THEIR 2'S RANT MULTIPLICATION IS EXECUTED. RESULT (16
		4	(BITS)	IS SENT	TO PORTS A (M.S	B.BYTE) AND B (L.S.BYTE) OF AN I/O DEVICE, WITH
		5	; NEGAT	IVE VALU	ES REPRESENTED E	BY THEIR 16 BIT 2'S COMPLEMENT.
		7				
0000		8 9	MULT:	MOV	A, MUL1	
		10				
0003	A2E7	11		MOV	C.ACC.7	TEST FOR POLARITY OF 1ST MULTIPLIER.
0005	5003	13		JNC	A1	;(MUL1) IS POSITIVE.
0007	F4	14 15		CPL	A	(MUL1) IS NEGATIVE. FIND ITS 2'S
0008	2401	16 17		ADD	A, #1	;COMPLEMENT.
000A		18	A1:	MOV	B,A	
000C		19 20		MOV	A, MUL2	
000F		21		MOV	C.ACC.7	REPEAT POLARITY TEST FOR 2ND MULTIPLIER.
0011	5003	22		JNC	A2	
0013	F4	24		CPL	A	
0014	2401	25 26		ADD	A, #1	
0016	F57C	27	A2:	MOV	TEMP1,A	;SAVE ACCUMULATOR.
0018		28 29		MOV	A,MUL2	; AFTER EXCLUSIVELY DRING (MUL1) AND (MUL2),
001A	657A	30 31		XRL	A, MUL1	;ACC.7 WILL INDICATE PRODUCT POLARITY.
001C		32		MOV	C.ACC.7	
001E	9220	33 34		MOV	SIGN1,C	SAVE PRODUCT SIGN (CARRY BIT IS ALWAYS CLEARED FOLLOWING MUL AB INSTRUCTION).
- management		35		V Santra		, decimely roccowing roc no markocribin.
0020		36 37		MOV	A, TEMP1 AB	
0023		38		MOV	C,SIGN1	
0025	500A	39 40		JNC	A3	BOTH MULTIPLIERS ARE EITHER NEGATIVE OR
		41				;POSITIVE. PRODUCT IS POSITIVE.
0027	F4	42		CPL	A	; ONLY ONE MULTIPLIER IS NEGATIVE. HENCE
9928	2191	11		onn	0 01	PPODICT IS NEGATIVE AND MIST BE REPRESENTED
002A	C5FØ	45 46		XCH	A,B	BY ITS 16 BIT 2'S COMPLEMENT.
002C	F4	47 48		CPL	A A,#0	
002F	C5F0	49		XCH	A.B	
0031	906502	50 51	A3:	MOV	DPTR, *PORTB	:TRANSFER LOWER BYTE OF RESULT TO PORT B OF
0034	FØ	52		MOVX	@DPTR,A	;OUTPUT DEVICE.
0035 0037	906501	53 54		MOV	A,B DPTR, *PORTA	;HIGHER BYTE TO PORT A.
003A		55 56		MOVX	@DPTR,A	
003B	80FE	57	HALT1:	SJMP	HALT1	
007		58 59	MUL 1	DATA	7AH	
007		60 61	MUL2 TEMP1	DATA	7BH 7CH	
		62				
002	50	63 64	SIGNI	BIT	20H	
656		65 66	PORTA PORTB	EQU	6501H 6502H	
036		67		Luu	030211	
		68	END			
XREF	SYMBOL TAB	LE LISTING				
NAME	TYPE	VALUE AND	REFERENCE	S		
	L CSEG	000AH 13				
A3.	L CSEG	0016H 23 0031H 40				
ACC	. N DSEG	00E0H 11	21 32			
HALT	. N DSEG	00F0H 18 003BH 57	o 57			
	. N DSEG	007AH 8 007BH 19				
MULT	. L CSEG	0000H 8*				
PORT		6501H 54	65*			
		002011 33	20 CZA			



OC OBJ	LINE	SOURCE			
	1 2 3 4 5	; DIV2 (	BITS ( 2°S COM DER (8	EACH). PROVIDED PLEMENT, A TRUE BITS EACH) ARE S	N-CHIP RAM ADDRESS DIVI BY THE CONTENTS OF THAT MEGATIVE VALUES ARE REPRESENTED BY ALGEBRAIC DIVISION IS EXECUTED. QUOTIENT AND ENT TO PORTS A AND B, RESPECTIVELY, OF AN 1/O REPRESENTED BY THEIR 2'S COMPLEMENT.
0000 E57E 0002 C3	7 8 9	DVD:	MOV CLR	A.DIV2	
0003 AZE7	10		MOV	C.ACC.7	:TEST FOR DIVIDE FOLARITY.
0005 5003	12 13		JNC	81	;(DIV2) IS POSITIVE.
0007 F4 0008 2481	14 15 16 17		CPL	A A,#1	;(DIV2) IS NEGATIVE, FIND ITS 2'S COMPLEMENT.
000A F5F0 000C E57D 000E C3 000F A2E7 0011 9221	18 19 20 21 22	81:	MOV SLR MOV MOV	B.A A.DIVI C C.ACC.7 SIGN2,C	REFEAT POLARITY TEST FOR (DIVI).
0013 5003	23 24		JNC	82	
0015 F4 0016 2401	25 26 27		CPL ADD	A A,#1	
0018 F57F	28 29	B2:	MOV	TEMP2.A	:SAVE ACCUMULATOR.
001A ES7E 001C 657D	30 31 32 33		MOV	A,DIV2 A,DIV1	;AFTER EXCLUSIVELY ORING (DIV1) AND (DIV2), ;ACC.7 WILL INDICATE QUOTIENT FOLARITY.
001E A2E7 0020 9222	34 35 36		HOV	C.ACC.7 SIGN3.C	;SAVE QUOTIENT SIGN (CARRY BIT IS ALWAYS ;CLEARED FOLLOWING A DIV AB INSTRUCTION).
0022 E57F 0024 84 0025 A222	37 38 39		NOV	A, TEMP2 AB C, SIGN3	
0027 5003	40 41 42 43		JNC	B3	;BOTH DIVIDEND AND DIVIDER ARE EITHER ;MEGATIVE OR POSITIVE.QUOTIENT IS POSITIVE.
0029 F4 002A 2401	44 45 46		CPL ADD	A A,#1	JEITHER DIVIDEND OR DIVIDER IS NEGATIVE. JRUOTIENT MUST BE REPRESENTED BY ITS 2"S JOHPLEHENT.
802C A221 802E 5007 8038 C5F8 8032 F4 8033 2481 8035 C5F8	47 48 49 50 51 52 53	B3:	MOV JNC XCH CFL ADD XCH	C.SIGN2 B4 A.B A A.#1 A.B	REMAINDER SIGN IS EQUAL TO THAT OF THE SDIVIDEND.
0037 906501 003A F0 003B C5F0 003D 906502 0040 F0	54 55 56 57 58 59	B4:	MOV MOV MOV	DPTR, *PORTA @DPTR, A A, E DPTR, *PORTB	*TRANSPER QUOTIENT TO PORT A CF DUTPUT DEVICE.
0041 80FE	60 61 62	HALT2:		@DFTR.A HALT2	TRANSFER REMAINDER TO PORT B.
007D 007E 007F	63 64 65 66	DIVI DIV2 TEMP2	DATA DATA DATA	7DH 7EH 7FH	
0021 0022	67 68 69 70	SIGN2 SIGN3	BIT	21H 22H	
6501 6502	71 72 73 74	PORTA PORTB	EQU	6501H 6502H	
XREF SYMBOL	TABLE LISTING	END			
NAME TYPE	VALUE AND R	EFERFNOES			
ACC N DSE B . N DSE B1. L CSE B1. L CSE B2. L CSE B3. L CSE B4. L CSE DIVVI N DSE DIVVI N DSE DIVVZ N CSE HALTZ L CSE PORTIA N SIGNZ N BSE	G DDECH 11 2 G BOFRH 18 3 G D018H 24 2 G BO2CH 41 49 5 G BO3CH 19 3 G BO7DH 19 3 G BO7EH 81 G BO41H 61¢ G501H 55 7 G502H 58 7	1 34 0 53 57 8 th 9 th 5 th 2 64 th 65 th 61 1 th			

## Circuit-Board-Design Without the Tedium

smARTWORK™ lets the design engineer create and revise printed-circuit-board artwork on the IBM Personal Computer.

Forget tape. Forget ruling. Forget waiting for a technician, draftsman, or the CAD department to get to your project. smARTWORK™ software turns your IBM Personal Computer into a professional, high-quality drafting tool. It gives you complete control over your circuit-board artwork — from start to finish.

smARTWORK™ is the only lowcost printed-circuit-board artwork editor with all these important advantages:

- Complete interactive control over placement and routing
- ☐ Quick correction and revision
- ☐ Production-quality 2X artwork from pen-and-ink plotter
- ☐ Prototype-quality 2X artwork from dot-matrix printer
- Easy to learn and operate, yet capable of sophisticated layouts
- □ Single-sided and doublesided printed-circuit boards up to 10 x 16 inches
  - ☐ Multicolor or black-andwhite display


WINTER

- ☐ 32 user selectable color combinations; coincident points can be displayed in contrasting colors.
  - ☐ Can use optional Microsoft Mouse as pointing device


smARTWORK™ transforms your IBM PC into a CAD system for printed-circuit-board artwork. Display modes include both single-layer black and white and dual-layer color.

HIHIMINI

What makes smARTWORK™ so smart is that it understands electrical connections. Conductor spacing is always correct, lines don't become too narrow, and connecting lines do not intersect other conductors. smARTWORK™ can automatically find and draw the shortest route between two conductors. Or you can specify the route.



Twice scale
hardcopy of your
artwork is produced using
the Epson dot-matrix printers or the
Houston Instrument DMP-41 penand-ink plotter. Quick 1X check plot
is also available from Epson printers.



Dual-layer color display of a 2" by 4" section of a 10" by 16" circuit board

#### The Smart Buy

At \$895, smARTWORK™ is an exceptional value, particularly when compared to conventional engineering workstation costs.

Call or write us for more information on smARTWORK™ We'll be glad to tell you how smARTWORK™ helps us design our own circuit boards and what it can do for your business.

Send a purchase order, or major credit card number, and smARTWORK™ can be working for you next week.

#### System Requirements

- ☐ IBM PC or XT with 192K RAM, 2 disk drives and DOS Version 2.0
- ☐ IBM Color/Graphics Adapter with RGB color or b&w monitor
- ☐ Epson MX-80/MX-100 or FX-80/ FX-100 dot-matrix printer
- ☐ Houston Instrument DMP-41 pen-and-ink plotter (optional)
- ☐ Microsoft Mouse (optional)



"smARTWORK" and "Wintek" are trademarks of Wintek Corporation.

#### **DESIGN SOLUTIONS**

the quotient, and register B receives the remainder.

The 8051 assembler represents negative numbers by their 8-bit two's complement. For example, -3 is represented in hexadecimal by FD; -100 would be shown as 9C. Negative and positive values can be distinguished by their most significant bit. The MSB for negative numbers, those ranging from -1 to -128 in the 8-bit two's complement representation, will be 1. For positive numbers that range from 0 to 127, the MSB will be 0.

The routine called MULT (Program 1) tests for the polarity of each multiplier, converts negative values into their two's complements, and then performs the multiplication. The result is the product of the absolute values of the two multipliers. The sign of the product is determined by exclusive-ORing the two original multipliers and checking the MSB of the result. A logic 1, for example, indicates that the product is a negative number.

If the product is indeed negative, its 16-bit two's complement value is calculated and the final result sent to an I/O device, such as an 8155 programmable I/O port device.

The routine DVD (Program 2) is quite similar to MULT except that the result consists of an 8-bit integer quotient and an 8-bit remainder. Each is represented by a two's complement if it is a negative value. The sign of the remainder will always be the same as that of the dividend.


#### Winner for October 31, 1984

Simple program finds parts values for phase-locked loop

**Steve Lubs**, Electronic Engineer, 312 18th Ave., Brooklyn Park, Md. 21225.


#### Send us your Ideas for Design.

Submit a description of an important new circuit idea or design technique exclusively to ELECTRONIC DESIGN. You will receive \$50 for each published idea. If your idea is voted best-of-issue by our board of judges, you become eligible for the annual award of \$1000.





## Standard MIL-SPEC DC/DC CONVERTERS



#### Designed, qualified and ready for evaluation.

They're now available! TRI-SERVICE qualified DC/DC converters from Rantec . . . 300, 150 and 75 watt single output ratings, 180 watt dual output ratings and 175 watt triple output ratings. A 20-32 VDC input provides 5, 12, 15, 24 or 28 VDC outputs.

Switching regulation, power MOSFET technology and base plate cooling optimize the efficiency and power density making the converter easy to install in those tight places.

Standard product means you avoid costly nonrecurring engineering charges, delays in waiting for product to develop and ultimately the uncertainty of performance to your specs.

So don't wait 13 to 18 months and spend between \$125,000 and \$300,000 for a custom design.\* Rantec's DC/DC converters are already qualified for airborne, shipboard and ground use along with an extensive line of 1Φ and 3Φ MIL-SPEC DC power supplies. Rantec is the source for MIL-POWER. Call us today for an evaluation unit.

\*U.S. Navy/Industry Power Supply Ad Hoc Committee Estimate for Time and Cost.



**75W Single** 5/12/15/24/28 VDC @ 15/6.3/5/3.1/2.6A† 7"L x 2.25"W x 2.625"H

150W Single 5/12/15/24/28 VDC @ 30/12.5/10/6.3/5.3A† 7"L x 3.5"W x 2.625"H



**300W Single** 5/12/15/24/28 VDC @ 60/25/20/12.5/10.7A† 7"L x 5"W x 2.625"H



180W Dual ±12/15/24/28 VDC @ 7.5/6/3.8/3.2A† 7"L x 4.5"W x 2.625"H



175W Triple 5 VDC @ 20A & ±12/15/24/28 VDC @ 3/2.5/1.5/1.3A† 7"L x 5"W x 2.625"H



†Other V/A combinations available within the same power rating.

CIRCLE 121



Rantec/Power Systems • Division of Emerson Electric Co. • Department DE 9401 Oso Avenue, Chatsworth, CA 91311 • (818) 885-8223 • TWX: 910-493-1247

# Design Contest Memo DISTRIBUTE TO ENGINEERING STAFF

Still debating whether to submit an entry to Mini-Circuits Design Contest? Do it now. Don't wait for a revolutionary design breakthrough . . . it may be years away. And that's not what the contest is about. It's intended as a stimulating exercise to encourage engineers to pass along, handy, practical application ideas involving the use of RF signal-processing components. We'll list some examples below.

And don't get up tight about writing style. The dreaded lab reports of your college years are behind you... for your contest entry, write in the same words you would use if you were describing your ideas to a couple of your engineering buddies during a coffee break. Be informal... the words will flow naturally.

Same with any drawings or schematics. Forget the T-square . . . neat, handwritten sketches are fine.

#### Now, for some examples of topical subjects:

- improve VSWR by changing LO drive
- use opposite rather than adjacent ports in a power splitter to achieve higher isolation for mixer IM measurements
- improve system performance by using a high-figure-of-merit phase detector
- employ directional couplers to measure VSWR of non-linear devices (such as class-C amplifiers)
- minimize RF leakage and systems bugs with pin diode switches with internal terminations
- isolate ground loops with a wideband RF transformer
- change logic state with a center-tapped balanced transformer

Relax, close your eyes and think about your days on the bench. Any ideas pop up that somewhat follow the above examples? If so, jot them down now and put them in the mail. If you are a winner, not only will you become an owner of an IBM PC or VCR, you will also advance your career and enhance your company's image, since winning entries will be published in the Microwave Journal. Every company is proud when one of its engineers presents a paper at a technical conference, or authors an informative article, or wins a creative design contest. Bright engineers reflect a bright company.

Most companies encourage engineers to write and present talks...publicize the prestigious event in their in-house newsletter... and forward copies to the author's personnel file to remind his manager of the "extra effort" contribution when salary reviews and promotions are being considered.

So, don't delay any longer. We've extended the deadline date to late January 1985 to offset extensive mailing delays due to the holiday season and international deliveries.

Best wishes for a happy holiday season—and good luck on your entry.

President

Mini-Circuits

P.S.—If your company's policy does not permit individual awards, we'll be glad to donate the prize to a charitable organization of your choice on behalf of you and your company.

## Win Exciting Prizes!

enter Mini-Circuits'

## Design Contest



IBM® PC Personal Computer,

dual disk-drives, printer, software (word processing, spreadsheet and planner). A complete system ... a \$4,000 VALUE!

A complete system ... a \$4,000 VALUE! ... a \$500 VALUE! IBM is a registered trademark of International Business Machines Corporation. Value at time of press. All applicable taxes and duties are the sole responsibility of the winners.

#### It's Easy to Enter...

Do you have a clever design idea or application involving IF/RF/microwave signal-processing components—mixers, power splitter/combiners, attenuators, RF transformers, directional couplers, amplifiers or RF switches? Or perhaps a versatile setup for testing them or a novel approach to enhance their performance.

If you have an original idea, enter Mini-Circuits Design Contest now. Type or legibly print your submissions. Start with a brief abstract describing the key point of your idea (cost saving, improved performance, simplified testing, etc.). List RF signal processing components used. Then proceed with the detailed explanation. Make schematics and block diagrams clear; include values of circuit components. Be sure to include performance data and curves; judges' scores will be based on content, multiplicity of products involved and thoroughness.

finding new ways ... setting higher standards

#### Mini-Circuits A Division of Scientific Components Corporation

World's largest manufacturer of Double Balanced Mixers
P.O. Box 166, Brooklyn, New York 11235 (718) 934-4500
Domestic and International Telex 125460 International Telex 620156

#### **Contest Rules**

3 speed, remote control, timer,

electronic tuning ... including 6 tapes

2-4-6 hr. VHS Videocassette Recorder

- 1. Submit as many entries as you wish.
- Ideas should be original and non-proprietary. †
- Entries will be judged by the editorial staff of Microwave Journal and their decisions will be final. The top 25 winning entries will be published in Microwave Journal.
- 4. All entries become the property of Mini-Circuits Laboratory and must be received by January 1985

†Winners may be asked to sign an affidavit of eligibility & release.


- Employees of Mini-Circuits
   Laboratory, Microwave Journal and their sales representatives, are not eligible.
- Contest void where prohibited by law.
- Make sure to include your business address and phone number. In addition, for non-U.S. entries, indicate AC power line voltage and frequency.
- Send your entries to:
   Mini-Circuits' Design Contest
   P.O. Box 137
   Brooklyn, NY 11235

#### Good Luck, and Thanks.

The Mini-Circuits Design Contest, with its competitive excitement and fabulous prizes, is our way of thanking all of the designers worldwide whose staunch customer support has been responsible for our continuing growth.



## Make your 212A modem



### for half the cost.

#### Your Design Problems are Over

Now available to you are the LSI circuits and software know-how needed for your own design and implementation of an operational Bell 212A compatible modem - all from one experienced source, EXAR

#### **EXAR Delivers the Solution**

First, you get high technology, quality IC's that form the heart of a 212A modem. The XR2123 CMOS Modulator/Demodulator provides the 1200 BPS PSK function, the XR14412 modem system performs the 300 BPS FSK modulation/demodulation function required for 212A compatibility and the XR2120 switched capacitor filter, also CMOS technology provides the 1200 and 300 BPS filtering requirements for the modem.

1/2 THE COST

#### Cut Costs, Reduce Space, Improve Reliability

By getting our IC's along with our know-how you make sure your modem will be right.

With our LSI components, you can design a modem for about half the money you would normally spend for a finished board and reliability is improved because our LSI circuits reduce the number of necessary parts and the space to house them.


#### 1200 BPS PSK MOD/ DEMOD XR-14412 300 BPS FSK MOD/ DEMOD

#### More Modem Solutions

EXAR provides modem solutions for a wide variety of applications, from telephone communications compatible with Bell and CCITT standards to high speed transmission over twisted-pair wires. Modem types available included are Bell Standard 103 (300 BPS FSK). 202 (1200 BPS FSK), and 212A circuits as well as CCITT compatible V.21 (300 BPS FSK), V.22 (1200 BPS

PSK), V.23 (1200/75 BPS FSK) and V.26 (2400 BPS PSK).

To round out a complete design EXAR provides RS-232 line drivers and receivers for interfacing and a wide range of op amps to perform amplification and signal conditioning functions.



212A Compatible Modem

#### The Solution is Available Now

Just send the coupon below or give us a call. You'll get everything you need, including our compilation of modem design and technical data, called the Modem Design Handbook.

So let EXAR get your modem design going. Send us the coupon today.

#### Help me make my modem!

- $\square$  Send me the EXAR
- Modem Design Handbook. ☐ I am in design, please have an
- Applications Engineer contact me.
- ☐ Please have your Sales Representative call me.

Company\_\_\_

Dept./Div.\_\_

Address\_

\_\_\_\_\_Zip\_\_\_\_\_ State

\_)\_\_\_\_Ext.\_ Phone (\_\_\_\_


Application\_


ED 12/13/84



750 Palomar Avenue Sunnyvale, CA 94086 Tel. (408) 732-7970 TWX 910-339-9233

For telecommunications, industrial, medical and military IC applications ... EXAR Goes One Step Further.





Hitachi laser diodes of all types and outputs, plus fiber optic modules capable of high-efficiency, high-volume data transmission—the right products for any application.

## FOR THE LASER DIODES AND FIBER OPTIC PRODUCTS YOU NEED, EXACTLY AS YOU NEED THEM, LOOK TO HITACHI AND THE LINE-UP THAT'S


## VERS PERSON

Optical fiber networks, laser-beam printers, laser pickup systems...all benefit from Hitachi's wide variety of high-quality products. These devices and components are based on our pioneering technologies for optics, semiconductors, ultraprecise machining and assembly. So whether you require laser diodes or fiber optic modules, you're sure to find the specific device you require in the Hitachi line-up.

#### A full range of laser diodes

Hitachi provides a complete array of laser products for sophisticated equipment development. They feature such remarkable properties as small size, light weight, low power consumption, high collimating efficiency, monochromaticity and high-speed direct modulation capability.

#### Hitachi Laser Products Line-up



Hitachi's high-power products provide outputs up to 30 mW for memory discs with mass storage and quick random-access capabilities. Variable independent peak wavelength products (780, 830, 1200 and 1300 nm) are available for communications equipment, information terminals, disc systems, medical appliances, and many other applications.

These diodes come in a variety of packages, each one the product of Hitachi's most advanced technology and extensive R&D capabilities.

#### Innovation in fiber optics

The trend in data processing is away from stand-alone equipment toward totally integrated systems—local area networks for offices, factories and laboratories. Hitachi fiber optic systems and components provide optimum efficiency in these applications, for speedier, higher-volume transmission of data.

Hitachi fiber optic transmission modules, for example, combine a variety of key functions in compact, single-chip LSI transmitter/receiver packages. They reduce space requirements, increase ease of installation, and provide high reliability over a wide range of data rates.

So if you are looking for systems and components that will be serving the business and industry of tomorrow and beyond, look to Hitachi for exceptional products with proven versatility.



# INSTALL THE LAN OF THE FUTURE, NOW.

Proteon is today's only source for IBM® compatible token passing ring networks. It's called proNET® and it's from a leading independent manufacturer.

proNET is a high performance 10 megabit/second LAN with unprecedented reliability and fail-safe operation. It links many vendors including IBM, Digital Equipment, Sun Microsystems, Texas Instruments and in addition operates on the IBM cabling system. Plugging directly into UNIBUS, Q-Bus, Multibus and Universal Bus it uses a combination of transmission media including twisted pair, infrared, co-axial and fiber optic.

The proNET system includes the hardware, software, cabling, installation, and service support. And it's comfortably priced; your investment can be modified, updated and easily expanded. One last point: the proNET token ring is available now.

proteon

Invest now in your token ring LAN. Call Proteon, Inc., 4 Tech Circle, Natick, MA 01760. (617) 655-3340.

\*proNET is a trademark of Proteon, Inc. \*IBM is a registered trademark of International Business Machine.
\*Unibus and Q-Bus are registered trademarks of Digital Equipment Corporation. \*Multibus is a registered trademark of Intel, Inc.

CIRCLE 125

## **P**RODUCT REPORT

## FOCUS ON BOARD-LEVEL MODEMS

Pushed on by the influx of small computers, modem makers are successfully shrinking their boards, adding new features, and pressing the upper speed limits.

he same phone lines that stretch from coast to coast have long been recognized as the most efficient way of tying together remote computer systems. And as personal computers and other small machines show up more frequently, a modem's size, speed, and cost—plus the user's preferences—are more important than ever.

Increased portability has fueled the development of smaller boards, which simplify servicing and make it easy for an OEM to add or delete modems at the customer's whim. Unlike chips, which generally require some dedicated support circuitry, a board can be easily inserted into a socket on the CPU card when communications capabilities are desired.

As computers of all types become more powerful, their ability to create data, as well as their demand for data, increases. Typically, high-speed modems operate in conjunction with large high-speed computers. In addition, greater capabilities of personal computers are pushing users to higher transmission rates. It is no longer difficult to find 9600-bit/s modem cards, and even 14.4-kbit/s units are emerging.

Nevertheless, lower transmission rates translate into even lower costs. The 300-bit/s modems of a few years ago are still popular, and 1200-bit/s devices are rapidly emerging. Many of the latter cards maintain the 300-bit/s rate for the sake of compatibility. For example, the 212A standard specifies 1200 bits/s but incorporates 300 bits/s as a fallback rate.

One of the key areas of development focuses on letting modems talk over unconditioned lines. Although communications at 9600 bits/s and up require dedicated lines, eliminating the need for conditioning lowers line costs substantially in the long run. Greater value is prompting manufacturers to add features like voice and data transmissions, and rare is the card that does not give users the flexibility to work with either pulse or tone frequencies. Automatic dialing and answering solicit a "yes" from virtually all buyers of the typical card. In

**Terry Costlow** 

#### PRODUCT REPORT

#### Focus: Modem boards

addition, some manufacturers are making an effort to customize their modems, providing base features and then building in other functions at the user's request.

Obviously size plays an important part in portable computers. One card, designed by Racal-Vadic, measures just 5 by 51/4 in. (Fig. 1), small enough to fit into the short rack in the portable IBM PC personal computer, as well as desktop versions and compatible systems.

The 300PC, a member of Racal-Vadic's Maxwell modem line, handles both automatic and manual dialing and automatically determines whether tone or pulse signaling is needed. It can also report on call progress, so that users know if the line is busy, ringing, or answered.

The card also includes software that lets users keep track of unattended calls, recording the numbers dialed, how many times they were dialed, and the total number of completed calls. In addition, users can choose to vary the log-on sequence. That sequence includes time delays, message recognition, and fields to be transferred. With a text-editing feature, users can create or alter messages without leaving the communications program.


Half-size cards let users add communications capabilities without taking up a full-size expansion slot. One of the smallest cards, aptly named the Half Card by Ven-Tel, comes in at just 51/4 by 37/8 in. The card is designed to fit into the short slots of the IBM PC XT, IBM portable, and many compatible systems, including Compag. It operates at 1200 and 300 bits/s, with automatic speed detection assuring compatibility with other modems. In addition, it offers both half- and full-duplex transmissions and selects either tone or pulse dialing.

The Half Card comes with software that lets users store all information for a call, including files desired, call parameters, and the phone number. Thus, the user can do other tasks and later retrieve the data from a printer or disk.

AST Research has shrunk its 1200/300-bit/s modem to fit the half-card slot in IBM PCs and compatible systems. Dubbed Reach!, the card handles both voice and data, and it enables a user to interrupt a data transmission to talk with someone at the other site without losing the phone line. The card houses a loud-speaker (Fig. 2) that either gives audible indications of call progress or permits voice communications. Standard features include local and remote loopback diagnostics and full- or half-duplex communication.

Rockwell's R1212U modem transmits at 1200 bits/s using either the 212A or CCITT V.22 standards. The 4-by-4.7-in. card draws only 3 W during operation. The card features automatic adaptive equalization for maintaining low error rates even when operating over poor phone

Small cards are also useful in terminals, workstations, and peripherals such as printers, so that users can transmit data to remote sites. CTS Data Communication's CTS212AT, which has dimensions of only 4 by 6 in., has a variety of features, including line status monitoring and



1. With dimensions of 5 by 51/4 in., the 300PC modem card from Racal-Vadic lets users of the IBM PC communicate at 1200 bits/s without taking a full-size slot in the computer.

built-in diagnostics, including local analog and digital loopback.

Full-size cards are still popular, and they, too, are adding features to keep their edge over other products in this crowded field. Multi-Tech's MultiModem PC card, which includes a floppy, is one of the first to fit the IBM 3270 personal computer (Fig. 3). The bundled package can store incoming data on disk or printer, a large number of phone numbers and setup instructions, the keys' programmable functions (for one-strike dialing), and optional passwords.


It also recognizes dial tones and busy signals, instead of simply dialing after a predetermined delay. If it detects a busy signal or if the call goes unanswered, the modem will automatically dial a second number or redial the same number. The card transmits at both 1200 and 300 bits/s.

#### **High speeds**

Currently, 14.4 kbits/s is the highest transmission rate for commercial modems. The Rixon R14.4 transmits at that rate in either full- or half-duplex operation, with synchronous transmissions. Its multiplexer accepts data from six channels, set at 2.4, 4.8, 7.2, 9.6 and 14.4 kbits/s, and transmits them at 14.4 kbits/s over dedicated four-wire telephone lines. The card, which features automatic origination and answering, can be mounted in standard 19- or 23-in. racks.

Although it communicates much faster than a 1200-bit/s modem, Rockwell's 9600-bit/s R96FT/2C modem—at 3.64 by 6.3 in.— takes up only slightly more space than the slower board (Fig. 4). The synchronous modem operates over unconditioned lines. The Fast Train card quickly adapts to the modem at the opposite end of the call, running through the training sequence in just 30 ms at 9600 bits/s or only 20 ms at the 4800 fallback rate, a particularly important feature in multipoint systems. The card, which will be introduced next spring, consumes only 4 W normally and is compatible with both V.29 and V.27 bis and ter specifications.

Universal Data's 9600-bit/s, V.29-compatible modem—designated UDS 2092108— has standard features like adaptive equalization and 7200- and 4800-bit/s fallback rates. Moreover, it puts great emphasis on simplifying testing and



2. The Reach! card from AST Research enables users to interrupt transmissions to talk with someone on the other end. A loudspeaker enables them to monitor speech or data transmissions, the latter to let them know the message is being transmitted.


#### Focus: Modem boards

repair. Not only does it conduct analog and digital loopbacks, it can also tie into the company's eye-pattern generator, letting field personnel visually monitor its activity through a 26-pin test connector (Fig. 5).


Since the cost of a modem generally rises with its transmission rate, users of high-speed systems are particularly interested in minimizing the number of cards. With that in mind, Micom has combined a time-division multiplexer with its 9600-bit/s card. The Model 4096/4+ can simultaneously transmit incoming data from up to four separate terminals, using any combination of rates that total 9600 or less. For instance, if all four channels are in use, each can transmit at 2400 bits/s. If two are used, they can each send at 4800 bits/s or one can operate at 7200 bits/s and the other at 2400 bits/s. If just one channel is active, it can use the full 9600 bits/s.

#### **Medium speeds**

Though high speed is on everyone's wish list, 2400-bit/s products are still the most widely available. One such modem, the 201BR from Develoon, is compatible with both the CCITT V.24 and Bell 201B standards. The rackmounted card overcomes one of the key diffi-




3. Built-in software enables MultiTech's MultiModem to store incoming data on either a disk or a printer.



4. The Rockwell R96FT/2C sends and receives at 9600 bits/s, quickly adapting to line conditions and selecting the optimal speed. It adjusts to 9600 bits/s in 30 ms or to 4800-bit/s transmissions in 20 ms.

# **ANOTHER** STAND-ALONE SYSTEM FROM MICRO-LINK



Micro-Link's newest single board computer represents another significant price and performance breakthrough for system designers. It eliminates the need for separate memory, I/O and time functions, while maintaining STD Bus compatibility-all at the price of a conventional STD Bus CPU card.

#### Take a Look at Our 8085A CPU!

The STD-145, an 8085A CPU, with three (or optional five) MHz clock provides a high throughput for your system software with a memory flexibility never before implemented on the STD Bus. Two 28-pin JEDEC-compatible memory sockets may be configured for a variety of memory types. ROM or

RAM may be implemented with battery back-up capability for one of the sockets. Wait state generation for slow ROM is provided. Base address of the system memory can be set at any boundary determined by the size of the memory chips used. Boot address for the system ROM is selectable at any 4K boundary. One or both sockets may be phantomed from the system to allow the use of 64K of offboard memory. MEMEX and IOEX are implemented by writing to a control port to select the memory map or I/O map desired.

#### Interested in Z80A Options?

Micro-Link also offers the STD-147 single board Z80A computer with 64K dynamic RAM and multiprocessing capability for Z80 users.

#### **Free Catalog**

Call now to request data sheets and our complete catalog featuring over 50 STD Bus cards.



CORPORATION

14602 North U.S. Highway 31 Carmel, Indiana 46032 317-846-1721 (in Indiana)

800-428-6155

**GSA Contract Number** GS00K8401S6013

#### PRODUCT REPORT

#### Focus: Modem boards


culties of modem communications with its antistreaming feature. When a board gets stuck in the transmit mode, the garbled information it sends can cause errors, jam up a network, and drive up costs by keeping the modem on line. A time delay option can disconnect the 201BR after a user-determined period whenever streaming is detected. The modem will transmit over any four-wire, unconditioned line in full or half duplex. The card measures  $9\frac{1}{2}$  by  $10\frac{1}{2}$  in.

Rockwell's R2424 card complies with CCITT standards for 2400 bits/s and with Bell 212A and 103 standards for fallback to 1200 and 300 bits/s, respectively. It meets CCITT V.22 bis and V.22 standards, addressing communications over the common two-wire public phone system. The full duplex card, occupying only 22 in.2, uses VLSI circuits and signal processing to keep power consumption down to 3 W.

Like the Rockwell card. Penril's 2024 meets the V.22 bis specification, lowering overall cost by letting users tie into the public telephone network rather than the more costly four-wire lines. Standard features are automatic dialing; full diagnostics, including remote testing; and fallback to 1200 bits/s using either the Bell 212A or V.22 standards.

Rixon's R2424 communicates over the public phone network, as well as over private lines. Front-panel pushbuttons on the rack-mounted card enable users to run through diagnostics and set up the card, selecting either 1200 or 2400 bits/s and either full- or half-duplex communications.

Somewhat less popular than the 2400- and 9600-bit/s speed boards are a number of modems that transmit at maximum speeds of 4800 or 7200 bits/s. Micom's 4048/V.27 + card, for instance, meets the CCITT specification for 4800 bits/s. The 8-by-11-in. card quickly latches onto the best possible speed, transmitting for 9 ms before moving to 2400 bits/s, then increasing to 4800 bits/s after only 26 ms if errors are not excessive. The modem, which operates over unconditioned leased phone lines, also features antistreaming, so that a faulty modem cannot



5. The UDS 2092108 modem board takes servicing into account, providing a test connector so that users can tie into the Eye Pattern Generator feature and visually monitor activity.



# workstations that integrate in-house systems on every engineer's desk.

#### **Maximize Productivity.**

Control Data looked at the need to integrate the design, layout, analysis and logic simulation functions ... saw a way to place low-cost design tools in front of your engineers... and developed the Electronic Design Workstation.

IBM PC Compatible.

The Control Data Electronic Design Workstation offers full IBM PC and XT compatability and complete system integration that can speed you through 80 to 90% of your design tasks at about 1/5th the cost of functionally equivalent systems.

**Broad Applications.** 

SCALD Hierarchical Design Concepts at about 1/4th the cost of conventional workstations... and more:

- Advanced Schematic Entry
- Documentation
- Logic Simulation 36 State Multi-Level Simulation
- Netlist Extraction:
   TEGAS SPICE ASPEC •
   SYSCAP SCICARDS •
   LOGIS \*
- Project Management

Easy Custom Interface.

All drawing and netlist files are

in a readable ASCII file format that makes developing interfaces to your in-house codes easy. You can do it yourself or we can do it for you.

Find out how you can integrate your system and put Electronic Design Workstations in front of your engineers. Call tollfree 1-800-253-4004, ext. 1430. In Minnesota, call collect 1-612-921-4400, ext. 1430. Or write Control Data, Electronic Marketing, P.O. Box 0, Dept. HQW09A, Minneapolis, MN 55440.

\*TEGAS is a registered trademark of Calma Div., General Electric Corp. SYSCAP is a registered trademark of Rockwell International, Inc. SCICARDS is a registered trademark of Scientific Calculations, Inc.



#### Focus: Modem boards

monopolize the leased line.

Penril's 1800 DED is compatible with the Bell 202 standard, which calls for 1800-bit/s fullduplex transmissions over a dedicated fourwire lines. A selective carrier detector speeds up the polling task by preventing noise from activating the modem when it is checking other modems for messages. The card also communicates over standard two-wire phone lines at the 212A standard's 1200-bit/s rate.

#### Low speeds

Despite the emphasis on 1200 bits/s, 300 bits/s is far from dead. Hayes, which has set industry standards for many basic commands and responses of personal computer modems, recently added feature-laden software to its Micromodem IIe card. Designed for the Apple He, the card has a top speed of 300 bits/s, with the fallback rate of 110 bits/s specified by the Bell 103 standard. Incorporating a loudspeaker for listening while the call is in progress, the board also offers pulse and tone dialing; automatic dialing, answering, and disconnecting; and full- and half-duplex communication. Program prompts let users create, display, and erase files, as well as easily adjust parameters, such as passwords.

Another 300-bit/s modem, from Universal Data Systems, is compatible with CMOS and TTL levels, easing the system integrator's tasks. Since the UDS 1032168, like most other 300-bit/s parts, is designed to keep costs low, its features are limited to automatic dialing and answering, using either pulse or tone dialing.


The Novation 103 Auto Dial card also aims at the low-speed Bell standard specified in its name. The 3-by-4-in. card draws only 110 mA maximum at 5 V, putting little drain on the system's power supply.

Although low-speed modems generally conform to the Bell standards set before the telephone company divestiture, modems transmitting at 2400 bits/s or higher typically follow standards set by the International Consultative Committee on Telephone and Telegraphy (CCITT).

#### Customization


As with many OEM products, modem cards call for a degree of customization. While most manufacturers alter their standard products to fit the demands of large customers only, a few firms specialize in such adjustments.

U.S. Robotics has designed the Core, which incorporates the basic modern circuitry but lets



6. A semicustom board from U.S. Robotics provides the basic communications functions and allows system designers to add features at will. The Core card measures 3 by 4 in.

# COMMANDING.



4SS-3133R1

# Sprague's new UDN-2952B and UDN-2952W full-bridge motor drivers are designed for 2-phase bipolar control of stepper motors, brushless d-c motors, and some servo applications. Continuous output currents to 2 A at 40 V are allowed, and peak start-up currents as high as 3.5 A. For high-power requirements, the UDN-2952W in a 12-pin SIP power tab package is suggested. For lower power applications, the UDN-2952B in

a 16-pin DIP is supplied. Both are compatible with standard logic families. Volume prices (50k) for the DIP version is less than \$2, and the SIP version just over \$2. Write for Engineering Bulletin 29319 to Technical Literature Service, Sprague Electric Co., a Penn Central unit, 347 Marshall Street, North Adams, Mass. 01247. For applications assistance, call Mark Heisig at 617/853-5000.



Focus: Modem boards

	Below 2400 bits/s	2400 bits/s and above	Circle
Anderson Jacobson Inc. San Jose, Calif. (408) 945-9030	*	*	451
AST Research Inc. Irvine, Calif. (714) 863-1333	*	*	452
Com Data Corp. Morton Grove, III. (312) 470-9600	*		453
CTS Corp., Datacomm Products Division Danbury, Conn. (203) 743-3681	*		454
Develcon Electronics Inc. Warmister, Penn. (800) 528-8423	*	*	455
Hal Communications Corp. Urbana, III. (217) 367-7373	*		456
Hayes Microcomputer Products Inc. Norcross, Ga. (404) 449-8791	*		457
Micom Systems Inc. Chatsworth, Calif. (213) 998-8844	*	*	458
MultiTech Systems Inc. New Brighton, Minn. (612) 631-3550	*		459
Novation Inc. Chatsworth, Calif. (818) 996-5060	*		460
Penril DataComm Gaithersberg, Md. (301) 921-8600	*	*	461
<b>Racal-Vadic</b> Milpitas, Calif. (408) 946-2227	*	*	462
Rixon Inc. Silver Spring, Md. (301) 622-2121	*	*	463
Rockwell International, Semiconductor Products Division Newport Beach, Calif. (714) 833-4700	*	*	464
<b>S.I. Tech</b> Geneva, III. (312) 232-8640	*		465
Timeplex Inc. Woodcliff Lake, N.J. (201) 391-1111	*		466
Universal Data Systems Huntsville, Ala. (205) 837-8100	*	*	467
U.S. Robotics Inc. Skokie, III. (312) 733-0497	*		468
Ven-Tel Inc. Santa Clara, Calif. (408) 727-5721	*		469

users determine the final configuration, adding features deemed necessary (Fig. 6). The 3-by-4-in. card, which is compatible with Bell 212A, 102, and 113, can be used in printers and other peripherals, as well as in terminals and computers. The basic card has voice and data capabilities, digital filtering, and automatic parity detection.

ComData, another firm focusing on customization, specializes in devices operating below 4800 bits/s. Although its cards can be configured to work with Bell standards, the company specializes in nonstandard cards that must be compatible with older modems that combine many standards or use proprietary encoding.

CTS, which until last year dealt exclusively with custom modems, still maintains a heavy interest in that area. Its 825 line, for 1200-bit/s communications, puts a variety of features on cards measuring less than 30 in.<sup>2</sup>.

#### Addressing other needs

Whereas most modems address basic communications needs, others tackle different purposes. Penril's Auto Data addresses the increasingly important need for security protection against unauthorized access to important data bases. When the modem answers an incoming call, it verifies a user code by referring to previously stored data. If the caller is authorized, the modem calls back using a telephone number that is stored along with the verification code. Thus, even if an unauthorized caller has a valid code, there is no contact unless he or she also gains access to the telephone actually associated with that code.

The 1200-bit/s modem, which can be rack-mounted for large computer systems, has extensive remote capabilities. Phone numbers can be downloaded from a host modem to a remote modem, with up to 10 dialing sequences, each consisting of up to 20 numbers, stored on board. Additionally, the Auto Data card lets users key in numbers to be called from remote terminals.

A rather unusual IBM PC-compatible modem lets users communicate over either telephone lines or via shortwave radio. The PCI-2000 from Hal Communications lets users copy radio teleprinter information or relay data to seagoing vessels.

# YEW's New **Multifunctions**

A powerful tool for waveform analysis. With computing capability and 4-color plotter.



"Multifunctional." That's what you'll call YEW's new Model 3655 Analyzing Recorder once you consider all the multiple functions for waveform analysis, born of the YEW all-in-one design concept. Powerful multiple functions: The 3655 is a data logger. Recorder. Transient analyzer. FFT analyzer. And more. **Powerful multiple input:** The 3655 accepts up to 4 channels of DC V and 5 standard TC's. Powerful multiple presentation of the data: One touch of a key and the 3655 gives a 4-color hard copy of the CRT display. The 7" CRT and



color plotter provide real eye fidelity! The 3655 can digitize signals at a rate of up to 50kHz with 14-bit resolution. And the buffer capacity is 32K words/channel. Discover the 3655 and its many multifunctions. You won't find a more cost-effective tool for waveform analysis! For more information, contact Yokogawa Corp. of America, (404) 253-7000. In Europe: Yokogawa Electrofact B.V. (The Netherlands), (0) 33-10543. In Japan: Yokogawa Hokushin Electric Corp., (03) 349-0621.



# DASH-BAK SETS UP THE FAST BREAK



#### AIE MAGNETICS GIVES YOU FAST ACCESS TO THE INDUSTRY'S MOST COMPLETE LINE OF POWER

INDUCTORS. When you need power inductors—and you're faced with a demanding schedule—AIE Magnetics can help you get a fast break on your design. We've got the most extensive

line of power inductors in the industry, and we offer a variety of package styles, inductance ranges and current ranges to meet your specific requirements.

And no one puts the ball in your court faster than AIE Magnetics. With our Dash-Bak service, we ship sample quantities of "straight-from-the catalog" items within 72 hours and components that require design modifications within 5 days.

Simply write or call us about your next design; we'll gladly send you our catalog and your own Dask-Bak service card. They'll set up the winning shot for you.



701 Murfreesboro Road Nashville, Tennessee 37210 615/244-9024

"A Division of Vernitron Corporation"

CIRCLE 130

### **N**EW PRODUCTS

# CMOS comparator chip multiplexes 4 inputs under digital control

he first comparator with multiplexed inputs is also the first with a built-in d-a converter that acts as a digitally controlled reference. A CMOS chip from National Semiconductor, the ADC0854 has a serial input through which a command enters to select one of four analog inputs.

The selected analog signal is fed into one input of the chip's automatic-zeroing comparator. The other comparator input, the voltage reference, is fed from the 8-bit digital-to-analog converter, which is also programmed by commands through the serial input.

The comparator has a clocked output, updated at a 400-kHz rate, an offset error of 2.5 mV, and a typical output drive of 16 mA.

The serial input accepts a 13-bit command word consisting of a start bit, 4 bits to select the analog input (1 bit per input), and 8 bits to drive the d-a converter. The converter supplies the reference voltage for the comparator by dividing a voltage applied to an external pin down into 256


selectable levels accurately to within  $\pm \frac{1}{2}$  LSB.

The chip can be used to detect when a voltage limit is reached by loading a command over the serial input to select one of the 256 reference voltage levels. If the comparator's input exceeds the reference level, the output pin will toggle. The chip can also be used as a pulse-width generator that would replace a 555 timer while allowing the pulse width to be adjusted with a serial command.

The comparator comes in a 14-pin DIP and is priced at \$2.85 in 100-unit quantities. A sister chip, the ADC0852, has two multiplexed inputs and sells for \$2.65 in the same quantities; it is available in an 8-pin DIP. Both parts operate from a single 5-V supply and draw 30 mA.

National Semiconductor Corp., 900 Semiconductor Drive, Santa Clara, Calif. 95051, Attn: Data Acquisition Marketing; (408) 721-5225.

CIRCLE 308



A digital command entering through the serial input (D<sub>I</sub>) controls the ADC0854's two unique features: a multiplexer that handles several inputs (four for this chip, two for a sister chip) and a d-a converter that feels the voltage reference.

**Curtis Panasuk** 

## **Analog array groups** devices in like blocks for faster turnaround

prefabricated array of transistors groups its unwired components into blocks, or tiles, bringing to semicustom analog design much of the speed and convenience associated with the CAE approach based on gate arrays and cell libraries popular for digital chips. The tile approach cuts turnaround time to 6 weeks from the 12 typical with earlier transistor arrays.

Designed by Micro Linear, the FB300 Mosaic Array includes capacitors—one of the few arrays to do so—as well as resistors and diodes, plus the transistors. It lays out its tiles in a way that makes the chip look like a mosaic, giving rise to its name.

Each tile can be formed into a high-level analog function and will allow engineers to submit analog semicustom designs to Micro Linear in the form of a block diagram instead of in the traditional drawing of detailed transistor interconnections.

Previously, semicustom analog designs were done by wiring together a totally random collection of transistors


and resistors. This approach is labor-intensive and unsuitable for offloading onto software.


It also sometimes results in very long connection paths; these paths create unwanted capacitances that interfere with circuit operation. The tile approach and the use of two layers of metal, in contrast, holds down connection lengths.

Of the four classes of tiles, the largest has over 135 components, and there are 10 of them on the chip (visible in the photograph). These tiles each have 19 npn and 13 pnp transistors. There are also 103 resistors ranging in value from 18 to 25 k $\Omega$ , as well as built-in capacitors, which eliminate the need for extra components on the pc board. The other types of tiles provide voltage references, general-purpose transistors, and power transistors for use in an output stage having a drive capability of up to 20 mA.

To speed the conversion of the block diagram submitted by the designer into a finished part, Micro Linear uses a library of different metalization patterns that can be applied individually to a tile to

#### **Curtis Panasuk**





If you've been searching for an ultra-fast A/D converter that combines high-speed digitization with low power consumption, look to Siemens . . . a world leader in advanced IC technology.

Our new SDA 5200N and SDA 5200S flash A/D converters offer 6-bit resolution and the excellent linearity you require, plus the highest sampling rate available anywhere. Just look at these outstanding features:

- Super high-speed A/D conversion
- 100 MHz sampling rate
- Accurately digitizes 50 MHz input (Nyquist) 2V P-P
- 6-bit resolution plus overflow bit (stackable to 8-bits)
- ± 1/4 LSB linearity
- 140 MHz small signal bandwidth
- 500V/µsec slew rate of input stage
- ECL compatibility
- 550 mW power dissipation

And, if your requirements are less demanding, Siemens offers two other flash A/D converters: SDA 5010: Input slew rate 200V/µsec; accurately digitizes

10 MHz input signal at 100 MHz sampling rate.

SDA 6020: Input slew rate 300V/µsec; accurately digitizes 25 MHz input signal at 50 MHz sampling rate.


Siemens flash converters are ideal for a wide range of applications including: high-energy physics equipment; transient recorders; digital oscilloscopes; TV digitizing; Rot 100 lasin hat hi cons radar signal processing and analysis; hybrid/modules; and high-resolution circuitry.

These ICs, all in 16-pin packages, are available now, in quantity. For immediate delivery call these franchised distributors: Arrow Electronics; Hall-Mark Electronics. (Or, for a literature package, clip the coupon below or call Siemens at (800) 222-2203.)

Siemens....a world leader in advanced IC technology.

H108830

# Technipower Does The Job Right!



#### "Mil-Qual" Modular Power Supplies

Today's requirements demand Technipower "Mil-Qual" modular power sources. Specify as you would a component, and get precise, regulated power far more economically than with custom builts. Choose from sealed and partly sealed Switchers; harsh environment Linears; partly sealed AC/DC Converters; lower cost, "Hi-Rel," sealed types; and custom modifications. Whatever the job—

harsh environment, EW/Defense, aerospace or computers — Technipower does the job right! Send for details. 5 year warranty.



P.O. Box 222, Commerce Park, Danbury, Conn. 06810 Tel: (203) 748-7001 TWX: 710-456-9280

CIRCLE 140



## LONGEST LASTING LCD.

Even in heat, humidity and stress situations, this liquid crystal display stays bright and sharp longer than other LCDs, longer than other types of displays. Literally years longer. Exceeds JEDEC

Class 4 (automotive and outdoor) environmental requirements. Low power, good readability at any angle. Inquire about our long life display. LXD Inc., 24500 Highpoint Road,

Beachwood, Ohio, 44122. (216) 292-3300.

**NEW PRODUCTS** 

#### ANALOG

wire its components into a high-level function (or "macro") such as an op amp, an analog-to-digital or digital-to-analog convertor, or a timer (see the box).

The chip's transistors have an  $f_T$  of 1 GHz, making it possible to configure tiles into video amplifiers or modulators.

#### Some of the high-level functions available

Pnp input op amp (LM324)
Npn input op amp (LM741)
Operational transconductance
amplifier (LM13600)
Ground-sensing comparator
(LM339)
High-speed latching comparator
(LM360)
Video amplifier (LM592/LM733)
Double-balanced modulator
(LM1496)
Timer (LM555)

In the future, each of the standard macros will be available separately in a DIP, for breadboarding. Furthermore, an engineer will be able to send in the description of any special macro he or she requires and the company will create the wiring pattern.

Micro Linear is now accepting designs for the chip. The nonrecurring engineering cost for an average design is in the range of \$10,000 to \$20,000. In high volume, the finished parts are available for under \$5 each.

Micro Linear Corp., 2092 Concourse Drive, San Jose, Calif. 95131; (408) 262-5200.

CIRCLE 317

# 574 a-d converter slips sample-and-hold chip into its 28-pin package

in-for-pin-compatible with the industry-standard 574 analog-to-digital converter, the HS 9474 from Hybrid Systems also fits a sample-and-hold circuit into its 28-pin DIP. The 12-bit hybrid device has a maximum throughput of 31 kHz and the monolithic BiFET sample-and-hold circuit sports a 7- $\mu$ s acquisition time (typical) with 0.01% nonlinearity for a full 10-V input swing.

The successive-approximation converter features a 25-µs conversion time and is followed by a three-state output buffer, which ensures easy interfacing with busstructured microprocessorbased circuits. It is readily configured to perform self-triggered continuous conversions.

The device includes a 1000-pF hold capacitor and a 10-V reference. Through the use of external zero and gain calibration potentiometers, off-set and full-scale gain errors are adjustable to zero, with the latter specification requiring the use of an external  $50-\Omega$  resistor.

The converter has an aper-

ture time of 200 ns or less, and jitter is on the order of 10 ns. It is specified for either  $\pm 0.025\%$  or  $\pm 0.012\%$  nonlinearity at 25°C, with a drift of  $\pm 0.5$  ppm/°C maximum and with monotonicity guaranteed over 11 or all 12 bits.


The converter is factory-set either for the 0-to-10- and  $\pm$ 5-V ranges or for a single  $\pm$ 10-V range. All versions require  $\pm$ 15- and  $\pm$ 5-V power supplies and typically dissipate 600 mW.

The device can be ordered in a hermetically sealed ceramic package, with processing to MIL-STD-883D, which guarantees an operating temperature range of  $-55^{\circ}$  to  $+125^{\circ}$ C. A commercial package is offered for operation over  $0^{\circ}$  to  $70^{\circ}$ C.

An HS 9474 in a commercial package with 11-bit accuracy is priced at \$47.50 apiece in 100-unit quantities. The same part in a military package costs \$130 each for the same quantity. Availability is from stock to four weeks.

Hybrid Systems Corp., 22 Linnel Circle, Suburban Industrial Park, Billerica, Mass. 01821; Jack Worthen, (617) 667-8700.

CIRCLE 320



## Resolver-to-digital converters deliver accurate velocity, as well as position, data

family of resolver-todigital converters permits designers of velocity servo systems to replace either a combination of absolute optical encoder and tachometer generator or a similar mix of resolver, tachometer, and r-d converter with a single brushless resolver and an r-d converter. The result of the substitution, using a member of the 1S family of converters from Analog Devices, is a system that is more accurate, lower in cost, simpler, and more reliable.

The four members of the family range in resolution from 10 to 16 bits, or 21 arcminutes to 20 arc-seconds. and they can track from 630 rpm (the 16-bit 1S64) to 40,800 rpm (the 10-bit 1S14), specifications that are available with other converters.

However, it is when they are compared, from a system point of view, with a tachometer generator that they shine.

Whereas a low-cost tachometer (\$150 to \$300) has a nonlinearity, maximum error, and output ripple of 1%, 10%, and 5%, respectively, these specifications are 0.1%, 1%, and  $0.5\% + 200 \,\mu\text{V}$  for the converters, at a price of \$183 to \$294 for commercial units. Moreover, a tachometer to meet the 1S specifications costs about \$4000.

The velocity outputs are dc voltages scaled to the resolution of the device. These run at 0.25, 1, 4, and 16 V/1000 rpm for the 10-, 12- (1S24), 14-(1S44), and 16-bit units. The tracking rate of the 12- and 14-bit converters is 8670 and 2550 rpm, respectively.

The converters have three additional features: a dc analog error signal for testing, for carry-overs, and to indicate the direction of rotation: an angle offset permitting a trimming potentiometer to move the output up to 32 LSBs; and an analog voltage output proportional to the distance between two adjacent code changes. This last feature permits the designer to stiffen, or increase, the gain of the servo.


The accuracy of the units over their operating temperature range is  $\pm 25$ ,  $\pm 8.5$ ,  $\pm 5.3$ , and  $\pm 4$  arc-min, respectively, for the 5YO 10-, 12-, 14-, and 16-bit versions. The 4YO version raises this to  $\pm 2.6$  arcmin. for the 16-bit 1S64. Regardless of resolution, all units are monotonic, and their repeatability is to 1 LSB.

Commercial and military grades of each model are available in 40-pin ceramic and metal DIPs, respectively. For nine or fewer pieces, the unit cost is \$183, \$186, \$199. and \$294 for the 10-through 16-bit commercial models. The military units run \$366, \$372, \$398, and \$588.

Analog Devices Inc., Box 280, Norwood, Mass. 02062; Richard Parker, (617) 329-4700.

CIRCLE 310

#### Frank Goodenough



#### **ANALOG**

#### Two SDCs boast high tracking rates



wo hybrid synchro/resolver-to-digital converters deliver tracking rates that are 50% faster than competitive devices. The SDC/ RDC1767 and 1768 combine a velocity output with a maximum tracking rate of 36 revolutions/s for the 12-bit 1767 and 18 revolutions/s for the 14-bit 1768.

The converters' internal

transformers provide isolation to 350 V dc-making the devices particularly useful in military and aerospace applications. The units have a signal and reference frequency range of 400 Hz to 2.6 kHz. They produce parallel outputs with a load-driving capability of 6 TTL. Maximum error is guaranteed at  $\pm 8.5$  and  $\pm 5.3$  arc-minutes for the 1767 and 1768, respectively, over a range of  $-55^{\circ}$  to  $+125^{\circ}$ C.

Analog Devices Inc., 2 Technology Way, Norwood, Mass. 02062; (617) 329-4700. \$471 and \$503 for the 1767 and 1768, respectively (10 to 24 units); six to eight weeks.

CIRCLE 322

#### **DAC** specifications suit robotics

esigned for robotics and other precision servomotor applications, two 16-bit digital-to-analog converters provide a differential linearity error of +0.006%, -0.003% of full-scale reference—ensuring 15-bit monotonicity around bipolar zero over the entire specified temperature range of 0° to 70°C. The settling time (to within  $\pm 0.003\%$  of FSR) is 350 ns for the DAC710KH and 4 μs for the 711KH.

Burr-Brown Corp., PO Box 11400, Tucson, Ariz. 85734; (602) 746-1111. \$29 (100 units).

CIRCLE 323

#### The Little Board™...\$349\*

The world's simplest and least expensive CP/M computer



- 4 MHz Z80A CPU, 64K RAM, Z80A CTC, 2732 Boot ROM
- Mini/Micro Floppy controller (1-4 Drives, Single/Double Density, 1-2 sided, 40/80 track)
- Only 5.75 x 7.75 inches, mounts directly to a 5 1/4" floppy drive
- 2 RS232C Serial Ports (75-9600 baud & 75-38,400 baud), 1 Centronics Printer Port
- Power Requirement: +5VDC at .75A; +12VDC at .05A/On-board -12V converter
- . AMPRO Utilities included:
- read/write to more than 2 dozen other formats (Kaypro, Televideo, IBM CP/M86....)
   format disks for more than a dozen other computers
   menu-based system customization


- BIOS and Utilities Source Code Available
- SCSI/PLUS Adapter:
- ints directly to Little Board Slave I/O board control Full ANSC X3T9.2



Distributor/Dealer/Reps Inquiries Invited

Z80A is a registered trademark of Zilog. Inc.

67 East Evelyn Ave. • Mountain View, CA 94041 • (415) 962-0230 • TELEX 4940302 •



# **NMOS** chip integrates all the filters needed by 4800-bit/s modems

single NMOS chip is the first to contain all the filters needed by a 4800-bit/s modem. Reticon's R5637 is for use with Bell 208/CCITT V.27 modems operating either full duplex over four-wire cable or half duplex over two-wire cable.

The chip integrates four switched-capacitor filters: the receiver bandpass filter, a fixed compromise delay equalizer, a 75/150-baud secondary channel filter (Bell 202/CCITT V.23), and a 3000-Hz transmitter low-pass filter. It also includes two un-

committed op amps that can be used for gain control or clock or anti-aliasing filters.

The bandpass filter has a 1-dB bandwidth of 750 to 2800 Hz, a passband ripple of 1 dB, and an adjacent channel rejection ratio of 53 dB. Its stopband rejection ratio is -55 dB at 600 Hz and +50 dB at 3700 Hz, and its group delay variation from 1100 to 2500 Hz is less than 200 µs.

The delay equalizer compensates for the average group delay encountered in telephone systems in the U.S. It has a nominally flat amplitude response (0 dB). The transmitter filter prevents

frequencies above 3000 Hz on the chip from getting on the line and causing aliases. It is connected between the modem's d-a converter and the telephone line.

The op amps need an external 3.6864-MHz clock input or a 3.6864-MHz crystal.


Also available is the R5936. for 2400-bit/s modems (Bell 201/CCITT V.26) operating full duplex over four-wire cable. It has a similar set of four filters but only one unconnected op amp. This chip's bandpass filter has a 1-dB bandwidth-760 to 2860 Hz; a lower passband ripple of 0.5 dB; and a stopband rejection ratio of  $-50 \, dB$  at  $400 \, Hz$  and +60 dB at 4000 Hz. The adjacent channel rejection ratio and group delay variation remain the same.

Both chips operate from  $\pm$  5- to  $\pm$  10-V power and from 0° to 70°C; they come in a 22-pin plastic DIP. The R5637 costs \$12.75 and the R5636 \$14.75 in lots of 1000. Small quantities are available from stock.

EG&G Reticon, 345 Potrero Ave., Sunnyvale, Calif. 94086; Ken Small, (408) 738-4266.

CIRCLE 318

#### Frank Goodenough



#### **ANALOG**

### 14-bit DAC has deglitched output

With its low-glitch voltage output of 10 mV pk-pk and its 10-MHz update rate for small step changes, the DAC-02310 d-a converter is suitable for use in vectorstroke CRT displays, waveform generators, and automatic test equipment. The hybrid converter is available in linearity-error grades of  $\pm 0.006\%$  and  $\pm 0.012\%$ , each with 14-bit resolution. Settling time to within  $\pm \frac{1}{2}$  LSB for a full-scale  $\pm 2.5$ -V step change is 600 ns.

The DAC-02310 can be programmed for five output voltage ranges with a maximum output current of 5 mA. Specified for operation over the commercial and military temperature ranges, the price of the unit is \$245 and \$269, respectively.

ILC Data Device Corp., 105 Wilbur Place, Bohemia, N.Y. 11716; (516) 567-5600.

CIRCLE 324

### Converter links LVDT with microprocessor

Suitable for industrial measurement and positioning applications, the 2S50 is an 11-bit ratiometric tracking converter that interfaces an LVDT with a microprocessor. The converter is specified for operation over the commercial and military temperature ranges, with accuracies to within 0.1% and 0.2% of full scale. Each version is available with one of two reference frequency

options: 400 Hz or 1 kHz to 10 kHz.

Because the 2S50 converts the ratio of the excitation signal to the output signal, it is insensitive to changes in the excitation voltage amplitude, frequency, and waveshape.

Analog Device Inc., 2 Technology Way, Norwood, Mass. 02062; (617) 329-4700. From \$92 (100 units); stock.

CIRCLE 325

#### Have you had problems in the field you can't identify?

It could be Electrostatic Discharge (ESD). With the Schaffner NSG 430/431 Electrostatic Discharge Simulator, your equipment can be pre-tested against the problems ESD can cause. Now you can test for and guard against damage to computer functions, microprocessors, digital circuits, controllers and other kinds of electronic equipment.


#### A lot more features, for a lot less money

The hand-held NSG 430/431 is easy to use, lightweight (just 2 ½ lbs.) and is completely self-contained. And best of all, you'll find the sensible pricing no shock at all...as much as \$1500 less than competitive models. For

more information about the NSG430/431, and all three dimensions of Schaffner EMC, call or write today.

### The Schaffner ESD Simulator...

because discovering a static discharge in the field can be a real shock to everyone.



#### SCHAFFNER

RFI Suppression Filters
 EMC Test Equipment
 Test and Application Services
 USA: Schaffner EMC, Inc., 825 Lehigh Ave., Union NJ 07083/(201) 851-0644
 Switzerland: Schaffner Elektronik AG, CH-4708 Luterbach, Switzerland/Telefon 065 4231 31

# Two new solutions to new product development.



PHOTONEECE" —Applied Fine Pattern

Toray **PHOTONEECE** photosensitive polyimide-precursor solution provides almost unlimited applications for a wide range of microelectronics in computers, facsimile transmission devices and other products. As a protection layer for computers and facsimile microelectronics. As insulating layers in multilayer semiconductors. And for many, many other purposes. The super heat resistance of Toray's photosensitive **PHOTONEECE** is making this versatile polyimide coating an integral part of ongoing research and development in the electronic industry worldwide.

Toray **SEMICOFINE**\* is applicable to many fields such as protection coatings and multilayer insulation films for diodes, transistors, ICs, LSIs, VLSIs and for microelectronic circuits used in computers and facsimile transmission devices. For  $\alpha$ -particle protection and as alignment coating for LCDs too.

**PHOTONEECE** and **SEMI-COFINE**. New electrochemical products for tomorrow's electronics. From Toray, naturally.


#### TORAY INDUSTRIES, INC.

Tokyo Office: Tel: 03-245-5560 Telex. J22623 (TORAYINC) Osaka Office: Tel: 06-445-3737 Telex. J63453 (TORAYINC) New York: TORAY INDUSTRIES (AMERICA), INC. Tel: (212) 697-8150 Telex. 233067 (TAMI UR), 421119 (TAMI UI) Los Angeles: TORAY INDUSTRIES (AMERICA), INC. Los Angeles Office Tel: (213) 628-1301 - 2 Telex. 686150 (TORAYAMINCL SA) London: TORAY EUROPE LTD. Tel: 4869374 - 6 Telex. 919176 (TORAY G) Hamburg: TORAY INDUSTRIES, INC. Hamburg Office Tel: 36 74 51 Telex. 214784 (TORAY D) Hong Kong: TORAY INDUSTRIES (HK), LTD. Tel: 3-675051 - 5 Telex. 43634 (TORAY HX) Singapore: TORAY INDUSTRIES (SINGAPORE) PTE.. LTD. Tel: 5333288 Telex. TORAY RS34710

CIRCLE 145

#### ANALOG

# Dual op amp chip sets performance marks



ased on the single-unit OPA111 introduced by Burr-Brown earlier this year (ELECTRONIC DESIGN, Feb. 9, p. 97), the OPA2111, also by Burr-Brown, is the highest-performing dual op amp ever. It costs about 20% less per op amp than its predecessor, takes up less space, and requires less production labor to install.

Even though, as with any dual version, there are some sacrifices in performance, the OPA2111 nevertheless boasts outstanding specifications, including the same voltage noise floor of  $8\text{nV}/\sqrt{\text{Hz}}$  maximum over the frequency band of 10 Hz to 10 kHz (for which it is 100% tested).

Its bias current of 4 pA maximum, still impressively low, is necessarily higher than the 1 pA of its single version (because the quiescent current through two op amps

**Heather Bryce** 

is higher than through one, thus heating the chip slightly more and thereby increasing the bias current).

Similarly, it still sports a low offset voltage drift— $2.8 \,\mu\text{V/°C}$  (vs  $1 \,\mu\text{V/°C}$  for the OPA111). The low offset voltage of 500  $\,\mu\text{V}$  maximum is twice that of the OPA111, owing to the compound yield of two devices over one. The dual unit also has a high open-loop gain of 114 dB minimum and a high common-mode rejection ratio of 96 dB minimum.

The OPA 2111 AM, which works over the temperature range of  $-25^{\circ}$  to  $+85^{\circ}$  C, costs \$9.95; the slightly better-performing OPA 2111-BM, for the same temperature range, is priced at \$16.50; and the OPA 2111 SM, for  $-55^{\circ}$  to  $+125^{\circ}$  C, costs \$16.75—all in 100-unit quantities. Delivery is from stock.


Burr-Brown Corp., PO Box 11400, Tucson, Ariz. 85734; (602) 746-1111.

CIRCLE 303

#### Quad CMOS chip switches 100-MHz signals

esigned to replace p-i-n diode switches at a tenth the price, as well as providing more isolation and needing no external parts, a four-channel CMOS chip handles 100-MHz signals with a flat response to within ±3 dB. When off, the four SPST switches on the IH5352 from Intersil feature an input-to-output isolation achieved by the use of a series-shunt, or T, configuration—of 60 dB at 10 MHz, and cross-coupling between channels is more than 60 dB.

Moreover, the typical turnon and turn-off times are



The switch on each of the CMOS IH5352's four channels uses a T circuit to achieve 60 dB of inputoutput isolation at 10 MHz.

under 150 ns and 80 ns, respectively. Also, break-beforemake switching is guaranteed. Another major feature is the on-resistance—typically 75  $\Omega$  for matching trans-

mission lines.

The chip uses three supplies, a 5- to 15-V logic supply and analog supplies that can vary from  $\pm 4.5$  to  $\pm 16$  V. All draw a maximum of  $10 \mu A$ .

The commercial IH5352-CPE comes in a 16-pin plastic DIP, and the IH5352IJE and IH5352MJE industrial and military units in 16-pin ceramic DIPs. In lots of 100, the commercial unit sells for \$7.75 each. Small quantities are available from stock.

Intersil Inc., 10710 Tantu Ave., Cupertino, Calif. 94014; Paul Delazari, (408) 996-5273.

CIRCLE 309



The relay that started the revolution five years ago continues to be your best buy. A superior reed relay combining such rugged construction, high reliability and maximum paractility.

mum versatility...at so economical a price. Just \$.56 each in quantities of 50K for LG 101-1-5. This is a low profile, highly durable reed relay, with proven performance and a choice of switches to meet virtually all applications.

#### **PREMIUM SWITCHES**

•Low Contact Resistance • Wide Range of Contact Ratings • Highest strength glass-to-metal seats available

#### **FCC PART 68**

Standard Relays to meet 1500 VDC Isolation: switch to coil. Contact ratings available to 25 VA.

#### TYPICAL APPLICATIONS


• Telecommunications • Modems • Security Systems

#### **Standex Electronics**

4538 Camberwell Road, Cincinnati, Ohio 45209 • (513) 871-3777 Morley Road, Tonbridge, Kent, England • (732) 358398



CIRCLE 146



When you want the best of both worlds in graphics, we'll be there.


Now you can shape the future in black-and-white or brilliant color...at prices that are really down to earth.

Qume's two new terminals provide powerful graphics capabilities for a multitude of engineering, scientific, and business decisionsupport applications. They're worlds apart from other graphics terminals, with the latest in people-pleasing ergonomics: space-saving design, a detached, low-profile keyboard, and a full tilt-and-swivel display.

When you're ready for the beauty and precision of color graphics, our new QVT 511GX<sub>w</sub> terminal is the ideal choice. For much less cost than ever before, it provides flicker-free, non-interlaced raster scan graphics, with a selection of up to eight colors from a palette of 64. It's

fully compatible with the Tektronix 4105 and accepts all of its software, including PLOT 10 packages. The QVT 511GX can also be used in Tektronix 4010, 4100 and 4110 series environments, and works beautifully with the Tektronix 4695 color graphics copier. What's more, it conforms to both ANSI X3.64 and ISO 6429 protocols for text editing. A mouse device is standard equipment on the QVT 511GX.

QVT-511GX. FULL-COLOR TERMINAL



Qume's new QVT 311GX, monochrome graphics terminal provides full compatibility with both Digital's VT 125 and Tektronix' 4010/4014 series, at a price substantially lower than either! It's the first terminal that gives you the mobility to draw on an entire universe of graphics software — both PLOT 10 and ReGIS — plus full ANSI text-editing capabilities. It provides full bitmapped graphics on a 14" non-glare white phosphor screen, with four shades of gray. And an optional mouse device is available to provide complete flexibility in graphics editing.

These graphics terminals measure up to Qume's exceptional standards for performance, quality control, and reliability. What's more, they're backed by our experience

and resources as an ITT company. So wherever your imagination may take you, you know we'll be there with a dazzling display of technical support.

For more information about these and other Qume graphics and alphanumeric terminals, or our full line of daisywheel printers and disk drives, call (800) 223-2479. Or write Qume Corporation, 2350 Qume Drive, San Jose, CA 95131.

QVT-311GX, MONOCHROME TERMINAL



© Qume Corporation 1984

CIRCLE 234

One out of every two companies building Ethernet-compatible products builds them with Seeq Ethernet components.

That's because our 8003 Ethernet Data Link Controller and 8023 CMOS Manchester Code Converter are the industry's most practical Ethernet shortcuts.


Why?

Simple logic.

Instead of wrestling with the dark side of Ethernet—boards full of components, lost weekends, algorithms written by committee—you drop in two VLSI packages.

A few coffee breaks later, transmission, reception, backoff and code conversion are up and running in the best way possible.

# EVERY OTHER COMPANY APPRE



Trouble free.

And that promise is backed by millions of hours of on-the-job performance. Plus 100% off-the-shelf availability. No wonder our Ethernet family is so widely appreciated.


Give yourself the same chance. Send for our free Ethernet data package. Fifty pages of theory and practice for putting your project online.

Just write Seeo Technology, 1849 Fortune Drive, San Jose, California 95131. Or call (408) 942-1990.

And appreciate what every other company already does.

CIRCLE NO. 75

# CIATES SEEQ'S PART IN ETHERNET.



# DMA controller chip addresses 4 Gbytes, works with 68000 family

he first full 32-bit peripheral, Motorola's MC68442 DMA controller has two 16-bit channels and handles 32-bit addresses giving 4 Gbytes of direct addressability. It is fully compatible with the M68000 bus, including all exception conditions, as well as with the asynchronous VMEbus and VERSAbus.

The chip is an enhanced version of the MC68440 DMA

controller. Aside from containing the needed address pins, it includes an extra function code output that distinguishes between DMA and CPU bus cycles.

A unique feature is an internal transfer mode called limited-rate auto-request. This mode guarantees that the controller does not monopolize the bus indefinitely. Programming certain bits in the global control register limits the percentage of the bus bandwidth the controller

can use to between 6.25% and 50%, preventing it from hogging the bus.

The chip has three other modes for generating direct memory requests. In the external burst mode, the transfer occurs for as long as the peripheral holds the request line. Consequently, peripheral devices that require very high data transfer rates can use all of the bus bandwidth.

In the external cycle-stealing mode, the peripheral must generate pulses of a highenough frequency for the controller to continue holding the bus for transfer. This mode is used for devices that generate a pulse for each transfer.


Finally, the chip's simple internal maximum rate mode constantly has the transfer request pending for a channel until all data has been transferred. It uses 100% of the available bus bandwidth.

Ready now for sampling, the controller will be available in production quantities by March. It comes in a 68-lead pin-grid array and costs \$59.69 in quantities of 100.

Motorola Inc., Microprocessor Division, 3501 Ed Bluestein Blvd., Austin, Texas 79721; (512) 928-6860.

CIRCLE 307

#### **Heather Bryce**



The MC68442 two-channel DMA controller is the first full 32-bit peripheral chip. Capable of addressing 4 Gbytes directly, it is designed for the M68000 bus but is also compatible with the VMEbus and VERSA-bus.


# Floppy-disk controller chip has everything but buffers

Ithough a well-established chip, the 765A floppy-disk controller requires considerable support circuitry to function in a system. To cut that burden, the FDC9266 combines on one chip the control functions of the 765A with a digital data separator that handles both single- and double-density requirements.

Developed by Standard Microsystems, which manufactures NEC's 765A controller under license and makes a stand-alone data separator (the FDC9229), the FDC9266 eliminates the external adjustments previously needed and also permits variable write precompensation (track-selectable).

An excellent choice to help reduce the cost or size of IBM-compatible personal computers, the chip operates identically to the 765A from the host interface side. Additionally, it does not suffer from the occasional lock-up problem encountered with the 765A, caused by improper alignment of the falling edges of several timing signals.

Like the 765A, the new chip manages either 5½- or 8-in. disk drives; handles data record lengths of 128, 256, 512, or 1024 bytes; can transfer multiple sectors and tracks; and controls up to four drives. Additionally, it can scan a single



sector or an entire track's worth of data fields, comparing, on a byte-by-byte basis, data in the processor's memory with the data read from the diskette. Track stepping rate, head load time, and head unload time all are user-programmable.

The controller also includes an address-mark detection circuit, thus simplifying the circuitry required to read data. To use the controller in a system, just line buffers, a decoder, and a latch are needed.

Fabricated with the company's patented COPLAMOS n-channel silicon-gate process, the device operates from a 5-V supply and an 8-MHz clock and has a worst-case power rating of about 1 W.

The FDC9266 comes in a 40-pin DIP. It costs \$25.10 in 100-unit quantities, and samples are available from stock.

Standard Microsystems Corp., 35 Marcus Blvd., Hauppauge, N.Y. 11788; (516) 273-3100.

CIRCLE 304

**Dave Bursky** 

## ATTENTION: ENGINEERS PROGRAMMERS

## PolyFORTH\*II

the operating system and programming language for real-time applications involving ROBOTICS, INSTRUMENTATION, PROCESS CONTROL, GRAPHICS and more, is now available for...

#### DEC\* PDP-II\* and LSI-II\* Systems

The PolyFORTH II high performance features include:

- Multiple users (30 terminals on a LSI-II)
- Unlimited control tasks
- High speed interrupt handling
- Reduced application development time

PolyFORTH II software will run on any standard PDP\* or LSI-II with RX02 disk (RSX\* optional), Micro/PDP-II\* and PROFES-SIONAL\* 350 and is fully supported by FORTH, Inc.'s:

- Extensive on-line documentation
- Complete set of manuals
- Programming courses
- The FORTH, Inc. hot line
- Expert contract programming and consulting services

From FORTH, Inc., the inventors of FORTH, serving professional programmers for over a decade.

Also available for other popular mini and micro computers.

For more information contact:

#### FORTH, Inc.

2309 Pacific Coast Hwy. Hermosa Beach, CA 90254 213/372-8493 RCA TELEX: 275182

Eastern Sales Office 1300 N. 17th St. Arlington, VA 22209 703/525-7778

\*Registered trademarks of Digital Equipment Corp.

## 1000 V SWITCHMOS® POWER MOSFETS



If you're looking for high voltage Power Mosfets with fast switching characteristics, look no further. Solitron's new Switchmos series delivers improved current ratings, higher gains and switching speeds. That's important news when you want to improve designs and need a reliable source for switching power supplies, motor controls, inverters, choppers, and voltage regulators.

TYPE NO.	ID	VDS	
SDT50A	2.5A	1000V	
SDT53A	2.6A	1000V	
SDT54	5.3A	1000V	
SDT57	2.5A	1000V	
SDT58A	3.7A	1000V	

For complete information, call Sales Dept. toll free 1-800-327-8462.



1177 Blue Heron Blvd. Riviera Beach, Florida 33404 (305) 848-4311/TWX: (510) 952-7610

#### Dave Bursky

# SAR chip consumes 10% to 1% the power

sumption of just a few milliwatts, a CMOS chip can directly replace the popular but powerhungry bipolar 2504 12-bit successive-approximation register. The first CMOS replacement for the bipolar SAR, the ZX25C04 dissipates just a tenth to a hundredth the power of its bipolar counterpart.

Developed by Zytrex, the chip is manufactured with the company's proprietary metal-gate, dual-layer-metal CMOS process, which provides high drive currents and performance equivalent to that of bipolar circuits.

The chip contains all the storage and control logic needed to build an analog-todigital converter. Also, it has provisions for register extensions and truncations, and it can be operated in either a start-stop or a continuousconversion mode, features that make it useful as the control and storage element for other recursive digital routines. Additionally, the chip can be set up to operate as a ring counter or as a serial-toparallel counter.

Guaranteed to operate at a minimum clock frequency of 15 MHz, the device has a typical upper clock frequency of 60 MHz. At one clock pulse

ZX25C04N 8441

per bit, plus one bit per period for overhead, the 15-MHz clock frequency translates into slightly more than a 1-MHz conversion rate for a 12-bit a-d converter.

When the chip is not being cycled, the quiescent supply current is a mere  $8\,\mu\mathrm{A}$  (all outputs open); that specification increases to several milliamperes when clocked. The register operates from a 4.5-to 5.5-V power supply and over  $-40^{\circ}$  to  $+85^{\circ}\mathrm{C}$ . The output voltage levels allow direct interfacing with other CMOS logic devices, as well as with TTL circuits.

A vailable in a 24-pin 300-mil DIP the SAR costs \$6.90 apiece in 100-unit quantities. An unpackaged chip for use in hybrid circuits costs \$6 each for a minimum order of 5000 units. Delivery takes six to seven weeks for packaged devices and less for bare chips.

Zytrex Corp., 750 E. Arques Ave., Sunnyvale, Calif. 94086; Orlando Gallegos, (408) 733-3973.

CIRCLE 305

# Dual-port RAMS have largest byte-wide capacity

vailable with either 8 or 16 k bits of storage space, a pair of dualport RAMs offers the largest capacity of any byte-wide monolithic dual-port memories. What's more, the chips, made with Integrated Device Technology's CEMOS II 2-µm process, do not sacrifice access time for the low power of CMOS.

The best maximum access times are 90 and 100 ns for the commercial and military versions, respectively, and the typical power consumption is just 325 mW. When deselected, the standard version ("S" suffix) of either memory consumes just 200  $\mu$ W; for even lower standby power requirements, an "L" suffix version draws only 50  $\mu$ W.

Both chips—the 1-kbyte IDT7130 and 2-kbyte IDT7132 have two independent address and data ports with separate control lines, thus permitting simultaneous read and write operations to any location in the memory. Each port also has its own chip-enable/power-down line, so that power can be saved if one port is not needed.

Busy output signals provide feedback to the host system by delaying access to one port when both ports try simultaneously to access the same location. If that occurs, an onchip arbitration circuit will make a decision and set the Busy flag of the delayed port.

The IDT7130 includes interrupt output lines for each port. These lines make possible communication between ports or systems. However, they are not included on the 7132, since the pins are needed for the extra address line for each port.

The low-power version of the RAMs also permit them to retain data, even when powered by a 2-V battery. In that case, power consumption drops still further—to a bare 2.5  $\mu$ W.

Both memories are available in models for the commercial, industrial, or military temperature range, with maximum access times of 90 or 100 ns (commercial) and 100 or 120 ns (military or industrial). The military units are 100% processed in compliance with MIL-STD-883, method 5004.

The chips come in either 48-pin DIPs or 48-contact leadless chip carriers. In 100-unit quantities and housed in a DIP, the 120-ns military parts cost \$185 (8k chip) and \$324 (16k chip). Samples will be available in the first quarter of 1985.

Integrated Device Technology Inc., 3236 Scott Blvd., Santa Clara, Calif. 95051; Sam McCarthy, (408) 727-6116.

**Dave Bursky** 

# SINGLE BOARD COMPUTER PC BUS



Put the power of the IBM PC into your OEM system with the new I-Bus Single Board Computer and Enclosures. Now you can make use of that vast array of PC-compatible expansion cards—for communications, graphics, data acquisition, peripheral control, and every other imaginable task.

I-Bus Systems has coupled Intel's powerful new 80188 CPU with 64K of RAM and up to 160K of on-board EPROM, plus a serial console port to talk to a terminal or a PC. Just plug the SBC into an I-Bus 6-slot chassis or 9-slot card cage and you have the heart of a computer system, ready to run.

Best of all, the IBM PC works perfectly as a software development system. You can assemble and test applications programs on the PC, then download them to the I-Bus system for dedicated execution.

For all the details, give us a call today at (800) 382-4229. In California, call (619) 569-0646.





9235 Chesapeake Drive San Diego, CA 92123

IBM PC is a trademark of International Business Machines

#### Chip makes 80286 look like 8088

single chip allows the 16-bit 80286 microprocessor to emulate the control signals and 8-bit

transfer sequences of the 8-bit 8088 microprocessor. Thus the EL-286-88 processor converter chip, from Edsun

Laboratories, gives 80286 systems designers easy access to the plethora of 8-bit IBM PC-compatible peripherals now available. It also serves the upgrading of 8088 systems by providing a ready link between the software-compatible 80286 and an 8088 bus and therefore speeding up the design time for such upgrades.

The converter translates data width, control signals. and circuit timing. Control inputs determine which memory address ranges and I/O devices the chip is to service and which are to be accessed directly by the 80286.

To the 80286, the converter appears as a 16-bit memory or peripheral device, and to the 8-bit peripheral it looks like an 8-bit 8086. Fully asynchronous operation allows the 80286 to run at its full 8-MHz clock rate and address peripherals designed for, and running at, typical 8088 data rates of 4.77 MHz.

The chip requires a single 5-V power supply. Implemented in CMOS, the TTLcompatible device dissipates 100 mW, with no heat sink required.

The converter will be available in sample quantities in January. It is housed in a 68-pin leadless chip carrier (the same as the 80286) and priced at \$48 for orders of 10,000 units.

Edsun Laboratories, Inc. 7 Sears Road, Wayland, Mass. 01788: Steven Edelson, (617) 358-5667.

CIRCLE 319



Every time NCR ships an "S" Series MOSFET switching power supply, it has already been certified to exacting international safety and EMI standards. UL, CSA, VDE(TUV), FCC and IEC set the design and performance requirements our products routinely meet. NCR also certifies custom designed and modified standard power supplies prior to shipment.

We offer a wide choice of MOSFET switchers — single or multiple output, 100 watts and up, open frame or enclosed.

If your application demands the latest in power supply technology, with safety and EMI standards already met, contact NCR for detailed specifications and price quotation. NCR Power Systems, 584 S. Lake Emma Road, Lake Mary, FL 32746. Phone 800/327-7612.

Power Systems

### Phase controller comes in SO package

hase controller IC, which includes a high triac drive suitable for a wide range of control applications, is housed in a space-saving small-outline package. The TDA 2086, which is based on the TDA 2085 16-pin dual-inline-packaged controller, is approximately one-half the length and one-quarter the volume of conventional dualin-line packages. In addition to its ability to drive highpower triacs, the chip features a 5-V supply for ancillary CMOS circuitry and a power consumption of 3.1 mA.

Plessey Solid State, 3 Whatney, Irvine, Calif. 92714; (714) 951-5212. \$2.59.


CIRCLE 326

### Clock driver works at 2000 MHz

or driving high-speed GaAs circuits, the CD2.5A clock driver operates from dc to 2000 MHz, allowing random pulse trains of varying rates and duty cycles to be faithfully reproduced with a truly differential output of 2.5 V per side into  $50 \Omega$ . The output offset may be set anywhere between -4 and +2.5V. The CD2.5A features rise and fall times (20% to 80%) of less than 75 ps and a gate on/off/on time of only 100 ps. A resistor divider can be used for ECL-compatibility.

Colby Instruments Inc., PO Box 84379, Los Angeles, Calif. 90073; (213) 450-0261; \$2800.

CIRCLE 327



#### NEW

R5635 CCITT V.22 bis, full-duplex Switched-Capacitor Filter I.C. with MUXes.

R5636 Bell 201/CCITT V.26 combo filter I.C.

R5637 Bell 208/CCITT V.27 combo filter I.C.

R5638 Bell 209/CCITT V.29 combo filter I.C. (available Dec.'84).

R5630 Bell 103, full-duplex filter I.C. with MUXes.

R5631 CCITT V.21, full-duplex filter I.C. with MUXes.

R5632 Industry Standard, Bell 212A/CCITT V.22 full-duplex combo filter I.C.

**R5633** Selectable filter array I.C. for 103, V.21, DTMF and Videotex applications.

R5626 Mask programmable to your specification.

**Contact:** EG&G Reticon 345 Potrero Avenue, Sunnyvale, CA 94086-4197 (408) 738-4266 TWX 910 339-9343; or, Chicago (312) 640-7713; Boston (617) 745-7400; Japan 03-343-4411; England (0734) 788666; Germany (089) 92692-666.



# FORCE COMPUTERS System 68000 VMEbus

Single board solutions for 16/32 bit "open systems" in industrial, business, and scientific environments


If your application requires advanced technology available in production quantities if quality, reliability, and price/performance ratio are the major criteria for supplier selection – then compare our product portfolio with other alternatives.

- Three CPU's for most applications from intelligent I/O controllers to multiuser/ multitasking environments with powerful UNIX\* or real time operating software PDOS\* and up to 1M byte of on-board memory: CPU-1B, CPU-2, CPU-3.
- Two DRAM Boards: 512KB and 2MB; two SRAM Boards: 128KB and 512KB.
   RAM/ROM Board: 512KB (max.); DRAM-1, DRAM-2, SRAM-1/2, RR-1/S/E
- Mass memory interface boards with either direct control of up to seven drives (WFC-1) or intelligent VMEbus interface to SASIbus with DMAC (SASI-1).
- Six-channel serial I/O board with Multi-Protocol-Communications-Controller (SIO-1).
- 32-channel parallel I/O boards either optically isolated (1000V) with DMAC (OPIO-1) or TTL-level with 64 mA drive capability signals (PIO-1).
- Intelligent high resolution graphics subsystem (master/slave) with resolution of 1024 x 1024 pixels and up to 12 bits of pixel depth. Powerful graphics operation through local 68000 MPU in parallel with 7220 graphics controller(s) GDC-1M/1S.
- Winchester/Floppy drive modules with up to 80M bytes: WFMOD-20/80.
- Auxiliaries: Backplanes, chassis, power supplies.
- A variety of Software Products, e.g.:
  - PDOS\* Real-Time, Multi-Tasking, with Basic interpreter, Pascal, Fortran 77, and C Compilers.
  - COHERENT\* UNIX\* V.7 compatible with C Compiler, Pascal and Fortran 77 in preparation.
- UNIX\* System V, Multi-User, Multi-Tasking.
- In development: memory boards with byte parity and 32 bit addressing; dedicated LAN-Controller; high performance communication I/O.

Supported by a worldwide network of distributors and representatives, FORCE Computers is recognized by its customers (and competitors) as the leading supplier of 68000/VMEbus board products.

\*PDOS is a TRADEMARK of Eyring Research, COHERENT is a TRADEMARK of Mark Williams Co., UNIX is a TRADEMARK of AT&T.

Consider, compare, and contact: FORCE COMPUTERS INC.





# He who finishes first, wins.

A lot of PCB CAD/CAM systems may be able to get your PCB's to market. But only one can get you there before all the rest. Our MAXI DESIGN STATION. Partly because you won't have to struggle with start-up bugs. (MAXI has already designed *millions* of PCB's.) Partly because MAXI already has all the functionality others are promising. But mostly because MAXI will run 2-3 times faster than the others. So it can't help but finish first.

If you'd like to get ahead of

your competition: get MAXI. And don't look back. Linking Concept to Product

RACAL-REDAC Linking Concept to Product

4 Lyberty Way, Westford, MA 01886 (617) 692-4900

## Computer system automatically burns in and tests on-board PROMs

aking the complexity out of PROM programming, a computerbased benchtop PROM programmer can be tailored to automatically burn in and test PROMs on circuit boards, eliminating the uncertainties of premounting burn-in. Both the system software and mounting interfaces of the Z-2500 in-circuit memory programming system, from Sunrise Electronics, can be modified at the factory to meet special requirements, thereby delivering a turnkey system

to the user.

Moreover, the unit is a complete CP/M-based computer system that can be used as a stand-alone development

The system, which incorporates a Z80 microprocessor. two 1.2-Mbyte 8-in. floppy disks, a parallel printer port. and an RS-232-C serial interface with a maximum baud rate of 19,200, can program multiple boards simultaneously and handles data paths of up to 32 bits. The interface adapter, mounted on a 96-pin connector, drives up to eight cards in parallel, and the cabinet contains two individual EPROM sockets for off-board programming.

The unit works with various data formats: Intel hexASCII, Motorola S record. Tektronix TEKhex, Mostek, simple binary, and an internal format. It is rated for a maximum of 50 W, and external power supplies are available for more power.


A menu-driven interface lets the user direct the system and add or modify memory patterns. Source code is provided for the programmer's software, which is written in well-commented assembly language, so that the user can make modifications if desired. Also available is the assembler, as well as other CP/M-based software.

The programmer is available now, at a price of \$16,500 for the base unit, with onetime modification costs of \$2500 for a custom interface adapter design, \$750 to \$900 for the actual adapter, and \$5000 to \$7000 for a custom software package.

Sunrise Electronics Inc., 524 South Vermont Ave., Glendora, Calif. 91740; (818) 914-1926.

CIRCLE 315


**Ray Weiss** 







# Board set aids programs for Forth $\mu$ C chip



simple board set eases the development of Forth programs for Rockwell's single-chip Forth microcomputer. The HE4TH-01-16K development system, built by Horne Electronics, provides a full programming environment for the R65F11 microcomputer, which contains in ROM the Forth-79 run-time routines.

The set uses Rockwell's R65010 microcomputer to emulate the more restricted chip, making possible the use of a full 16 kbytes of RAM for development. In addition, a development ROM and a Forth kernal ROM chip are used, creating a full Forth environment for the R65F11.

The main board contains a floppy-disk controller chip (the WD2793) capable of managing up to four quaddensity, double-sided 51/4-in. floppy-disk drives. It also has a parallel printer port, an RS-

232 port, a 40-pin connector for off-board expansion, a bank selection mechanism for off-board RAM, and a PROM burn-in capability.

The other member of the set is a piggyback board holding the R65010. It mounts onto the main board in a socket normally used for a R65F11.

The motherboard also can be used to develop Forth programs directly on the R65F11 processor.

The boards are available either as simple circuit cards or fully assembled and tested. All the necessary components to build a full development station are also available, including power supply, terminal, floppy disks, and cabinet. A single fully assembled and tested board set is priced at \$585. Delivery is from stock.

Horne Electronics Inc., 8602 Bayonne Drive, Huntington Beach, Calif. 92646; (714) 963-4182.

CIRCLE 316

#### **Ray Weiss**

#### **Switchers**

We don't want to see them again.

Our built-in reliability assures we won't.



#### **REASONS**

- 168 Hour Burn-In
- No 50/60 Hz Magnetics
- 105°C Capacitors
- · Short-Circuit Proof Outputs

#### **FEATURES**

- · Completely Enclosed
- Single/Triple/Quad Outputs
- 70% Typical Efficiency
- No Temperature Derating
- Built to meet VDE, UL, CSA,
   & RFI requirements
- 2 Year Warranty

Small - Better!



Twin Lakes Road ● PO Box 185 North Branford, CT 06471 (203) 481-5721 ● TWX 710-452-3092

A PRIME TECHNOLOGY COMPANY

CIRCLE 185 FOR LITERATURE ONLY

CIRCLE 186 FOR IMMEDIATE APPLICATION

#### Scope calibrator is fully mobile

ypically, oscilloscopes have to be removed from their working environment and brought to the laboratory for calibration. Now, thanks to the 4003A-Mod 101 mobile automated calibration system from Ballantine Laboratories, such operations can be carried out right on the production floor.

Capable of calibrating oscilloscopes with bandwidths as high as 1 GHz, the system features a sweep range of 5 s/cm to 500 ps/cm, an amplitude range of 40 µV to 200 V, and a rise time as fast as 200 ps. Dubbed Calcart, it is built around an IBM PC with a high-resolution full-color display, dual floppy-disk drives, 256 kbytes of RAM, and an IEEE-488 interface. Rounding out the hardware is a bidirectional 160-char/s printer and the company's 6127BN programmable oscilloscope calibrator.

Equally important is the company's Computest software that ties the system together. The software features color-coded, menu-driven operation for ease of use.

During calibration, the software analyzes error data and gives quick pass or fail responses. Moreover, it supplies instructions on the action needed to correct the fault. When an instrument passes the checks, a calibration certificate is printed out.

The system is priced at \$29,950. Delivery is in 30 to 45 days after receipt of an order, and versions containing the necessary sources to fully calibrate digital multimeters also are available.

Ballantine Laboratories, Inc., PO Box 97, Boonton, N.J. 07005: (201) 335-0900.

CIRCLE 312



#### Covering the full spectrum of your telecommunications needs.

Solve your telecommunications design problems with Teltone's complete family of telecom IC's. You'll find innovative, up-to-the-moment single-chip and hybrid generators, detectors, receivers and relays — all backed by Teltone's commitment to performance, reliability and quality.

Leading the industry in DTMF technology.

Consider the M-957, a monolithic 22-pin CMOS DTMF receiver. It needs fewer support components, so designs can be simple and use a minimum of space. The new M-958 is a hybrid PCM-compatible DTMF receiver that is dial tone immune and packs  $\mu$ -Law or A-Law PCM input at up to 3 MHz into a single 22-pin package.

Designing the first call progress IC's. Need to monitor for or generate dial tone, circuit or station busy, audible ringing and other call routing tones? Take a look at our exciting 8-pin CMOS M-980 Call **Progress Tone Detector** or our unique new 14-pin CMOS M-991, the only Call Progress Tone Generator on the market. If you require precise detection of the four common call progress tones (350, 440, 480 and 620 Hz), Teltone has a 22-pin CMOS solution for you called the M-982.

A reputation for telecom innovations. Rounding out our complete family of telecommunications components are the M-949 Line Sense Relay and the M-959 Dial Pulse Counter and Hook Status Monitor. The M-949 is a small PWB-mount loop current detector that, when connected to the tip and ring voice pair of an ordinary telephone line, responds to currents of 18-125 mA with a 1 form A relay closure. The CMOS M-959 features independent hook status monitoring and includes time-guarded dial pulse counting and pinselectable dialing speeds of 10 or 20 PPS.

For more information on components from the leader in telecom technology, call Teltone today: 1-800-227-3800, ext. 1130.

#### TELTONE

Teltone Corporation, the telecommunications company. P.O. Box 657, Kirkland, WA 98033. In the east call: Teltone Corporation, (904) 262-6910. In Canada, contact: Teltone Ltd., 183 Amber Street, Markham, Ontario L3R 3B4, (416) 475-0837.

#### 100-kHz signal analyzer is versatile

sers who work with frequencies between dc and 100 kHz can now avail themselves of a single instrument that excels at network, spectrum, and waveform analysis. The HP 3562A from Hewlett-Packard features an 80-dB dynamic range, built-in noise and sinewave sources, an amplitude accuracy to within  $\pm 0.15$  dB. and a frequency resolution of 25.6 µHz. What's more, its two input channels are matched to within  $\pm 0.1$  dB for amplitude and to within  $\pm 0.5^{\circ}$  for phase.

For network analysis, the

analyzer offers three measurement techniques: linear-resolution FFT, logarithmic resolution, and true swept sine wave. Moreover, block-operation waveform math can be used to normalize network measurements or compute secondary functions.

When spectrum analysis is needed, the unit's speed and accuracy permit on-line determination of distortion, drift, modulation, and phase noise. Furthermore, time and frequency traces may be displayed simultaneously, or one trace may be used to display a 100-kHz spectrum while the


other trace zooms in on a portion of the spectrum.

Complete analysis of time waveforms and transients is simplified by two modes. Time capture uses the instrument's internal memory as a 20,000-sample buffer, and time throughput stores sampled data on an external disk drive.

The HP 3562A is priced at \$23,900. Delivery takes 16 weeks.

Hewlett-Packard Co., Inquiries Manager, 1820 Embarcadero Road, Palo Alto, Calif. 94303.

CIRCLE 311



#### **Constant Current Sources**

☐ Teledyne Crystalonics, the leading producer of constant current sources (CCS), offers a full range of two terminal devices, both standard and special.
☐ The array of devices includes the popular FET CCS's in the D0-7 package (1N5283-1N5314, also available as JAN, JANTX and JANTXV and CIL-250 series) which have values from 0.2 to 10 mA. Higher current FET CCS's, to 50 mA, are supplied in the T0-5 package.


— Other devices are offered in various TO packages from 1 μA to 1 amp current levels with peak operating voltages to 1000 V.

Some applications of these devices are:


- · Active load, biasing and coupling resistors
- Waveform generators (triangle, square, sawtooth, stairstep)
- Low noise, low voltage, zero T/C voltage references
   Non destruct fuses.
- Non-destruct fuses
- Two-step battery chargers
  Send for free application notes and data sheets.

#### \*\*TELEDYNE CRYSTALONICS

147 Sherman Street Cambridge, MA 02140 Tel: (617) 491-1670 TWX 710-320-1196



# Solutions




# Networks that will improve your cost.

#### Dale's CSC.

Low cost, plus the assured quality and delivery of Dale's ZIP program makes CSC thick film resistor networks tough to beat. These epoxy conformal coated networks are available in .195", .250" and .350" aboveboard heights with 3 through 11 resistors (1 pin common) and 2 through 6 isolated resistors. Tolerances of 1%, 2%, 5%, 10% and 20% are available in a range from 10 ohms to 3.3 megohms. Evaluate the CSC...as part of Dale's ZIP program. It's guaranteed to give you problem-free delivery and quality. Contact: Dale Electronics, Inc., Box 26950, El Paso, TX 79926.

For more details, call: **915-592-3253** 

CIRCLE 190



#### Hybrid clocks are ready from stock.


#### Dale's XO-43.

We're ready to match your timing requirements from a ready-to-ship stock of clock oscillators in 23 standard frequencies —1.0 to 50 MHz. Dale X0-43 clocks will drive up to 10 TTL gates and are available in accuracies from .005% to 1% over a temperature range from 0 to 70°C. Input voltage is +5 VDC. Their rugged, resistance welded metal case provides a hermetic seal and requires minimum board space (.225"Hx.600"Lx.515W). Grounding for EMI shielding is also provided. For information on the frequency you need, contact Dale Electronics, Inc., 1155 West 23rd St., Tempe, AZ 85282.

For more details, call: **602-967-7874** 



# from Dale



#### Ultra-precise, compact and ready to ship

#### Dales PTF

PTF thin film resistors let you package tolerances down to .01% in spaces as small as .175" L. x .070" D. PTF's are designed to meet MIL-R-122, and they're available from stock in 1/20, 1/8 and 1/4 watt sizes in a range from 10 ohms to 1 Meg. Count on PTF's for low levels of reactance and noise combined with an absolute T.C. as low as ±5 PPM/°C. They're available in matched sets... are automatically insertable...and very competitively priced. For details and application assistance, contact: Dale Electronics, Inc., 2300 Riverside Blvd., Norfolk, NE 68701.

Call this 402-371-0080

CIRCLE 192

#### Here's how to replace RCR carbon comps

#### Dales RLR

Better performance. Better delivery. Competitive price. If you need more reasons to move from carbon comps to RLR (Dale type ERL) metal film resistors, give us a call. We can help you forget about tolerance problems due to moisture absorption while you gain the added stability of MIL-R-39017's more stringent requirements...all in a size and value range that will match your present -05, -07 and -20 needs. It's worth your time to get all the facts and find out how much better we can serve you. Contact Dale Electronics, Inc., 2300 Riverside Blvd., Norfolk, NE 68701.

For complete 402-371-0080 information:



#### Logic analyzer operates at 100 MHz

o acquire timing data, most logic analyzers use fast, dedicated input channels that are separate from those used for state acquisition. In contrast, all 48 channels of Gould's K205 can operate at 100 MHz.

Not only that, the analyzer is fast enough and wide enough to serve the needs of the hardware designer debugging bit-slice, ECL, and gate-array designs. What's more, an optional user-definable disassembler, the A12520, enables users to cap-

ture and disassemble code from any nonstandard microprocessor or algorithmic

state machine.

Sixteen independent triggering decision levels, with four commands at each level, take advantage of the unit's speed. Four decisions can be made every 20 ns, permitting designers to locate difficult problems by selectively triggering on a unique event.

Moreover, the instrument has a unique feature that speeds analysis by comparing timing sequences with stored references. For intermittent fault isolation and reliability analysis, multiple measurements may be automatically stored on the unit's disk drives.

The analyzer also has a glitch mode that displays transient noise on all of its channels. When this mode is enabled, a latching scheme maintains full channel width and memory depth.

The K105 is priced from \$14,000. Delivery takes six weeks. The A12520 costs \$950 and is delivered in 30 days.

Gould Inc., Design and Test Systems Division, 4600 Old Ironsides Drive, Santa Clara, Calif. 95050; (408) 988-6800.

CIRCLE 313

#### **UNIX** MASTER

#### Single board UNIX™ — Battle Proven

Designed for maximum power at minimum cost, the HK68<sup>™</sup> — UNIX<sup>™</sup>MASTER — is a proven leader providing Multibus<sup>™</sup> users more space, more speed, and more flexibility to apply to difficult design problems.

Powerful and versatile, the Heurikon HK68<sup>™</sup>, sports 68000/68010 CPU (8Mhz or 10Mhz), quad channel DMA controller, MMU, 128K, up to 1M byte of dual access RAM with parity, up to 64K bytes of EPROM, four RS-232-C ports

(optional RS-422 on one port), winchester I/F, streamer tape drive I/F, eight user definable LED's, four dipswitches, and two iSBX<sup>TM</sup> connectors for further I/O expansion — all on a single board. Other operating systems available include PolyFORTH<sup>TM</sup>, CP/M-68K<sup>TM</sup>, Regulus<sup>TM</sup>, and VRTX<sup>TM</sup>.

Make your tough decision an easy choice. Call Heurikon direct 1-800-356-9602, in Wisconsin 608-271-8700


PolyFORTH is a trademark of Forth, Inc., CP/M-68K is a trademark of Digital Research. Regulus is a trademark of Alcyon Corporation. VRTX is a trademark of Hunter & Ready. UNIX is a trademark of Bell Laboratories. iSBX and Multibus are trademarks of Intel Corporation. HK68 is a trademark of Heurikon Corporation.



1 · 800 · 356 · 9602 In Wisconsin 608 · 271 · 8700

HEURIK CORP. N 3201 Latham Dr., Madison, WI 53713

.....



#### Your new interconnect systems are here.

ELFAB now offers you our newest line of interconnect products. Our surface-mounted Finger-Pac™ and new two-row or four-row Box-Pac™ connectors simply reflow solder onto your daughter boards. Box-Pac offers high-current bussing capabilities, and occupies the least amount of real estate, of any high-density two-piece connector system available today.

Our new Press-Pac<sup>™</sup> card-edge and standard DIN connectors pressfit from the top of the insulator into your backplanes quickly and economically, with no special tooling required. Or you might prefer our complete Inverse DIN system for other applications.

Whatever your interconnection needs may be, we're ready to meet them, and the competition, head-on. Call ELFAB today.



Elfab Corporation • P.O. Box 810555 • Dallas, TX 75381-0555 (214) 233-3033 Toll-free 800-527-0753 TWX 910-860-5460

#### Scopes optimize industry-standard 2465

Improving on the powerful features of the industrystandard 300-MHz 2465 portable oscilloscope are three units that integrate five new measurement capabilities. In addition, the stand-alone scopes work equally well as controller-driven measurement packages. Designated the 2465 Special Editions, the instruments comprise a digital video system (DVS), a digital multimeter system (DMS), and a counter-timer system (CTS).

The DVS incorporates a talker/listener IEEE-488 interface bus, a counter-timertrigger, a word recognizer, an autoranging digital multimeter, and television-waveform measurement capability. The DMS provides the same capabilities as the DVS, minus the TV function. Similarly, the CTS offers all but the TV and digital multimeter capabilities.

Tektronix Inc., PO Box 1700, Beaverton, Ore. 97075; (800) 426-2200 or (503) 627-9000. \$8500, \$7800, and \$6600 for the DVS, DMS, and CTS, respectively.

CIRCLE 328

#### Port turns IBM PC into development system

n emulator port transforms the IBM PC XT into a universal development system for designing, testing, debugging, and implementing hardware and software for most popular micropro-

cessor devices. The Kontron PC Interface (KPCI) package consists of hardware and a set of software developmentsupport tools, including a cross assembler, a linker, and an emulator, as well as additional CP/M utilities. When an application program is completed, an optional Pascal compiler or assembler can process the edited source text. Once text editing is finished, the linker combines smaller modules into one main load module, which becomes an absolute binary module for loading and executing in the target system with the support of an emulator subsystem. The emulator connects to the IBM PC through the connector on the KPCI card.

Kontron Electronics, 630 Price Ave., Redwood City, Calif. 94063; (415) 361-1012. \$1500; six weeks.

CIRCLE 329

#### Digital manometer has $\pm$ 1.5% nonlinearity



eplacing basic hydrostatic models, a 3½-digit manometer measures pressure by means of a solid-state piezoresistive transducer. The unit achieves a full-scale accuracy to within  $\pm 1.5\%$ . ±1 digit typical at 25°C. The primary measurement range

is 0 to 10 in. H<sub>2</sub>O, while other units of measure are transposed internally and displayed in kilopascals, mmH<sub>2</sub>O, and mmHg-with respective ranges of 0 to 2.49, 0 to 254, and 0 to 18.7. Features include a zero-adjust calibration control, a hold function that freezes the display, and a continuity tester to verify circuit integrity.

Cleveland Controls Inc., Sensing Switch Division, 1111 Brookpark Road, Cleveland. Ohio 44109; (216) 741-9444.

CIRCLE 330

#### Portable calibrator works with IBM PC

upplied with IBM PC-Compatible software, the Model 4100 Portocal is an automatic calibration system designed for in-situ calibration of multimeters and automatic test equipment. The portable cart houses the Model 4000A (dc voltage, current, and resistance) and the Model 4200 (ac voltage and current) calibrators.

The system software provides menu prompts to guide the user through predefined calibration procedures. If the unit under test is one of Datron's Autocal series multimeters-or an IEEE-488-compatible instrument incorporating internal electronic calibration—the software automatically recalibrates it without removing the instrument cover.

Datron Instruments Inc., 3401 SW 42nd Ave., Stuart, Fla. 33494; (305) 283-0935.

# One of these Datel Sample-Holds can help you achieve your design engineering goals.

If your system's design calls for exceptionally accurate, high-speed sample and holds, then Datel has a precision device that can help you realize your design goals.

**High Speed, High Accuracy** Our SHM-4860 is a 12-bit hybrid sam-

ple-hold that acquires a 10V input change to .01% accuracy in only 200

nsec.

The SHM-4860 is complete with internal hold capacitor and offers 60 nsec sample to hold settling time to .01% and an aperture uncertainty of only ±50 psec.

Applications Include: • Data Acquisition and Distribution Systems • Transient Recorders • Fourier Analyzers

Video Speed, Dual Output

Now you can order a new, low-cost sample-hold designed just for ultra-fast video data conversion. Our SHM-7 acquires a 2V input change to 0.1% in only 40 nsec with only 20 nsec hold-mode settling time, providing sampling rates of up to 17 MHz.

The SHM-7 features dual buffered outputs ( $\pm$ 5V, 30mA, 13 $\Omega$ ). It's an ideal choice for two-stage conversion

techniques

Applications: • Parallel or Flash A/D Converters • Video Processing Systems • Radar Signal Sampling • Transient Analyzers

Low Cost, High Speed

The SHM-20 is a low-cost, highperformance monolithic sample-hold designed for high-speed signal processing. It features a typical 1.0 µsec acquisition time for a 10V step to .01%, with typical aperture uncertainty of 1.0 nsec.

Applications: • Data Acquisition and Distribution Systems • Deglitching Circuits • Auto Zero Circuits • Peak Amplitude Detectors

NOTE: For military and aerospace applications Datel's Sample-Holds can be subjected to rigorous screening procedures in accordance with MIL-STD-883, method 5008, Class R

For your FREE Engineering Data Sheets call 617/339-9341 Extension 121, or write Mr. Bob Leonard, Applications Engineer, Datel, 11 Cabot Boulevard, Mansfield, MA 02048.



#### Unit performs digital, analog, discrete tests

he LTS-2020, a benchtop component test system, combines high-speed ac digital test capability with the ability to test analog circuits-including data converters-and discrete and passive components. The instrument executes instructions in approximately onehalf the time of earlier LTS series testers, while maintaining 16-bit accuracy. It is programmed in Basic and can run programs developed on other LTS consoles. The LTS 2020 has 128 kbytes of memory-84 of which are available to the user.

Configured for ac digital testing with the LTS-2510 family board, the LTS-2020 costs \$44,500 and is the only tester to offer  $\pm 1.5$ -ns accuracy and 500-ps resolution for under \$80,000.

Analog Devices Inc., Component Test Systems Division, 10 Corporate Place, Burlington, Mass. 01803; (617) 273-4780.

CIRCLE 332

#### 1-GHz scope aids high-speed logic design


A fully programmable digitizing oscilloscope offers designers of high-speed logic circuits 1-GHz performance and 100-ps time-base accuracy.

The HP 54100 comes with two vertical channels and one or two trigger inputs, configured with removable pods. The scope automatically measures frequency, period, pulse width, transition times, and peak-to-peak amplitude. Sweep rates of 100 ps/division to 1 s/division allow the user to view both very fast and very slow events.

Hewlett-Packard Co., Inquiries Manager, 1820 Embarcadero Road, Palo Alto, Calif. 94303; call local sales office. \$17,600 (A) and \$19,300 (D); four weeks (A) and eight weeks(D).

CIRCLE 333

# Fujitsu believes an OEM deserves lots of fast talk.



The world's first 14.4 kilobit modem card; superior reliability in a compact package 9,600, 4,800 & 2,400 bps core modems and stand-alone modems also available.

That's why Fujitsu now offers the world's *first* 14,400 bit per second modem card, along with companion 9,600 bps, 4,800 bps and 2,400 bps core modems. All three single PC boards employ custom digital signal processors. And from a standpoint of versatility, the units are compatible with *any* type of equipment.

By offering your customers the fastest, most reliable, and economical modem, you're not only offering state-of-the-art technology, but a product that is backed by a world leader in the telecommunications and computer industry.

We also realize that diversity sells your products and increases your profits. So, Fujitsu not only offers core modems, but also offers a full line of stand-alone modems.

Fujitsu modems meet the future head on. And that's the kind of fast talk you deserve.

FUJITSU


Fujitsu America, Inc. • Data Communications Division • 3055 Orchard Drive, • San Jose, California 95134 • (408) 946-8777



When you need Axial Leaded Tubular Capacitors with Single Layer Construction and Inductors...you want reliability and price. Taiyo Yuden provides both. And what's more, axial leaded components from Taiyo Yuden are available in three sizes with lead spacing as close as 200-mils.

Now manufactured in southern California to give you instant delivery, Taiyo Yuden components are specifically designed and sold for use in automatic insertion equipment.

No matter what your specs, Taiyo Yuden offers you the broadest range of product...axial leaded inductors from 0.22 to  $1000\mu h$ ...Axial Leaded Tubular Ceramic Capacitors from 1 to 33,000pF & 12 to 50-V...Melf (Metal Electrode Face-bonding) Leadless Tubular Ceramic Capacitors from 1 to 22,000pF & from 16 to 50-V. Taiyo Yuden...where experience and reliability means quality. To find out more about Taiyo Yuden components, write or call today:



# EHVQ™ SWITCHING POWER SUPPLIES WITH OPTIONAL BATTERY BACKUP



Optional battery backup in a switching power supply - a unique idea? Not according to our customers. With an EHVQ™ in your UNIX™ based system, lost data bases are a thing of the past. Our battery backup board has enough status signals to make interface with any operating system an easy job for hardware and software designers.

Other applications include industrial controls, point of sale systems, and medical electronics. Any system needing protection against brownouts or power failures can use an EHVQ™. Best of all, the battery backup is a field upgradeable option. The backup board plugs into your system's EHVQ™ as easily as adding more memory.

Write or call for information about our EHVQ™ evaluation kit. TII Electronics EHVQ™ switchers...

#### HELPING YOU BEFORE YOUR CHIPS ARE DOWN.™

	170,	220, 360	Watt Mod	lels	
		OUTI	PUTS		
MODEL NO.	MAIN	*AUX 1	AUX 2	AUX 3	SIZE
170 - 4	5V 15A	12V 4A	12V 4A	5V 1A	13.4 x 5 x 2.6
220 - 6	5V 25A	12V 6A	12V 4A	5V 1A	15 x 5 x 2.6
360 - 6	5V 45A	12V 10A	12V 5A	5V 1A	15 x 6.5 x 2.6
*AU	Х 1 сара	ble of 4A	surge for :	20 secon	ds.

Over 30 other single, double, triple and quad output models are available.  $EHVQ^{\text{in}}$  Switchers are backed by a one year warranty.




226 Terminal Road, E. Setauket, New York 11733 516-751-6285

Circle 199 for literature

Circle 200 to have applications engineer call

©1983 TII ELECTRONICS

UNIX is a trademark of AT&T Bell Laboratories.



医水流 医外外	MILITARY	INSERTION LOSS PER MIL-STD-220							
FILTER TYPE	STANDARD	100KHZ	1MHZ	10MHZ	1GHZ	10GHZ			
Feed-Thru	MIL <sup>2</sup> C-39014			5db	40db	60db			
Solder-in Pi	MIL-F-15733		5db	50db	60db	60db			
Threaded Bushing Pi	MIL-F-15733		5db	50db	60db	60db			
Coaxial Feed-Thru	MIL-C-83439	19db	35db	55db	70db	70db			
Coaxial LT	MIL-F-15733	27db	57db	70db	70db	70db			
Coaxial LB	MIL-F-15733	28db	44db	60db	70db	70db			
D Connector	MIL-C-24308		2db	20db	55db	50db			
Multi-Network (6 line)	MIL-F-15733			10db	50db	50db			
Multi-Network (12 line)	MIL-F-15733			5db	50db	50db			
Cylindrical Connector	MIL-C-38999			20db	60db	55db			

### MURATA ERIE EMI/RFI FILTERS

Murata Erie manufactures one of the broadest lines of EMI/RFI filters in the bloadest lines of LMIKI Tritlers if the world. Covering every frequency from 60Hz to 10GHz, these filters meet virtually every application requirement including all appropri-ate MIL specifications. Feed thrus, low pass and power line filters, as well as a complete line of filter connectors are all available. These filters are all backed by a Quality Assurance program that meets or exceeds the requirements of MIL-Q-9858 and DND-1015.

Murata Erie also specializes in custom-designed filters for special applications and maintains a complete in-house staff of experienced application engineers to aid in solving the most difficult EMI/RFI problems.

To receive complete technical information on Murata Erie's comprehensive line of EMI/RFI filters, write to Murata Erie North America, Inc., 1148 Franklin Road, SE, Marietta, Georgia 30067 or call 613-392-2581.

Regional Sales Offices: West—714-835-4822 Southeast—305-644-0954 Central—312-297-5560 Northeast—617-245-7880 Canada—416-676-9484

muRata 😑

#### Low-cost unit programs wide range of EPROMs



The Model 21A programs over 120 different MOS and CMOS EPROMs and EEPROMs having densities of up to 256k. At \$1450, the unit offers a variety of features that are commonly found only in higher-priced programmers.

The 21A features compre-

hensive test facilities to guarantee reliable programming. On power-up, a self-diagnostic routine checks the internal RAM and ROM, the frontpanel display, the microprocessor, and the serial I/O port. Before programming, the 21A monitors devices for programmed bits and protects them from overvoltage, overcurrent, and incorrect insertion. After programming. the unit checks for V<sub>CC</sub> margin and correct output polarity, as well as calculating a check sum of the programmed

Data I/O Corp., 10525 Willows Road NE, Redmond, Wash. 98073; (206) 881-6444. Two weeks.

CIRCLE 334

#### In-circuit emulator carries low price tag



esigned to provide engineers with a portable stand-alone instrument for developing, testing, and maintaining 6502-based hardware and software, the DA6502-B in-circuit emulator costs less than \$600—considerably lower than comparable units. With the DA6502-B, the user can examine processor registers, read and modify memory locations, halt a program at a specific address, step through a program one instruction at a time, and stop a program at a location after a number of loops have been completed.

The unit comprises a 6½-by-7½-by-3½-in. terminal with a keyboard and a display, emulator logic and program, a 6502 microprocessor, a bus switch that connects the emulator to the user's system, and a power supply. Its 24 functions are invoked by simple one- and two-keystroke sequences.

Da-Tech Corp., 92 Steamwhistle Drive, Ivyland, Pa. 18974; (215) 322-9410. \$595 (OEM discounts available); 30 days.

CIRCLE 335

### At last, benchtop accuracy and stability in a portable voltage calibrator.

The smallest, most dependable and most accurate microprocessor-based voltage calibrator on the market today is Datel's Model DVC-350.

Don't let its size fool you. The DVC-350 is a precision instrument. Its overall accuracy of 0.015% @ 25°C traceable to NBS is comparable to many expensive benchtop instruments.

The DVC-350 is the choice of engineers, scientists and field service technicians who appreciate "true" portability, but who can't afford to sacrifice

accuracy.

The DVC-350 is ideal for remote site calibration and laboratory use for the calibration of DPMs, strip chart recorders, oscilloscopes, data acquisition systems, A/D and V/F converters, test set-ups, breadboarding and many other applications. Wherever accuracy and portability are required.




#### Why pay more for less performance? At \$369.00, the DVC-350 offers . . .

- True portability
- Battery operation
- Laboratory accuracy of ± .015%
- $\pm$  12.000 volt output range
- 100 μV resolution

- 20mA current limited drive capability
- Inherent isolation
- Microprocessor controlled functions
- Decimal and hexadecimal output modes

If you're looking for true portability, but can't afford to sacrifice accuracy, Datel's new DVC-350 is the Voltage Calibrator you've been looking for. To order or for more information contact: Datel, 11 Cabot Blvd., MA 02048 (617) 339-9341.



# Tearalong the plotted line.

And rip through deadlines in record time. With Pertplotter,™ the new network logic plotting program designed to complement Westminster's Pertmaster™ project management software.

Pertmaster is the professional's choice. It's the critical path management program capable of handling up to 2500 activities using industry standard notations. And Pertplotter is its logical

and perfect companion.

extension

That's because Pertplotter can plot and print logic diagrams of up to 500

activities in Arrow or Precedence notation. Using a variety of easy-tofollow colors that help monitor the progress of your projects from concepts to completion.

It also reduces plot
times by giving you highly
compressed logic diagrams.
Time windowing. A "fastplot" option for quick
views of nodes and connectors. And full
control of title
block, activity

data content, line styles, and much more. And at \$495.00, we don't think you can afford to wait. Just call us or




your local Pertmaster dealer for more information: (415) 424-8300.



Westminster Software, Inc. 660 Hansen Way, Suite 2 Palo Alto, California 94304























### At Nichicon, we want to help you find your capacitor choice.

#### **Miniature Aluminum Electrolytic Capacitors**

Series Type	Feature	Operating Temp. (°C)	D.C. Leakage Current (μA)	Construction	Rated Voltage Range (V.DC)	Capacitance Range (μF)	Standard Capacitance Tol. (%)
LB	Standard Size	-40~+85	0.03CV (A*)	Radial (U)	6.3~100	0.1~10,000	± 20 (M)
LB	General Purpose	-40~+85	(4μA Min.)	Axial (T)	6.3~100	0.47~33,000	± 20 (M)
VX	Smaller Standard Size     High CV Density     General Purpose	-40~+85	0.01CV (B*) (3μΑ Min.)	Radial (U)	6.3~100	0.47~10,000	±20 (M)
HU	High Voltage	-25~+85	0.00014 - 40.001	Radial (U)	160~450	1~100	-10~+50 (T)
HU	High voltage	-25~+85	0.06CV + 10 (C*)	Axial (T)	160~450	1~470	-10~+50 (T)
BU	High CV Products	-40~+85	0.02CV (C*) (3000μA Max.)	Radial (U)	6.3~100	1,000-3,300	±20 (M)
VS	Low Profile Design	-40~+85	0.01CV (B*) (3μA Min.)	Radial (U)	6.3~50	0.1~4,700	±20 (M)
кв	Low Leakage		0.002CV (B*)	Radial (U)	6.3~100	0.1~100	±20 (M)/±10 (K
KB	Tantalum Replacement	-40-+85	(0.4μA Min. – Ü) (1μA Min. – T)	Axial (T)	6.3~100	0.47~100	±20 (M)/±10 (K
SA	Super Miniature (7mm Height)     Tantalum Replacement	-40~+85	0.01CV (B*) (3μΑ Min.)	Radial (U)	6.3~50	0.1~100	±20 (M)
SL	Super Miniature (7mm Height)     Tantalum Replacement     Low Leakage	-40~+85	0.002CV (B*) (0.4μA Min.)	Radial (U)	6.3~50	0.1~100	±20 (M)
SP	Super Miniature (7mm Height)     Non-Polarized	-40~+85	0.05CV (B*) (10μA Min.)	Radial (U)	6.3~50	0.1~47	±20 (M)
MA	Ultra-Miniature (5mm Height)     Tantalum Replacement	-40~+85	0.01CV (B*) (3μΑ Min.)	Radial (U)	4~50	0.1~220	±20 (M)
EB	Non-Polarized	-40~+85	0.01CV (C*)	Radial (U)	6.3~100	0.47~1,000	±20 (M)
ED	* Non-Polanzed	-40~+85	(5µA Min.)	Axial (T)	6.3~100	0.47,~3,300	±20 (M)

#### **Miniature High Temperature Capacitors**

PC	Standard Size     Wide Temp. Range	-55~+105	0.03CV (A*) (4μΑ Min.)	Radial (U)	6.3~100	0.47~10,000	±20 (M)
	General Purpose	-40~+105	0.03CV (A*) (4µA Min.)	Axial (T)	6.3~100	0.47~10,000	±20 (M)
BB	High Temperature	40 405	0.002CV (C*)	Radial (U)	10 100	0.47-1,000	- 20 (84)
00	High Reliability	-40-+105	(2µA Min.)	Axial (T)	10~100		±20 (M)
BE	• High Temp. (+125°C)	-40125	0.002CV (C*)	Radial (U)	10-50	0.47-470	± 20 (M)
DC	High Reliability	-40125	(2µA Min.)	Axial (T)	10-50	0.47-470	±20 (M)
ST	High Temp. ( + 105°C)     Super Miniature (7mm Height)	- 40~ + 105	0.01CV (B*) (3μA Min.)	Radial (U)	6.3~50	0.1~100	± 20 (M)

#### **Miniature Special Application Capacitors**

PX	Low ESR     Smaller Package     High Ripple	-55~+105	0.03CV (A*)	Radial (U)	6.3~63	22-2,200	± 20 (M)
TM	For Timing Circuits     Very Stable at High Temp.	-40-+85	0.001CV + 1 (B*)	Radial (U)	10~50	1~470	± 20 (M) ± 10 (K)
HA	High Frequency, High Ripple	-25-+85	100 (C*)	Radial (U)	25	2.2~10	±10 (K)

#### **Can Type Lytics**

HL/LL	P.C.B. Mount	-40~+85	3√CV (C.)	Can (L)	16~100	470~22,000	-10~+30 (Q)
UB	Snap-in Term., P.C.B. Mount     Smaller Size	-40~+85	3√CV (C*)	Can (L)	16~100	1,000~15,000	±20 (M)
NW/NK/NS	Computer Grade	-25~+85	3√CV (C*) (10mA Max.)	Can (L)	6.3~450	120~1,000,000 (1F)	-10~+50 (T)
PS [LR]	Snap-in Term, P.C.B. Mount     For Switching Regulators     [Smaller Size]	-40~+85 (160~250) -25~+85 (350~450)	3√CV (C*)	Can (L)	160~450 [400]	47~1,000 [47~330]	± 20 (M)
PK	High Ripple, Switching Reg.     Extended Temp. Range     Snap-in Term., PC.B. Mount	-40~+105	3√CV (C*)	Can (L)	200-250	150~1,000	±20 (M)
GM [GF]	High Ripple, Switching Reg.     Extended Temp. Range     Snap-in Term., PC.B. Mount     [Smaller Size]	-40~+105 (160~250) -20~+105 (400)	3√CV (C*)	Can (L)	160~400 [400]	47~1,000 [47~330]	±20 (M)
FL	Low Profile (20mm Height)     Snap-in Term., PC.B. Mount     For Switching Regulators	-40~+85	3√CV (C*)	Can (L)	160~250	82-270	±20 (M)

#### **Class III Semiconductive Ceramics**

Series Type	Temperature Characteristics	Rated Voltage (V. DC.)	Capacitance (μF)	Standard Capacitance Tolerance	Insulation Resistance (MΩ)	Dissipation Factor (at 1kHz)
HET YST	12	0.022-0.47		12V:		
	Y5T	25	0.01~0.1		0.022~0.1μF -1 Min.	
1111	ne.	50	0.01~0.1		0.22μF	12V: 7.0% Max.
		12	0.047~0.47	± 20% (M) + 80 20% (Z)	0.47μF -0.25 Min.	25V: 5.0% Max.
	Y5V	25	p.022~0.47	+8020% (2)	25V: 0.01~0.22µF -1.000 Min.	50V: 5.0% Max.
HEV	150	50	0.01-0.1		0.47μF –1,000 Min. 50V: –1,000 Min. –1,000 Min.	

#### **Polyester Capacitors**

Series Type	Rated Voltage (V. DC)	Capacitance (μF)	Standard Capacitance Tolerance	Insulation Resistance	D.F.
QYA	100	0.001-0.47	±5% (J). ±10% (K). ±20% (M)	9.00MΩMin.	1.0% Max. at 1kHz
QXM (Radial)	250, 400, 630	0.01~2.2	±5% (J). ±10% (K) ±20%(M)	≤0.33μF-9.00 MΩMin.	1.0% Max. at 1kHz
QAM (Axial)	250, 400, 630	0.15-10	± 5% (J). ± 10% (K). ± 20% (M)	>.033µF-3,000 MΩMin	1.0% Max. at 1KHZ
QAL	125V. AC	0.0047~.022	± 10% (K). ± 20% (M)	9,000MΩMin. at 100 V. DC 1 Min.	1.0% Max. at 1kHz

(A\*) = Leakage Current after 1 minute (B\*) = Leakage Current after 2 minutes (C\*) = Leakage Current after 5 minutes



#### NICHICON (AMERICA) CORPORATION

927 EAST STATE PARKWAY CIRCLE 206 SCHAUMBURG, ILLINOIS 60195
PHONE • (312) 843-7500 TELEX • 20-6577











#### SOFTWARE

#### Automatic translators aid Fortran users

ACT, for Fortran Automatic Conversion Tool. provides automatic translation and documentation of Fortran programs from one computer to another and from one dialect to another. The program is currently available for converting VAX-11 Fortran into Data General Fortran 77, HP-UX Fortran/9000, Apollo Fortran. Gould Fortran 77+. IBM PC Professional Fortran, and Microsoft Fortran. Also available are tools for converting IBM Fortran IV into HP-UX Fortran/9000 and Data General Fortran 5 into Data General Fortran 77.

The translators may be purchased as stand-alone tools or as an integrated transportation package, including the documentation of operating system dependencies, optimization assistance, and more.

Softool Corp., 340 S. Kellogg Ave., Goleta, Calif. 93117; (805) 964-0560.

CIRCLE 337

#### Graphics program creates scientific plots

Running on an IBM PC or PC-compatible computer, a general-purpose high-resolution graphics program makes screen and printer graphs for scientific and financial applications. With PCPLOT software, users can create linear, semilogarithmic, and full logarithmic plots in any combination of

the X axis and the two Y axes. Forced scaling and automatic scaling is supported in any combination of the three axes. Up to four plots can be made on the same graph using optional legends. PCPLOT is

completely menu-driven and program-prompted.

BV Engineering, 2200 Business Way, Suite 207, Riverside, Calif. 9250l; (714) 781-0252. \$62.95



#### SOFTWARE

#### Software tools let IBM PC talk

he SoundWare series of software not only allows an IBM PC XT to perform telephone answering and management activities, but it also permits software developers to write applications with voice communication capabilities. The series includes a voice communication card, VoiceMate telephone management software, and programming software called SoundTools.

Used in conjunction with VoiceMate, the Communicard records high-quality voice onto a hard disk. Once the telephone is plugged into the card's RJ11 connector and the card plugged into a half slot of the computer, the user need only speak into the handset to record a message.

For customizing applications. Sound Tools offers function calls that include Record A File, Play A File, Receive A Touch Tone Digit, and Generate A Touch Tone Digit. It can be used with several programming languages, such as MS Basica, C, assembly, and MS Pascal.

Digital Pathways Inc., 1060 E. Meadow Circle, Palo Alto, Calif. 94303; (415) 493-5544. \$449.

CIRCLE 339

#### Interface program guides Unix users

coftShell, a simplified user interface, allows users to take full advantage of the Unix operating system's

considerable capabilities. The program provides templates to facilitate choosing options for all major commands, a structured "walk" to traverse the many layers of the Unix file system, and context information to orient users at all times within the Unix system. SoftShell also serves as a screen handler and a menu

SoftShell divides the CRT screen into two parts: a window and a scroll. The desired Unix command, including parameters and options, can be entered directly into the scroll. If the command is known, but not its arguments, the user can invoke a special template that appears in the window to prompt him for the correct information.

Logical Software Inc., 17 Mount Auburn St., Cambridge, Mass. 02138; (617) 864-0137.

CIRCLE 340

#### Program adds photos to data-base systems

erging photographs with M data-base management systems is a product called PhotoBase, an operating system extension that runs on an IBM PC or PC-compatible computer. The types of pictorial information incorporated into a data base might include photographs of people, signatures and fingerprints, components, charts and graphics. or laboratory setups. Any data-base system that writes to the display using the computer's BIOS will work with Photo-Base.

Photos are created using high-quality pictures captured from a VCR or video camera by the PhotoBase image manager and the PC-Eve video capture system (sold bundled for \$690). A highresolution graphics adapter (\$695) and a composite monochrome monitor are also required.

Chorus Data Systems Inc., 6 Continental Blvd., Merrimack, N.H. 03054; (800) 624-6787 or (603) 424-2900.

CIRCLE 341

#### **Development tools** ensure reliability

Based on the standard real time language RTL/2, the microMagic system provides users of PDP-11, VAX, or Professional 350 computers with reliable development software for embedded 16-bit microprocessor applications. Its extensive set of tools performs checks at each stage of program development to ensure system integrity and keep development and debugging time to a minimum. The combination of a standard language and a run-time executive provides an easy transition path between different target systems.

In addition to the RTL/2 compiler for the host machine, the microMagic system includes an RTL/2 cross compiler for 8086, 6809, 68000, LSI-11, or Falcon processors.

Intelligent Industrial Systems Inc., 300 Harmon Meadow Blvd., Secaucus, N.J. 07094, (201) 865-6550.



#### "BOSCHERT'S FULL LINE OF HIGH PERFORMANCE POWER SUPPLIES BEGINS WITH HIGH PERFORMANCE ENGINEERING." Chuck Forge Chief Engineer, Boschert Inc.

"A quality, long lasting product is not just an engineering objective at Boschert; it's a corporate directive. And has been ever since Boschert pioneered switching power supplies for OEM applications 10 years ago.

"In fact, each Boschert design must meet corporate guidelines for low failure rate, high performance and long life. PLUS, it must be manufacturable at a competitive cost.

"Meeting these objectives takes longer and costs more up front, but the end result is a more reliable product with a lower overall cost to the customer.

"That's why Boschert annually invests about eight percent of its revenues in engineering. And why we insist on having experts on staff in critical areas such as magnetics, materials, components and safety.

"It's also why every Boschert product undergoes a grueling series of product evaluations, design reviews, environmental tests and manufacturing engineering reviews. As well as reviews by worldwide safety and regulatory agencies, including UL, CSA, VDE, IEC, BT, and the FCC.

"Superior design, top people, and sound procedures mean a great product. A *Boschert* product."

For more information, send the coupon to Boschert Incorporated, 384 Santa Trinita Avenue, P.O. Box 3426, Sunnyvale, CA 94088-3426. Or call 408-732-2440.

Please send me Boschert's new fullline power supply catalog.



A BICC Compan 3ED 12/13

Name

Title

Address

ridarosc

ty State

Mail coupon to Boschert Inc.

Company

384 Santa Trinita Avenue P.O. Box 3426 Sunnyvale, CA 94088-3426 Boschert



# Boschert POWER YOU CAN RELY ON

CIRCLE 208 "SEE US AT WESCON BOOTHS #3348 & #3350"

#### **FACTORY AUTOMATION**

#### Motion controller plugs into bus systems

nterfacing via a single serial port with any industrial board-level computer—including Multibus, VERSAbus, STD bus, or VMEbus systems—an intelligent single-board module offers high-performance motion control of ac or dc servomotor systems. Using an RS-422 serial bus, up to 32 devices can be connected with simple twisted-pair or mass-terminated cable.

Operating as an intelligent slave controlling velocity and position in response to highlevel ASCII commands, the PCM-901 programmable controller eliminates the need for potentiometer adjustments by utilizing gain and compensation data stored in its nonvolatile memory.

Ormec Systems Corp., 19 Linden Park, Rochester, N.Y. 14625; (716) 385-3520. \$848, including MPL (100 units).

CIRCLE 343

#### IBM PC controls Bitbus network

Interfacing the IBM PC with Intel's Bitbus is a line of distributed control modules for use in factory automation and industrial control. The DT2806 board links the PC with the Bitbus via the

DTX344 daughter board, an intelligent Bitbus master controller.

The DT901, a stand-alone controller, interfaces the Bitbus network with iSBX modules for remote measurement and control. The DT901 may also be used as an I/O expansion device, collecting and transferring data to the host.

Each DT901 includes an onboard microcontroller and four iSBX connectors. The connectors support any combination of a-d (DTX311), d-a (DTX328), and digital I/O (DTX350) modules.

Data Translation Inc., 100 Locke Drive, Marlboro, Mass. 01752; (617) 481-3700.

CIRCLE 344

### HI-RES B. & W. MONITORS

1.6 Million Pixels Non-Interlaced


- 100MHz 3 Bit Video Amp-Drive 3 Bit Planes direct (no D-A required)
- 100MHz Composite/Linear Video
- 140MHz ECL Video Amplifier
- Up to 70KHz Horizontal Scan
- 15", 17" or 19" CRT's Landscape or Portrait
- **UL Recognized**
- Fast Delivery
- **■** Cabinets Available

Shouldn't You be looking at US?



59 Fountain Street Framingham, MA 01701 (617) 875-6958

#### **HI-REL Relays**



Whether an off the shelf standard or a custom requirement, Gordos is prepared to meet your needs with:

- · SIP, DIP and MIP Packages
- Molded Packages for Environmental Immunity
- Long Life Reliability Provided by Dry Reed or Mercury Wetted Contacts
- · Designs for Automatic Insertion

Let Gordos provide the solution, call or write:



A Division of Gordos International Corporation 250 Glenwood Avenue, Bloomfield, New Jersey 07003 U.S.A. 201/743-6800—TWX 710-994-4787

#### GRIMES SWITCHES: YANKEE INGENUITY AT AN IMPORT PRICE

BREA, CA-Grimes Company may be the best kept secret in the electronics industry.

For years they have been the exclusive supplier of low-profile keyboard switches to one of the most successful personal computer manufacturers in the industry.

Aiming to produce the most inexpensive, highquality American-made switch available, Grimes spent over \$2 million perfecting the high-volume automated assembly equipment that can do it. These machines are capable of producing over 2.8 million switches per week.

This year the company tripled its total gross sales over last year's figures. Yet hardly anyone has heard of them.

Recently Grimes' management decided to let their secret out. And the industry may never be the same again.

Marketing and Sales Vice President John Gunnoe explained that after years of supplying one manufacturer with switches, joy sticks and monitor stands, Grimes felt it was time to expand their marketing base.

"We enjoy a very healthy John Gunnoe relationship with that one manufacturer," Gunnoe said. "But you never want to put all your eggs in one basket."

Gunnoe declined to reveal the identity of that major manufacturer, but he did say "you can't turn around without seeing one of the ads in a magazine or on television."

As part of their aggressive new marketing strategy, Grimes Company will promote the advantages of their low-cost American-made switch over foreign competitors.

"Grimes' American-made switches cost less because of our high volume automated manufacturing process," said Operations Vice President Bruce Shepard.

"And American-made means immediate delivery, immediate credit and no overseas freight charges," he added.

Shepard was quick to point out that Grimes didn't sacrifice high quality for their low price. Their switches are proven reliable for over 10 million cycles; most switches are good for only 100,000 cycles.

After establishing their presence in the electronics market, Grimes plans to continue researching and developing new products for the personal computer field. Recently Grimes Company purchased Track House, maker of the programmable lle Tender keypad for the Apple IIe.

"We want to be able to supply our customers with new products, not just components or technology. The more services we can provide to our customers, the better," said Gunnoe.

For more information about Grimes' low-profile switches, (714) 671-3931.



#### Get a free sample of the American Switch

Are you ready to trade your Seoul supplier for some Yankee ingenuity? Switch to Grimes.

Grimes' low-profile, low-cost keyboard switches are used by one of the most popular personal computer manufacturers. And for good reasons: they're proven reliable at over 10 million cycles; stamped spiral springs control tolerances better than coiled springs; a built-in jumper eliminates the need for jumper wires and double sided circuit boards; and the unique bottom bearing reduces binding.


Grimes' switches cost less because their high-volume automated production reduces assembly costs. And American-made means immediate delivery, immediate credit and no overseas freight charges.

To get your free sample of Grimes' switches with and without tactile feel, call **1-800-671-3938** or circle the reader service number.

Feel for yourself why Grimes' highquality low-profile keyboard switches will make you want to sell your Seoul.



115 S. Arovista Circle Brea, CA 92621



# IF YOUR LAST CUSTOM IC PROJECT TURNED INTO A MONSTER, IT'S TIME TO TURN TO HOLT.

If your last custom IC cost you more money and took longer than it should, consider the Holt alternative. At Holt, we're willing to guarantee that a new design will work the way we both agree it should. Our confidence springs from over seven years of solving some pretty tough circuit integration problems. For you, our experience means peace of mind.

We do more than just promise to meet your design specs. We also help you make sure that those specs result in a part that really works in your application. You'll get a working breadboard of the chip, so you can put the design through its paces. That way, you can be sure the part will work in your product, not just in computer simulation.

If you think your next IC project might turn into a monster, talk to us. Call Rick Stevens at (714) 859-8800. Or write him at Holt Inc., 8 Chrysler Avenue, Irvine, CA 92714. Or telex 753307.

HOLT:
INTEGRATED CIRCUITS
MAKING CMOS WORK FOR YOU.

# GOODS PIER PROFILED TO BE REFERENCE PROFILED T

Stant Charles

The Fujitsu MB81416 16K X 4 DRAM. Now available in quantity.

Nobody puts tastier technology into a DRAM

than Fujitsu.

Like the fastest access time available – 100ns.

A TCAC/TRAC ratio of 2:1 for easier timing. Low power consumption, too.

And in a variety of packages. Like plastic DIP. JEDECapproved compatible with the TMS 4416 and INMOS 2620. Mmmm mmmm, good.

Best of all, we've got plenty in stock. So call the nearest FMI sales office listed below. For immediate gratification.

	100ns	120ns	150ns	Page Mode	TRAC/ TCAC	CAS before RAS refresh
FUJITSU	yes	yes	yes	yes	2:1	yes
TI	no	no	yes	yes	1.66:1	no
INMOS	yes	yes	yes	no	1.66:1	yes

### FUJITSU MICROELECTRONICS, INC.

Technology that works.

3320 Scott Boulevard, Santa Clara, CA 95051 · 408/727-1700

FMI Sales Offices. Atlanta 404/449-8539. Austin 512/343-0320. Boston 617/964-7080. Chicago 312/885-1500. Dallas 214/669-1616. Houston 713/784-7111. Minneapolis 612/454-0323. New York 516/361-6565. No. Calif. 408/866-5600. S. Calif. 714/720-9688.

#### **FACTORY AUTOMATION**

#### Robot performs quick solder masking

Automatic masking of printed circuit boards for soldering and conformal coating is performed as much as 35 times faster than conventional methods with a robotic liquid-dispensing system. The special valve design of the ECLD 311's end effector, which dispenses both high-and low-viscosity maskants, virtually eliminates clogging. The valve's adjustable flow rate dispenses dots, lines, irregular patterns, and circles.

The robot system performs at a speed of 55 in./s, five times faster than nonrobotic automated systems. The liq-

uid dispensing time is programmable; resolution is to within  $\frac{1}{1000}$  second.

Chad Industries, 1060-K N. Batavia St., Orange, Calif. 92667; (714) 997-4350. \$40,000 to \$45,000; six weeks.

CIRCLE 345

#### **EPROM** contains graphics symbols

When plugged into any IBM PC or PC-compatible color graphics board, an EPROM chip provides 86 graphics symbols for creating displays of control processes. The EPROM contains all of the standard ASCII control and printing characters.

However, it replaces the foreign characters contained in the standard IBM ROM set with symbols for generating valve bodies and actuators, motors, pumps, pipes, corners, transmitters, orifice plates, ladder diagram symbols, bar graphs, and process vessels.

All of the characters are accessible with IBM Basic, as well as any other language. When the screen is used in color text mode, the EPROM provides graphics displays in 16 colors. The device comes with a diagnostic program.

Intellution Inc., 35 Perwal St., Suite F, Westwood, Mass. 02090; (617) 329-8188.

CIRCLE 346

#### **Blunder-Free Tape Backup**

Anritsu's DMT2000 Streaming Magnetic Tape Drive

When you're saving that all-important data from a Winchester disk or other source, you need a dependable backup unit — the Anritsu DMT2000. A 1/2'' streaming magnetic tape drive with an **MTBF of some 7,400 hours.** You can be sure every bit of your data will stay accurate.

**Front-loading convenience:** And space-saving low profile. **Automatic threading:** Of tapes once they've been inserted into the drive. Automatic loading, too.

Two tape speeds: 100 or 25 IPS.
Three reel sizes: 7, 8.5 or 10.5 inches.

ANSI/IBM-compatible: For data exchange, CAD/CAM, etc., at 1600 bpi.

Distributorship available now! For more information, call or write Anritsu.



ANRITSU AMERICA, INC.

128 Bauer Drive, Oakland, NJ 07436, U.S.A. Telex: 642-141 ANRITSU OKLD Phone: 201 337-1111



# MicroEnergy can make you a Power Supply that's smaller, cooler and more reliable.

here's why: Switching at high frequencies. Power supplies that switch above 100kHz give you significant savings in space,

weight and thermal loading when compared to power supplies that switch under 50kHz.

Our MicroENERGY MEogo™series, for example, switches at 125kHz. It delivers over 2 watts/cubic inch and weighs only a pound. And with 70%-85% efficiency, its thermal loading is significantly reduced. The ME000 is one of the reasons MicroENERGY regularly provides customized power supplies for computer, telecommunication, automation and robotics manufacturers.


### Customized from a family of power

supplies. The efficient cross-use of standard, proprietary modules and sub assemblies from within our family of power supplies lets us customize high frequency switching power supplies to your specifications. No need to compromise with off-the-shelf units. No need to pay the cost and invest the time for a total custom design.

See what our designers can do for your application. And see how our automated assembly, testing and burn-in systems will insure product reliability.

Call us today at (312) 620-8101. Ask for our free capabilities brochure. Call us now—before your competitors do.





## MR62 Subminiature Relays



# Leading reliability from a world leader in computers and communications.

When space is tight and conditions tough, specify MR62. It's the reliable DIP DPDT relay that really thrives on challenge. And delivers flawless performance in far-ranging applications.

MR62 relays—with nitrogengas-filled, twin crossbar contacts —come encased in impermeable armor. Their PBT shield scorns almost any attack—auto soldering, immersion cleaning, even chlorinated solvents.

Yet all this reliability stands only 0.45-inch high. And occupies a mere 0.31 square-inch of precious PC board real estate.

MR62 relays come in two series: standard and extra-high reliability.

We use our own relays in a full range of NEC computers and communications equipment. So we totally understand your need for reliability. Because our reputation, like yours, can rest on a single relay.

Contact form: 2C (DPDT).
Contact rating: 30W, 150VDC,
1.25A; 50VA, 125VAC, 1.25A.
Dimensions: H0.45" (+pins 0.13")
×W0.795"×D0.386".
Availabilities: Single Coil
Latching Type; High
Breakdown Voltage Version
(Meets FCC Part 68).

NEC America, Inc. Electromechanical Devices Department, 532 Broad Hollow Road, Melville, New York 11747, USA. Tel: 516-752-9700. Telex: 144658 NEC AMER MELV.

World Products, Inc., (U.S. distributor) 19678 8th Street East, Sonoma, CA 95476, P.O. Box 517, USA. Tel: 707-996-5201. Telex: WORLD PROD SNOM 171715.




### This unique transformer gives Toko switching power supplies the edge on performance

When you select a switching power supply, your product's reliability and performance are on the line. Will the sample you approve be typical of OEM production? It will if you evaluate Toko. We reinvented the transformer to assure a consistent level of performance not possible with conventional transformer designs.

Unlike ordinary wire-wound transformers, Toko transformers are based on a better idea—inductive copper strips interwound with Mylar\* insulation over a high-efficiency iron core. This design\*\* significantly tightens performance tolerance limits and improves transformer reliability. The chances of a shorted winding are greatly reduced and the probability of an open winding is virtually eliminated.

For even greater performance assurance and added value we've derated our component specifications by 20%. Such steps combine with a very high level of quality control to let us offer a two-year warranty—twice the industry average. All of these attributes, too, make Toko a better idea—not just a better power supply.



Toko also offers guaranteed delivery dates on standard supplies in virtually any quantity. We've made major investments in reserve plant capacity to easily handle your largest OEM orders.


We also meet every major testing standard for safety and EMI/RFI suppression.

Contact us today for a copy of our new switching power supply catalog and more information on Toko.


Toko America is the U.S. subsidiary of Toko, Inc., a large Japanese manufacturer of a broad range of high quality electronic products. Here's a sampling...



**Delay Lines** 



Transformers and Inductors



**Numerical Control Boards** 






**TOKO AMERICA, INC.**5520 West Touhy Avenue Skokie, IL 60077 (312) 677-3640. Telex 72-4372 Facsimile: (312) 674-2910 (G III)

10050 N. Wolfe Road Cupertino, CA 95014 (408) 996-7575 Facsimile: (408) 996-7280 (G III)

TOKO... NOT JUST A BETTER POWER SUPPLY, A BETTER IDEA

# Presenting the 1984/85 GOLD BOOK



The Reference Resource Designed for

HAYDEN PUBLISHING CO., INC., 10 MULHOLLAND DRIVE,

Use these cards to communicate directly with the participating companies.

IMMEDIATE ACTION CARDS VOLUME

PRODUCT DATA FILES

ElectronicDesign's

NOTAL

ElectronicDesign's

GO' BC Elect

75 VOLUME

VOLUME

WORLD.

WORLD.

DIRECTORY AND PM

Electronic Design's Directory/Master Catalog

Electronic Designs

DIRECTOR WORLDWIDE STIFFER SOURCE INCOME. TO BE A SOURCE TO BE A S


Your Convenience

HASBROUCK HEIGHTS, N.J. 07604 201-393-6253

GOLD BOOK

#### **FACTORY AUTOMATION**

#### Photoelectric scanner slashes package size



photoelectric scanner with a self-contained amplifier and a visible light beam for easy alignment is one-third the size of conventional self-contained scanners. Called the Valu-Beam. the three-wire unit is only 21/8 in. high by 13/8 in. wide by 13/8 in. deep. It is available in ac or dc models and operates in retroreflective, convergent, diffuse, and opposed scanning modes. In the retroreflective mode, the Valu-Beam's range is up to 15 ft. The device may be adjusted for sensitivity and for light or dark operation.

In addition to a visible beam, the scanner employs a second built-in system that indicates both alignment and exact signal strength. The Valu-Beam's low leakage current enables it to interface directly with all programmable controllers.

Banner Engineering Corp., PO Box 9414, Minneapolis, Minn. 55440; (612) 544-3164. Less than \$40 in large quantities.

**CIRCLE 347** 

#### **Ultrapure-water monitor** detects organic carbon

he A-100 TOC (total organic carbon) analyzer is an on-line monitoring system for measuring the organic contamination of VLSI process water. It eliminates the need for chemical reagents by using an ultraviolet light to break down the organic compounds. A conductivity measurement then determines the total concentration of organic carbon down to 10 parts/billion.



The A-100 consists of a 2½-by-5-by-7-in. control unit, a small power pack, and an 11-lb chamber, which is designed to be installed anywhere within the water purification and distribution system. Analysis parameters are programmed via the controller's front panel.

At less than \$9000, the A-100 is priced considerably lower than current process systems, which range between \$15,000 and \$30,000.

Anatel Instrument Corp., 2200 Central Ave., Suite F, Boulder, Colo. 80301; (303) 442-5533.

CIRCLE 348

#### **Announcing** the new Marconi **Instruments** 1GHz **Signal** Generator at \$3950.

the brochure has been removed, please check reader service No. 120



3 Pearl Court, Allendale, NJ 07401 (201) 934-9050

Tear

# Trio of power MOSFETs has lowest on-resistance for 50- and 60-V devices

hree power MOSFETs fabricated with Motorola's new TMOS III process attain the lowest onresistance per cell size of any available power MOSFETs rated for under 100 V. One, rated at 12 A and 60 V, has an  $R_{DS}(on)$  of 0.15  $\Omega$  and is the least expensive device—only 60¢—for its specifications. Designated the MTP3055A, it aims at replacing the industry-standard bipolar 2N3055, which is priced about 25% to 67% higher. Its 50 µA of leakage current is almost 100 times better than that of the 2N3055's 5 mA.

The other two devices are the 14-A, 50-V MTP14N05A, which has an on-resistance of 0.10  $\Omega$ , and the 16-A, 50-V MTP16N05A, which at 0.08  $\Omega$  provides the lowest on-resistance and best performance for its die size—96 mils square—in the industry.

As is true of MOSFETs in general, switching speeds are superior: The MTP3055A has a turn-on delay time of 20 ns, compared with 150 ns for its bipolar counterpart. Its other relevant specifications are a rise time of 60 ns and turn-off delay and fall times of 65 ns

each. The MTP14N05A and MTP16N05A are close behind at 30 ns, 80 ns, and 85 ns, respectively.


In addition, the MTP3055A has an input capacitance of 500 pF and reverse-transfer and output capacitances of 200 pF each.

Of course, all devices sport the other inherent advantages of MOSFETs over bipolar devices: an intrinsic source-drain diode with switching times comparable to the MOSFET itself, a voltage gain that is constant with increasing collector current, and higher efficiency because current is required only to switch the device.

The 60¢ price of the MTP-3055A is for 100-unit lots. In similar quantities, the MTP-14N05A and MTP16N05A cost \$1.31 and \$1.46, respectively. Samples and prototype quantities are available from stock; delivery of production quantities takes six to eight weeks.

Motorola Semiconductor Products Inc., PO Box 20912, Phoenix, Ariz. 85036; (602) 244-6786.

CIRCLE 321



Made with a new process, TMOS III, the 12-A, 60-V MTP-3055A has half the on-resistance, and hence losses, of its bipolar counterpart, the popular 2N3055, with an equivalent die size—and it also costs less.

**Heather Bryce** 

#### **POWER**


#### **Power MOSFETs** withstand up to 800 V

series of high-reliability, fast-switching power MOSFETs offers drain-tosource voltages from 50 to 800 V and drain currents from 3 to 45 A. The devices are offered in eutectic-bonded, isolated TO-61/I, TO-111/I, and TO-228AA cases—designated the FNA-, FNB-, and FNC-15/80, respectively. Features include very low on-resistance, no secondary breakdown, and excellent temperature stability.

Solitron Devices Inc., 1177 Blue Heron Blvd., Riviera Beach, Fla. 33404; (305) 848-43ll. \$39.50 (1000 units): six to eight weeks.

CIRCLE 349





**IB-15** 

Resistor conductor can be assembled freely

2.0 mm Connector pitch Height (MAX) 5.0 mm

**IB-20** 

Resistor, capacitor, diode, conductor can be assembled freely 2.0 mm Connector pitch Height (MAX)

**IB-25** 

Resistor, capacitor, diode, transistor and conductor can be assembled freely Connector pitch 2.5 mm Height (MAX) 11.5 mm

Send inquiries to:

#### RIVER ELECTRONICS CORP.

7.5 mm

18321 S. Western Ave., Suite H, Gardena, CA 90248 USA Tel: 213-329-6359 Telex: TWX910-346-6394


Outside USA:

#### FUJI SANGYO CO.,LTD.

14-40, Nishi Shinjuku 4-chome, Shinjuku-ku, Tokyo, Japan Tel: 03-377-5444 Telex: 232-2382

CIRCLE 218

#### Switching supply utilizes MOSFETs




roviding outputs ranging from 5 V dc at 100 A to 48 V dc at 12 A is the Series W switching power supply. The MOSFET switching circuitry. which operates at 55 kHz, reduces component count and increases efficiency compared with bipolar designs having comparable ratings. Efficiency for the Series W is typically 76%. Line and load regulation are  $\pm 0.05\%$ .

The supply is housed in a compact 3.4-by-6.3-by-9.3-in. metal case. LED lamps indicate normal operation and shutdown due to latch-up of the overvoltage protection circuit. The unit also features soft-start operation and automatic shutdown in the event that input voltage is too low.

Acopian Corp., PO Box 638, Easton, Pa. 18044; (215) 258-5441. \$950; two weeks.

# IF YOU THINK THAT SIGNETICS ONLY MAKES RUN-OF-THE-MILL PRODUCTS, IT'S TIME YOU TURNED THE PAGE.

## NO GUTS. NO GLORY.



Give your terminals the guts to deliver maximum performance at the minimum price.

Just call us. We already supply the key circuits in a third of all the alphanumeric CRT terminals built today. And we can supply almost three-fourths of the part types you'll need for yours.

By putting more and more features on less and less silicon, we're making it easier for you to build all the right features into your terminals. And you can make them more compact, reliable and easy to test.

With this much going for you, your sales can take off. But however high they climb, we've got the

production capacity to keep up. That assures the volume you want at the price you need. And you get high quality parts and service in the bargain.

So phone us toll free or fill in the coupon for literature about our terminal components, including our MOS Microprocessor Manual and free samples. Ask for the number of your nearest Signetics sales office for applications support and further information.

We'll give you the guts to make it. While reducing the price of that glory.

#### 800-227-1817, Ext. 910 C

☐ Keyboards	☐ CPU/Datacomm	☐ CRT Displays
Name	Titl	е
Company	Div	ision
Address	City	
State	Zip	
Phone		

#### We've got the parts.

Keyl	ooard	CPU/Datacomm		CRT
8048	8040	8048	2641	2670
8049	8031	8049	2651	2672
8050	80C51	8050	2652	2673
8051	80C31	8051	2653	2674
2671	80C39	68000	2661	2675
8035	80C49	68008	2681	2677
8039		68010		





# Slave processor puts distributed processing on the STD bus at low cost

piggyback combination of a slave processor and an I/O card brings low-cost distributed processing to STD bus systems. The slave processor board costs only \$180, and the I/O cards from \$95 to \$680, for a total price much lower than that of adding a full-fledged STD bus system for greater processing power.

Developed by Micro/Sys. the SB8275 processor interfaces directly with the STD bus and one of a number of specially designed I/O boards that is mounted on it. The combination uses only one slot and can be dedicated to a single I/O application, such as monitoring analog lines.

In such a case, the slave performs the basic processing of the raw data. That increases system throughput by freeing the system CPU to concentrate on scheduling and higher-level processing and minimizing traffic on the STD bus. Similarly, individual application tasks can be served by dedicated slave processors running the application programs, again boosting system throughput.

All communication among processors is through the system CPU, to which the slave processor looks like four

sequential I/O ports. Data passes through 8-bit mailbox registers on the slave processor.

The slave uses a National NSC800 and can hold up to 32 kbytes of PROM and 8 kbytes of RAM. It also contains two 16-bit timers.

The slave processor and I/O board interface is simple and general-purpose, and the physical connection is straightforward: The I/O board is mounted using standoffs and a board connector on the slave.


Three I/O boards are currently available: the SB8276, which has 32 bidirectional digital lines; the SB8277, which has 16 analog inputs and a 12-bit analog-to-digital converter; and the SB8278. which has 8 analog outputs plus a 12-bit digital-to-analog converter.

Deliveries are from stock. The prices for the cards in 50-unit lots are \$180, \$95, \$495, and \$680 for the processor and the SB8276. SB8277, and SB8278, respectively. Delivery is from stock.

Micro/Sys Inc., 1011 Grand Central Ave., Glendale, Calif. 91201; (818) 244-4600.

CIRCLE 314

#### **Ray Weiss**



#### **COMPUTER BOARDS**

# 64-Mbyte memory board expands to 2 Mbytes

Starting with as little as 64 kbytes of RAM, IBM PC users can expand to a full two Mbytes of memory on a single board. What's more, with MegaCache and MegaSpool software, speed improvements from three- to tenfold can be realized.

The board, dubbed the 2megaboard, provides up to 32 64-kbyte segments, eight of which may be mapped into a 512-kbyte region of the computer's memory. It performs parity checking and reporting, and any of the eight segments may be write-protected. The module requires less than 300 mA at +5 V dc when fully configured.

Datatron Inc., 12191 Mariners Way, Garden Grove, Calif. 92643; (714) 554-8214.

CIRCLE 354

## Multiplexing controller works with Unibus


An asynchronous communications controller, the Optimux/16DMF+, is the first in a family of optimized Unibus-compatible multiplexers for use with PDP-11 and VAX computers. It performs all of the standard functions of Digital Equipment's DMF32 and DH11 subsystems, while permitting connection of 16 peripheral devices from a single backplane slot.

The Optimux/16DMF+ offers software-selectable data transfer rates from 50 to 34.800 bits/s—twice the maximum data transfer rate of most communications controllers. Moreover, during high-throughput operations its bidirectional data-flow control virtually eliminates data loss, and its multiword DMA burst mode significantly reduces Unibus overhead.

Distributed Logic Corp., 1555 S. Sinclair St., PO Box 6270, Anaheim, Calif. 92806; (714) 937-5700. \$3000; 30 days.

CIRCLE 355

# VME System Packaging: Electronic Solutions Makes it Easy.



- Double size card cages with 5, 7, 9, 12, 16 or 20 slots
- 5, 7, 9, 12, 16 or 20 slots☐ Single size card cages with5, 7, 9, 12, 16 or 20 slots
- Double size prototyping cards with hole pattern or 2-level wire wrap
- pattern or 2-level wire wrap

  Single size prototyping cards with hole
- pattern or 2-level wire wrap


  Double size and single size extender cards

  VME enclosures with card cage and
- □ VME enclosures with card cage and backplanes with disk drive or Winchester option
- ☐ Backplanes
- Test sets

Electronic Solutions is also the major manufacturer of Multibus™ cages and enclosures—a dependable, domestic source for your VME system requirements. For all the details, give us a call today.

Call Toll Free **(800) 854-7086** in Calif. (800) 772-7086

Multibus is a trademark of Intel Corp



**VIME**asy

Electronic Solutions

9255 Chesapeake Drive San Diego, CA 92123 (619) 292-0242 Telex II (TWX): 910-335-1169

#### **COMPUTER BOARDS**

# Multibus SBC is iSBC-86/05-compatible

The ZX-86/05A, a Multibus single-board computer, is compatible with the iSBC-86/05 and features a 10-MHz

8086 processor for fast system throughput. The board's flexible memory section—consisting of eight 28-pin JEDEC sockets, each capable of supporting up to 512k EPROMs and 64k static RAMs—allows

the user to tailor the board for many applications.

Enhancing the ZX-86/05A's I/O capabilities are dual USARTs and 24 parallel I/O lines, as well as three iSBX connectors. An onboard 8087 numeric coprocessor socket spares the expense of adding an expansion module when a coprocessor is required.

Zendex Corp., 6644 Sierra Lane, Dublin, Calif. 94568; (415) 828-3000. \$1000 with 8 kbytes of RAM (100 units); four weeks.

CIRCLE 356


## VME SBC with

# ONE MEGABYTE

#### Performance Oriented

- Dual-ported memory with parity
- · Zero wait states
- 68000 CPU
- · Multi-master capability
- · System control functions
- Optional MMU
- Two RS-232C channels

he DVME-102 from DY-4 has proven its performance record in the field, and lends its features to ease of System Design. A full One Megabyte of on-board memory eliminates the need for data transfer across the VMEbus. Send for more on the DVME-102 and the entire line of VME modules from DY-4 Systems.





1475 S. Bascom Ave, Campbell, CA 95008, (408) 377-9822 888 Lady Ellen Place, Ottawa, Ontario, Canada K1Z 5M1 (613) 728-3711 Solbakken 48, DK-8450, Hammel, Denmark (06) 96-3624 TLX 60938 (Dendy DK)

# Single board employs dual processors

A single printed circuit board features a dual-processor architecture utilizing Intel's 80286 and 80186 microprocessors, each running dedicated environments. The board, designated the DPX86/ME, is available with three major operating systems: Xenix, iRMX-286, and PC-DOS.

A shared-memory feature allows I/O processing—including Ethernet, RS-232-C asynchronous, and either Centronics-type or SCSI disk communications—to occur simultaneously with 80286-controlled applications. The board can be configured with a total of up to 1 Mbyte of RAM and 400 kbytes of ROM.

Little Machines Inc., 4141 Jutland Drive, San Diego, Calif. 92117; (619) 483-3606. From \$4000, not including software (100 units).

#### **COMPUTER SYSTEMS**

# Workstations speed pc board design

Three printed circuit board CAD workstations extend a line of design automation systems known for its price/performance ratio. The systems include the CDX-5000A, a cost-reduced version of the existing CDX-5000 workstation; the CDX-50000, a high-performance CAD system with a graphics accelerator engine; and the CDX-59000, a complete design and layout workstation with full CAE/CAD capabilities.


The CDX-5000A offers all the functionality of the CDX-5000, which sells for \$74,500, at a cost of only \$49,900. The CDX-50000, with its graphics accelerator engine, a hierarchical schematic editor, and automatic placement and routing software, allows the user to design very large boards (in the 700-IC range) with ease and speed. This system sells for \$79,900.

At the top of the line, the CDX-59000 adds powerful design analysis software to the high-performance CDX-5000 configuration. It features the CADAT twelvestate logic simulator and a SCALD-based timing analyzer. A graphic waveform editor simplifies test pattern development. The \$94,900 CDX-59000 takes the user from logic design and verification to pc board layout and manufacturing outputs in a single workstation.

Cadnetix Corp., 5757 Central Ave., Boulder, Colo. 80301; (303) 444-8075.

CIRCLE 336

# CAE workstation builds on IBM PC AT for low cost



ne of the first CAE workstations based on the new IBM PC AT, the Personal Logician AT, from Daisy Systems, provides many of the same functions, including schematic entry and logic simulation, and the same interactive graphics capabilities of larger workstations at a fraction of the cost—only \$25,000.

Unlike other personal computers used for CAE, the workstation does logic simulation, as well as schematic entry. In addition, larger engineering tasks, such as design rule checking, can be uploaded to larger computers through an Ethernet local-network interface.

The IBM PC AT foundation of the Personal Logician AT uses an 80286 processor and 610 kbytes of local memory. The hardware also includes a 20-Mbyte hard-disk drive, a 1.2-Mbyte floppy-disk drive,

Stephan Ohr

serial and parallel I/O ports, and Daisy's high-resolution graphics subsystem. The last item consists of a specialized video controller and a monochrome monitor with a resolution of 1022 by 840 pixels—the same as the company's Logician workstation. (A color monitor is an option.)

A complete workstation, including the PC AT computer, the graphics subsystem, disk drives, and software costs \$25,000. Existing PC ATs with at least 512 kbytes of memory and a 20-Mbyte hard disk can be converted into Personal Logician AT workstations by adding the graphics subsystem, additional RAM, and software, for \$20,000. A color version of the system costs an additional \$10,000, and an Ethernet capability adds \$2500.

Daisy Systems Corp., 700 Middlefield Road, Mountain View, Calif. 94043; Robert Spivack, (415) 960-6956.

#### **COMPUTER SYSTEMS**

#### Off-line workstation supports color plotting

An off-line plotting work-station supports electrostatic color and high-resolution (200- and 400-point/in.) plotting on Versatec plotters from CalComp 921/925 tapes. The workstation performs all vector sorting and vector-toraster conversion. It also accepts seven Versatec standard data formats. Plot processing from the workstation results in a 10:1 speed advantage over pen plotters for most drawings and maps. The system includes a microprocessor, 64 kbytes of memory, a video display, a 24-Mbyte Winchester disk, a magnetic

tape drive, and a bipolar algorithmic processor.

Versatec, 2710 Walsh Ave., Santa Clara, Calif. 95051; (408) 988-2800, \$46,000; 30 days.

CIRCLE 358

#### 32-bit workstation joins VAX family

nhancing the VAX family of computers is the VAXstation I. a true 32-bit single-user workstation system. Built around the Micro-VAX I, the system features a 19-in. display, high-resolution graphics, and full VAX/ VMS operating system resources. It supports GKS

(Graphic Kernel System) as its first graphics application interface language.

The basic configuration includes the processor with 1 Mbyte of main memory, a 1k-by-2k bit-mapped video RAM, dual 400-kbyte floppydisk drives, a 3l-Mbyte 51/4-in. Winchester drive, a monochrome monitor, and a mouse. The VAXstation I can be connected to DECnet/Ethernet networks, enabling access to larger VAX computers, VAXclusters, and other VAXstation I workstations.

Digital Equipment Corp., 146 Main St., Maynard, Mass. 01754; (617) 897-5111. From \$21.095.

CIRCLE 359



#### THE TROUBLE ELIMINATERS Potrans Trouble-free Transformers



We make UL-listed plug-in AC-to-DC and AC-to-AC transformers, both direct and indirect, regulated and unregulated They can save your money: use one of our plugin transformers, and you can get immediate UL approval for your product because the unit doesn't have to be retested with the transformer inside. That reduces space, heat, and leakage flux in your design. We also welcome your custom designs for new transformers. For Details please call or write to:

MODEL		OUTPUT
WP350218	18V	0.1A
WP350312	12V	0.25A
WP350324	24V	0.1A
WP410412	12.6V	0.3A
WP410612	12V	0.5A
WP410614	14V	0.4A
WP410624	24V	0.25A
WP481012	12V	0.83A
WP481024	24V	0.42A
WP571616	16V	1.0A
WP571618	19V	0.84A
WP572012	12V	1.67A
WP572024	24V	0.83A
WP572408	8V	3.0A
WP572412	12V	2.0A
WP663021	21V	1.4A
WP663322	22V	1.5A
WP664012	12V	3.3A
WP664024	24V	1.67A

III LISTED DI LIGUN CLASS S









POTRANS ELECTRICAL CORP., LTD.

OFFICE: 5 FL-2 NO. 2 LANE 199, HSIN-YI-RD. SEC. 4, TAIPEI, TAIWAN. 106 TEL: (02) 701-6769, 707-7296, 707-8253 TELEX: 10905 POTRANS U.S.A. LIAISON OFFICE: 550 EAST PACIFIC COAST HIGHWAY SUITE 211, SEAL BEACH CALIF. 90740 U.S.A

TEL: (213) 596-4456 TELEX: 656458 POTRANS USA

New Hampshire Ave. and Rte. 70. Lakewood. N.J. 08701 • (201) 364-1800 • TWX 710-723-8343


**ELECTRONICS** 

INCORPORATED

#### **PACKAGING & MATERIALS**

#### Frame accepts Multibus II boards

nticipating Intel's final specifications for Multibus II is a frame that will accept cards for the new bus structure. The Microrack, from BICC-Vero, has 10 double-Eurocard iPSB slots, 6 of which (the maximum number now permitted by the Multibus II specifications) also connect to the iLBX bus; it also has 4 user-definable



single-height card slots.

Since Multibus I will still be around for some time, the card frame has six Multibus I slots as well. The six-layer backplane has off-board terminations.

The 19-in.-wide rack comes in a standard 9U height and is 550 mm deep. The top 2U can house a full-height Shugart-compatible 5½-in. disk drive; the 6U center is the Multibus section, conforming to the DIN 41494 standard; and the bottom 1U is allocated to cooling and front-panel controls.

A 400-W switching power supply is mounted on the frame's hinged rear panel, which also carries cutouts for four 25-way D shells and three 37-way D shells. Four integral fans beneath the card frame blow air across the boards, and an extractor fan is fitted to the rear panel.

The frame can be tailored to a customer's requirements.

BICC-Vero Electronics Inc., 171 Bridge Road, Hauppauge, N.Y. 11788; (516) 234-0400.

BICC-Vero Electronics Ltd., Hedge End Industrial Estate, Flanders Road, Southampton, Hants. SO3 3LG, England; (04892) 81424/5; Telex: 477984.

CIRCLE 302


# Neo-iron magnet alloy delivers high energy

Crumax 30 is a neodymium-iron permanent-magnet material specifically developed for electric motor applications. The alloy has an energy product of 30 MGOe (megagauss oersteds) and is available in two subgrades: Crumax 30A, which has a retentivity (B<sub>r</sub>) of 11,000 G and a coercivity (H<sub>c</sub>) of 10,600 Oe; and Crumax 30B, with a B<sub>r</sub> of 11,600 G and an H<sub>c</sub> of 10,500 Oe.


Relatively inexpensive raw materials are used in Crumax 30, making it an economical high-energy permanent magnet for applications requiring straight-line demagnetization characteristics and operating temperatures of up to 150°C. Such applications include linear actuators and computer peripherals.

Colt Industries, Crucible Magnetics Division, RFD No. 2, Elizabethtown, Ky. 42701; (502) 769-1333.

CIRCLE 405



CIRCLE 225



MS-534

COMARK CORPORATION'S MS-534 IS A FULLY PROGRAMMABLE, COST EFFECTIVE COMMUNICATIONS CONTROLLER FOR MULTIBUS ARCHITECTURE.

#### FEATURES:

- TWO OR FOUR PORTS OF SERIAL I/O
- ONE PARALLEL I/O PORT
- SIX PROGRAMMABLE TIMERS
   SIXTEEN INTERRUPT INPUTS WITH PROGRAMMABLE PRIORITY
- SIXTEEN BIT ADDRESS RANGE
- I/O ACCESS TIME OF 400ns
   20ma CURRENT LOOP INTERFACE (optional)
   PROGRAMMABLE BAUD RATES UP TO
- PROGRAMMABLE BAUD RATES UP TO
   19.2KB
   SYNCHRONOUS OR ASYNCHRONOUS
- OPERATION

  TOTALLY COMPATIBLE WITH INTEL'S
- iSBC-534
   QUANTITY ONE PRICES STARTING AT
- O.E.M. DISCOUNTS AVAILABLE

FOR MORE INFORMATION ON THIS AND OUR OTHER FINE PRODUCTS, CONTACT:

COMARK CORPORATION

93 WEST STREET ● P.O. BOX 474

MEDFIELD, MA 02052

(617) 359-8161

#### **PACKAGING & MATERIALS**

#### **Evaluation kit contains** ceramic display



he latest benefits in display technology can be explored with the SCD solid ceramic display evaluation kit. SCD displays use a polycrystalline ceramic of PLZT (lanthanum-doped lead zirconate titanate) to provide a 160° viewing angle, a 500-μs response time, and operating temperatures down to  $-40^{\circ}$ C without the use of heaters. Conductive patterns on the crystal surface create standard seven-segment digits when energized.

The SCD evaluation kit can exercise one of six displays in reflective, transflective, and transmissive viewing modes. The metal-enclosed unit includes a 12-hour chronograph with an alarm and a batterybacked clock memory. It operates from a 115-V ac supply.

Motorola Ceramic Products, Market Development, 4800 Alameda Blvd. NE, Albuquerque, N.M. 87113; (505) 822-8801. \$990; stock.

CIRCLE 360

#### Quiet cable extends transmission distances

he latest addition to an extensive line of data cables, EDQ cable enables longer transmission distances and reduces EMI/RFI noise emissions. The cable's low capacitance of 12 pF/ft allows it to carry data signals for a longer distance than standard EIA cables without loss of signal integrity. RS-232-C signals are transmitted up to distances of 500 ft at 9600 bits/s without using modems, line drivers, or repeaters.

To reduce electronic noise interference, the EDQ cable has two shields-one of aluminum foil to suppress highfrequency emissions and the other of braided copper to reduce low-frequency emissions. The cable may be ordered with a molded-on connector hood, which includes a metallic shield, or with a removable metal hood. Both hoods extend suppression to the interface connector.

Black Box Corp., PO Box 12800, Pittsburgh, Pa. 15241; (412) 746-5500.

CIRCLE 361

#### **Brushless fans** are light, compact

he SJF series of brushless fans is available in two lightweight, compact sizes: 60 by 60 mm and 80 by 80 mm, each with a depth of 23 mm and weighing 75 and 100 grams, respectively. A noise level of 35 or 45 dB may be specified for models of either size. The eight models that

comprise the series offer 12or 24-V operation at various currents, ranging from 0.12 to 0.32 A. The fans deliver 0.40. 0.25, 0.80, and 0.55 m<sup>3</sup> of air per minute at respective pressures of 4.0, 2.0, 3.1, and 2.0 mmH<sub>2</sub>O. Operating temperatures range from -10° to +60°C.

International Components Corp., 1740 N. Marshfield Ave., Chicago, Ill. 60622: (312) 772-4400.

CIRCLE 362

#### Conductive laminate serves as work surface

harge-Guard is a mate-Crial with electrical and mechanical characteristics developed and engineered specifically for electronic workstation surfaces. The hard laminate is a suitable surface on which all types of equipment containing staticsensitive electronic components can be handled. It consists of a rugged top layer and a conductive middle laver bonded to a bottom core material. It has a surface-toground resistance of 10<sup>5</sup> to 10<sup>7</sup> Ω. Charge-Guard resists solvents common to the electronics industry, and hot solder or solder flux will not damage its surface. It is available in 4-by-8- and 5-by-12-ft sheets and in cut form in three UVresistant, semigloss colors (blue, beige, and gray).

3M Co., Static Control Systems Division, Department ST84-12, PO Box 33600, St. Paul, Minn. 55133; (612) 733-1186.

# Bivar introduces a new PCB Packaging Concept!

THE SOLUTION TO CARD GUIDE INVENTORY, SPACING AND COSTS. =

CIRC

#### Snap-in Anywhere...

- ... Any Spacing
- ... Any PCB Thickness
- ... Any PCB Length

patents pending

rails, drawers, etc.

CIRC-O-GIDE™. It's a totally new method for spacing, guiding and giving firm retention for printed circuit boards that adds a new dimension of versatility to PCB packag-ing. These simple, easy-to-install by hand, button-style CIRC-O-GIDEs can be used just about anywhere a .172" diameter hole can be made. Card cages, PCB retaining

REDUCES STOCKING REQUIREMENTS

Instead of worrying about the different sizes of PCBs you will use in your application, and the many corresponding lengths of conventional card guides you would need in your inventory, just identify spacing and quantity requirements. CIRC-O-GIDEs are available in a choice of 5 standard gripping thicknesses from .078" to .187" for maximum retention and 7 diameters for .312", .400", .500", .600", .750", .800" and 1.000" spacing for the space that's just right for you. All are available from stock, and in many cases only one size may have to be stocked for all your applications. stocked for all your applications.

5 Thicknesses-7 Diameters-35 Standards

#### SAVES GUIDE USAGE

When used as pairs throughout, any spacing of .312" and over can be used, giving the designer absolute license in choosing location, density and gripping action. When spacing is standard, CIRC-O-GIDEs also offer substantial economies by reducing the number of guides required. Aligned pairs are used for the first PCB, and single rows thereafter.

Made of durable black, glass reinforced NYLON per ASTM D4066, U.L. rated 94V-O, these little CIRC-O-GIDEs can take it. And you can take them for less because they're low in cost.

Can Be Used In Pairs

For Any Spacing

You can realize savings in time, space and in your PCB packaging costs today, without waiting. Call your nearest BIVAR Representative, stocking Distributor, or the factory for complete specifications.


BIVAR. We've just added to a growing family of over 4050 cost-saving aids. And this time, it's a snap.

Thanks Bivar!

**IMPROVED CARD/SYSTEM COOLING** 

By eliminating the continuous length of the conventional card guide, CIRC-O-GIDEs afford added space for cooling slots in card cages, and substantially open otherwise confined, air-limiting space in assemblies where heat between printed boards is a continuing concern.





BIVAR, INC. • 4 Thomas • Irvine, CA 92718 • (714) 951-8808 • TWX 910-350-1746 CIRCLE 227

# miniature wideband amplifiers



# 10 to 2000 MHz only \$179

IN STOCK...IMMEDIATE DELIVERY

- 22 dB gain, flat ±1.5 dB
- 40 dB isolation
- meets MIL-STD-202
- operates from -55° to +100°C
- · boost signal/sweep generator output to 50 mW
- achieve broadband isolation
- use as amplifier driver
- SMA connectors
- rugged 1.25 in., sq. × 0.75 in. RFI-shielded case
- one-year guarantee

#### ZFL-2000 SPECIFICATIONS

10-2000 MHz **FREQUENCY** GAIN 20 dB GAIN FLATNESS  $\pm 1.5 dB$ **OUTPUT POWER** +17 dBm 1 dB compr. NOISE FIGURE 7.0 dB INTERCEPT POINT, 25 dBm 3rd order VSWR, 50 OHMS 2.1 DC POWER +15V, 100 mA

Call or write for 64-page RF Designers Guide or refer to EEM, EBG, Gold Book, Microwaves & RF Directories.

> finding new ways. setting higher standards



A Division of Scientific Components Corporation
World's largest manufacturer of Double Balanced Mixers P.O. Box 166, B'klyn, N.Y. 11235 (718) 934-4500

CIRCLE 228

#### COMPONENTS

#### Slide switches come in micromini packages

wo families of slide switches—the MMS and SSJ series—boast high performance in an unusually small package. For example, the SSJ-12 SPDT switch is only 0.394 in. long by 0.157 in. wide and stands 0.26 in. high, including the actuator. The devices' standard silverplated double-wipe contacts have a rating of 100 mA at 30 V dc. The shorting contacts also have a rated life of 10.000 operations.

The MMS family consists of one-, two-, and four-pole versions. The single-pole device has an upright actuator with a two-position on function. The two- and four-pole types are available with upright or side actuators, as well as twoand three-position on func-

The SSJ series is available in single- and double-pole versions with upright or side actuators. The double-pole unit comes with a two-position on function, while the singlepole switch also offers threeposition on-on-on.

Augat/Alcoswitch, 1551 Osgood St., North Andover, Mass. 01845; (617) 685-4371.

CIRCLE 364

#### 1/4-W resistor shrinks package size

he CCF-50, a compact metal-film resistor, gives designers 1/4 W of power (at 70°C) in a package that is the same size as conventional 1/8-W resistors. The 0.150-in.-

long resistor body has a diameter of 0.062 in. Its 0.020-in, leads make it suitable for use with automatic insertion equipment.

The CCF-50 has a tolerance of  $\pm 1\%$  over a resistance range of 10  $\Omega$  to 1 M $\Omega$ . The resistance temperature coefficient is ±100 ppm/°C over the operating temperature range of -65° to +165°C. Maximum working voltage is 200 V rms.

Dale Electronics Inc., 2300 Riverside Blvd., Norfolk, Neb. 68701; (402) 371-0080. Approximately \$0.05 (100,000) units).

CIRCLE 365

#### **Dot-matrix print head** boasts speed, low cost

eaturing high-resolution graphics output, the Model 900 radial dot-matrix print head is capable of operating at speeds of up to 150 char/s. It also offers one of the industry's lowest prices.

The 900 print head has a seven- or nine-dot yield. Graphics are enhanced by a fine needle diameter of 0.012 in. and dot diameters of 0.015 in. The head produces a vertical spacing of 72 dots/in. Horizontal resolution is 60 dots/in. for full-dot spacing and 120 dots/in. for half-dot spacing. Character height is 0.122 in. for the nine-wire array and 0.094 in. for the seven-wire formation.

Litton Industries, Westrex OEM Products Division, 51 Penn St., Fall River, Mass. 02724; (617) 676-1016, \$48.

# Think Teledyne...For Fast Dual Power MOSFET Drivers.



Fast drivers.

There are thirty-three at the Indy 500.

Teledyne Semiconductor has its own high-speed driver—the TSC426/427/428. And it's available. You get high speed along with high load driving capacity.

The TTL/CMOS input voltage level is translated into an output voltage level swing equalling the supply, and the low impedance, high-current driver outputs will swing a 1000 pf load to 18 V in only 30 ns. The extremely low power dissipation of the CMOS TSC426/427/428 will make virtually any system more reliable than before.

For your *complete* power control requirements: the TSC426 inverts; the TSC427 is non-inverting; and the TSC428 has a driver for each. It drives a high-capacity load ... and fast.

Whatever your application ... robotics ... switch-mode power supplies ... DC-to-DC converters ... alarm drivers ... incandescent lamp drivers ... high-speed clock distribution ... give yourself the Teledyne advantage ... with the TSC426/427/428 Dual Power MOSFET Driver.

Terra Bella Avenue • Mountain View, CA 94043 • Telephone: (415) 968-924

CIRCLE 235

Please send me more	Name
information on the	
TSC426/427/428 Dual	Address _
Power MOSFET Drivers.	Telephone

Name	Title	Company	
Address	City	State Zip	

Application

9FDTTSC426

# **Electronic Design**

ELECTRONIC DESIGN's function is:

■ To aid progress in the electronics industry by promoting good design.

■ To give the electronic design engineer concepts and ideas that make his job easier and more productive.

■ To provide a central source of timely electronics information.

■ To promote communication among members of the electronics community.

Want a subscription? ELECTRONIC DESIGN is circulated free of charge to those individuals in the United States and Western Europe who function in design and development engineering in companies that incorporate electronics in their end product and government or military agencies involved in electronics activities. For a free subscription, use the application form bound in the back of the magazine or write for

an application form.

If you do not qualify, paid rates for a one year subscription (26 issues) are as follows: \$45. U.S., \$60. Canada, Mexico and Central America. International annual subscription rates listed below include air delivery: \$95. Europe; \$145. Japan, North Africa & Mid East; \$170. Australia; \$185. South America; \$210. Central/South Africa & Other Asia; \$245. New Zealand/ New Caledonia. Single copies (when available) may be purchased for \$5. U.S., Canada, Mexico & Central America; \$7. Europe; \$8. Japan, North Africa, Mid East, South America; \$10. Central/ South Africa, Other Asia, Australia, New Zealand/New Caledonia. The GOLD BOOK (27th issue) may be purchased for \$50. U.S., Canada, Mexico, Central America and \$65. all other countries, via surface mail.

If you change your address, send us an old mailing label and your new address; there is a coupon in the Products section of the magazine for this purpose. Please allow 6 to 8 weeks for address change to become effective. You must requalify in order to continue receiving ELECTRONIC DESIGN free of charge

ELECTRONIC DESIGN'S accuracy policy:

■ To make diligent efforts to ensure the accuracy of editorial matter.

■ To publish prompt corrections whenever inaccuracies are brought to our attention. Corrections appear in "Letters.

■ To encourage our readers as responsible members of our business community to report to us misleading or fraudulent advertising.

■ To refuse any advertisement deemed to be

misleading or fraudulent.

Individual article reprints and microfilm copies of complete annual volumes are available. Reprints cost \$6.00 each, prepaid (\$.50 for each additional copy of the same article), no matter how long the article. Microfilmed volumes cost \$66.80 for 1982 (Vol. 30); \$75.70 for 1974-1981 (Vols. 22-29); \$50.20 for 1973 (Vol. 21); varied prices for 1952-1972 (Vols. 1-20). Prices are subject to change. For further details and to place orders, contact Customer Services Dept. University Microfilms, 300 N. Zeeb Rd., Ann Arbor, MI 48106. (313) 761-4700.

Where necessary, permission is granted by the copyright owner for libraries and others registered with the Copyright Clearance Center (CCC) to photocopy any article herein for the base fee of \$1.00 per copy of the article plus 50¢ per page per copy. Payments accompanied by the identifying serial fee code below should be sent directly to the CCC, 21 Congress St., Salem, MA 01970. Copying done for other than personal or internal reference use without the express permission of Hayden Publishing Co./ELEC-TRONIC DESIGN is prohibited. Requests for special permission or bulk orders should be addressed to the editor. Serial fee Code: 0013-4872/1984 \$1.00 + .50

Want to contact us? Address your correspon-

ELECTRONIC DESIGN 10 Mulholland Dr. Hasbrouck Heights, NJ 07604

# **P**RODUCT NEWS

#### Improved logic analysis for HP 64000

or high-speed logic design on the HP 64000 development system, Hewlett-Packard Co. (Palo Alto, Calif.) has developed a subsystem that provides state analysis rates of up to 125 MHz and timing analysis for up to 32 input channels at rates of 200 and 400 MHz. Designated the HP 64610S. the analyzer is an extension of and a replacement for the HP 64600S logic timing/hardware analyzer. The expanded feature set of the new subsystem is provided by a control board that accepts an external clock, new operating software, and two additional eight-channel data-acquisition boards. Existing HP 64600S subsystems can be upgraded to include the new features. Prices for the HP 64610S range from \$7000 to \$20,000, depending on the number of channels selected.

CIRCLE 371

#### Software speeds gate-array design

software package that improves productivity in the design and test of CMOS gate arrays by as much as 50% has been released by International Microcircuits Inc. (Santa Clara, Calif.). Called Easygate, the application utilities software permits the design of 2- to 4- $\mu$ m arrays (from 240 to over 5000 gates) on Daisy or Mentor CAE workstations. Easygate features line delay corrections for fan-out, temperature, and voltage, and the user can run simulations using Sentry-compatible test vectors to verify both design and testability. Once completed, the final design can be sent to IMI on an 8-in. floppy disk. A Daisy Logician workstation, including the Easygate software, can be leased from IMI. CIRCLE 372

#### 8-in. Winchesters access 35% faster

he average access times of an entire family of 8-in. Winchester disk drives have been reduced by 35%. Mega-Vault Memories (Woodland Hills, Calif.), the manufacturer of the disk drives, reports that access times have dropped from 38 ms to a minimum of 25 ms for all models. which range in capacities from 83 to 212 Mbytes. The faster access times are the result of replacing ferrite magnets with more powerful rare-earth magnets and incorporating a special iron housing to improve the magnetic circuitry, enabling the head actuator to achieve higher positioning speeds. Additionally, the microprocessor was reprogrammed. CIRCLE 373

#### Card adds ac capability to analog IC tester

eveloped by Pragmatic Test Systems Inc. (Milpitas. Calif.), an expansion card adds ac functions and measurement capabilities to the dc parametric test capabilities of the company's TM-7A and TM-7B linear IC test heads. Up to four cards can be plugged into the expansion bus of the test systems to provide combinations of programmed sine, square, and triangle waves—0 to 12 V amplitude, with or without dc offset, at frequencies of 40 Hz to 100 kHz to any pin on the test head matrix. Additionally, the power supply voltages of the device under test can be modulated to evaluate device characteristics (such as noise immunity). Op amp slew rates (from 0.1 to 500 V/ $\mu$ s) can be measured by specifying the measurement parameters in a few lines of Basic-like code. Rms voltage measurements have 16-bit resolution.

CIRCLE 374

#### Z family $\mu$ Ps can be surface-mounted

GS Semiconductor Corp. (Phoenix, Ariz.) is packaging its family of Z type microprocessors and peripherals in space-saving surface-mounted enclosures. Quad-inline, J-bend-type chip carriers (plastic or ceramic) can be specified for the Z8, Z80, Z8000, and Z8500 product lines. The devices are available for the commercial, industrial, and military temperature ranges, as well as with a  $\pm 10\%$  power supply range. Future prices of the surface-mounted devices in volume production quantities are expected to be nearly equivalent to that of their dual in-line counterparts.

CIRCLE 375

#### Software derives tests from design data

ointly developed by Daisy Systems Corp. (Sunnyvale, Calif.) and Factron/Schlumberger (formerly Fairchild Test Systems), a software interface package links Daisy's CAE workstation with Factron's test systems to reduce the design-to-manufacturing cycle of complex VLSI-based boards. Information generated during the design phase is captured and translated into a test program, which is used for production testing or debugging through a guided-probe technique. By linking the design data base to the test system, the time required to develop the board test programs can be reduced by as much as 50%. The software package can be purchased from either company for \$3800.

CIRCLE 376

# **ElectronicDes**

#### **Advertising Sales Staff**

Paul C. Mazzacano, National Sales Manager Sunnyvale, CA 94087 (408) 736-6667

#### Hasbrouck Heights, N.J. 07604

Thomas P. Barth, Robert W. Gascoigne, Gail Goldstein, Constance McKinley, Becky McAdams, Stan Tessler, Carol Helton Sales Assistants: Francine Guerra, Supv.: Karen Schwartz, Bernadette Zajicek 10 Mulholland Dr., (201) 393-6000 TWX: 710-990-5071, (HAYDENPUB HBHT)

#### Philadelphia

Thomas P. Barth (201) 393-6072 Becky McAdams (201) 393-6074

M.E. "Casey" McKibben, Jr., Joseph Burke 260 Bear Hill Rd., Suite 100 Waltham, MA 02154 (617) 890-8050

Jeff Hoopes (408) 736-6667

#### Chicago 60611

Thomas P. Kavooras, Craig L. Pitcher Sales Assistant: Mary Nardulli 200 East Ontario, (312) 337-0588

Thomas P. Kavooras (312) 337-0588

9451 LBJ Freeway, Ste. 220 Dallas, TX 75243 (214) 234-0508

Stanley Ehrenclou (213) 641-8544

#### Los Angeles 90045

Stanley I. Ehrenclou, Ian C. Hill Sales Assistant: Betty Fargo 8939 South Sepulveda Blvd., Suite 260 (213) 641-6544

#### Orange County/San Diego

2082 Michelson Drive. Suite 212 Irvine, CA 92715 (714) 476-0315; (213) 641-6544

lan Hill (213) 641-6544

#### San Francisco

Bill Sleight, Rich Bastas, Jeff Hoopes, Pamela Rock Sales Assistant: Jacqueline Gray 1307 South Mary, Suite 212 Sunnyvale, CA 94087, (408) 736-6667

Craig Pitcher (312) 337-0588

#### United Kingdom-Scandinavia/Israel

Constance McKinley 10 Mulholland Dr., Hasbrouck Heights, N.J. 07604 (201) 393-6000

#### Austria, Belgium, Holland Switzerland, Germany

W.J.M. Sanders, S.I.P.A.S. Oosterpark 6-P.O. Box 25 1483 ZGdeRYP, Holland Phone: 02997-1303 and 3660 Telex: 13039 SIPAS NL Telegrams: SIPAS-Amsterdam

France: Gerard Lasfarques 32 rue Desbordes Valmore 75116 Paris, France, Phone: 1-504-97-94

Italy: Luigi Bancati 20090 Segrate Milano S. Felice Torre 5, Italy, Phone: 02-75-31-445, Telex: 311010 Orchid 2


Japan: Haruki Hirayama, EMS, Inc. Sagami Bldg., 4-2-21, Shinjuku, Shinjuku-ku, Tokyo 160, Japan Phone: (03) 350-5666, Telex: 2322520

#### Hong Kong-Taiwan

Owen Wang, Ace Media Agency, Inc. P.O. Box 26-578 Taipei, Taiwan, R.O.C. Phone: (02) 751-3636 Telex: 14142 ACEGROUP

Recruitment Advertising Manager: Gail Goldstein (201) 393-6000 Susan Barnes

# Discover the Secrets of **Better BASIC**



#### **Secrets of Better BASIC** Ernest E. Mau

Reveals the sophisticated programming techniques used by professional software authors to write more effective programs. Also discloses professional secrets for

- · testing & debugging programs
  - · using memory efficiently
  - · executing loops & subroutines
  - · creating disk files

Helps you overcome the limitations of BASIC programming, improve program execution time, handle files more easily, and format your programs for easy reference.

#6254, \$14.95

Order By Phone • 1-800-631-0856 operator FE63 • In NJ 201-368-2202, ext. 19

### Havden

Dept. FE63 • Hayden Book Company, Inc. 10 Mulholland Dr., Hasbrouck Hts., N.J. 07604 Please send me Secrets of Better BASIC. If I am not completely satisfied, I may return the book undamaged within 10 days for a complete refund.

Please add \$2.00 to cover shipping and han-

airing.	
Enclosed is my ch	neck or money order.
Please hill my Vis	MasterCard

Name	
Address	
City	
State/Zip	
Visa/MasterCard #	Exp.
Signature	
	nd CA must add sales

# **APPLICATION NOTES**

#### Digital voice and T-1 transmission

he first of a series of technical backgrounders, Digital Voice and T-1 Facilities is a 16-page booklet that examines concepts central to digitizing voice and the effective utilization of T-1 (1.544-Mbit/s) transmission facilities. Accompanying diagrams illustrate key points made in the text, while technical concepts are presented in a straightforward manner.

Timeplex Inc., 400 Chestnut Ridge Road, Woodcliff Lake. N.J. 07675; (201) 930-4600.

CIRCLE 377

#### **Designing EMI** shielding windows

onsiderations of EMI Shielding-window design are explored in a 40-page brochure, written to assist the designer in conducting a detailed review of transparent barriers used for viewing and EMI shielding of large window areas. Specific treatment of EMI shielding performance, optical performance, optically clear window substrates, contrast enhancement, and assembly and mounting techniques are among the topics covered. Characteristics of CRT phosphor screens and a glossary of terms are also included.

Tecknit, Corporate Communications, 129 Dermody St., Cranford, N.J. 07016.

CIRCLE 378

#### **Optical encoder** design guide

12-page pamphlet assists the design engineer in specifying the proper encoder to meet specific application requirements. The primer differentiates between absolute and incremental styles of encoders and explains the use of tachometer- and quadrature-type outputs. The literature also describes various count multiplication techniques and contains a glossary of terms and typical application examples.

BEI Motion Systems Co., Industrial Encoder Division, 7230 Hollister Ave., Goleta, Calif. 93117.

CIRCLE 379

#### **Custom hybrid** microcircuit design

ntitled An Electrical Design Guide sign Guide for Users of Hybrid Microcircuits, this 20-page booklet focuses on cost-effective approaches to circuit design in order to optimize performance. The guide probes digital and analog circuit types, exploring a variety of design, packaging, and implementation considerations. Component selection, circuit partitioning, funneling, derating, and other subjects are discussed.

Teledyne Microelectronics. 12964 Panama St., Los Angeles, Calif. 90066; (216) 267-2700.

## Microwave, vibration, and rf test instruments

Containing descriptions, specifications, and applications data, a 334-page hard-bound catalog presents instruments used for antenna measurements, determining radar cross section, telecommunciations, spectrum analysis, vibration testing, machine protection, and signal detection and analysis.

Scientific-Atlanta Inc., PO Box 105072, Atlanta, Ga. 30348; (404) 449-2075.

CIRCLE 387

# Standard-cell library

Synertek's standard-cell library data book describes the basic functions and operating characteristics of approximately 200 pretested standard cells. TTL and CMOS cross-reference charts, packaging information, and a section on characteristics common to all cells precede each data sheet.

Synertek Inc., PO Box 552, Santa Clara, Calif. 95052; (408) 748-7047.

CIRCLE 388

# 300-baud modem and filter chip set

Data sheets describe a low-power 300-baud modem and filter chip set. The eight-page document includes block diagrams, pin assignments, electrical characteristics, timing charts, interconnection diagrams, and package dimensions.

S-MOS Systems Inc., 50 W. Brokaw Road, San Jose, Calif. 95110; (408) 993-1212.

CIRCLE 389

## Miniature coaxial connectors



The Nu-Lok 1200 series of miniature coaxial connectors, designed to meet the requirements of MIL-C-25516, is the subject of a 20-page catalog. The catalog covers the connectors' electrical, environmental, and physical performance characteristics.

TRW Electronic Components Group, Cylindrical Connector Division, 8821 Science Center Drive, Minneapolis, Minn. 55428; (612) 537-1010.

CIRCLE 390

# Manufacturing software programs

over 500 software programs for manufacturing are described in the 1985 Handbook of Manufacturing Software. Programs include inventory control, CAD/CAM, robotics, and process

control software. The book also covers the fundamentals of applying computers to the manufacturing environment.

SEAI Technical Publications, PO Box 590, Madison, Ga. 30650; (404) 342-9638.

CIRCLE 391

## D-subminiature filtered connectors

miniature connectors—preassembled with one of seven distributed element filters or one of four capacitor filters—are presented in a catalog. Also detailed are 10-, 26-, 34-, 40-, and 60-pin filtered headers, filtered adapters for circular plastic connectors, and filtered circular metal-shell connectors.

Amp Inc., PO Box 3608, Harrisburg, Pa. 17105; (717) 564-0100.

CIRCLE 392

# Catalog describes computer books

A 16-page catalog contains detailed information—including chapter contents and pricing—for a wide variety of computer books. Publications include tutorials on operating systems (e.g., CP/M, iRMX, MS-DOS and Unix), language translators, and 8088 µP design.

Microcomputer Applications, 827 Missouri St., Fairfield, Calif. 94533; (707) 422-1622.

# **N**EW LITERATURE

#### STD bus cages and motherboards

orty new STD bus card cages and eight new STD bus motherboards are highlighted in a 12-page brochure, which comes with a separate price sheet that lists prices for Matrix's entire line of STD bus products. Individual product features, mechanical drawings, and optional accessories are covered within the literature. The new introductions, designated group 11, offer systems engineers greater customization for STD bus systems and eliminate many of the previous packaging restrictions.

Matrix Corp., 1639 Green St., Raleigh, N.C. 27603; (919) 833-2837.

CIRCLE 381

#### Ac power sources and uninterruptibles

A wide range of manual, programmable, and microcomputer-controlled ac power sources and uninterruptible power systems are described in a 54-page catalog. The specification data is combined with pricing information and complemented by an informative piece on six major considerations to take into account when comparing the ratings of ac power supplies.

Behlman Engineering Corp., 1142 Mark Ave., Carpinteria, Calif. 93013; (805) 684-8311.

CIRCLE 382

#### Rocker switches

Internationally approved rocker switches are presented in a catalog that is packed with information. In this first edition, it gives electrical and mechanical specifications, dimensional drawings, and part-number selection codes. Also featured is a reference section listing the various international approval marks and the approving agencies for each country listed.

Dreefs Switch Inc., 3782 Hawthorn Court, Waukegan, Ill. 60085; (312) 662-7667.

CIRCLE 383

#### Linear supplies and dc-dc converters

nine-page brochure fea-Atures linear ac/dc power supplies and modular dc-dc converters. Pc board-mounted supplies range from 5 V at 250 mA to  $\pm 15 \text{ V}$  at 150 mA: chassis-mounted versions range from 5 V at 1000 mA to ±15 V at 500 mA. Dc-dc converters span 5 V at 100 mA to  $28 \text{ V at } \pm 190 \text{ mA}$ . Application notes discuss power supply test procedures, transients. and thermal derating. The brochure also illustrates grounding techniques for avoiding noise and oscilla-

Analog Devices Inc., Route 1 Industrial Park, PO Box 280, Norwood, Mass. 02062; (617) 329-4700.

CIRCLE 384

#### Display and control instrumentation



Display and control instruments are the subject of a 45-page catalog that provides complete specifications for a line of analog and digital panel meters, optical and solidstate meter relays, and microprocessor-based temperature controllers.

LFE Corp., Process Control Division, 55 Green St., Clinton, Mass. 01510; (617) 835-1000.

CIRCLE 385

#### **Push-button** switches

he 75 Series of pushbutton switches—manufactured by Rafi of West Germany and marketed through Ledex Inc.-is depicted in a 21-page bulletin (PB-5507). Technical data for each of the device configurations is given, as well as accessory information.

Ledex Inc., PO Box 427, Vandalia, Ohio 45377; (513) 898-3621.

# Low in Profile. High in Performance.



#### SMK LOW PROFILE KEYBOARDS

If you want the best possible custom, low profile keyboard for your system—then SMK is the name to depend on. Why? Because SMK's expert engineering staff can quickly translate your needs into the keyboard design perfect for your application. Then, SMK utilizes only the best materials and workmanship to produce a truly superior product. The result: an outstanding keyboard in terms of reliability, appearance, and performance. SMK builds low profile keyboards utilizing membrane, mechanical, or conductive rubber technology. They're available encoded or unencoded, in virtually every "low pro" configuration. Plus, SMK keyboards feature longer key life and sensational tactile feel. You can specify them with standard or sculptured keytops, and in the color perfect for your system. What's more, SMK mechanically and electrically inspects every unit built in their modern, fully automated plant. So call SMK today for more information today. We'll save you keyboard headaches tomorrow. SMK Electronics, 1901 Nancita Circle, Placentia, California 92670.


(714) 996-0960.



KEY SOLUTIONS FROM SMK CIRCLE 232

#### **NEW LITERATURE**

#### **Chart explains** resistor color code



Explaining the part-mark-ing systems used for Mepco/Electra's various resistor products is a four-page pocket-size chart. The chart defines the standard color code used on most carbonfilm and metal-film resistors and explains the alphanumeric systems used on military-screened devices. The chart also includes a table of standard resistance values for the 10-to-100 decade.

Mepco/Electra, Columbia Road, Morristown, N.J. 07960. CIRCLE 394

#### X-Y and rotary positioning tables

recision- and commercialgrade positioning tables for electronics manufacturing, robotics, and automated assembly are the subject of a 20-page brochure. In addition to selection and application data, the literature contains photographs and mechanical drawings of X-Y, single-axis, and rotary positioners. Also covered are positioning system components, options, and accessories.

Design Components Inc., 1 Kenwood Circle, Kenwood Industrial Park, Franklin, Mass. 02038; (617) 528-7300.

CIRCLE 395

#### Radiation-hardened bipolar ICs

An eight-page brochure contains 28 detailed graphs that demonstrate device tolerance to gamma radiation. The bipolar ICs that are evaluated for their radiation hardness include inverting op amps, instrumentation amps, low-noise op amps, and precision voltage references.

Micro Power Systems Inc., 3100 Alfred St., Santa Clara, Calif. 95050; (408) 727-5350.

CIRCLE 396

#### Visual microelectronic package inspection

handy reference guide Acovers specifications for the visual inspection of microelectronic packages and covers. The data contained in the 34-page publication is based on the JEDEC Solid State Products Engineering Council Standard No. 9 (published August, 1984). Topics covered include visual inspection criteria, glass insulators, brazing, lead frame, pins, and many others.

Airpax Corp., W. Johnson Ave., PO Box 8968, Cheshire, Conn. 06410; (301) 228-4600.

CIRCLE 397

#### Software for the Series 32000 µP

comprehensive software catalog details the growing base of application, development, and operating system software available for the Series 32000 microprocessor family. The 138-page publication covers nearly 130 products and contains cross-referenced listings of software developed by National Semiconductor and approximately 50 independent software vendors (including addresses, telephone numbers, and availability).

National Semiconductor Corp., Literature Department, 2900 Semiconductor Drive, M/S 23-205, Santa Clara, Calif. 95051; (408) 721-4902.

CIRCLE 398

#### **Special-function VLSI** circuits

he CMOS/NMOS Special Functions Data Manual (DL130) is a complete compilation of product specification and application information for more than 60 special-function VLSI devices. Chapters for each family of devices include: a-d and d-a converters, decoders and display drivers, op amps and comparators, phase-locked loops and frequency synthesizers, and more.

Motorola Literature Distribution Center, Broadway Bldg. 1, 616 W. 24th St., Tempe, Ariz. 85282; (602) 994-6561. \$1.60 (one to nine copies).

#### **NEW LITERATURE**

# Surface-mounted components

Various types of surfacemounted components are presented in a 24-page brochure, which provides device specifications and dimensional drawings. Products include multilayer ceramic and solid tantalum capacitors; resistor networks; discrete semiconductors, such as transistors and diodes; and integrated circuits, including linear and Hall-effect designs.

Sprague Electric Co., Technical Literature Service, 347 Marshall St., North Adams, Mass. 01247; (413) 664-4411.

CIRCLE 400

# General-purpose and standard relays

rully illustrated with photographs and outline drawings, a 20-page catalog provides technical data for general-purpose, midget, power, miniature power, low-profile, telephone-type, and automotive-type relays. A chart presents the specifications for each of the relay series for quick comparison.

Schrack North America Inc., 3 Westchester Plaza, Elmsford, N.Y. 10523; (914) 592-1305.

CIRCLE 401

## Optical waveguides for local networks

The Light Brigade is a reprint of an article describing optical waveguides designed for local area net-

works. The article discusses the emerging local-access market for optical communications technology and describes the feasibility, component development, waveguide design choices, and the benefits of optical fiber in local-access applications.

Corning Glass Works, Telecommunications Products Division, MP-BH-5, Corning, N.Y. 14831; (607) 974-4432.

CIRCLE 402

# Linear and switching power supplies

over 400 linear, phase-controlled, and switching power supplies for laboratory, industrial, and OEM applications are described in a 100-page catalog. In addition to operating specifications, the catalog contains photos, dimensional drawings, and a matrixed power supply selection chart.

Sorensen Co., 676 Island Pond Road, Manchester, N.H. 03103; (603) 668-4500.

CIRCLE 403

#### Fiber-optic system testing

A pocket-sized guide covers testing procedures for fiber-optic cables, transmitters, receivers, and system data transmission. It also contains a power conversion chart (dB to W) and a dB-to-% transmission table.

Fotec Inc., 560 Harrison Ave., Boston, Mass. 02118; (617) 542-1719.

CIRCLE 404

# spst, spdt Switches



10 to 2500 MHz only \$2995 (6-24)

IN STOCK...IMMEDIATE DELIVERY

- rugged construction; pin-diode chips
  - pin-diode chips on thick-film substrate
- only 5v control signal for 1  $\mu$  sec switching
- 50 ohm matched in "open" state, SPST only
- low insertion loss, <2 dB typ.
- high isolation, >30 dB typ.
- hermetically-sealed to meet MIL-STD-202
- one-year guarantee

## SPECIFICATIONS FOR PSW-1111 (SPST) and PSW-1211 (SPDT)

10-2500 MHz FREQUENCY RANGE INSERTION LOSS 10-2000 MHz 1.7 dB max. 2000-2500 MHz 2.7 dB max. ISOLATION 10-500 MHz 40 dB min. 500-1000 MHz 30 dB min. 1000-2000 MHz 25 dB min 2000-2500 MHz 22 dB min. 1.5 max. ("on" state) SWITCHING SPEED 1 μ sec. (max.)

MAXIMUM RF INPUT +20 dBm

CONTROL +5 V (5 mA max.)

OPERATING TEMPERATURE -54°C to +100°C

STORAGE TEMPERATURE -54°C to +100°C PRICE (6-24)

PSW 1111 \$29.95 PSW 1211 \$29.95

Call or write for free 64-pg. catalog

finding new ways ... setting higher standards

## Mini-Circuits

A Division of Scientific Components Corporation
World's largest manufacturer of Double Balanced Mixers
P.O. Box 166, B'klyn, N.Y. 11235 (718) 934-4500

C102-3 REV. ORIG

# Recruitment Advertising

# **Electronic Design**

YOU CAN REACH ENGINEERS WITH TITLES LIKE THESE:

- Test Engineer
   Systems Engineer
   Digital Engineer
   Quality Assurance Engineer • Software Engineer • Analog Engineer • Director of Engineering • Data Communications Engineer • Hardware Engineer
- Reliability Engineer
   R & D Engineer
   Operations Manager

#### Circulation 128,279 **Total Readership 384,837**

#### RECRUITMENT CLOSING DATES

Electronic Design is mailed every two weeks. Because of its timeliness, personnel recruitment advertising closes only two weeks before each issue's mailing date.

Issue Date	Closing Date	Mailing Date
Dec. 27	Dec. 7	Dec. 21
Jan. 10	Dec. 21	Jan. 4
Jan. 24	Jan. 4	Jan. 18
Feb. 7	Jan. 18	Feb. 1
Feb. 21	Feb. 1	Feb. 15
Mar. 7	Feb. 15	Mar. 1

#### Electronic Design RECRUITMENT ADVERTISING RATES

15% commission to recognized agencies supplying offset film negatives. Net 30 days. Four column makeup.

		DIM	ENSIO	NS				
SPACE	Wi	de		Deep		CC	OST	
One column inch	1-3	3/4"	x 1"			\$ 9	1	
1/8 page	1-3	3/4"	x 5"			\$4	51	
1/4 page	1-3	3/4"	x 10	" Vert.		\$9	101	
	3-	1/2"	x 5"	Hor.				
1/2 page	3-1	1/2"	x 10	" Vert.		\$1	,802	
	7 "		x 5"	Hor.				
3/4 page	5-3	3/4 "	x 10	"		\$2	,703	
1 page	7 "		x 10	"		\$3	,604	
Rates	1X	4X	7X	13X	19X	26X	39X	52X
Per Column Inch	\$91	\$89	\$83	\$77	\$74	\$71	\$70	\$68

	COLO	R RATES	
Second color, per page or fraction Additional insertions, same form	\$430 310	Matched color, per page or fraction Additional insertions, same form	\$735 430
3 & 4 color, per page or fraction Additional insertions, same form	780 460	Sheen inks, per page or fraction Additional insertions, same form	835 430

Camera-ready film (right reading negatives, emulsion side down) or cameraready mechanicals must be received by deadline. Or, if you wish us to set your ad (typesetting is free) simply pick up the phone and call our RECRUITMENT HOT LINE - (201) 393-6000/6076. Ask for:


#### Gail Goldstein RECRUITMENT ADVERTISING MANAGER

**ELECTRONIC DESIGN** 

10 Mulholland Drive, Hasbrouck Heights, New Jersey 07604

# FEDERAL EXPRESS... INTRODUCING NEW TECHNOLOGY

Federal Express has an opportunity for you to work with our absolutely, positively, incredible technology. The pioneer leader in overnight delivery of high priority business goods and documents is taking the next logi-cal step...announcing ZapMail, the two-hour electronic express service. Rapid growth of our Electronic Products Division has created the need for the following individual





#### SR. RELIABILITY ENGINEER

As Sr. Reliability Engineer you will analyze the reliability of electro-mechanical components and systems for the purpose of improving reliability and enhancing mainpurpose of improving reliability and enhancing maintainability. A Bachelor's degree in Electrical or Mechanical Engineering is required. You must have five years professional reliability experience in the copier or similar electro-mechanical high technology industry. The ability to define, develop and implement reliability test programs related to complex electro-mechanical hardware designs is essential.


This is an opportunity for you to work in a company with high recognition, unparalleled growth, high incentives, and extensive and unique benefits...a company on the leading edge of high technology. For prompt consideration please forward a letter indicating your experience and salary history. Send your resume if you have one.

#### FEDERAL EXPRESS CORPORATION

Electronic Products Division P.O. Box 727, Dept. 3514-433 Memphis, TN 38194

Equal Opportunity Employer M/F

**OUR COMPANY IS KNOWN BY THE PEOPLE IT KEEPS** 



# E-SYSTEMS

#### E-SYSTEMS, INC., ECI DIVISION, ST. PETERSBURG, FLORIDA

And also by the technology we produce. At the ECI Division in St. Petersburg, we're involved in building military communications systems, including everything from satellite communications systems and space communications equipment to shipboard terminals, transmitters, receivers and amplifiers. Electronic data handling systems, including transmission systems, teleprinters and digital plotters. Microwave phased array antennas, conformal arrays and adaptive null steering antennas.

That's why we're known by the people we keep. Because it takes engineers and technical support personnel of the highest quality to live up to the unique challenges we have. If you're qualified, come see what our package of career-long challenges, Flexible Employee Benefits, Human Resource Program, Employee Stock Ownership Plan and Relocation Assistance have to offer.


If engineers are known by the company they keep, E-Systems ECI Division is where you need to be. Openings:

- Reliability Engineers
- Sr. Test Équipment Engineers
- Product Engineers
- RF Engineers
- Transmitter Design Engineers
- Component Engineers
- Antenna/Microwave Engineers
- EMI-TEMPEST Engineers
- Quality Engineers
- Systems Engineers
- Member Technical Staff Data Communications/ Real-Time Systems
- Software Designers ADA Packet Switching

If you're the person we're looking for, get to know our company. Send resume to: Mr. T.B. Harris, Director of Employee Relations, E-Systems, Inc., ECI Division, Dept. 26, P.O. Box 12248, St. Petersburg, Florida 33733.



U.S. Citizenship Required. An Equal Opportunity Employer, M/F, V, H.



# SOFTWARE ENGINEERS

There are key openings right now for talented people on B1-B Avionics, AI, Image Generation, Radar, Flight Simulation and Commercial Avionics programs.

These positions offer challenging opportunities for the development of advanced technology for the next generation of software engineering.

SOFTWARE/COMPUTING SYSTEMS & ANALYSIS

SOFTWARE OPERATIONS SUPPORT

OPERATIONAL SOFTWARE DEVELOPMENT

SOFTWARE AND COMPUTER TESTING AND EVALUATION

SUPPORT SOFTWARE DEVELOPMENT

REAL TIME SYSTEMS/ SIMULATION SOFTWARE ENGINEERING

AUTOMATED SYSTEMS TESTING

Some positions require U.S. citizenship.

If you're the right person for the assignment, send your résumé, with present and expected salary, to The Boeing Company, P.O. Box 3707-THX, Seattle, WA 98124.

# Join Racal-Milgo... where the approach to research allows individual options.

Dr. Ming-Luh Kao had the option of taking his advanced technology idea (video compression) through the product development phase...or only through prototype. Dr. Kao elected to start on the next area of technology, yet remained available to those in Development who were preparing the product for market.



An EEO/Affirmative Action Employer

"Join the 'right-size' Racal-Milgo research group where you can provide input into the Company's strategic plan, pursue individual specialties, and gain recognition ...while enjoying project diversity, excellent research 'tools' and a large commitment to data communications industry leadership."


 Dr. C. R. Baugh Senior Director, Applied Research

Racal-Milgo, a world leader in the design, development, manufacture and marketing of data communications systems, has a record of continuous growth, scientific breakthroughs, technical excellence and quality products. Right now we seek research professionals with advanced degrees and/or extensive experience in multiple areas of...

- Communications Software Technology
- Speech/Image Signal Processing
- Technology Forecasting
- Communications Protocols
- Packet/Circuit Switching
- Local Area Networks
- Broadband Networks

We offer fast-paced challenges, sunny Florida lifestyles, and a beautiful new corporate headquarters. If this sounds like an environment that's right for you, contact us today.

Briefly describe a recent project:	
	Name
	Address
	City
Employer (optional):	State Zip
	Phone day () night ()
Engineering Employment Supervisor	Degree(s)
Racal-Milgo®	from
Dept. 12446ED 7800 W. Oakland Park Blvd.	Years of experience
Ft. Lauderdale, Florida 33321	Please enclose a resume if you have one.



Progressive engineering opportunities; liberal relocation policy; dramatic business growth; warm Southwestern hospitality; hot technology — you'll find it all at Sperry.

Sperry's Defense Systems operation in Albuquerque offers you a rare opportunity to break new ground in your career. We're developing revolutionary avionics for such sophisticated aircraft as the F-15 and F-16 fighters, AH-64 attack helicopter and B-1B bomber, in a modern facility undergoing its second expansion in only two years. Opportunities include:

#### **Engineering Design CRT Displays**

Requires a BSEE and two or more years' experience in one of the following areas: hardware design of microprocessorbased electronic systems; analog circuit design related to CRT displays; high and low voltage power supplies; and design of programmable symbol generation systems.

- Analog Design
- Electronic Flight Instruments
- Programmable Symbol Generators
- Software Development

#### **Helicopter Avionics**

Requires a BSEE and two or more years' experience in one of the following areas: analog and digital circuit design; test equipment design; human factors/systems design; microprocessor-based systems including I/O, 1553B bus architecture and data processing.

- Analog and Digital Design
- Human Factors
- Software Development
- Systems Integration

#### Flight Control Systems

Requires a BSEE and two or more years' experience associated with design or microprocessor-based systems including I/O, data transmission, bus architecture signal conversion, and analog digital circuit design. Applications include:

- Analog/Digital Circuit Design
- Flight Control System Development
- Software Development
- Simulation/Algorithm Development

## **Engineering Support**

#### Electronic Packaging Engineer

This position will require coordination of customer requirements, packaging concepts, analysis, manufacturing processes and tests to achieve a viable product. Requires a BSME and a minimum of two years' experience with military airborne or space electronic equipment.

#### Components Engineer

Preparation of component specifications and provision of technical liaison between Sperry component vendors. Need specialists in electrical/electronic and mechanical components.

#### Reliability Engineer

Performance of circuit stress analysis, reliability prediction and failure mode analysis, and participation in reliability development testing.

#### **EMIC Engineer**

You will participate in equipment design, prepare control and testing. Experience in EMIC testing and planning. Familiarity with MIL-STD-461 and -462 is necessary. Position also available for EMI technician.

#### Power Supply Engineer

Assist project groups in the analysis and design of low and high voltage power supplies for high-reliability applications. A working knowledge of MIL-STD-704 and power FET switchmode conversion circuitry is essential.

#### **Designers:**

#### Electrical

The position involves the layout of high density multi-layer boards with a background in automated design generation.

#### Mechanical


You will be involved in completing conceptual design layouts including form fit, function and tolerance analysis. Familiarity with ANSI Y14.5M, MIL-STD-100, DOD 1000, and engineering principles is preferred. Each of the above positions requires a BSEE or BS Engineering Physics.

#### Come Join Us . . .

With Sperry, you'll enjoy an excellent salary and benefits with one of the country's leaders in electronics. For consideration, send your resume and salary information in confidence to: Brandon Harwood, Sperry, P.O. Box 9200, Albuquerque, NM 87119.



Equal Employment Opportunity/Affirmative Action Employer. U.S. Citizenship Required.



# MATCH YOUR EXPERIENCE WITH OURS. AND CREATE

YOUR OWN FUTURE AT CSD.

From extreme environments on earth to remote areas of space—wherever the greatest challenges of modern communications are found, you'll find CSD. Our extensive resources, unmatched experience and total involvement in every area of communications technology makes CSD the pacesetter of the industry. If you can solve difficult communications problems by incorporating divergent technologies and innovations into a complete system design, join CSD on the threshold of new discoveries. Because of our depth, leadership and emphasis on individual achievement, we can create a position specially suited to your interests and abilities. Wherever your career goals lie, you'll find the room to accomplish them at CSD—because we have the future for you.

#### SYSTEMS ENGINEERS, SOFTWARE ENGINEERS

We are seeking qualified engineers with a BS, MS or PhD in Electrical Engineering or Computer Science, 5+ years experience with military communications systems. Project needs will utilize technical expertise in the areas of:

Digital Signal Processing
 Computer Controlled Data Communications
 Systems
 Computer Communications
 Networks
 Secure Systems
 Troposcatter Modems

If you possess specialized knowledge in one or more of these fields, and flourish in an environment whose teamwork brims with visibility and excitement, we invite you to contact us for further, more specific project information. Skills such as yours deserve the attention and rewards our company excels at providing.

Send your resume to: Harriet D. Solomon, GTE's Communication Systems Division, 77 "A" Street, Needham MA 02194. Or call us at 1-800-225-3956.

# SYSTEM DESIGN / ACQUISITION ENGINEER

#### **Packet Communications**

We require a system design engineer to lead front-end studies of packet networks. Responsibilities include system trade studies and transforming system requirements into hardware and software design specifications. You should have experience with current technology and systems, in either packet radio or packet switching, including analytical determination of correct packet size, network access schemes, coding techniques and other system parameters. BSEE or CS required, MS preferred. 5 + years experience. Familiarity with DoD requirements, specifications and systems is a plus.

Send your resume to: Sherry D. Huffer, Dept. ED 1213, GTE's Communication Systems Division, 400 Park Plaza, P.O. Box 13279 Research Triangle Park NC 27709. Or call us at 919-549-1111.

# SYSTEMS ENGINEERING MANAGER

This is an excellent opportunity for a professional with broad experience in communications including specific knowledge of data communications and telephony. We also require a background in hardware programs for real time aspects of stored program control. Your range of experience should include individual contributor level positions through to senior level management of hardware and software groups. You must have at least 15 years experience with a BSEE and MS in EE or CS.

# TELEPHONE SYSTEM O&M DESIGN

In this position you will design modern telephone operation and maintenance methods involving SPC switching equipment and centralized O&M facilities. You will provide support to our U.S. operations, with the potential for advancement into European support activities. We require 5-10 years in the above areas along with a BSEE or equivalent experience.

Send your resume to: Brian D. Harris, GTE's Communication Systems Division, Suite 441, 1777 North Kent St., Arlington VA 22209.

We can give you a strong system of support and rewards. Advancement in managerial or technical directions. Recognition within GTE and across the communications industry. Colleagues at the top of their disciplines. And benefits including tuition reimbursement as well as life, medical and dental insurance covering your dependents. For the important opportunities in communications, we can be the last place you'll ever have to look. U.S. Citizenship is required.

An Equal Opportunity Employer M/F

#### IF IT'S HAPPENING IN COMMUNICATIONS, IT'S HAPPENING AT CSD.

Research Triangle Park NC, Arlington VA, Colorado Springs CO, Rockville MD, Natick & Needham MA





South Florida Opportunities

Racal-Milgo is a world leader in the expanding field of data communications. Our products are high tech and we are growing rapidly! Bring your knowledge and expertise to Racal-Milgo and help us continue to grow in:

- Multiplexing
- Digitized Voice
- Switching

- Networking
- Protocols
- Encryption

We have multiple openings for professionals with experience and skills in one or more of the following high technology areas.

Digitized Voice Engineer — CVSD, ADPCM; E&M interface; loop-start, ground-start signaling; trunk and subscriber line interface.

Real-Time Software — high level languages, assembly language, operating system internals, multitasking, multiuser.

Software Quality Assurance — standards, reliability and maintainability; quality monitoring and improvement in the design environment.

Microprocessor Hardware/Firmware — software and hardware for smaller microprocessor-based projects.

Your professional career at Racal-Milgo offers many advantages: a "leading edge, highly sophisticated, professional environment; modern facilities and equipment; an excellent total compensation plan with comprehensive benefits; and an outdoor Florida lifestyle featuring a comfortable climate and diverse recreational opportunities related to sunny days. For confidential consideration, send your resume and salary requirements, in confidence to:

Patrick Ahern, Technical Recruiter

7800 W. Oakland Park Blvd. (12692) • Ft. Lauderdale, FL 33321

An EEO/Affirmative Action Employer



# **Electronic** Design

**BRINGS YOU** 

THE HIGHEST

NUMBER

OF QUALIFIED

**EOEM** 

**ENGINEERS AND** 

**ENGINEERING** 

**MANAGERS** 

**ANYWHERE** 

. . . AT THE

LOWEST COST

ANYWHERE!

# With Electronic Design

# you reach engineers with titles like these:

- Chief Engineer Development Engineer Design Engineer
- Project Engineer
   Electronic Engineer
   Engineer-Supervisor
  - Section Leader
     Staff Engineer
     Systems Engineer
    - Test Engineer
       Standards Engineer
    - Master Engineer with Electronic Design

# Advance your career in advanced electronics.



We have initiated an exciting new program in modern electronics design and packaging. A dedicated team of highly skilled engineers is performing advanced electronics systems analysis, design, development and production using the latest computer aided engineering tools and VLSIC technology. We are hiring innovative goal oriented engineers who are interested in expanding their technical and management horizons.

We are advancing careers in the fields of:

- Ultra high speed signal and image processing system analysis and design and sub-system architecture design and development.
- Computer aided engineering system design and support using UNIX.
- Sophisticated signal processing algorithm development, simulation and test.

- Firmware design, integration and test.
- High speed analog or digital semicustom VLSIC design.
- VLSI circuit research, design and packaging.
- Modern electronics packaging and design.
- Microprocessor applications and custom microprocessor design.

Special CAE and semicustom VLSIC design courses are provided for qualified candidates. Positions are available at entry level and above for individuals with BSEE, BSCS, or BSME.

For immediate consideration, send your resume to Professional Staffing, Dept. 5l8BX07, Lockheed Missiles & Space Company, P.O. Box 3504, Sunnyvale, CA 94088-3504. We are an equal opportunity, affirmative action employer. U.S. citizenship is required.

Lockheed Missiles & Space Company

Leadership in Technology

# **Ph.D Electrical Engineering**

This opportunity at the AT&T Engineering Research Center requires the candidate to perform studies involving thin film display materials and display technology. Duties include the active matrix addressing of displays using thin film transistors and metal-insulator-metal varistor technology, and the multiplexing of displays.

#### Position requires:

 Ph.D. in Electrical Engineering with a strong background in material science.

Educational training must include:

- Knowledge of amorphous thin film semiconductor alloys and their application to thin film devices.
- Thin film material characterization by laser spectroscopy.
- Process engineering, photolithography, wet and dry etching and deposition techniques, i.e., sputtering and evaporation.
- Fabrication and evaluation of thin film devices.
- Reactive and anodic oxidation of thin metal films.

Position requires one year of experience which integrates the above expertise into the development of large area thin film device arrays.

Salary: \$43,440

If interested, send resume and transcripts to: Lynn Schreiber, Ref. 137, AT&T Engineering Research Center, P.O. Box 900, Princeton, NJ 08540.



An Equal Opportunity Employer

#### Personal computer users:

#### FOR FREE ACCESS TO A BETTER JOB CALL CLEO.

EASTERN U.S.: (201) 688-5599 (301) 982-0224 WESTERN U.S.: (213) 618-8800 (408) 294-2000 (415) 482-1550 (619) 224-8800 (714) 476-8800 (818) 991-8900 300 BAUD, Full Duplex, ASCII code For 1200 BAUD #'s and access assistance: (213) 618-1525 Advertisers call (800) 621-9147. In California, call (800) 328-2263.



seeking exceptional professionals for high technology environments

Charles A. Binswanger

EXECUTIVE SEARCH SPECIALISTS

P O Box 5325 • Baltimore Md 21209 • 301 433-6610

# ★ South & Southwest ★

Engineering / Management send resume or call Bob Hogue; Sr. Mbr. IEEE

SouthWest Technical

P.O. Box 33070 San Antonio, Texas 78265 (512) 650-0988

★ Clients Pay All Fees ★ ★

Sunbelt Opportunities in Electronics
1-800-428-4406
Toll free

Computer Engineer to design and develop hard and software for micro processor based systems for real time data acquisition and other real time application = software interfacing of different systems using higher computer languages. eg. Fortran, Basic. 925/600 dlrs/wk. Base/22.50 dlrs/hr. o/t. M.S. in computer engineering/2 yrs exp. as research engineer in computer engineering or equivalent required. Resumes to 7310 Woodward Ave. Room 415, Detroit MI 48202 Reference No. 36984. Employer paid ad

# Tomorrow is taking shape at a company called TRW.

# A four-day work week in the beautiful Rocky Mountains

TRW Electronic Products, Inc. is an industry leader in the manufacture of state-of-the-art military and aerospace communications equipment. Our excellent working conditions, superior benefits package and superb location all add up to make us one of the best in the West. Our current opportunities include:

- RF/Digital Engineers
- Component Engineers
- Process Engineers
- Program Administrators
- Sr. Manufacturing Engineers
- Manufacturing Engineering Manager
- Reliability Engineers
- Quality Engineers

Send your resume to:

TRW Electronic Products, Inc. Employment Dept. KB 198 3650 N. Nevada Ave. Colorado Springs, CO 80907

Equal Opportunity Employer U.S. Citizenship Required

TRW

H/W & S/W Engineers & Managers
Our clients need Unix "C" comm Protocol, OP
SYS, Graphics & Gate Array Professionals.

SEARCH NORTHWEST
ASSOCIATES
Ports O'Call-Swan Island
4505 N. Channel, Portland, Oregon 97217
Phone: (60) 298 6566

Ports O'Call-Swan Island 4505 N. Channel, Portland, Oregon 97217 Phone: (503) 288-6560 Keith Nyman or Doug Jansen All Fees Employer Paid Nationwide Openings in Defense, Electronics, Telecomm Communications, ATE, Avionics, MIS, Hardware/Software, Aerospace, Computer Systems & Prog, QA/QC, CAD/CAM, VLSI/LSI

ALL FEES COMPANY PAID
William Bell
CAREER OPPORTUNITIES INC.
734 Walt Whitman Road
Melville, NY 11747
(516) 549-0425

# PUBLISHED EVERY TWO WEEKS

Because there is an issue of *Electronic Design* published every two weeks — 26 times a year — your help-wanted message gets into the marketplace quickly, yet gains the impact that only a technical journal can provide.

# Big ads equal big savings

The regular or ROP rate

for

Electronic Design's

full page

black and white unit

is

23% greater

than the

special rate for

recruitment advertising.

By using a full page,

advertisers get

important positioning,

frequent domination

of the spread -

and significant

cash savings.

Small-space classified

display ads

are a bargain, too,

but nothing

can match

full pages for

full impact.

#### Gail Goldstein

Recruitment Advertising Manager

ELECTRONIC DESIGN 10 Mulholland Drive Hasbrouck Heights, N.J. 07604 (201) 393-6000/6076 Electrical Engineer Vacuum Technician Mechanical Engineer Computer Science Physicist

# GROWTH CAREERS IN OPTICAL STORAGE

3M has a major commitment to the development and manufacture of optical recording media. We have immediate openings for innovative technical professionals who will contribute to the growth of our high technology erasable and read only optical discs. The location of each position (either St. Paul, Minnesota and/or Menomonie, Wisconsin) is shown within the description.

#### #1 RESEARCH SPECIALIST

We require an advanced degree in Physics or Optics with 3+ years applied research experience in thin films, optics, microstructures, and/or semiconductors. Will also consider new PhD's with appropriate related graduate level research. Responsibilities include R&D in the areas of mastering and replication of our optical disc recording, and/or development of optical test and recording systems. Location: St. Paul, MN.

#### **#2 RESEARCH SPECIALIST**

A BS or advanced degree in Electrical Engineering, Computer Science, or Physics with 3+ years experience in real-time programming, computer interfacing and familiarity with electronic subsystems is required. Responsibilities include developing the software necessary for process control of our thin film deposition systems, and interfacing to process control hardware. Location: St. Paul, MN.

#### #3 ELECTRICAL ENGINEER

BSEE with educational emphasis in analog and digital design and implementation. We require 3+ years R&D that has involved analog and digital circuitry for electro-optic servo controls and signal processing. Will be responsible for the design and building of optical disc test systems. Location: St. Paul, MN and Menomonie, WI.

#### **#4 ROBOTICS ENGINEER**

We prefer an MS in Mechanical, Electrical Engineering or Computer Science. 3+ years experience in the application and implementation of robotic systems, their mechanical modification and software design. Must understand the mechanical limitations of robots. Responsibilities include the specification and customization of robotic systems for clean-room parts handling. Location: St. Paul, MN and Menomonie, WI.

#### **#5 THIN FILM ENGINEER**

We will consider a BS or MS in Mechanical, Chemical or other engineering discipline with appropriate experience. Must have working knowledge of and process engineering experience with sputtering and/or other thin film deposition processes and equipment. Responsibilities include specifying and optimizing several thin film processes. Location: Menomonie, WI.

#### **#6 VACUUM TECHNICIAN**

Responsibilities include the maintenance, troubleshooting and repair of thin film vacuum coating equipment. Candidates should have 3+ years experience in metal deposition using sputtering and E-Beam methods. Location: Menomonie. WI.

Salary will be based upon candidates level of experience. 3M offers a highly competitive employee benefits program. Relocation expenses paid.

#### PERMANENT RESIDENCY IS REQUIRED ON THE ABOVE POSITIONS.

Interested candidates should mail (no phone calls or agencies please) their resumes referencing the appropriate position number and title to Jerry K. Buegler.

Staffing & Employee Resources/3M 224 1W 3M Center St. Paul, MN 55144

We Are An Equal Opportunity Employer M/F/H/V




# Electronic Design's recruitment newspaper is now reaching 195,000 engineers professionally and personally on the move

1985 CAREER EXTRA ISSUES TO GO MONTHLY!



#### FIRST CHOICE TO THE SUN. PRINCESS CRUISES.





SOLID STATE AC/DC RELAY Teledyne's 640-1 is a solid state pin compatible replacement for DIP reed relays where higher reliability and long life are required. Switches AC or DC up to 50V. Low onresistance is 2 ohms. Control voltage range is 3.8 to 10VDC. Transformer coupling provides 1500 (P-P) isolation, low off-state leakage, & high switching speed. Employs hybrid microcircuits in TO-116 DIP. \$6.15 ea for 5000 pcs. Teledyne Relays, 12525 Daphne Ave, Hawthorne, CA 90250 (213) 777-0077

251 RELAYS



#### THE BEST TEST SITES.

Accuracy, simplicity, and ease-of-operation characterize the best FCC/VDE/EMI test sites. For yours, choose our Roberts® A-100 dipole antennas; the industry standard-identical to those used by the FCC at its sites. Or select our B-1000 line of accurate, portable biconicals ranging from 30 MHz-1000 MHz, with antenna factors traceable to national standards. And our motorized masts are perfect for any antenna set. Compliance Design Inc., 593 Massachusetts Avenue, Boxborough, MA 01719 (617) 264-4668.

ANTENNAS & MASTS

252

#### **MICROCOMPUTERS** AND **INTERFACES**



We have six single board computers, two video boards and interfaces for the IBM-PC and APPLE Ile computers. You can use our products for security systems, heat control, light control, automated slide show, traffic lights, irrigation systems, home computer systems, automated process control, and robot control just to name a few. OEM prices available. For catalog call or write to: JOHN BELL ENGI-NEERING, INC. 400 OXFORD WAY, BELMONT, CA 94002. (415) 592-8411.

MICROCOMPUTER/INTERFACE CATALOG 253



Fast turn-around on Connector, Switch, Cardfile Assemblies & more. Peerless combines speed, quality and availability to save you time, reduce overhead costs, and increase productivity. Our Value Added capabilities are virtually unlimited; we have the most modern facilities and the manufacturers we represent are the world's finest and most innovative. So in every way it pays to depend on Peerless for your specialized Value Added requirements. Write or call today. Peerless Radio Corporation, 19 Wilbur Street, Lynbrook, N.Y. 11563 (516) 593-2121, in NYC (212) 523-3456. Call Toll Free 800-645-2268.

PEERLESS RADIO

254

257



Vii's 2501 Video Generator is programmable providing a full range of test patterns at virtually any scan rate. Using keyboard entry in real numbers, it stores all pulse and proportion parameters for up to 69 raster formats, permanent EEPROM data storage, user-friendly with 16-character display with complete support manual. Only \$4950. Contact your Vii Rep or send for literature: Vii, P.O. Box 33, Xenia, OH 45385-0033. Telephone: 513-376-4361

PROGRAMMABLE VIDEO GENERATOR

255



**ELECTROSTATIC DISCHARGE CONTROL: Tarak** N. Bhar & Edward J. McMahon, A complete guide to establishing, implementing, and monitoring an ESD control program. Static control materials, manufacturing processes, and special precautions are emphasized. Send \$21.95 plus \$2.00 to cover postage & handling to Hayden Book Company, 10 Mulholland Dr., Hasbrouck Hts., NJ 07604. Reference number 5689 must be included on your check or money order. If not satisfied, return the book undamaged, within 10 days for refund.

HAYDEN BOOK

256




"TOTAL POWER TO YOU" A complete series of EN-CAPSULATED LINEAR AC/DC and DC/DC supplies up to 40W. LINEAR OPEN FRAME supplies, single and multiple outputs up to 200W. Open frame/enclosed single and multiple output SWITCHING SUPPLIES up to 2000W. RFI LINE FILTERS in metal and plastic case. Custom Requirements Welcome. Total Power International, Inc., 418 Bridge St., Lowell, Ma. 01850

**POWER SUPPLIES** 



Heavy Duty Hash Chokes for interference suppression; in stock from 3.35 uH/20 Amps to 500 uH/2 Line Filter Chokes from 135 uH/20 Amps to 600 uH/2 Amps. Over a million inductors in stock; Catalog on request. J.W. MILLER DIVISION of Bell Industries, 19070 Reyes Ave., P.O. Box 5825, Rancho Dominguez, CA 90224. (213) 537-5200.

HASH CHOKES 258



Z8000™ MULTIBUS™ SBC.Z8001 or Z8002 16bit CPU (6 MHz); 32K or 128K DRAM (upgradable to 512K); up to 48K static RAM or EEPROM; up to 128K EPROM; 2 RS-232 ports (Z8030 SCC); 40 parallel I/O lines, six 16-bit counter-timers (Z8036 ClOs); vectored interrupts. EPROM Debug Monitor, MICRO CONCURRENT PASCAL, C, FORTH, VRTX. Dev. Z8000 software on IBM PC, PDP-11, Intel MDS, Olivetti M20 or 8080/Z80 CP/M system. Z8000™ Zilog, Multibus™ Intel Corp. SINGLE BOARD SOLUTIONS, 7669 Rainbow Dr., Cupertino, CA 95014. 408-253-0181

SINGLE BOARD SOLUTIONS


259



VME 68000 FAMILY MODULES Full MOTOROLA compatible but reinforced 8MHz/10MHz CPU modules with battery backed-up RTC & onboard CMOS RAM, 512KB and 2MB DRAM memory modules. Static 64KB RAM, ROM, Floppy I/F, Hard Disk I/F, Serial I/F modules. AMPERE, INC. Asahi Bldg., 5-chome, Nishi-Shirijuku, Shirijuku-ku, Tokyo Japan Telex J33101 AMPERE PHONE 03-365-0825.



MASS-PLATE NI-CD BATTERY PUTS 40% MORE CAPACITY IN LESS BOARD SPACE. Varta massplate NiCd batteries offer major advantages over cylindricals: 100 mAh units with 40% higher capacity in less space; 4 times greater capacity retention after five months; charging rates as low as 1mA (instead of 4-7mA) and four configurations that use board space best, including pin-for-pin replacements for Data Sentry™. Call: Varta Batteries, 150 Clearbrook Road, Elmsford, NY 914 592-2500.



CMOS IC GENERATES CALL PROGRESS TONES. Generate audible ringing and other call-routing tones such as dial, busy and reorder—with just one chip. Teltone's M-991 produces combinations of seven standard frequencies using one 5V supply and a 3.58 MHz crystal. As the only tone generator on the market, it joins Teltone's family of telecommunications generators, detectors, receivers and relays. 1-800-227-3800, ext. 1130. Teltone Corporation, P.O. Box 657, Kirkland, WA 98033.

**CPU MODULES** 

260

MASS-PLATE BATTERIES

261

M-991

262



FIRST IN SOUTHEAST ASIA. FEATURES NMOS Technology • Internal Memory-2K × 8 ROM • 128 × 8 RAM • Internal Timer/Event Counter • Single level interrupt • Single 5-volt supply • Over 90 instructions. 70% Single Byte • Timer/counter interrupt available • Reduced Power Consumption • Compatible with Intel's MCS-80/85 peripherals • Easily Expandable Memory and I/O • Up to 1.36 µsec instruction cycle (11 MHz operation), all instructions 1 or 2 cycles. ERSO/ITRI

8th Fl. No. 315, Sung Chiang Rd., Taipei, Taiwan, ROC Telex 12974 ERSO ITRI Tel (02) 542-8212.


SINGLE CHIP MICROCOMPUTER

263



Analog and Power Control I/O...in a Single Board Computer. 6801 Micro Control System designed for DISTRIBUTED CONTROL or STAND-ALONE use: 6801 or 68701 MPU with 2K ROM or EPROM, 128 RAM, timer. Eight 12-bit analog inputs, 8-bit analog output, 8 AC or DC inputs or outputs, serial I/O, digital I/O, power supply. Wintek Corporation, 1801 South Street, Lafayette, IN 47904-2993. (317) 742-8428.


264




10 MB Half-Height Winchester Disk Drives. The HH-612 provides 10 MB formatted storage w/ very low voltage requirements & very high reliability features usually found in larger mass storage units. Weighs 3 lbs. & is ideal for use where space, wt., & power are critical considerations. It's the drive of choice for use in office, factory, & military systems as well as portable computers. For complete info, pricing, & delivery, call/write: Microscience International Corporation, 575 E. Middlefield Rd., Mountain View, CA 94043, 415-961-2212, Tlx: 275907.

HH-612 DISK DRIVE

265




**EMI PROBLEMS?** Let Eagle Magnetic solve your magnetic shielding problems! For more information write or call: Eagle Magnetic Co., Inc., P.O. Box 24283 • Indianapolis, Ind. 46224 Phone (317) 297-1030.



6801 MICRO CONTROL SYSTEM

T-134 LED Mounts in Strip Form BIVAR, INC. has introduced an entirely new line of T-134 LED Mounts in strip form. Molded in one-piece strips of 12 stations, these "Strip-Mounts®" are designed for LED mounting on 1/4" spacing. A single mount can be used for an entire array. Or, couplings between individual mounts can be easily cut, allowing the user to size arrays from 2 to 12 stations. For complete data and pricing contact BIVAR, INC., 4 Thomas, Irvine, CA 92718. (714) 951-8808.



**68008 Single Board Computer.** 100 by 160mm Eurocard. 3 RAM/EEPROM/EPROM sockets for 2K-64K byte devices (2K RAM included). 6 8-bit Bi-Dir I/O ports with handshake and individually vectored interrupts. 4 16-bit timers. Dual async serial RS232 ports. 256b nvRAM. Diagnostics LEDs. Multitasking kernal option. \$295/unit. Quantity discounts available. Heritage Systems Corporation, P.O. Box 10588, Greensboro, NC 27404. (919) 274-4818.

MAGNETIC SHIELDING PROBLEMS

266

LED MOUNTS

267

32BIT SINGLE BOARD COMPUTER

268



GTEK's Model 7228 (E)EPROM Programmer features Intelligent Programming Algorithms and supports the newest devices available through 512 Kbits and programs 6x as fast as standard algorithms. The 7228 programs the 2764 in one minute! It supports Intel 2764A and 27128A chips. It also supports Tektronics, Intel, Motorola and other formats. Priced at just \$549. GTEK, Inc., P.O. Box 289, Waveland, MS 39576; 601-467-8048.



ROLYN OPTICS CO. supplies all types of "Off the Shelf" optical components. Lenses, prisms, mirrors, irises, microscope objectives and evenieces and many others. All from stock. We also supply custom products and coatings in prototype or production quantities. 75 page catalog describes products and prices. ROLYN OPTICS CO., 738 Arrowgrand Circle, Covina, CA 91725 (818) 915-5707 & (818) 915-5717. TELEX: 67 0380.



PLANE FACT. Nothing prevents warpage of printed wiring boards during soldering more simply and effectively than Rogers' board stiffeners. Contact Rogers for a free board stiffener sample. You'll see how they can also serve as ground or voltage suppliers of up to 25 amps. Call today for the full story. And get it straight. Rogers Corporation, Bus Products Division, 5750 E. McKellips Rd., Mesa, AZ 85205, telephone 602-830-3370

**EPROM PROGRAMMER** 

269

**OPTICS** 

270

**BOARD STIFFENERS** 

272



LOW COST EPROM ERASERS that ERASE AND VERIFY. UV unit that comes in 4 models. Models M515 & M515V erase 10 EPROMS, Models M530 & M530V erase 25 EPROMS. M515V & M530V automatically VERIFY when the EPROM is erased & cease the process. Non-eraseable EPROMs can be checked in this manner. Safety shutoffs & ONE YEAR WARRANTY standard. M515-\$89.95, M515V-\$139.95, M530-\$139.95, M530V-\$179.95. GAM INDUSTRIES, 2273 Providence Rd, Northbridge, Ma 01534 617-234-6391



**OFF THE SHELF!** 12" monitor housings molded of UL VO 94-95 materials. ONLY \$73.25 each in 1-100 quantity. Custom fabrication, EMI/RFI shielding, painting available. Other sizes also, plus keyboard housings. Hettinga, Inc., 2123 N.W. 111th St., Des Moines, Iowa 50322, U.S.A. Telephone 515-270-6900. Telex 478315.



TP-102 SERIES SINGLE HOLE, PC MOUNTED TEST POINTS. • Direct replacement alternative to expensive "turret" type terminals. • Two styles accommodate complete range of popular "turret" hole diameters. • Spring tempered, flaired leads eliminate secondary staking operations. • Accepts all commonly used spring loaded test probes and clips. • Cunistan® alloy, comparable spring quality and strength to beryllium copper at less cost. COM-PONENTS CORP., 6 Kinsey Place, Denville, NJ 07834. (201) 627-0290.

The IM3016 programs up to 16 different masters

in one cycle. Suitable for engineering applications with large EPROM sets & RS232 computer interfac-

ing. The IM3016 provides dependable, high-throughput operation for production environments

using electrically isolated sockets, one-key control, & fast programming algorithms. Software selection for all common EPROMs including 2764, 2764A, 27128, 27128A, 27256 & 27512. INTERNATION-AL MICROSYSTEMS, INC. 11554 C Avenue, Autor CA SEGS. SOR MARCHATE ACTION ACTION.

burn, CA 95603. FOR IMMEDIATE ACTION CALL:

**EPROM ERASERS** 

273

12" MONITOR HOUSINGS


274

**TEST POINT 102** 

275



AFFORDABLE ENGINEERING SOFTWARE ACNAP2 Fast Circuit Analysis, 200 parts 30 nodes, chained circuits, I/O impedance, full circuit editor, \$69.95. **DCNAP** DC Analysis, worst-case, power dissipation, \$59.95. **SPP** Transient Signal processonsipation, \$59.95. SPF Transient Signal processing, FFT, LaPlace, \$59.95. PCPLOT-Pixel resolution graphics, linear-log, 2 Y-axes, full labeling, \$59.95. PLOTPRO General purpose graph printing, \$49.95. MSDOS-CP/M-PCDOS—TRSDOS. BV Engineer-2200 Business Way #207, Riverside, CA 92501 (714) 781-0252



**ENGINEERING SOFTWARE** 

276



FREE for Intel MDS users: Guide to time saving opportunities for Intel microprocessor development systems 20-90% TIME SAVINGS. If you have or plan to get an Intellec Series II, III or Model 800 you need this guide. Call: Winchester Systems, 400 West Cummings Park, Woburn, MA 01801. Toll free: 800-325-3700, in Mass 617-933-8500.

277

MULTI-SET EPROM PROGRAMMER

916/885-7262.

278

WINCHESTER SYSTEMS

# INDEX OF ADVERTISERS

ACDC Electronics.         18           AIE Magnetics, Div. of Vernitron.         26           AMP.         80-8	1
AVX Ceramics Corporation	6
Ampere Inc.         36           Amphenol, an Allied Company         14           Ampro Computers         27           Analog Devices         Cover Γ	7 5 V
Analogic Corp.         8           Anritsu Electric         198-199, 38           Apex Microtechnology         1           Avocet Systems         12	5
BV Engineering         36           Badische Chemicals         7           Bay Components         31           John Bell Engineering         36	*
John Bell Engineering         36           Bivar         343, 36           Boschert Associates         313           Burr-Brown Corporation         153, 228-22	7 * 9
Caddock Electronics         16           Cadnetix         .38-3           Calma         133-13           Compacted	9 5
Cermetek.         109           Cherry Semiconductor         9           Chomerics         20           Cogito.         23	7 2
Comark         34           Comlinear         6           Compliance Design Inc.         36           Components Corporation.         36	0 6
Components Corporation. 36 Computer Products Inc., Compower Div. 23 Control Data, OEM. 18 Control Data, Industry Marketing Electronics 25	9 3
Colleraft	Б
D.A.T.A. Books       15         DY-4 Systems       33         Dale Electronics       298-29         Darnell Corp.       24	8
Data I/O Corp.       3         Data Translation.       303*, 308         Datel       303*, 308         Deltron       210, 211-21         Digital Equipment       58-5         Discour       112	7
Dejetal Equipment   210, 211-21	
EG&G Reticon	
Electronic Technology Corp. 18 Eagle Magnetics 36 Eastern Air Devices 29	1 7 7
Electronic Conventions 37 Electronic Designs 2 Electronic Industrial Equipment 114J Electronic Measurements 17 Electronic Solutions 210, 33 Electronic System Products 88	0 8 †
Electronic Solutions       210, 33         Electronic System Products       88         Elfab       301         Exar       246-24	7 8 *
Ferranti Semiconductors	*
John Fluke Mfg. Co., Inc.       4         Force Computers.       290-29         Forth Computers.       28         Fuji Sangyo       33	1
Fuji Sangyo 33 Fujitsu America 116, 117, 304 Fujitsu Microelectronics 317	*
GAM Industries, Div. Eagle Computer       36         GTEK, Inc.       36         Gold Book       322-323         Gordos       314	8 * *
Gould AMI Semiconductors	$\frac{6}{3}$
Harris Semiconductor, A Div. of Harris	
Corp.         4           Heritage Systems         36           Hettinga, Inc.         36           Heurikon         36           Hewlett-Packard         1,14,184-18	8


Heyco Molded Products	
Intel Corp.   65-7   Interconics, a unit of BMC Industries   19   International Microsystems, Inc.   36   International Rectifier   14   KSM	Holt Integrated Circuits 316
LXD	I-BUS       28         Inmos       19         Integrated Device Technology       22         Intel Corp.       65-7         Interconics, a unit of BMC Industries       19         International Microsystems, Inc.       36         International Rectifier       14
Linear Technology	KSM       17         Keystone Carbon Co.       5         Klinger Scientific Corp.       2         Kwan Chiu       24
Mepco/Electra, Inc.         98           Micros Cience International         36           Micro Link         25           Micro ENERGY.         319           J.W. Miller Div/Bell Industries         36           Mini-Circuits Laboratory, a Div. of Scientific         353, 101E, Cover II           Mostek Corp.         26, 30, 101, 244-245, 344           Mostek Corp.         5           Motorola Semiconductor Products, Inc.         17-24           56-57, 96-97*, 114R-114S†         307           NCR         149, 28           NEC America         320           NJE         2           Nichicon (America) Corp.         310           OMTI, a sub. of Scientific Micro Systems.         23           Olivetti SpA         114H           Omron         108           Oregon Software         17           Panasonic Electronic Components         114           Peerless Radio Corp.         36           Perlmag         21           Phihong Enterprise         34           Philips Elcoma         102E-103E           Philips Elcoma         102E-103E           Philips Elcoma         114E-113E           Powertec         91-94	LXD       27         Lambda Electronics Corp263-266*, 267-268         Linear Technology       22         Lundy Electronics & Systems       8
NCR         149, 28           NEC America         320           NJE         2           Nichicon (America) Corp.         310           OMTI, a sub. of Scientific Micro Systems.         23           Olivetti SpA         114H           Omron         108           Oregon Software         17           Panasonic Electronic Components         114           Peerless Radio Corp.         36           Permag         21           Phihong Enterprise         34           Philips Elcoma         102E-103E           Philips Elcoma         112E-103E           Philips Elst & Measuring Instruments,         Inc.           Inc.         114F           Plessey Semiconductor         112E-13E           Potrans Electrical Corp.         34           Powertec         91-94           Precision Monolithics.         52,5           Prime Power, a Prime Technology         29           Princess Cruises         36           Protean         25           Pulse Instruments.         110           Qume         280-28           RCA Solid State Division         136-137, 16           Racal-Redac         292-29	Magnetics         15           Marconi Instruments         .324-330           Matra Harris Semiconductor         .114K-114L           Mepco/Electra, Inc.         98           Microscience International         36           Micro Link         25           Micro ENERGY         319           J.W. Miller Div./Bell Industries         36           Mini-Circuits Laboratory, a Div. of Scientific         Components Corp.           Components Corp.         2, 6, 30, 101, 244-245, 34
NCR         149, 28           NEC America         320           NJE         2           Nichicon (America) Corp.         310           OMTI, a sub. of Scientific Micro Systems.         23           Olivetti SpA         114H           Omron         108           Oregon Software         17           Panasonic Electronic Components         114           Peerless Radio Corp.         36           Permag         21           Phihong Enterprise         34           Philips Elcoma         102E-103E           Philips Elcoma         112E-103E           Philips Elst & Measuring Instruments,         Inc.           Inc.         114F           Plessey Semiconductor         112E-13E           Potrans Electrical Corp.         34           Powertec         91-94           Precision Monolithics.         52,5           Prime Power, a Prime Technology         29           Princess Cruises         36           Protean         25           Pulse Instruments.         110           Qume         280-28           RCA Solid State Division         136-137, 16           Racal-Redac         292-29	Mostek Corp. 5 Motorola Semiconductor Products, Inc. 17-24 56-57, 96-97*, 114R-114S† Murata Erie, N.A. 307
Olivetti SpA       114H*         Omron       108         Oregon Software       17         Panasonic Electronic Components       114         Peerless Radio Corp       36         Permag       21         Philong Enterprise       34         Philips Elcoma       102E-103E         Philips Test & Measuring Instruments,       1nc         Inc       114F         Plessey Semiconductor       112E-113E         Power-One       23         Power-One       23         Power-One       29         Pericesion Monolithics       52, 5         Prime Power, a Prime Technology       29         Princess Cruises       36         Protean       25         Pulse Instruments       110         Qume       280-28         RCA Solid State Division       136-137, 16         Racal-Redac       292-29         Rantec Power Systems       24         Renco Electronics       77         Rolyn Optics       36         Rockwell International       2         Ropers Corp       115, 200, 36         Rohde & Schwarz       100E	NCR       149, 28         NEC America       320         NJE       2         Nichicon (America) Corp.       310
Peerless Radio Corp.       366         Permag.       21         Phihong Enterprise       34         Philips Elcoma       1.02E-103E         Philips Etst & Measuring Instruments,       1.1         Inc.       1.14F         Plessey Semiconductor       1.12E-113E         Potrans Electrical Corp.       34         Powere One       23         Powertec       91-94         Precision Monolithics.       52, 5         Prime Power, a Prime Technology       29         Princess Cruises       36         Protean       25         Pulse Instruments.       110         Qume       280-28         RCA Solid State Division       136-137, 16         Racal-Redac       292-29         Rantec Power Systems       24         Renco Electronics       76         Rolyn Optics       36         Rockwell International       2         Ronde & Schwarz       100E	OMTI, a sub. of Scientific Micro Systems       23         Olivetti SpA       114H         Omron       108         Oregon Software       17
Qume       .280-28         RCA Solid State Division       136-137, 16         Racal-Redac       .292-29         Rantec Power Systems       24         Renco Electronics       .7         Rolyn Optics       .36         Rockwell International       .2         Rogers Corp.       .115, 200, 36         Rohde & Schwarz       .100E	Peerless Radio Corp.       36         Permag       21         Phihong Enterprise       34         Philips Elcoma       102E-103E
RCA Solid State Division     136-137, 16       Racal-Redac     292-29       Rantec Power Systems     24       Renco Electronics     7       Rolyn Optics     36       Rockwell International     2       Rogers Corp.     115, 200, 36       Rohde & Schwarz     100E	Qume
SGS-ATES     .96E-97E†, 104E-105E†       110E-111E†, 114M-114N       SMK Electronics Corp. of America     35       S-MOS     19       Schaffner     27       Seeq Technology     282-28       Siemens     271*, 114P       Signetics     .77-79, 333-33       Siliconix     16       Silicon General     20	RCA Solid State Division     136-137, 16       Racal-Redac     292-29       Rantec Power Systems     24       Renco Electronics     7       Rolyn Optics     36       Rockwell International     2       Rogers Corp.     115, 200, 36       Rohde & Schwarz     100E
The color of America   35	SGS-ATES
Silicon Systems	110E-111E†, 114M-114N   SMK   Electronics   Corp. of America   35   S-MOS   19   Schaffner   27   Seeq   Technology   282-28   Siemens   271*   114P   Signetics   77-79, 333-33   Siliconix   16   Silicon   General   20

Single Board Solutions         366           Socapex         106E†           Sprague Electric Co.         34,259           Sprague Goodman.         16           Standard Microsystems         82-83           Standard Power         106-107*           Standex Electronics         279           Supertex         221
TI Electronics       306*         TRW/LSI Products Div       55         TRW Microwave       209         Taiyo Yuden (U.S.A.)       305*         Technipower       272         Technipower       272         Telecontrolli       98E†         Teledyne Crystalonics       297         Teledyne Relays, A Teledyne Co       10         Teledyne Semiconductor       345         Teledyne Solid State Products       366         Teletek       169         Teltone       296, 367         Teradyne Connection Systems       172-173         Texas Instruments       32-33         Thomas Electronics       1140†         Toka America       321*         Toray Industries       278         Torwico       340         Total Power International, Inc       366         Tristar       230-231
U.S. Pixel     314*       Union Carbide     195       United Chemicon     89
Varta Batteries Inc.         367           Vii.         366
Wandel & Golterman         109E†           Warren         370           Wavetek San Diego         1131           Westminster Software         309*           Winchester Systems, Inc.         368           Wintek Corp.         241, 367
Yokogawa Hokushin Electric
Zendex         16           Zilog         138-139           Zycad         8-9

#### Recruitments

																		×			362
																					356
es																					362
ge	r																				362
0																					362
Ses	r	c	h	•	ì	•	ì	١	•	î	i	•	i	ĺ	•	ì	•	•		î	362
./		•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	354
			•	*	•	•	•			•		•	•	•	•	•	•	•	٠	•	250
			•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		•	٠	261
	٠.		•			٠	۰					٠	٠							,	
	٠.		٠			•				٠				٠	٠		ė	50	)	١,	300
											•				٠			٠.			362
												٠									358
													·								363
	Sea.)	Bear Bear Bear Bear	Search	esger Search)	es	es	es	es	es	es ger Search )	es ger Search )	es ger Search .)	es ger Search )	es ger Search )	es ger Search .)	es ger Search .)	es ger Search .)	es ger Search .)	es ger Search .) 	es ger Search .) 	es

\*Advertisers in U.S. Edition †Advertisers in International Edition



6200

CIRCLE 219



#### NOW THOUSANDS OF CALIFORNIA OEM'S AND SYSTEMS INTEGRATORS FOCUS ON JUST ONE SHOW.

And so can you...on Mini/Micro West.
Mini/Micro West is the one West Coast
event that focuses entirely on computer design
needs. That means you, as an exhibitor, can
deal face to face with the prime concentration of
OEM's, systems integrators and software
developers.

Having their own event recognizes the importance of the California OEM market today. For you, it presents a unique opportunity to zero in on California OEM's face to face—in an environment undiluted by other interests.

So if you're after California OEM's and systems integrators, be at Mini/Micro West. For complete information, call toll-free: 800-421-6816. In California, 800-262-4208.

The Anaheim Hilton Exposition Center, February 5-7, 1985.

Sponsored by California regional units of IEEE and the Electronic Representatives Association



# transformers



3 KHz-800 MHz **over 50 off-the-shelf models** from \$295

Choose impedance ratios from 1:1 up to 36:1, connector or pin versions (plastic or metal case built to meet MIL-T-21038 and MIL-T-55831 requirements\*). Fast risetime and low droop for pulse applications; up to 1000 M ohms (insulation resistance) and up to 1000 V (dielectric withstanding voltage). Available for immediate delivery with one-year guarantee.

Call or write for 64-page catalog or see our catalog in EBG, EEM, Gold Book or Microwaves Directory.



setting higher standards

# Mini-Circuits

A Division of Scientific Components Corporation
World's largest manufacturer of Double Balanced Mixers
P.O. Box 166, Brooklyn, New York 11235 (718) 934-4500
Domestic and International Telex 125460 International Telex 620156

CIRCLE 132

C71 Rev. Orig.

The AD625 makes short work of long-standing in-amp problems. And it does it inexpensively.


re her in a

Like a low-cost differential gain block.

If you've been using a discrete approach involving several op amps and a resistor network, stop right here. The AD625 is available in a plastic version. Just \$6.10 in 1,000's.

Like a low-cost software programmable gain amplifier (SPGA).

An AD625 plus a CMOS multiplexer and a suitable resistor network will deliver 12-bit precision. It's configured such that the switch on-resistance doesn't add to the gain-setting network



—no expensive relays are needed. If you can think of a better way to make a low-cost programmable gain amplifier call us

Like fixed gain applications.

If you're looking for non-standard gains—those not found on the AD524 or AD624—the AD625 is the in-amp you've been waiting for. With three external resistors, the AD625 will provide any gain from 1 to 10,000. And the gain accuracy and gain T.C. depend almost entirely on the choice of external resistors.

More good news.

The AD625 delivers 0.001% nonlinearity, 0.25 $\mu$ V/°C input offset drift and 0.2 $\mu$ V p-p low-frequency noise. It delivers the performance you expect from an Analog Devices in-amp. Write us. Analog Devices, P.O. Box 280, Norwood, MA 02062. Or call us at (617) 658-8313 and ask for Applications. We're offering an evaluation kit to qualified users, and we'd like to send you one. Do it today. It could solve a lot of problems.





# The new AD625 In-Amp: Come up with a problem it can't solve.

Analog Devices, Inc., Two Technology Way, Norwood, MA 02062; Headquarters: [617] 329-4700; California: [714] 641-9391; [619] 268-4621, [408] 947-0633; Colorado: [303] 590-8906; Florida: [305] 851-3939; Illinois: [312] 653-5000; New York: [716] 425-4101, [315] 437-5277; Ohio: [614] 764-8795; Pennsylvania: [215] 643-7790; Texas: [214] 231-5094, [713] 664-6704; Washington: [206] 251-9550; Belgium: [3] 237-4803; Demmark: [2] 845800, France: [1] 687-34-11; Holland: [1620] 51080; Israel: [052] 289995; Italy: [2] 6883831, [2] 6883833; [2] 6883833; [2] 6883831; [2] 6883831; [2] 6883831; [2] 6890; Italy: [2] 6890; Italy